PA Mixer Amplifiers



SSA-250®M

250 WATTS ■ AC & 24V DC Operation

- 6 Mic & 2 Aux Inputs.
- Preamplifier and Line Output for connecting to a Booster Amplifier and for recording the programme.
- Line Input for connecting any external mixer or permitting SSA-250®M to be used as a Booster Power Amplifier.
- Resettable circuit breaker for overload and short circuit protection. Instant transfer to DC power (Car Battery) if AC power fails.
- Box Speaker/Driver Unit selector switch. Bass boost defeated at Driver Unit position for safer operation of driver units.



SSA-250®FX

250 WATTS ■ AC & 24V DC Operation

- 6 Mic & 2 Aux Inputs.
- Built-in digital effect processor for 2 Mic Inputs.
- Preamplifier and Line Output for connecting to a Booster Amplifier and for recording the programme.
- Line Input for connecting any external mixer or permitting SSA-250®M to be used as a Booster Power Amplifier.
- Resettable circuit breaker for overload and short circuit protection. Instant transfer to DC power (Car Battery) if AC power fails.
- Box Speaker/Driver Unit selector switch. Bass boost defeated at Driver Unit position for safer operation of driver units.



SSA-160®EM

160 WATTS ■ AC & 24V DC Operation

- 5 Mic & 2 Aux Inputs.
- Preamplifier and Line Output for connecting to a Booster Amplifier and for recording the programme.
- Line Input for connecting any external mixer or permitting SSA-160®EM to be used as a Booster Power Amplifier.
- Resettable circuit breaker for overload and short circuit protection. Instant transfer to DC power (Car Battery) if AC power fails.
- Box Speaker/Driver Unit selector switch. Bass boost defeated at Driver Unit position for safer operation of driver units.

SPECIFICATIONS	SSA-250®M	SSA-250®FX	SSA-160®EM
POWER OUTPUT	300W Max., 250W RMS at 10% THD	300W Max., 250W RMS at 10% THD	220W Max., 160W RMS at 10% THD
	220W RMS at 5% THD, 200W RMS at 2% THD	220W RMS at 5% THD, 200W RMS at 2% THD	140W RMS at 5% THD, 120W RMS at 2% THD
OUTPUT REGULATION	≤ 2 dB, no load to full load at 1kHz	≤ 2 dB, no load to full load at 1kHz	≤ 2 dB, no load to full load at 1kHz
INPUT CHANNELS	6×Mic 0.65mV/4.7kΩ, 2×Aux 100mV/470 kΩ,	6×Mic 0.65mV/4.7kΩ, 2×Aux 100mV/470 kΩ,	5×Mic 0.65mV/4.7kΩ, 2×Aux 100mV/470 kΩ,
	1 × Line 1V/50kΩ	1 × Line 1V/50kΩ	1 × Line 1V/50kΩ
DELAY SYSTEM	—	Digital Signal Processing	—
DELAY RANGE SETTING	—	60-300ms	—
FREQUENCY RESPONSE	50-15,000Hz ±3dB	50-15,000Hz ±3dB	50-15,000Hz ±3dB
SIGNAL TO NOISE RATIO	60dB	60dB	60dB
TONE CONTROLS	Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz	Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz	Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz
OUTPUTS	Preamp 200mV/600Ω, Line 1V/1kΩ	Preamp 200mV/600Ω, Line 1V/1kΩ	Preamp 200mV/600Ω, Line 1V/1kΩ
SPEAKER OUTPUTS	4Ω, 8Ω, 70V & 100V	4Ω, 8Ω, 70V & 100V	4Ω, 8Ω, 70V & 100V
POWER SUPPLY	AC: 220-240V 50/60Hz	AC: 220-240V 50/60Hz	AC: 220-240V 50/60Hz
	DC: 24V (2×12V Car Battery)	DC: 24V (2×12V Car Battery)	DC: 24V (2×12V Car Battery)
POWER CONSUMPTION	AC: 460VA DC: 6A	AC: 460VA DC: 6A	AC: 300VA DC: 4A
DIMENSIONS	W450 × H160 × D340 mm	W450 × H160 × D340 mm	W420 × H155 × D320 mm
WEIGHT	15.40kg	15.70kg	13.60kg