FMX-112DP AC Operation

With built-in MP3 Recorder & Digital Effects



12 CHANNEL

- Professional 12 channel mixer with user friendly features, in a compact & aesthetically superior construction.
- 10 MIC, 10 LINE & 01 STEREO Balanced inputs, through 6.3 mm (1/4") stereo phone jack socket.
- Built-in digital MP3 player with recording & BT functions.
- Digital Effects channel with DELAY, REPEAT & LEVEL controls.
- Each input channel has a GAIN control, 3 band active EQ controls, AUX, FX and PAN controls.
- The STEREO channel has a GAIN control, 3 band active EQ controls, AUX, FX and PAN controls.
- Each input channel provides Peak LED to indicate excessive input signal levels.
- Each channel has a signal Mute switch and a slide fader control for accurate setting of signal level.
- Selector switch available between Stereo channel (Ch.11/12) & USB playback channel.
- Balanced Left & Right MAIN Mix outputs through M/XLR connectors as well as 6.3 mm (1/4") stereo phone jack sockets.
- MONITOR L&R outputs through 6.3 mm (1/4") phone jack sockets and individual monitor fader control.
- AUX SEND output with independent level control.
- Headphone output with Phones Control for output monitoring.
- Operates on 240V 50Hz AC mains.

SPECIFICATIONS	FMX-112DP
MIC INPUT	
Impedance/Gain	: 2kΩ Balanced/65dB
LINE INPUT	
Impedance/Gain	: 20kΩ Balanced/45dB
STEREO INPUT (L/Mono & R)	
Impedance/Gain	: 10kΩ Balanced/20dB
THD	: <0.1%
FREQUENCY RESPONSE	
L/R Line Output	: 25Hz - 20kHz (+0, -1dB)
EQUALIZATION	
TREBLE/MID/BASS	: ±12dB at 12kHz/2.5kHz/80Hz
CLIP LED INDICATION	: 4 dB prior to true clip
LINE OUTPUT	
Nominal/Max Level	: 4dBu/21dBu (1.22V/9V)
Impedance	: 600Ω
DELAY SYSTEM	: Digital Signal Processing
DELAY RANGE SETTINGS	: Variable from 20 to 300ms
DIGITAL PLAYER	: MP3 Player/Recorder with USB Reader, Bluetooth
HEADPHONE OUTPUT	: 200mV at 8Ω, THD <1%
MONITOR OUTPUTS (L&R)	: 1.6V
SIGNAL TO NOISE RATIO	: >80dB
POWER SUPPLY	: AC: 220-240V, 50/60Hz
DIMENSIONS	: W520 × H105 × D350mm
WEIGHT	: 5.20kg