



1. Description

1.1. Project

Project Name	stm32-usb-cdc1
Board Name	NUCLEO-F767ZI
Generated with:	STM32CubeMX 6.2.0
Date	03/17/2021


1.2. MCU

MCU Series	STM32F7
MCU Line	STM32F7x7
MCU name	STM32F767ZITx
MCU Package	LQFP144
MCU Pin number	144

1.3. Core(s) information

Core(s)	Arm Cortex-M7
---------	---------------

2. Pinout Configuration



3. Pins Configuration

Pin Number LQFP144	Pin Name (function after reset)	Pin Type	Alternate Function(s)	Label
6	VBAT	Power		
7	PC13	I/O	GPIO_EXTI13	USER_Btn [B1]
8	PC14/OSC32_IN *	I/O	RCC_OSC32_IN	
9	PC15/OSC32_OUT *	I/O	RCC_OSC32_OUT	
16	VSS	Power		
17	VDD	Power		
23	PH0/OSC_IN	I/O	RCC_OSC_IN	MCO [STM32F103CBT6_PA8]
24	PH1/OSC_OUT	I/O	RCC_OSC_OUT	
25	NRST	Reset		
27	PC1 *	I/O	ETH_MDC	RMII_MDC [LAN8742A-CZ- TR_MDC]
30	VDD	Power		
31	VSSA	Power		
32	VREF+	Power		
33	VDDA	Power		
34	PA0/WKUP	I/O	ADC1_IN0	
35	PA1 *	I/O	ETH_REF_CLK	RMII_REF_CLK [LAN8742A-CZ- TR_REFCLK0]
36	PA2 *	I/O	ETH_MDIO	RMII_MDIO [LAN8742A-CZ- TR_MDIO]
38	VSS	Power		
39	VDD	Power		
40	PA4	I/O	DAC_OUT1	
41	PA5	I/O	SPI1_SCK	
42	PA6	I/O	SPI1_MISO	
43	PA7 *	I/O	ETH_CRSDV	RMII_CRSDV [LAN8742A- CZ-TR_CRSDV]
44	PC4 *	I/O	ETH_RXD0	RMII_RXD0 [LAN8742A-CZ- TR_RXD0]
45	PC5 *	I/O	ETH_RXD1	RMII_RXD1 [LAN8742A-CZ- TR_RXD1]
46	PB0 **	I/O	GPIO_Output	LD1 [Green]
47	PB1	I/O	ADC1_IN9	
51	VSS	Power		
52	VDD	Power		


Pin Number LQFP144	Pin Name (function after reset)	Pin Type	Alternate Function(s)	Label
61	VSS	Power		
62	VDD	Power		
71	VCAP_1	Power		
72	VDD	Power		
74	PB13 *	I/O	ETH_TXD1	RMII_TXD1 [LAN8742A-CZ- TR_TXD1]
75	PB14 **	I/O	GPIO_Output	LD3 [Red]
77	PD8 *	I/O	USART3_TX	STLK_RX [STM32F103CBT6_PA3]
78	PD9 *	I/O	USART3_RX	STLK_TX [STM32F103CBT6_PA2]
83	VSS	Power		
84	VDD	Power		
91	PG6 **	I/O	GPIO_Output	USB_PowerSwitchOn [STMP2151STR_EN]
92	PG7 **	I/O	GPIO_Input	USB_OverCurrent [STMP2151STR_FAULT]
94	VSS	Power		
95	VDDUSB	Power		
96	PC6	I/O	USART6_TX	
97	PC7	I/O	USART6_RX	
100	PA8 *	I/O	USB_OTG_FS_SOF	USB_SOF [TP1]
103	PA11	I/O	USB_OTG_FS_DM	USB_DM
104	PA12	I/O	USB_OTG_FS_DP	USB_DP
105	PA13 *	I/O	SYS_JTMS-SWDIO	TMS
106	VCAP_2	Power		
107	VSS	Power		
108	VDD	Power		
109	PA14 *	I/O	SYS_JTCK-SWCLK	TCK
111	PC10	I/O	UART4_TX	
112	PC11	I/O	UART4_RX	
120	VSS	Power		
121	VDDSDMMC	Power		
123	PD7	I/O	SPI1_MOSI	
126	PG11 *	I/O	ETH_TX_EN	RMII_TX_EN [LAN8742A- CZ-TR_TXEN]
128	PG13 *	I/O	ETH_TXD0	RMII_TXD0 [LAN8742A-CZ- TR_TXD0]
130	VSS	Power		
131	VDD	Power		
133	PB3 *	I/O	SYS_JTDO-SWO	SW0

Pin Number LQFP144	Pin Name (function after reset)	Pin Type	Alternate Function(s)	Label
136	PB6	I/O	I2C1_SCL	
137	PB7 **	I/O	GPIO_Output	LD2 [Blue]
138	BOOT0	Boot		
140	PB9	I/O	I2C1_SDA	
143	PDR_ON	Reset		
144	VDD	Power		

** The pin is affected with an I/O function

* The pin is affected with a peripheral function but no peripheral mode is activated

4. Clock Tree Configuration



5. Software Project

5.1. Project Settings

Name	Value
Project Name	stm32-usb-cdc1
Project Folder	/home/maddocks/stm32-usb-stock
Toolchain / IDE	Makefile
Firmware Package Name and Version	STM32Cube FW_F7 V1.16.1
Application Structure	Basic
Generate Under Root	No
Do not generate the main()	No
Minimum Heap Size	0x200
Minimum Stack Size	0x400

5.2. Code Generation Settings

Name	Value
STM32Cube MCU packages and embedded software	Copy all used libraries into the project folder
Generate peripheral initialization as a pair of '.c/.h' files	No
Backup previously generated files when re-generating	No
Keep User Code when re-generating	Yes
Delete previously generated files when not re-generated	Yes
Set all free pins as analog (to optimize the power consumption)	No
Enable Full Assert	No

5.3. Advanced Settings - Generated Function Calls

Rank	Function Name	Peripheral Instance Name
1	MX_GPIO_Init	GPIO
2	MX_DMA_Init	DMA
3	SystemClock_Config	RCC
4	MX_USB_DEVICE_Init	USB_DEVICE
5	MX_ADC1_Init	ADC1
6	MX_DAC_Init	DAC
7	MX_I2C1_Init	I2C1
8	MX_USART6_UART_Init	USART6
9	MX_SPI1_Init	SPI1
10	MX_UART4_Init	UART4

6. Power Consumption Calculator report

6.1. Microcontroller Selection

Series	STM32F7
Line	STM32F7x7
MCU	STM32F767ZITx
Datasheet	DS11532_Rev4

6.2. Parameter Selection

Temperature	25
Vdd	3.3

6.3. Battery Selection

Battery	Alkaline(9V)
Capacity	625.0 mAh
Self Discharge	0.3 %/month
Nominal Voltage	9.0 V
Max Cont Current	200.0 mA
Max Pulse Current	0.0 mA
Cells in series	1
Cells in parallel	1


6.4. Sequence

Step	Step1	Step2
Mode	RUN	STOP UDM (Under Drive)
Vdd	3.3	3.3
Voltage Source	Battery	Battery
Range	Scale1-High	No Scale
Fetch Type	ICTM FLASH-SingleBank REGON	n/a
CPU Frequency	216 MHz	0 Hz
Clock Configuration	HSE PLL	Regulator LP Flash-PwrDwn
Clock Source Frequency	4 MHz	0 Hz
Peripherals		
Additional Cons.	0 mA	0 mA
Average Current	118 mA	130 μ A
Duration	0.1 ms	0.9 ms
DMIPS	462.0	0.0
Ta Max	89.42	104.98
Category	In DS Table	In DS Table

6.5. Results

Sequence Time	1 ms	Average Current	11.92 mA
Battery Life	2 days, 4 hours	Average DMIPS	462.24005 DMIPS

6.6. Chart



7. Peripherals and Middlewares Configuration

7.1. ADC1

mode: IN0

mode: IN9

7.1.1. Parameter Settings:

ADCs_Common_Settings:

Mode	Independent mode
ADC_Settings:	
Clock Prescaler	PCLK2 divided by 4
Resolution	12 bits (15 ADC Clock cycles)
Data Alignment	Right alignment
Scan Conversion Mode	Disabled
Continuous Conversion Mode	Disabled
Discontinuous Conversion Mode	Disabled
DMA Continuous Requests	Disabled
End Of Conversion Selection	EOC flag at the end of single channel conversion

ADC_Regular_ConversionMode:

Number Of Conversion	1
External Trigger Conversion Source	Regular Conversion launched by software
External Trigger Conversion Edge	None
<u>Rank</u>	1
Channel	Channel 0
Sampling Time	3 Cycles

ADC_Injected_ConversionMode:

Number Of Conversions	0
-----------------------	---

WatchDog:

Enable Analog WatchDog Mode	false
-----------------------------	-------

7.2. DAC

mode: OUT1 Configuration

7.2.1. Parameter Settings:

DAC Out1 Settings:

Output Buffer	Enable
Trigger	None

7.3. I2C1

I2C: I2C

7.3.1. Parameter Settings:

Timing configuration:

I2C Speed Mode	Standard Mode
I2C Speed Frequency (KHz)	100
Rise Time (ns)	0
Fall Time (ns)	0
Coefficient of Digital Filter	0
Analog Filter	Enabled
Timing	0x20404768 *

Slave Features:

Clock No Stretch Mode	Disabled
General Call Address Detection	Enabled *
Primary Address Length selection	7-bit
Dual Address Acknowledged	Disabled
Primary slave address	0

7.4. RCC

High Speed Clock (HSE): BYPASS Clock Source

7.4.1. Parameter Settings:

System Parameters:

VDD voltage (V)	3.3
Flash Latency(WS)	7 WS (8 CPU cycle)

RCC Parameters:

HSI Calibration Value	16
TIM Prescaler Selection	Disabled
HSE Startup Timeout Value (ms)	100
LSE Startup Timeout Value (ms)	5000

Power Parameters:

Power Over Drive	Enabled
Power Regulator Voltage Scale	Power Regulator Voltage Scale 1

7.5. SPI1

Mode: Full-Duplex Master

7.5.1. Parameter Settings:

Basic Parameters:

Frame Format	Motorola
Data Size	4 Bits
First Bit	MSB First

Clock Parameters:

Prescaler (for Baud Rate)	2
Baud Rate	54.0 MBits/s *
Clock Polarity (CPOL)	Low
Clock Phase (CPHA)	1 Edge

Advanced Parameters:

CRC Calculation	Disabled
NSSP Mode	Enabled
NSS Signal Type	Software

7.6. SYS

Timebase Source: SysTick

7.7. UART4

Mode: Asynchronous

7.7.1. Parameter Settings:

Basic Parameters:

Baud Rate	115200
Word Length	8 Bits (including Parity)
Parity	None
Stop Bits	1

Advanced Parameters:

Data Direction	Receive and Transmit
Over Sampling	16 Samples
Single Sample	Disable

Advanced Features:

Auto Baudrate	Disable
TX Pin Active Level Inversion	Disable

RX Pin Active Level Inversion	Disable
Data Inversion	Disable
TX and RX Pins Swapping	Disable
Overrun	Enable
DMA on RX Error	Enable
MSB First	Disable

7.8. USART6

Mode: Asynchronous

7.8.1. Parameter Settings:

Basic Parameters:

Baud Rate	115200
Word Length	8 Bits (including Parity)
Parity	None
Stop Bits	1

Advanced Parameters:

Data Direction	Receive and Transmit
Over Sampling	16 Samples
Single Sample	Disable

Advanced Features:

Auto Baudrate	Disable
TX Pin Active Level Inversion	Disable
RX Pin Active Level Inversion	Disable
Data Inversion	Disable
TX and RX Pins Swapping	Disable
Overrun	Enable
DMA on RX Error	Enable
MSB First	Disable

7.9. USB_OTG_FS

Mode: Device_Only

7.9.1. Parameter Settings:

Speed	Device Full Speed 12MBit/s
Low power	Disabled
Link Power Management	Disabled
VBUS sensing	Disabled

Signal start of frame

Disabled

7.10. USB_DEVICE

Class For FS IP: Communication Device Class (Virtual Port Com)

7.10.1. Parameter Settings:

Basic Parameters:

USBD_MAX_NUM_INTERFACES (Maximum number of supported interfaces)	1
USBD_MAX_NUM_CONFIGURATION (Maximum number of supported configuration)	1
USBD_MAX_STR_DESC_SIZ (Maximum size for the string descriptors)	512
USBD_SELF_POWERED (Enabled self power)	Enabled
USBD_DEBUG_LEVEL (USBD Debug Level)	0: No debug message
USBD_LPM_ENABLED (Link Power Management)	1: Link Power Management supported

Class Parameters:

USB CDC Rx Buffer Size	2048
USB CDC Tx Buffer Size	2048

7.10.2. Device Descriptor:

Device Descriptor:

VID (Vendor Identifier)	1155
LANGID_STRING (Language Identifier)	English(United States)
MANUFACTURER_STRING (Manufacturer Identifier)	STMicroelectronics

Device Descriptor FS:

PID (Product Identifier)	22336
PRODUCT_STRING (Product Identifier)	STM32 Virtual ComPort
CONFIGURATION_STRING (Configuration Identifier)	CDC Config
INTERFACE_STRING (Interface Identifier)	CDC Interface

* User modified value

8. System Configuration

8.1. GPIO configuration

IP	Pin	Signal	GPIO mode	GPIO pull/up pull down	Max Speed	User Label
ADC1	PA0/WKUP	ADC1_IN0	Analog mode	No pull-up and no pull-down	n/a	
	PB1	ADC1_IN9	Analog mode	No pull-up and no pull-down	n/a	
DAC	PA4	DAC_OUT1	Analog mode	No pull-up and no pull-down	n/a	
I2C1	PB6	I2C1_SCL	Alternate Function Open Drain	Pull-up	Very High *	
	PB9	I2C1_SDA	Alternate Function Open Drain	Pull-up	Very High *	
RCC	PH0/OSC_IN	RCC_OSC_IN	n/a	n/a	n/a	MCO [STM32F103CBT6_PA8]
	PH1/OSC_OUT	RCC_OSC_OUT	n/a	n/a	n/a	
SPI1	PA5	SPI1_SCK	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	
	PA6	SPI1_MISO	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	
	PD7	SPI1_MOSI	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	
UART4	PC10	UART4_TX	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	
	PC11	UART4_RX	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	
USART6	PC6	USART6_TX	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	
	PC7	USART6_RX	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	
USB_OTG_FS	PA11	USB_OTG_FS_DM	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	USB_DM
	PA12	USB_OTG_FS_DP	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	USB_DP
Single Mapped Signals	PC14/OSC32_IN	RCC_OSC32_IN	n/a	n/a	n/a	
	PC15/OSC32_OUT	RCC_OSC32_OUT	n/a	n/a	n/a	
	PC1	ETH_MDC	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	RMII_MDC [LAN8742A-CZ-TR_MDC]

IP	Pin	Signal	GPIO mode	GPIO pull/up pull down	Max Speed	User Label
	PA1	ETH_REF_CLK	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	RMII_REF_CLK [LAN8742A-CZ-TR_REFCLK0]
	PA2	ETH_MDIO	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	RMII_MDIO [LAN8742A-CZ-TR_MDIO]
	PA7	ETH_CRS_DV	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	RMII_CRS_DV [LAN8742A-CZ-TR_CRS_DV]
	PC4	ETH_RXD0	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	RMII_RXD0 [LAN8742A-CZ-TR_RXD0]
	PC5	ETH_RXD1	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	RMII_RXD1 [LAN8742A-CZ-TR_RXD1]
	PB13	ETH_TXD1	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	RMII_TXD1 [LAN8742A-CZ-TR_TXD1]
	PD8	USART3_TX	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	STLK_RX [STM32F103CBT6_PA3]
	PD9	USART3_RX	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	STLK_TX [STM32F103CBT6_PA2]
	PA8	USB_OTG_FS_SOF	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	USB_SOF [TP1]
	PA13	SYS_JTMS-SWDIO	n/a	n/a	n/a	TMS
	PA14	SYS_JTCK-SWCLK	n/a	n/a	n/a	TCK
	PG11	ETH_TX_EN	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	RMII_TX_EN [LAN8742A-CZ-TR_TXEN]
	PG13	ETH_TXD0	Alternate Function Push Pull	No pull-up and no pull-down	Very High *	RMII_TXD0 [LAN8742A-CZ-TR_TXD0]
	PB3	SYS_JTDO-SWO	n/a	n/a	n/a	SW0
GPIO	PC13	GPIO_EXTI13	External Interrupt Mode with Rising edge trigger detection	No pull-up and no pull-down	n/a	USER_Btn [B1]
	PB0	GPIO_Output	Output Push Pull	No pull-up and no pull-down	Low	LD1 [Green]
	PB14	GPIO_Output	Output Push Pull	No pull-up and no pull-down	Low	LD3 [Red]
	PG6	GPIO_Output	Output Push Pull	No pull-up and no pull-down	Low	USB_PowerSwitchOn [STMP2151STR_EN]
	PG7	GPIO_Input	Input mode	No pull-up and no pull-down	n/a	USB_OverCurrent [STMP2151STR_FAULT]
	PB7	GPIO_Output	Output Push Pull	No pull-up and no pull-down	Low	LD2 [Blue]

8.2. DMA configuration

DMA request	Stream	Direction	Priority
USART6_RX	DMA2_Stream1	Peripheral To Memory	Low
USART6_TX	DMA2_Stream6	Memory To Peripheral	Low
UART4_RX	DMA1_Stream2	Peripheral To Memory	Low
UART4_TX	DMA1_Stream4	Memory To Peripheral	Low

USART6_RX: DMA2_Stream1 DMA request Settings:

Mode: Normal
 Use fifo: **Enable ***
 FIFO Threshold: Full
 Peripheral Increment: Disable
 Memory Increment: **Enable ***
 Peripheral Data Width: Byte
 Memory Data Width: Byte
 Peripheral Burst Size: Single
 Memory Burst Size: Single

USART6_TX: DMA2_Stream6 DMA request Settings:

Mode: Normal
 Use fifo: **Enable ***
 FIFO Threshold: Full
 Peripheral Increment: Disable
 Memory Increment: **Enable ***
 Peripheral Data Width: Byte
 Memory Data Width: Byte
 Peripheral Burst Size: Single
 Memory Burst Size: Single

UART4_RX: DMA1_Stream2 DMA request Settings:

Mode: Normal
 Use fifo: **Enable ***
 FIFO Threshold: Full
 Peripheral Increment: Disable
 Memory Increment: **Enable ***

Peripheral Data Width: Byte
Memory Data Width: Byte
Peripheral Burst Size: Single
Memory Burst Size: Single

UART4_TX: DMA1_Stream4 DMA request Settings:

Mode: Normal
Use fifo: **Enable ***
FIFO Threshold: Full
Peripheral Increment: Disable
Memory Increment: **Enable ***
Peripheral Data Width: Byte
Memory Data Width: Byte
Peripheral Burst Size: Single
Memory Burst Size: Single

8.3. NVIC configuration

8.3.1. NVIC

Interrupt Table	Enable	Preenmption Priority	SubPriority
Non maskable interrupt	true	0	0
Hard fault interrupt	true	0	0
Memory management fault	true	0	0
Pre-fetch fault, memory access fault	true	0	0
Undefined instruction or illegal state	true	0	0
System service call via SWI instruction	true	0	0
Debug monitor	true	0	0
Pendable request for system service	true	0	0
System tick timer	true	0	0
DMA1 stream2 global interrupt	true	0	0
DMA1 stream4 global interrupt	true	0	0
UART4 global interrupt	true	0	0
DMA2 stream1 global interrupt	true	0	0
USB On The Go FS global interrupt	true	0	0
DMA2 stream6 global interrupt	true	0	0
USART6 global interrupt	true	0	0
PVD interrupt through EXTI line 16	unused		
Flash global interrupt	unused		
RCC global interrupt	unused		
ADC1, ADC2 and ADC3 global interrupts	unused		
I2C1 event interrupt	unused		
I2C1 error interrupt	unused		
SPI1 global interrupt	unused		
EXTI line[15:10] interrupts	unused		
TIM6 global interrupt, DAC1 and DAC2 underrun error interrupts	unused		
FPU global interrupt	unused		

8.3.2. NVIC Code generation

Enabled interrupt Table	Select for init sequence ordering	Generate IRQ handler	Call HAL handler
Non maskable interrupt	false	true	false
Hard fault interrupt	false	true	false
Memory management fault	false	true	false
Pre-fetch fault, memory access fault	false	true	false
Undefined instruction or illegal state	false	true	false
System service call via SWI instruction	false	true	false

Enabled interrupt Table	Select for init sequence ordering	Generate IRQ handler	Call HAL handler
Debug monitor	false	true	false
Pendable request for system service	false	true	false
System tick timer	false	true	true
DMA1 stream2 global interrupt	false	true	true
DMA1 stream4 global interrupt	false	true	true
UART4 global interrupt	false	true	true
DMA2 stream1 global interrupt	false	true	true
USB On The Go FS global interrupt	false	true	true
DMA2 stream6 global interrupt	false	true	true
USART6 global interrupt	false	true	true

* User modified value

9. System Views

9.1. Category view

9.1.1. Current

10. Docs & Resources

Type	Link
Datasheet	http://www.st.com/resource/en/datasheet/DM00273119.pdf
Reference manual	http://www.st.com/resource/en/reference_manual/DM00224583.pdf
Programming manual	http://www.st.com/resource/en/programming_manual/DM00237416.pdf
Errata sheet	http://www.st.com/resource/en/errata_sheet/DM00257543.pdf
Application note	http://www.st.com/resource/en/application_note/CD00167594.pdf
Application note	http://www.st.com/resource/en/application_note/CD00211314.pdf
Application note	http://www.st.com/resource/en/application_note/CD00259245.pdf
Application note	http://www.st.com/resource/en/application_note/CD00264321.pdf
Application note	http://www.st.com/resource/en/application_note/CD00264342.pdf
Application note	http://www.st.com/resource/en/application_note/CD00264379.pdf
Application note	http://www.st.com/resource/en/application_note/DM00042534.pdf
Application note	http://www.st.com/resource/en/application_note/DM00046011.pdf
Application note	http://www.st.com/resource/en/application_note/DM00072315.pdf
Application note	http://www.st.com/resource/en/application_note/DM00073742.pdf
Application note	http://www.st.com/resource/en/application_note/DM00073853.pdf
Application note	http://www.st.com/resource/en/application_note/DM00080497.pdf
Application note	http://www.st.com/resource/en/application_note/DM00081379.pdf
Application note	http://www.st.com/resource/en/application_note/DM00129215.pdf
Application note	http://www.st.com/resource/en/application_note/DM00160482.pdf
Application note	http://www.st.com/resource/en/application_note/DM00164538.pdf
Application note	http://www.st.com/resource/en/application_note/DM00164549.pdf
Application note	http://www.st.com/resource/en/application_note/DM00173083.pdf
Application note	http://www.st.com/resource/en/application_note/DM00210367.pdf
Application note	http://www.st.com/resource/en/application_note/DM00220769.pdf
Application note	http://www.st.com/resource/en/application_note/DM00227538.pdf

Application note http://www.st.com/resource/en/application_note/DM00257177.pdf
Application note http://www.st.com/resource/en/application_note/DM00272912.pdf
Application note http://www.st.com/resource/en/application_note/DM00272913.pdf
Application note http://www.st.com/resource/en/application_note/DM00226326.pdf
Application note http://www.st.com/resource/en/application_note/DM00236305.pdf
Application note http://www.st.com/resource/en/application_note/DM00281138.pdf
Application note http://www.st.com/resource/en/application_note/DM00296349.pdf
Application note http://www.st.com/resource/en/application_note/DM00327191.pdf
Application note http://www.st.com/resource/en/application_note/DM00287603.pdf
Application note http://www.st.com/resource/en/application_note/DM00337702.pdf
Application note http://www.st.com/resource/en/application_note/DM00354244.pdf
Application note http://www.st.com/resource/en/application_note/DM00373474.pdf
Application note http://www.st.com/resource/en/application_note/DM00315319.pdf
Application note http://www.st.com/resource/en/application_note/DM00380469.pdf
Application note http://www.st.com/resource/en/application_note/DM00354333.pdf
Application note http://www.st.com/resource/en/application_note/DM00395696.pdf
Application note http://www.st.com/resource/en/application_note/DM00431633.pdf
Application note http://www.st.com/resource/en/application_note/DM00493651.pdf
Application note http://www.st.com/resource/en/application_note/DM00536349.pdf
Application note http://www.st.com/resource/en/application_note/DM00600614.pdf
Application note http://www.st.com/resource/en/application_note/DM00725181.pdf