RA8P1 E-READER

Development draft – not for fabrication.
Requirements: design/ereader_requirements.md
Tracking: GitHub epic #821.



Global supplies: +3V3_MCU and GND.
Core regulator output MCU_VCORE stays local to the processor power sheet.

Remaining subsystem circuits follow epic #821 and issues #824–#834:
radio, memory/storage, USB/battery, system rails, display controller,
panel power, touch, warm/cool lighting, buttons and sensors.
No empty subsystem sheets are represented as completed circuits.

Footprint and PCB qualification are deferred by scope.

Sheet: /
File: ereader_rev1.kicad_sch
Title: RA8P1 e-reader – schematic index

Size: A3	Date: 2026-09-05	**Rev: 0.3 DRAFT**
KiCad E.D.A. 10.0.5		Id: 1/8

DRAFT: Existing processor units retained. Signal allocation and clocks/debug wiring are not yet complete.



USB-004: USB-HS analog supply / FB1 + C43
FB1: 120 ohm at 100 MHz; DCR 0.05 ohm initial max.
Screen with combined USB-HS current: I = 55.3 mA.
Vdrop = I*R = 2.765 mV; P = I^2*R = 0.153 mW.
After-test DCR 0.10 ohm: 5.53 mV / 0.306 mW.
C43: 10 uF +/-10%, 35 V X7R; initial 9..11 uF.
TDK nominal bias curve: 9.644 uF at 3.3 V.
Not transient or all-corners qualification; verify rail ramp.
Full calculations: ../design/usb_interface.md [USB-004]

RADIO-008: SPIA_C P700..P703; IRQ26=P704, IRQ19=P705.
P706=RESET_REQ_N; P707=PWR_EN. Host-domain signals.
Switched-domain isolation and reset arbitration remain open.
Pin map + conflicts: ../design/radio_interface.md#radio-008-ra8p1-host-allocation

USB-002: USB full-speed supply / U1.U17, C40.
Renesas QDG Table 1, p.6: 3.3 V with 100 nF bypass.
C40 = 100*(1 +/-0.10) = 90..110 nF initial; 50 V X7R.
Nominal DC-bias estimate: 99.45 nF at 3.3 V (PWR-001).
Place C40 close to VCC_USB with a short VSS_USB return.
Full basis + Python check: design/usb_interface.md

USB-001: R6 USBHS current-reference resistor
Renesas QDG Table 2, p.7: 2.2 kohm +/-1%.
Rmin = 2200*(1-0.01) = 2178 ohm
Rmax = 2200*(1+0.01) = 2222 ohm
Initial tolerance only; not a derived PHY current.
Full basis + Python check: design/usb_interface.md

USB-003: USB-HS supply / U1.H15, C41, C42
Renesas QDG Table 1 p.6: 10 nF ceramic + 47 uF electrolytic.
C41 = 10*(1+/-0.10) = 9..11 nF initial; 50 V X7R.
TDK nominal bias model: C41(3.3 V) = 10.084 nF (not guaranteed).
C42 = 47*(1+/-0.20) = 37.6..56.4 uF initial; 6.3 V.
Voltage screening: 3.6/6.3*100 = 57.14% rating, not rail sign-off.
C42 positive to 3V3, negative to GND; no reverse voltage.
C41 close to H15; short returns to VSS1/VSS2_USBHS.
Full math + Python / qualification: ../design/usb_interface.md

MIPI unused: AVCC_MIPI to VCC; VSS_MIPI to GND.
Leave VCC18_MIPI and all six D-PHY lanes open.
Firmware: MSTPCRC.MSTPC10=1 and MSTPC17=1.
RA8P1 HUM Rev.1.30, section 21.4, p.862.

PWR-001: C39 AVCC_MIPI bypass, 100 nF (QDG Table 2, p.7).
TDK C1608X7R1H104K080AA; also used at C6 and C16-C34.
Initial C = 100*(1 +/-0.10) = 90..110 nF; 50 V X7R.
TDK DC-bias samples: 99.5575 nF / 3.15 V; 98.9525 nF / 4 V.
C(3.3 V) = 99.5575 + (3.3-3.15)/0.85*(-0.605) = 99.45 nF.
Interpolated nominal reference, NOT a guaranteed minimum.
Final rail / PDN qualification open; 3.3/50*100 = 6.6% rating.
Full basis + Python check: design/power_decoupling.md

RA8P1 e-reader
Sheet: /RA8P1 IO allocation/
File: mcu_interfaces.kicad_sch

Title: RA8P1 IO allocation

Size: A3 | Date: 2026-09-05 | Rev: 0.3 DRAFT
KiCad E.D.A. 10.0.5 | Id: 2/8



RA8P1 e-reader

Sheet: /RA8P1 internal core regulator/

File: mcu_core_power.kicad_sch

Title: RA8P1 internal core regulator

Size: A3	Date: 2026-09-05	**Rev: 0.3 DRAFT**
KiCad E.D.A. 10.0.5		Id: 3/8

I/O DECOUPLING — 100 nF AT EACH NUMBERED VCC / VSS PAIR



VCC and VCC2 use 3.3 V. All returns use one board ground plane.
VBATT follows the main rail; no separate backup-cell supply.
Analog references use AVCC0 / AVSS0. Place bypasses at named ball pairs.
USB/MIPI supplies remain on the interface sheet and are not yet wired.
HUM Rev.1.30: Table 69.2 p.4042; unused references: section 21.4 pp.861–862.
This is an electrical draft; capacitor MPN qualification remains open.

RA8P1 e-reader
Sheet: /RA8P1 IO and analog supplies/
File: mcu_supply_power.kicad_sch

Title: RA8P1 I/O and analog supplies

Size: A3	Date: 2026-09-05	**Rev: 0.3 DRAFT**
KiCad E.D.A. 10.0.5		Id: 4/8



CLK-001: Y1 24 MHz / Murata XRCGB24M000F3M19R0
Crystal CL = 6 pF; effective Cstray = 2 pF ASSUMED.
CL = C35*C36/(C35+C36) + Cstray
C35 = C36 = 2*(6-2) = 8 pF (NP0, +/-0.5 pF).
Check: 8*8/(8+8) + 2 = 6 pF. At fixed stray: 5.75..6.25 pF.
Different crystal or changed parasitics: recalculate and rematch.
Initial matching only: verify frequency, startup and drive <= 300 uW.
Full derivation + Python check: ../design/clock_calculations.md

CLK-002: Y2 ABS07-LR-32.768KHZ-6-1-T
Crystal CL=6 pF; Cstray=4 pF ASSUMED.
CL=C37*C38/(C37+C38)+Cstray
C37=C38=2*(6-4)=4 pF, +/-0.25 pF NP0.
Check: 4*4/(4+4)+4=6 pF.
Fixed-stray tolerance: 5.875..6.125 pF.
Initial mode: SODRV=10b; SOSEL=0.
Qualify startup, frequency, drive <=0.5 uW.
Full math/Python: ../design/clock_calculations.md



RST-001: U2 supervises +3V3_MCU; TP1 is internal MR service access.
CT open: release delay 12..28 ms; 12/2.4 = 5x MCU minimum.
Falling threshold = 3.07*(1 +/- 0.015) = 3.02395..3.11605 V.
Conservative release screen = 3.11605*1.025 = 3.19395125 V.
ASSUMED rail +/-2%: 3.3*0.98 - 3.19395125 = 40.05 mV margin.
R1 worst pull-up current = 3.6/9900 = 0.364 mA < 1 mA.
RES low margin = 0.2*3.02395 - 0.4 = 0.20479 V.
No RES capacitor; open-drain reset drivers only.
External RES startup path; do not assume internal POR flag.
Full math, limits and Python: design/boot_and_debug.md RST-001.

References: RA8P1 HUM Rev.1.30 sections 2.5, 4.3-4.4, 21.4.
Quick Design Guide R01AN7883EU0110 sections 2 and 6.
Reset timing: RA8P1 Datasheet Rev.1.30 Table 2.52 p.118.
Exact purchasing selections and status are maintained in the BOM.

Sheet: /RA8P1 clocks, reset and debug/
File: mcu_clocks_debug.kicad_sch

Title: RA8P1 clocks, reset and debug

Size: A3 | Date: 2026-09-05 | **Rev: 0.3 DRAFT**
KiCad E.D.A. 10.0.5 | Id: 5/8



RADIO-016: SPI_IO_EN = C6_EN AND RADIO_PWR_EN
R9 bounds: 9.801k..10.201k (1%, 100ppm/K, 100K).
Ihigh <= 3.6/9801 + 12uA = 0.379309mA.
3V test-point margins: 2.4-1.92=0.48V high;
0.89-0.45=0.44V low. Full-rail sequencing OPEN.
12uA/node allocation includes U8; other loads unqualified.
Calculations: ../design/radio_interface.md#radio-016-spi-output-enable-arbitration

RADIO-012: C52 / U6 reset-release delay
C52 = 1nF +/-5% NP0, CT to GND (not VIN).
At 100 C excursion, +/-30 ppm/C: 947.15..1053.15 pF.
tnom = 1nF*1.23V/1.15uA + 25us = 1.094565 ms.
Allocate +/-10nA external CT leakage; start discharged.
tcharge_min = 947.15pF*1.17V/1.36uA = 814.828 us.
tcharge_max = 1053.15pF*1.29V/0.89uA = 1526.476 us.
Charge-only screen, NOT total reset min/max limits.
C6 requires 50us stable supply and 50us reset low.
Complete reset sequencing remains open.
Math: ../design/radio_interface.md#radio-012-supervisor-reset-release-delay







RADIO-003: C46 bulk bypass / TDK C3216X7R1V106K160AC
10 uF nominal, +/-10%, X7R; DC bias reduces capacitance.
C(3.3 V) = 9.69875 + (3.3-3.15)/0.85*(9.38950-9.69875)
= 9.64418 uF; C(3.6 V) = 9.53503 uF (nominal).
Source curve interpolation, NOT a guaranteed minimum.
Rail: 3.0..3.6 V; source capability >= 0.5 A.
Supply and transmit transient qualification remain required.
Calculations: ../design/radio_interface.md#radio-003-bulk-capacitance

RADIO-014: R12/R13 switched-radio sense divider
33.2k / 20k; Susumu RG, 0.1%, 25ppm/C.
Allocate deltaT=100 C, 0.15% drift, +/-150nA total.
fmin/max=(1 +/-0.001)*(1 +/-0.0025)*(1 +/-0.0015)
= 0.99500774625 / 1.00500775375.
Vtrip = Vsense*(1+Rt/Rb) + Is*Rt.
Vfall >=1.15*0.99*(1+Rtmin/Rbmax)-150nA*Rtmax
= 3.004600 V; margin above 3V only 4.600mV.
Vrise <=1.15*1.01*1.00825*(1+Rtmax/Rbmin)
+150nA*Rtmax = 3.139622 V.
PWR-002 release headroom: 14.923mV, static only.
Idiv_nom=3.3/53.2k=62.030uA; each P <0.652mW.
MR arbitration and brownout dynamics remain open.
Math: ../design/radio_interface.md (RADIO-014)



RADIO-009: U5 isolates host and switched-radio signal domains.
C49/C50: 100 nF local bypass; TI TXU0304 section 12.1.
C50 adds 0.1 uF: fitted external radio capacitance = 10.2 uF nominal.
5 MHz budget: 100 - 11 - 11 = 78 ns remaining (5 pF test load).
SPI/OE and reset qualification remain open; timing is not closed.
Math: ../design/radio_interface.md#radio-009-spi-power-domain-isolation



PWR-002: upstream regulator / reset voltage budget
TPS63802 candidate: +/-1% feedback applies in PWM mode.
Example 56k/10k, 0.1%, 25 ppm/C; deltaT=100 C.
Vout = Vfb*(1+Rt/Rb) + Ib*Rt; allocate +/-100 nA.
PWM static screen: 3.242044..3.358485 V.
Radio: 3.242044 - 0.5 A*0.175 ohm = 3.154544 V.
Above U6 RADIO-014 rising screen: 14.923 mV remains.
MCU reset release headroom: 48.093 mV.
Not a transient guarantee; regulator circuit not fitted.
Math: ../design/power_decoupling.md (PWR-002)

RADIO-010: R9/R10 idle-state bias, 10k 1%
Rmin/max = 10k*(1 +/-1%)*(1 +/-1%) = 9801/10201 ohm.
12 uA adverse leakage is an ALLOCATION, not measured.
R9: Vlow = 12u*10201 = 0.122412 V.
TI VT- min = 0.17 V at the 1.1 V equal-rail test point.
R10 @3.3 V: VCS >=3.177588 V > VIH 2.475 V (25 C).
R9 enabled current = 3.3/10k = 0.330 mA.
R10 draws similar current only while CS is low.
OE arbitration, all-state leakage and timing remain open.
Math: ../design/radio_interface.md#radio-010-idle-state-bias

RADIO-004: U4 TPS22917DBVT / radio power gating
QOD tied to VOUT: Rdis = 150 ohm TYPICAL.
C45+C46+C50 = 0.1+10+0.1 = 10.2 uF nominal external load.
t90..10 = ln(9)*150*10.2u = 3.362 ms (ideal RC).
Not a guaranteed off-time: module C/load and VIN decay matter.
C48 connects CT to VIN, not GND; 50 V rating >=7 V required.
Reset/isolation and upstream regulator remain incomplete.
Load update: RADIO-009; device limits: RADIO-004.
Math: ../design/radio_interface.md#radio-009-spi-power-domain-isolation

RADIO-006: R7/R8 / active-high enable, default OFF
R7 series = R8 pulldown = 10k 1%; +/-2% screening envelope.
TPS22917 ON: low <=0.35 V; high >=1.0 V.
Assume node leakage <=10 uA and host VOL<=0.5 V, VOH>=2.5 V.
Rparallel <=5.1k; divider fraction = 0.49..0.51.
Vlow <=0.5*0.51+10u*5.1k = 0.306 V <0.35 V.
Vhigh >=2.5*0.49-10u*5.1k = 1.174 V >1.0 V.
Hi-Z screen: 10u*10.2k = 0.102 V; disable host pull-up.
Host pin, all power states, leakage and timing need qualification.
Full math: ../design/radio_interface.md#radio-006-enable-divider

RADIO-013: R11 / C6_EN reset pull-up
10k 1%, 100ppm/C; deltaT=100 C allocation.
Rmin/max=10k*(1 +/-1%)*(1 +/-1%)=9801/10201 ohm.
Allocate +/-12uA total adverse node leakage.
Isink <=3.6/9801+12uA=0.379310mA <0.4mA.
U6 VOL<=0.25V at 0.4mA, VDD>=1.5V.
At C6 table point 3.3V, 25 C:
VEN>=3.3-12uA*10201=3.177588V >2.475V VIH.
VIL=0.825V; low margin=0.825-0.25=0.575V.
Pmax=3.6^2/9801=1.322314mW.
MR arbitration, power states and timing remain open.
Math: ../design/radio_interface.md (RADIO-013)

RADIO-005: C47 / U4 VIN local bypass
10 uF nominal, +/-10%, 35 V X7R; same exact TDK part as C46.
C(3.3 V) = 9.69875 + (3.3-3.15)/0.85*(9.38950-9.69875)
= 9.64418 uF nominal; NOT a guaranteed minimum.
Droop = integral(Iload-Isource)dt / Ceff + ESR/ESL effects.
TI section 11: 1 uF usually sufficient; slow sources may need more.
C47 is upstream: exclude it from C45+C46 output-discharge math.
Regulator/transient qualification required; no source flag added.
Calculations: ../design/radio_interface.md#radio-005-input-bypass



RADIO-015: U7 Schmitt-input reset arbitration
IN1=GND: Y = MCU_RESET_N AND RADIO_RESET_REQ_N.
Either low asserts U6 MR; C53 = 100nF MCU-rail bypass.
R14: Rmin/max=10k*(1 +/-1%)*(1 +/-1%)=9801/10201 ohm.
12uA adverse-current ALLOCATION: Vlow <= 0.122412 V.
At U7 3V test point: VT-_min-Vlow = 0.717588 V.
At 3.6V: I_R14 <= 0.367309 mA; P <= 1.322314 mW.
If |I_U7out|<=100uA: MR low/high margins >=0.65/0.8V
on shared 3.0-3.6V rail. MR load bound NOT yet verified.
Reset hierarchy connected; full-rail thresholds/sequencing open.
Math: ../design/radio_interface.md#radio-015-reset-request-arbitration

RADIO-007: C48 / CT slew-rate control, TDK C1608NP01H102J080AA
1nF +/-5%, 50 V NP0; CT-to-VIN, NOT CT-to-GND.
TI 3.6 V / 25 C TYPICAL table point, not guaranteed at 3.3 V:
Slew = 1900/1000 = 1.9 mV/us; tON = 3.8*1000 = 3.8 ms.
tR(10..90%) = 1.6*1000 = 1.6 ms (TI test load).
C45+C46+C50 = 10.2 uF: Icap = C*dV/dt = 19.38 mA.
Open-CT comparison: 10.2u*44mV/us = 448.8 mA (typical).
Total inrush also includes module C/load and future rail parts.
Not a current limiter or reset delay; startup qualification required.
Timing model: RADIO-007; updated load: RADIO-009.
Full math: ../design/radio_interface.md#radio-009-spi-power-domain-isolation

RADIO-017: R15/R16/R17 boot/debug strap pull-ups to switched radio rail.
Flash boot: GPIO9=1. Download: GPIO8=1, GPIO9=0; service pads TP3 (RADIO-018).
GPIO15=1 selects USB JTAG with applicable eFuses; retain straps >=3ms after EN rises.
Rmin/max=10k*(1+/-1%)*(1+/-100ppm/K*100K)=9801/10201 ohm.
At 3.3V: Vhigh>=3.3-12uA*10201=3.177588V; VIH=2.475V; margin=0.702588V.
External low-state current<=3.6/9801=0.367309mA each; P<=1.322314mW each.
12uA total/node is an allocation. Internal pull-up sink current and full-state timing OPEN.
Math: ../design/radio_interface.md#radio-017-boot-and-debug-strap-bias

RADIO-018: TP3 internal C6 BOOT service pads; no fitted switch.
Fixture shorts pad 1 (GPIO9) to pad 2 (GND); GPIO8 must be high.
Hold GPIO9 low before C6_EN rises and >=3ms after C6_EN rises.
R16 external current <=3.6/9801=0.367309mA; add internal pull-up.
Fixture ALLOCATION: total sink <=1mA and path <=1ohm => Vlow<=1mV.
At 3.3V: low margin=0.25*3.3-0.001=0.824V (screen only).
Host-independent radio power/reset arbitration remains to be connected.
Math: ../design/radio_interface.md#radio-018-internal-boot-service-pads

Incomplete electrical design - not for manufacture

Sheet: /ESP32-C6 radio/
File: radio_esp32.kicad_sch

Title: ESP32-C6 radio

Size: A3	Date: 2026-09-05	Rev: DRAFT
KiCad E.D.A. 10.0.5		Id: 6/8



INCOMPLETE POWER CONTROL – NOT FOR FABRICATION
PB, INT, KILL, held supply and source supervisor are connected.
SYS_AON has no source; MAIN_PWR_EN has no converter load yet.
Fault–to–KILL clamp and main–rail discharge remain to be implemented.
Power–control operation is not yet complete or qualified.
Implementation and qualification: ../design/system_power_design.md
SYS–007; button calculations: ../design/single_button_power.md.

ERC supply path: U10 VOUT through R31.
PWR_FLAG declares that series–fed source only;
raw SYS_AON source remains unimplemented.



BTN–003: POWER–KEY INPUT / R18, R19, C56, SW1
R18=10k; R19=1k; C56=100nF. SYS_AON screen=3.0..4.6V.
R bounds: nominal*(0.99*0.99)..nominal*(1.01*1.01).
At PB=0.6V: Isource<=(4.6–0.6)/9801 + 15uA + 12uA
<435.13uA; Isink=0.6/(1020.1+0.5)>587.88uA.
Thus the closed switch pulls PB below its 0.6V falling threshold.
Min contact current=3/(10201+1020.1+0.5)–12uA>255.34uA.
Open contact>=2.87748V; SW1 minimum rating=10uA at 2V.
C56 discharge peak<=4.6/980.1<4.694mA < SW1 50mA rating.
12uA is a leakage ALLOCATION; ESD/transient validation required.
Full derivation + Python: ../design/single_button_power.md BTN–003/005/010.

SYS–007 REVISED: HELD SUPPLY / U10, R31, C62–C66
C63–C66: 4 x 100uF/10V; Cmin=400uF*0.9^3=291.6uF.
VIN=raw SYS; VOUT–>R31–>reservoir; CE senses reservoir.
Icontrol<=1.125mA incl 500uA bank leakage allocation.
Pre–trip reverse: 80mV/98.01ohm<0.817mA. Itotal=1.942mA.
Vinitial=3.263705831–max(0.250,0.001125*102.24)
=3.013705831V (threshold OR resistive–drop limit).
t_hold=[291.6uF*(3.013705831–2.7)V–1uC]/1.942mA
=46.589ms >38.380ms shutdown allocation.
1uC covers initial undershoot + reverse/gate transitions.
Qualify VIN=0..4.6V, slow/floating–source collapse and load.
R31 short: 4.6^2/98.01<0.216W; 1W nominal rating.
Control only: no MCU/audio/display loads on AON_HOLD.
Full assumptions and Python: ../design/system_power_design.md SYS–007.

BTN–004: HARDWARE FORCED–OFF TIMING / C57
C57=1uF; TDK C2012X7R1E105K125AB, 25V X7R +/–10%.
C[uF]=1.56e–4*(t_added[ms]–1).
t_force,nom=64ms + 1ms + 1/1.56e–4=6475.256ms (6.48s).
C tolerance/temp only: 1*0.90*0.85=0.765uF;
1*1.10*1.15=1.265uF –> 4.969..8.174s using NOMINAL IC equation.
Not guaranteed timing: excludes IC spread, DC bias, aging, leakage.
ONT intentionally open: internal turn–on debounce=26..41ms.
Release the initial ON press; after forced off, release then press again.
Full calculation + Python: ../design/single_button_power.md BTN–004/005.



SYS–007: SOURCE SUPERVISION / U11, R32–R34, C67–C71
Vtrip=Vref*(1+R32/R33)+Isense*R32.
Nominal=0.405*(1+732k/100k)=3.369600V.
Vref +/–2%, Isense +/–25nA; each R +/–0.1%, 25ppm/C, 100C.
Corner trip=3.263705831..3.476597632V.
C68: tau=(732k||100k)*1n=87.980769us (nominal).
C69–C71: 3x100n C0G; initial/temp=284.145..316.827nF.
CT delay=300/175+0.0005=1.714786s nominal.
0.6*(284.145/175+0.0005)=0.974511s MODEL, not guarantee.
Require qualified reset hold >=0.90s >650ms KILL blank +10ms.
R34: ENhigh>=2.7–3uA*(100k*1.01*1.01)=2.393970V.
ENlow<=0.4V; TPS63802 thresholds 1.13V rise/0.97V fall.
No additional exposed button; fault clamp/latch clear still needed.
Full math, Python and qualification: ../design/system_power_design.md SYS–007.

Sheet: /Power button and source control/
File: power_button.kicad_sch

Title: RA8P1 E-reader – power button and source control

Size: A3	Date: 2026-09-07	Rev: 0.3 DRAFT
KiCad E.D.A. 10.0.5		Id: 7/8



CMS−009 − FOUR INDEPENDENT PAGE / VOLUME KEYS
SW2..SW5; R23..R26=1k; R27..R30=10k; C58..C61=100n.
D2..D5: ESD441DPYR, IO1 / GND2, before series resistors.
VCC=+3V3_MCU: 3.0..3.6V screening envelope.
Resistors: +/−1%, plus +/−100ppm/C over 100C.
RPU=10k*(0.99^2..1.01^2)=9801..10201 ohm.
RS=1k*(0.99^2..1.01^2)=980.1..1020.1 ohm.
Contact <=0.5 ohm; adverse leakage allocation=2.2uA/key:
1uA MCU +0.1uA TVS +0.1uA capacitor +1uA board.
Capacitor and board leakage terms are design allowances.

VLOW=(VCC/RPU+Ileak)/(1/RPU+1/(RS+Rcontact)).
Worst screened VLOW<0.342V; correlated VIL margin>0.315V.
VHIGH>=3−2.2uA*10201=2.9775578V; VIH margin>0.57755V.
Icontact>=3/(10201+1020.6)−2.2uA >265.14uA.
Open contact>2.97745V: switch minimum load=10uA at 2V.
Peak capacitor discharge<3.6/980.1=3.674mA (<50mA).
Four keys held: 4*(3.6/(9801+980.1)+2.2uA)<1.345mA.

Full derivation, corner enumeration and verified Python:
../design/camera_storage_interfaces.md CMS−009.

CMS−009 − FILTER TIMING AND BUTTON BEHAVIOR
C58..C61: TDK C1608X7R1H104K080AA, 100nF, X7R, 50V.
Tolerance / temperature−only capacitance bounds:
Cmin=100n*0.90*0.85=76.5nF; Cmax=100n*1.10*1.15=126.5nF.
DC bias and aging excluded; qualify effective capacitance.

Nominal tau_assert=(10k||1k)*100n=0.090909ms.
t_assert=−tau_assert*ln[(0.2−1/11)/(1−1/11)]=0.193ms.
t_release=−10k*100n*ln[(1−0.8)/(1−1/11)]=1.514ms.
RC filters noise; it does NOT provide complete debounce.
Require 20ms continuously stable state; switch bounce<=10ms.
IRQ starts wake/debounce, not an immediate page/volume action.

Opposing page or volume keys cancel their associated action.
Ignore boot−held ordinary actions until release; no auto−repeat
from a stuck key. Disable MCU internal pulls.
In hard−off, these four keys cannot start power.
The separate POWER switch controls hardware start/forced−off.
ESD441 is not a 3.3V clamp; residual MCU voltage, series
resistor pulse stress and ESD current return need physical tests.

Full corner calculations, Python and wake−register contract:
../design/camera_storage_interfaces.md CMS−009.

Sheet: /Page and volume buttons/
File: user_controls.kicad_sch

Title: RA8P1 E−reader − page and volume buttons

Size: A3 | Date: 2026-09-07 | **Rev: 0.3 DRAFT**
KiCad E.D.A. 10.0.5 | Id: 8/8