University of Nottingham
UK | CHINA | MALAYSIA

ASSESSMENT BRIEF

Aerospace Engineering

MODULE CODE	MODULE TITLE	
AERO1005	Aerospace Electronic Engineering and Computing	
ASSESSMENT NAME	**ASSESSMENT TYPE**	
Coursework 2	Individual written report	
ASSESSMENT TITLE		**WEIGHT (INDICATIVE EFFORT)**
Solving engineering problems with a programming language		30% (Approx. 20 hrs)
DEADLINE DATE	**DEADLINE TIME**	**SUBMISSION METHOD**
06 May 2026	15:00 hrs	Moodle

STAFF MEMBER RESPONSIBLE

Chung Ket Thein

FEEDBACK DETAILS

Feedback will be provided by 24/05/2026 and will consist of an individual feedback spreadsheet.

LEARNING OUTCOMES ASSESSED (IN BOLD)

LO1 - Demonstrate knowledge of the use of basic electric and electronic devices and circuits. (AHEP 1)
LO2 - Evaluate the operation and performance of relevant electrical and electronic circuits. (AHEP 2)
LO3 - Understand the concepts of computation including: the use of variables, storage in memory, data types and precision, and their linking with program flow and instruction sequence. (AHEP 1)
LO4 Demonstrate knowledge of programming workflow and development with version control. (AHEP 13)
LO5 - Apply a programming language to write programs for solving engineering problems, with knowledge of methods for data analysis and security. (AHEP 2,10)

KEY SUBMISSION REQUIREMENTS

- The main code is to be submitted in a single MATLAB script file (i.e., '.m') using the template file on the course Moodle page, under the heading: **MATLAB Coursework 2.**
- **Put your name and e-mail address at the start of the script** preceded by the '%'.
- For questions which require you to write text (i.e., descriptive sentences), or include images and graphs, please add them to the Word submission template.
- The final submission should be a .zip file of your working folder containing the .m script, .m functions and .docx Word submission template.
- The permitted use of AI is limited to the Matlab copilot tool for debug purposes. The use of AI must be disclosed in the dedicated coursework section.

NO EVIDENCE EC ELIGIBLE?[1]	EC OUTCOME
Yes	Extension up to two weeks (maximum)

Before submitting an EC, please discuss with your tutor.

SUPPORT PLAN EXTENSION[2]

If you have an existing support plan and require a support plan extension for this assessment, you should email EZ-M3-DLO@exmail.nottingham.ac.uk (including module code, assessment name, original deadline including time and requested extension length, usually one working week).

MISCONDUCT INFORMATION[3]

The work submitted must be your own work and must adhere to the University's Academic Misconduct Policy. The University considers the unauthorised use of AI tools in assessments to constitute false authorship, which is an academic offence under the Academic Misconduct Policy (Section 2.2.2). Please refer to this briefing document for more detail on where AI use is permitted for this assessment, and how to declare usage of AI tools. By submitting your work, you are acknowledging that you understand and have abided by these expectations.

[1] EC regulations: https://www.nottingham.ac.uk/qualitymanual/assessment-awards-and-deg-classification/ext-circumstances.aspx
[2] Support plans: https://www.nottingham.ac.uk/studentservices/servicedetails/disability-support-services/disability-support-services.aspx
[3] Details of the University's policy procedures on Academic Misconduct and disciplinary procedures: https://www.nottingham.ac.uk/qualitymanual/assessment-awards-and-deg-classification/pol-academic-misconduct.aspx

COMPUTING COURSEWORK 2 – SOLVING ENGINEERING PROBLEMS WITH A PROGRAMMING LANGUAGE

INTRODUCTION

This coursework will help you revise the Matlab knowledge gained in Lectures 6-10, through an Arduino used as an I/O interface. This coursework is worth 30% of the module credits and will cover the following topics:

- 2D data: matrices, plotting and extracting data
- Functions
- Input/Output to/from files and Arduino interface
- Algorithms
- Version control

Please read the Assessment Guidelines below before attempting this coursework, as well as the mark sheet given on Moodle, so you know how the marks will be awarded.

The **submission deadline** for this coursework is: **3pm Thursday 6th May 2026.**

ASSESSMENT GUIDELINES

- All code sections are to be uploaded on your git repository as Matlab script file(s) (i.e., '.m'). There will be also .m functions, .docx and .txt files to be submitted. The submission template for this file is available on the course Moodle page, under the heading: **Matlab - Coursework 2.**
- Once completed the coursework, zip your local git repository folder, containing all the requested files, and submit it to Moodle.
- **Put your name and e-mail address at the start of the script** preceded by the '%' character – the markers will use this e-mail address to give you feedback.
- Questions which require you to write text (i.e., descriptive sentences) should be included in the .docx file.
- Include comments in your script file describing what part(s) of the question you are answering (if appropriate), what the program is doing and any features of note – you will get marks for this.
- You may need or be asked to comment part of the codes while answering the questions. Don't worry, these will be uncommented and checked upon assessment.
- Save your script with a name in the following format: Firstname_Surname_studentid.m.
  For example: **Julia_Smith_13344423.m**
- Ensure that you upload before the submission deadline, as late submissions without extenuating circumstances will be penalised (minus 5 marks and additional minus 5 marks every 24 hours).
- See "Coursework 2 Markscheme.xls" on Moodle to know how marks are awarded.
  A WORD OF CAUTION – Remember this is individual work, not group work. Work handed in must be entirely your own and not copied from anyone else. Discuss the coursework with your friends if needed, but answer the questions and write the code yourself. You may be awarded 0 marks if the work is copied.

ENGINEERING PROBLEM SCENARIO

You are working at an aerospace company flying sub-orbital spacecrafts and are responsible for ensuring the comfort of passengers on board. In particular, you are tasked with developing a system that monitors the crew capsule temperature to make sure it is within the range 18-24 °C, which is a typical temperature range of comfort. When in-range, a constant green light will indicate the temperature of comfort is reached, however when the temperature is below or above the range, there will be intermittent yellow or red lights flashing, respectively. It is also important to log historical temperature data during the journey, which takes about 10 minutes and goes beyond the Kármán line (100 km altitude), to ensure the capsule temperature is not affected by the change of outside temperature.

MATERIALS

- 1 PC/laptop with MATLAB installed
- 1 Arduino UNO
- 1 USB A to USB B data cable
- 1 red LED
- 1 yellow LED
- 1 green LED
- 1 breadboard
- 2 thermistors (MCP 9700A)
- 3 220 Ω resistors
- 8 jumper wires

PRELIMINARY TASK – ARDUINO AND GIT INSTALLATION [5 MARKS]

Information and practical support on the following tasks is provided in Lecture 8 and Worksheet 8.

a) GitHub

- Create a GitHub account.
- Ensure git is installed on the computer being used (it is already installed on those in the computer lab)
- Create a repository where you will work and include the files for this project.
- Include the coursework templates .m and .docx to the repository.
- Link your current MATLAB local working folder to your repository (Right click on “current folder” area - Source Control\Manage files…).
- Include all the files in this project in your repository and/or your working folder. You can work locally or in the cloud, as long as your submitted file is your actual repository zipped folder, containing all your files and the “.git” folder. The way we check your use of git is through this hidden ".git" folder that is present in your working folder, which is your local repository. Make sure that this .git folder is included in your submission ensuring your hidden files are visible, but do not copy/paste or change the hidden properties of the folder.
- As you create your .m files, implement version control for them (Right click on the file - Source Control\Add to Git).

- As you proceed with programming, for example after writing some code or after a session of programming, commit the changes you make to your repository (Right click - Source Control\View and commit changes…).
- Synchronise your local working folder with your git repository, or, "Push", so that your files are in cloud, (Right click - Source Control\Push).
- Keep this working practice as you proceed through your coursework.
- The marks associated with the use of git are 5/100 - if you have problems using git don't let that stop you working on the coursework.
- If you have troubles when entering git username and password in Matlab, try using a "token" instead of the password.

b) MATLAB/Arduino configuration

- From the menu tab "Home", "Add-Ons", install the "MATLAB Support Package for Arduino Hardware" add-on.
- Configure the Arduino Hardware Support Package according to the prompts on-screen.
- Keep in mind the Arduino Add-on documentation contains much valuable information for your coursework tasks!

c) Arduino communication

- Open your submission template and start programming in the "PRELIMINARY TASK" section.
- Establish communication between MATLAB and Arduino. To do this, assign a variable *a* to the "Arduino()" function. In parentheses, specify the port the Arduino is connected to, and the type of Arduino used. You will be able to use this variable *a* to address the Arduino in any future command.
- Connect the GND and 5V pins of the Arduino to the ground bus "–" and to the power bus "+".
- Connect one of the LEDs to the breadboard, with the two legs on two different lines.
- Using one jumper wire, connect the line where the long LED leg sits to a digital channel of the Arduino.
- Using one 220 Ω resistor, connect the line where the short leg of the LED sits to the ground bus "-".
- In the MATLAB command line, write "*writeDigitalPin(a,'DX',1)*", where "*a*" is your initialised variable, X should be substituted with the number of the chosen digital bus, and 1 means "high" level. This will apply 5V tension to the LED, lightening it.
- Switch off the LED by using the "*writeDigitalPin(a,'DX',0)*" command, this will bring the applied voltage to the "low" level, which is 0 V.
- Now on your submission template create a loop that makes the LED blink. Use the two commands above in a *for* loop, interval with a *pause()* command, so that your program makes the LED blink at 0.5 s intervals (this means 0.5 s ON then 0.5 s OFF and so on).
- This point in time would be an appropriate one to commit your changes to your git repository – keep doing this as you move on to the next tasks!
- You have successfully made MATLAB and Arduino communicate, power an LED and write digital signals! Now you are ready to pass on to the next tasks.

TASK 1 – READ TEMPERATURE DATA, PLOT, AND WRITE TO A LOG FILE [20 MARKS]

This question lets you practice the *sprintf* and *fprintf* commands, which are used in Matlab and other programming languages. It is important to be able to format computer text output, especially when dealing with limited size displays.

Remember you can find instructions for the *sprintf* and fprintf command by typing '*doc sprintf*' and '*doc fprintf* 'in Matlab.

a) Connect the temperature sensor to the breadboard, and link its power terminals to a 5 V voltage supply and to ground, and its output terminal to one Arduino analogue channel of choice. Note that the microcontroller power supply can generate noise which disturbs the temperature reading – you may want to use a resistor to stabilise this. Include a photograph of the implementation by adding it to your Word template .docx file. You can find the Thermistor data sheet in the "MATLAB Coursework 2" section.

b) Create a variable "*duration*" with value 600 – this indicates the acquisition time in seconds. Create the arrays that will contain the acquired data. Read the voltage values from the temperature sensor approximately every 1 second for 10 minutes (the time indicated in "*duration*"). Then convert the voltage values into temperature values by using the temperature coefficient T_C and the zero-degree voltage $V_{0°C}$ which you can find in the sensor documentation. Calculate three statistical quantities over the full dataset acquired: minimum, maximum and average temperature.

c) Create a temperature/time plot with appropriate axes' titles indicating the quantity (e.g. time) and units, using the functions "*plot*", "*xlabel*" and "*ylabel*". Save the plot as an image and include it in your Word submission template.

d) This part of the program prints the recorded capsule data to a screen. Using the *sprintf* command, make Matlab print the information in the format shown in the box below. Use the date when the data was recorded, the actual location, and substitute the 'Xs' with the values you recorded/calculated. Minute 0, Minute 1 etc mean the instant at 0 seconds, at 60 seconds etc. You should be able to format the information output to the console to be exactly as shown in Table 1, including:

- Separate lines for data entries.
- Spaces between lines.
- Correct alignment of the data entries using tabs.
- Any special characters (look at the documentation!).
- Two decimal digits for temperature values (does not need to work for negative numbers).

e) Using the *fopen* command, open a file called 'capsule_temperature.txt' with writing permission. Write the same data formatted as above into the capsule_temperature.txt log file. Make sure to close the file at the end of your script. Open the generated file in Matlab using *fopen* to check that the data has been written correctly. The formatting in the .txt file should be sensible, but not necessarily identical to Table 1.

Table 1 – Output to screen formatting example

Data logging initiated - 5/3/2024
Location - Nottingham

Minute	0
Temperature	XX.XX C
Minute	1
Temperature	XX.XX C
Minute	2
Temperature	XX.XX C
Minute	3
Temperature	XX.XX C
Minute	4
Temperature	XX.XX C
Minute	5
Temperature	XX.XX C
Minute	6
Temperature	XX.XX C
Minute	7
Temperature	XX.XX C
Minute	8
Temperature	XX.XX C
Minute	9
Temperature	XX.XX C
Minute	10
Temperature	XX.XX C
Max temp	XX.XX C
Min temp	XX.XX C
Average temp	XX.XX C

Data logging terminated

TASK 2 – LED TEMPERATURE MONITORING DEVICE IMPLEMENTATION [25 MARKS]

This section will allow you to implement an LED temperature monitoring device, where a set of LEDs will blink in real-time according to the recorded temperature. You will need to build on the breadboard configuration you have developed in Task 1. When asked to write a function, the important thing is that it is submitted as a separate .m file which is called from your main CW submission .m file. The function doesn't have to return values to the main workspace and all the items in the task can be entirely included in the function file.

f) Connect the three LEDs sensor to the breadboard, link their input terminals to three Arduino digital channels of choice, and their output terminal to ground. Include a photograph of the implementation by adding it to your Word template .docx file.

g) Now you are tasked with developing a function for displaying the temperature values and controlling the LEDs according to the measured temperature. For this, you will need to continuously monitor the temperature and to power the various LEDs according to the following directives:

- When the temperature is in the range 18-24 °C, the green LED should show a constant light.
- When the temperature is below the range, the yellow LED should blink intermittently at 0.5 s intervals.
- When the temperature is above the range, the red LED should blink intermittently at 0.25 s intervals.

Continuously means, the task should progress indefinitely rather than for a specific time. Make sure the data acquisition still follows the correct timing!

Before writing any code: Draw a flowchart to outline your implementation plan for this function and add it to your Word template .docx file, indicating the decision points and the loops used.

h) Now, write the actual function "temp_monitor.m" (create a separate file and commit to your repository) which implements the logic you have outlined in your flowchart. Call the function from your coursework template file to use it.

NOTE: Remember that a function has a different workspace to the one where from where it is called from – you will need to pass the Arduino object you have created at the beginning of the submission template (the *a* variable) to the function!

i) The first part of the function is about monitoring and plotting the temperature. Create a single live graph that shows the recorded values of the temperature as time progresses, at intervals of approximately 1 s. For this, the usual *plot* command will create the graph, and the additional commands *xlabel* and *ylabel* will generate proper axes titles. However, note that the dataset changes with time – and the graph needs to update and show accordingly! You may find useful other functions like *xlim* and *ylim*, which will ensure the graph shows a span which is appropriate for the dataset. As the loop progresses, the command *drawnow* will make your graph updated. Save a snapshot of the plot as an image and include it in your .docx template.

j) Now you can add some commands that will switch your LEDs on or off depending on the temperature values. To check the function is working correctly, you can hold the temperature sensor in your hand, move in a cold area e.g. close to a window, and/or change the temperature range temporarily to check it is operating correctly.

k) Note that LEDs need to blink according to a certain period, as well as the live graph has to update according to a certain period – make sure you take these into account for the overall temporisation of the function.

l) Write some short documentation (max 100 words) to be included in your function, which can be retrieved using the command *'doc temp_monitor'* and briefly explains the function use and purpose.

m) **After writing the code:** Draw a second flowchart in a similar fashion to the first one, which reflects the actual implementation that you have done. Add to your Word template .docx file this second, updated version.

TASK 3 – ALGORITHMS – TEMPERATURE PREDICTION [30 MARKS]

In case the capsule temperature is varying too quickly or approaching the (upper or lower) threshold of the comfort range, it would be convenient to detect this so that adjustments in the cabin temperature control system can be actioned in advance. In this task, you are asked to devise a way to alert if the temperature is varying too quickly (more than 4°C/min), and to also predict the temperature value expected in 5 minutes' time.

a) **Before writing any code:** Read through Task 3. Draw a flowchart to outline your implementation plan for this function and add it to your Word template .docx file, indicating the decision points and the loops used.

b) Create a function temp_prediction.m that you will call from the coursework template file. Devise a way to continuously calculate how fast, in °C/s, the temperature is changing, and print the value to screen. Note that the temperature change rate over time is the derivative of the data collected. Also keep in mind that in the short-term there may be noise spikes, which are smoothened out over the medium term.

c) Now that you know how fast the temperature is changing, let the function print out to screen at every cycle the current temperature, and the temperature expected in 5 minutes (assuming the rate of change remains constant over these 5 minutes).

d) Your function should also constantly monitor the temperature and generate a constant green light if the temperature is kept stable within the comfort range. If the rate of change in temperature is greater than +4°C/min (increase), a constant red light should show instead. If the rate of change in temperature is greater than -4°C/min (decrease), a constant yellow light should show. You can hold the thermistor with your fingers to test these!

e) Write some short documentation (100 words) to be included in your function, which can be retrieved using the command *'doc temp_prediction'*.

TASK 4 – REFLECTIVE STATEMENT [5 MARKS]

a) Write a reflective statement (400 words max) describing challenges, strengths, limitations, and suggested future improvements of your project. Add this to your Word template .docx file.

TASK 5 – COMMENTING, VERSION CONTROL AND PROFESSIONAL PRACTICE [15 MARKS]

a) Comment the code throughout in a way that would allow another programmer to be able to understand and contribute to the code you wrote.

b) Commit the changes to your git repository as you progress in your programming tasks. There should be at least one commit of your code files for each of the four programming tasks (preferably more to ensure good backup of your code).

c) Hand the Arduino project kit back to the lecturer with all parts and in working order.

END