

The schematic diagram illustrates the internal wiring of a USB-C to USB-A adapter. On the left, the USB-C connector (J1) is shown with its pins: VBUS, A4, A5, B5, A7, B7, A6, B6, AB, and BB. The USB-A connector (D1) is shown on the right with its pins: D+, D-, D+, and D-. The internal components include a USBLC6-25C6 chip, capacitors C1 and C2, and resistors R1 and R2. The shield connection is also shown. The USB-C connector is connected to the USB-A connector via the USBLC6-25C6 chip. The USB-C connector has a shield connection (SH) and a ground connection (GND). The USB-A connector has a ground connection (GND). The schematic shows the internal connections and components like capacitors (C1, C2), resistors (R1, R2), and a shield connection.

[illegible]

Diagram illustrating the pin connections for the RP2354A microcontroller (U1) and associated power supply components.

Microcontroller Pin Connections:

- Power Supply Pins:**
 - VREG_AVDD (Pin 46) → +3V3
 - USB_OTF_VDD (Pin 53) → +3V3
 - ADC_AVDD (Pin 44) → +3V3
 - QSPI_AVDD (Pin 54) → +3V3
 - QSPI_AVDD (Pin 55) → +3V3
 - VREG_VIN (Pin 49) → +3V3
 - VREG_VA (Pin 50) → +3V3
 - DVDD (Pin 6) → +1V1
- Ground Connections:**
 - VREG_PND (Pin 67) → GND
 - GND (Pin 61) → GND
- Other Pins:**
 - RUN (Pin 26) → RUN
 - USB_DM (Pin 51) → USB_DM
 - USB_DP (Pin 52) → USB_DP
 - QSPI_SS (Pin 60) → QSPI_SS
 - QSPI_SCLK (Pin 56) → QSPI_SCLK
 - QSPI_SDO (Pin 57) → QSPI_SDO
 - QSPI_SD1 (Pin 58) → QSPI_SD1
 - QSPI_SD2 (Pin 59) → QSPI_SD2
 - QSPI_SD3 (Pin 55) → QSPI_SD3
 - XIN (Pin 21) → XIN
 - XOUT (Pin 22) → XOUT
 - SWCLK (Pin 24) → SWCLK
 - SWDIO (Pin 25) → SWDIO
 - GPIO26/ADC0 (Pin 40) → GPIO26/ADC0
 - GPIO27/ADC1 (Pin 41) → GPIO27/ADC1
 - GPIO28/ADC2 (Pin 42) → GPIO28/ADC2
 - GPIO29/ADC3 (Pin 43) → GPIO29/ADC3
 - VTGT_SENSE (Pin 44) → VTGT_SENSE

Power Supply Components:

- 600R@100MHz** (FB1) → +3V3
- ADC_AVDD** (C18) → +3V3
- ADC_AVDD** (C18) → GND
- Capacitors:**
 - C13 (100nF) → +1V1 / GND
 - C14 (100nF) → +1V1 / GND
 - C15 (100nF) → +1V1 / GND
 - C37 (4.7uF/10V/20%/X5R/C0402) → +1V1 / GND
 - C7 (100nF) → +3V3 / GND
 - C8 (100nF) → +3V3 / GND
 - C9 (100nF) → +3V3 / GND
 - C10 (100nF) → +3V3 / GND
 - C11 (100nF) → +3V3 / GND
 - C12 (100nF) → +3V3 / GND
 - C16 (100nF) → +3V3 / GND
 - C17 (100nF) → +3V3 / GND

Note: C37: place at the bottom edge of U1 near DVDD pin

U1, NOT near L1/C21.

L1 polarity dot (pad 1) must face VREG_LX.
Do not substitute L1 or Y1 – see README.

[illegible][illegible]

The diagram illustrates the power connections for four mounting holes (H1, H2, H3, H4) on a PCB. Each hole is represented by a red circle with a black dot in the center. The connections are as follows:

- H1 MountingHole:** Connected to **PWR_FLAG** (top) and **GND** (bottom) via a green vertical line.
- H2 MountingHole:** Connected to **VBUS** (top), **PWR_FLAG** (middle), and **+5V** (bottom) via a green vertical line.
- H3 MountingHole:** Connected to **+5V** (top), **PWR_FLAG** (middle), and **+1V1** (bottom) via a green vertical line.
- H4 MountingHole:** Connected to **+1V1** (top), **PWR_FLAG** (middle), and **VREG_AVDD** (bottom) via a green vertical line.

File: sinodude-rp2354.kicad_sch	
Title: sinodude-rp2354	
Size: A2	Rev: A
Date:	
KiCad E.D.A. 10.0.6	Id: 1/1