



HP Web Jetadmin - Proxy Agents Readme

SUMMARY

This document contains information about HP Web Jetadmin Proxy Agents.

Legal Information

Copyright and License

© Copyright 2026 HP Development Company, L.P.

Reproduction, adaptation, or translation without prior written permission is prohibited, except as allowed under the copyright laws.

The information contained herein is subject to change without notice.

The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

Edition 43, 04/2026

Trademark Credits

Adobe®, Acrobat®, and PostScript® are trademarks of Adobe Systems Incorporated.

Apple and the Apple logo are trademarks of Apple Computer, Inc., registered in the U.S. and other countries. iPod is a trademark of Apple Computer, Inc. iPod is for legal or rightholder-authorized copying only. Don't steal music.

Microsoft and Windows are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.

Table of contents

1 Proxy agents.....	1
2 HP SNMP Proxy Agent 10.4.0	2
Features	2
System requirements	3
Install HP SNMP Proxy Agent.....	3
Standalone installation	4
Silent installation/network installation.....	4
Error logging.....	5
Supported devices.....	5
Questions and answers	5
Revision history (partial).....	6
3 HP WS Pro Proxy Agent 10.5.10	8
Features	8
System requirements	8
Install HP WS Pro Proxy Agent	9
Standalone installation	9
Silent installation.....	10
Install HP WS Pro Proxy Agent with User Account Control enabled	10
Uninstall HP WS Pro Proxy Agent from the command line	10
Error logging and troubleshooting.....	11
Validate that HPWSProxyService can communicate with a USB-connected printer.....	12
Validate that the HP Embedded Web Server password is cleared	12
Validate the hosted IP address in an environment with multiple network interfaces	12
Validate that remote communication with USB-connected HP LaserJet Pro and HP OfficeJet Pro devices is possible outside of HP Web Jetadmin.....	13
Validate that the devices HP WS Pro Proxy Agent does not support and non-HP devices are connected to the proxy agent PC via USB	13
Default ProxyServiceConfig.xml file	13
UIO test tool	16
Configure the HP WS Pro Proxy Agent service behind a firewall.....	17
Supported devices.....	18
Questions and answers	18
Revision history (partial).....	19
Configuration steps required for the HP ScanJet 8500/N9120 device.....	22
HP Web Jetadmin Instant-On USB Device Discovery.....	23
Instant-On Filter Capabilities Tool.....	23

Instant-On Configuration File	23
-------------------------------------	----

1 Proxy agents

A proxy agent is client-side software that HP Web Jetadmin uses to discover and manage devices connected directly to the client PC.

The proxy agent passes the same types of queries to PC-connected devices as are typically passed to network-connected devices. HP Web Jetadmin uses the proxy agent to gather additional device information about PC-connected devices, such as remaining toner levels, page counts, and status.



NOTE: The current version of this Readme (in English) is available from the [HP Web Jetadmin Software - Setup & User Guides](#) website.

HP provides the following proxy agents:

- HP SNMP Proxy Agent exposes object identifiers (OIDs) in the Printer management information base (MIB) to the Microsoft® SNMP service that runs on the host PC where the device is connected through a USB port.
- HP WS Pro Proxy Agent is a Web Service that runs under the network service account on a PC workstation. HP WS Pro Proxy Agent replicates a device's services from the host computer's USB interface to its network interface.

While most devices support HP SNMP Proxy Agent, a few devices require HP WS Pro Proxy Agent.

The HP Proxy Agents package includes the following:

- HP SNMP Proxy Agent: Separate MSI installers for the 32-bit and 64-bit operating systems
- HP WS Pro Proxy Agent: A single EXE installer for both the 32-bit and 64-bit operating systems

Use the following steps to download the HP Proxy Agents package:

1. Go to the [HP Inc. - Software Depot - HP Web Jetadmin](#) website.
2. Click the **Request** button. The HP account login page opens.
3. Perform one of the following actions:
 - If you already have an HP account, log in with your credentials.
 - If you do not have an HP account, click the **Sign up** link at the bottom of the page. Follow the instructions to create an HP account, and then log in.
4. On the **HP Web Jetadmin** page, follow the instructions to download the current HP Proxy Agents package.

As a general rule, you should install both HP SNMP Proxy Agent and HP WS Pro Proxy Agent. However, be aware that HP Web Jetadmin can discover some devices through both HP SNMP Proxy Agent and HP WS Pro Proxy Agent. If you install both proxy agents on a machine where HP Web Jetadmin discovers one of these devices, the device appears in the device lists twice.

For more information about the proxy agents, see the *HP Web Jetadmin - Discovering PC-Connected Devices* white paper (in English). This white paper is available from the [HP Web Jetadmin Software - Setup & User Guides](#) website.

2 HP SNMP Proxy Agent 10.4.0

HP SNMP Proxy Agent is installed on a desktop client PC. HP Web Jetadmin uses HP SNMP Proxy Agent to discover and manage HP printers and scanners connected locally (for example, through USB connections). HP SNMP Proxy Agent exposes management objects through the Microsoft SNMP service on the client PC.

In HP Web Jetadmin, a simple PC-connected discovery finds the locally attached devices. HP Web Jetadmin can then gather additional device information—such as remaining toner levels, page counts, and status—through the proxy.

Features

HP Web Jetadmin uses several features of HP SNMP Proxy Agent to discover and manage devices.

These features include the following:

- HP Web Jetadmin queries the HP-proprietary and standard management objects in the supported devices. Different devices offer various levels of support. Many devices expose the model name, engine page count, supplies levels, serial number, and so on.
- HP Web Jetadmin supports reading and writing information on PC-connected devices.
- HP Web Jetadmin detects status changes in a PC-connected device by polling or manually refreshing the device. HP Web Jetadmin does not support traps for PC-connected devices.
- A discovery must complete successfully before a PC-connected device is available in HP Web Jetadmin.
- HP SNMP Proxy Agent and HP Web Jetadmin support multiple PC-connected devices (for example, through a USB connection) on a single desktop client PC.
- HP SNMP Proxy Agent adds support for some HP OfficeJet Pro devices through the HP OfficeJet Basic Driver - IT Professional Use Only driver package.
- HP Web Jetadmin can use the IP broadcast method to perform a PC-connected discovery. HP Web Jetadmin uses an SNMP query for the IP broadcast packet. However, this discovery method provides limited results because many systems and networks block IP broadcast traffic for security and overall management reasons. The workstation or server HP Web Jetadmin sends the IP broadcast packet to must have an SNMP service that responds to these packets.

For a comprehensive and scaled discovery plan, HP recommends that you also use other discovery methods, such as IP range and Specified addresses.

- The polling interval determines how often HP Web Jetadmin communicates with the devices on the network. You can increase the polling interval to reduce how often HP Web Jetadmin communicates with devices and reduce network traffic.

In HP Web Jetadmin 10.5 SR4, the polling interval was changed to a setting in a configuration file. The `AllDeviceTimeBetweenBGpollingInMin` property in the `MoabDevice.config.xml` file defines the polling interval. This configuration file is available in the following directory:

C:\Windows\ServiceProfiles\NetworkService\AppData\Local\HP
Inc\HPWebJetadmin\WjaService\config

System requirements

HP SNMP Proxy Agent is supported on Microsoft operating systems.

The supported operating systems include the following:



NOTE: If 32-bit and 64-bit versions of an operating system are available, both versions are supported.

- Windows 7
- Windows 8.1
- Windows 10
- Windows 11
- Windows Server 2008

To allow queries from the HP Web Jetadmin server, HP Universal Print Driver (UPD) and the Windows SNMP service must be installed. The Windows SNMP service must be configured and running as follows:

- Install Microsoft .NET Framework 3.5x on the proxy client PC for HP SNMP Proxy Agent. Microsoft .NET Framework 3.5x is not required for HP Web Jetadmin 10.4 SR7 or later.
- Configure the SNMP service Properties so that **Accepted community names** includes **public** with **READ ONLY** rights.
- Enable a configuration so that it can be modified by choosing and configuring a **READ WRITE** community name.
- Configure the SNMP service Properties to accept SNMP packets from any host or from HP Web Jetadmin.



NOTE: Microsoft does not include the SNMP service with the Home editions of Windows. The exact mechanism for installing the SNMP service varies depending on the Windows version.

In Windows 7, go to **Control Panel > Programs and Features**. On the sidebar, click **Turn Windows features on or off**. Enable the **Simple Network Management Protocol (SNMP)** feature.

Firewall settings must permit HP Web Jetadmin to query the proxy agent using SNMP. UDP port 161 should be open.



NOTE: Not all versions of Windows automatically enable UDP port 161 when you install the SNMP service. If the SNMP service is running, but cannot be accessed from a remote machine, the firewall on the PC might be blocking SNMP traffic.

Install HP SNMP Proxy Agent

You must install the Microsoft SNMP service before you install HP SNMP Proxy Agent. You can install HP SNMP Proxy Agent either before or after you install the HP printer driver.

Two installation modes are available through standard tools, such as Microsoft Systems Management Server (SMS)—standalone mode and silent/network mode.

Standalone installation

The standard (non-silent) installation takes input in the form of responses to dialog boxes.

To initiate a standalone installation of HP SNMP Proxy Agent, run one of the following commands:

- `Msiexec /i "HP SNMP Proxy_32_10_4_0.msi"`
- `Msiexec /i "HP SNMP Proxy_64_10_4_0.msi"`

The installer then guides you through a series of dialogs.

Silent installation/network installation

The silent mode (without a UI) is provided for push-based installations.

To initiate a silent installation of HP SNMP Proxy Agent, run one of the following commands:

- `Msiexec /i "HP SNMP Proxy_32_10_4_0.msi" /qn`
- `Msiexec /i "HP SNMP Proxy_64_10_4_0.msi" /qn`

The following switches are also available with this installer:

- `/s`
Executes a silent extraction of the packaged binaries on the client system.
- `/qn`
Executes the MSI in silent mode. Specifying `/s` applies this setting.
- `/i`
Installs the package.
- `/fv`
Upgrades an existing package.
- `/x`
Uninstalls an existing package.
- `PERMITTEDMANAGERS="ipaddress1;ipaddress2;...;ipaddressn"`
Sets up the SNMP service to respond to requests only from the specified IP addresses. This parameter is used from the command line.

An empty value, such as `PERMITTEDMANAGERS=""`, removes all existing entries that the proxy installer previously made.

A value of `"*"` indicates that the SNMP service should be able to receive values from any server.
- `VALIDCOMMUNITIES="communityname1;communityname2;...communitynamen"`
Sets up the SNMP service to respond only to servers that send a request with one of the specified community names. This parameter is used from the command line.

Error logging

By default, the installer creates the `snmpprinst.log` file in the Windows folder. This is a hardcoded aspect of the installer and currently cannot be overridden.

Supported devices

HP Web Jetadmin uses HP SNMP Proxy Agent to discover a wide variety of devices.

For a complete list of the devices that can be discovered, see the *HP Web Jetadmin - Discovering PC-Connected Devices* white paper (in English). This white paper is available from the [HP Web Jetadmin Software - Setup & User Guides](#) website.

Questions and answers

This table provides the answers to some common questions about HP SNMP Proxy Agent.

Table 2-1 Questions and answers for HP SNMP Proxy Agent

Question	Answer
Why does HP Web Jetadmin fail to discover my locally attached device?	The following troubleshooting steps might help analyze this problem: - On the HP Web Jetadmin server, verify basic network connectivity with the PC client. Substitute the IPv4 address of the client PC for <code>IPAddr</code> in the following command: <pre>ping IPAddr</pre> - On the HP Web Jetadmin server, use a third-party tool, such as Net-SNMP <code>snmpget</code>, to verify that the SNMP service and firewall on the client PC is installed, configured, and running. Substitute the IPv4 address of the client PC for <code>IPAddr</code> in the following command: <pre>snmpget -v1 -c public IPAddr 1.3.6.1.2.1.1.1.0</pre> - On the HP Web Jetadmin server, use a third-party tool, such as Net-SNMP <code>snmpget</code>. Substitute the IPv4 address of the client PC for <code>IPAddr</code> in the following command: <pre>snmpget -v1 -c public IPAddr 1.3.6.1.4.1.11.2.4.3.13.1.0</pre> If SNMP and the proxy agent are functioning, the proxy agent responds with an INTEGER value greater than zero. If the proxy agent was not installed successfully, the response is <code>NO SUCH NAME</code>. - The following registry key identifies the proxied devices on the client PC: <pre>HKLM\SOFTWARE\Hewlett-Packard\HP SNMP Proxy\PrnId</pre> If the device does not appear in this list, restart the SNMP service or reboot the PC. If the device is installed, powered on, and working (for example, you can print to it), but the device still does not appear in this list, the device's driver might not implement an enterprise device management interface.

Table 2-1 Questions and answers for HP SNMP Proxy Agent (continued)

Question	Answer
After I run a PC-connected discovery and the locally attached devices are discovered, how do I know which devices are PC-connected devices?	Discovered PC-connected devices are displayed in the device lists with the network-connected devices. To display a device list that includes only the devices that were discovered as PC-connected devices, perform the following steps to enable a filter: 1. From the top menu bar, go to View > Preferences. 2. Select Device Filters. 3. In the Available filters section, double-click PC-Connected Devices. 4. Click OK. 5. In the Device Management navigation pane, expand All Devices, and then select PC-Connected Devices. To display the PC Connected column in a device list, perform the following steps: 1. In the Device Management navigation pane, expand All Devices, and then select a device list. 2. Right-click a column header, and then select Customize. The Select Columns window opens. 3. From the Category drop-down list, select All. 4. In the Available Columns list, double-click PC Connected. 5. Click OK.
Can I use the HP Web Jetadmin Reports feature to generate reports about my locally attached devices?	Yes. Reports about PC-connected devices should be possible. However, the data HP Web Jetadmin collects varies depending on the device.
What happens when the IP address of the client PC changes?	HP Web Jetadmin finds the proxied devices on the new IP address during the next successful discovery.
Can I use any version of HP Web Jetadmin to manage PC-connected devices?	HP SNMP Proxy Agent requires HP Web Jetadmin 10.2 or later for full functionality.

Revision history (partial)

This table provides a partial history of the improvements and fixes made for HP SNMP Proxy Agent.

Table 2-2 Revision history for HP SNMP Proxy Agent (partial)

Proxy version	Release date	Improvements and fixes
10.4.0 Update 1	HP Web Jetadmin 10.5 SR4 (10.5.116926) 12-October-2023	• Added support for Windows 11. • Changed the polling interval to a setting in a configuration file. You can increase the polling interval to reduce how often HP Web Jetadmin communicates with devices and reduce network traffic.
10.4.0	HP Web Jetadmin 10.4 (10.4.98174) 28-October-2015	HP SNMP Proxy Agent 10.4.0 now supports HP Universal Print Driver (UPD) 6.1 or earlier. Previous versions of HP SNMP Proxy Agent only supported versions of UPD earlier than 6.1.

Table 2-2 Revision history for HP SNMP Proxy Agent (partial) (continued)

Proxy version	Release date	Improvements and fixes
10.3.0010	HP Web Jetadmin 10.3 SR1 (10.3.85669) 26-November-2012	HP SNMP Proxy Agent now uses the latest language monitor DLL in HP Universal Print Driver (UPD) 5.6 or later. If UPD 5.6 or later is used, HP SNMP Proxy Agent 10.3.0010 is required to display the toner levels.

3 HP WS Pro Proxy Agent 10.5.10

HP WS Pro Proxy Agent supports HP printers that use Web Services (WS) to communicate with HP Web Jetadmin, but do not support enough of SNMP to discover them. HP WS Pro Proxy Agent runs under the less-privileged network service account when it is installed on workstations.

Features

HP Web Jetadmin uses several features of HP WS Pro Proxy Agent to discover and manage devices.

These features include the following:

- The polling interval determines how often HP Web Jetadmin communicates with the devices on the network. You can increase the polling interval to reduce how often HP Web Jetadmin communicates with devices and reduce network traffic.

In HP Web Jetadmin 10.5 SR4, the polling interval was changed to a setting in a configuration file. The `AllDeviceTimeBetweenBGpollingInMin` property in the `MoabDevice.config.xml` file defines the polling interval. This configuration file is available in the following directory:

C:\Windows\ServiceProfiles\NetworkService\AppData\Local\HP
Inc\HPWebJetadmin\WjaService\config

System requirements

HP WS Pro Proxy Agent is supported on Microsoft operating systems.

The supported operating systems include the following:



NOTE: If 32-bit and 64-bit versions of an operating system are available, both versions are supported.

- Windows 7
- Windows 8.1
- Windows 10
- Windows 11
- Windows Server 2008



NOTE: If User Account Control (UAC) is enabled on the Windows client, you must run the installation for HP WS Pro Proxy Agent as an administrator.

HP WS Pro Proxy Agent requires Microsoft .NET Framework 4.8 or later. The installer verifies that the correct version is installed. HP recommends that you install the latest security updates for Microsoft .NET Framework 4.8 or later.

Install HP WS Pro Proxy Agent

Two installation modes are available through standard tools such as Microsoft Systems Management Server (SMS)—standalone mode and silent mode.

⚠ CAUTION: PC-connected devices that support the Common Data Model (CDM): Support for these devices in HP WS Pro Proxy Agent 10.5.6 has been updated. If HP WS Pro Proxy Agent 10.5.4 or earlier is installed, you must uninstall the proxy agent before you install HP WS Pro Proxy Agent 10.5.6.

Standalone installation

The standalone installation takes input in the form of responses to dialog boxes.

To initiate a standalone installation of HP WS Pro Proxy Agent, run the following command:

```
HPWSProxyService_10_5_10.exe WJAHOSTIP=xxx.xxx.xxx.xxx  
WJADISCOVERYPORT=xxxxx LEDMDISCOVERYPORT=xxxxx
```

- WJAHOSTIP=xxx.xxx.xxx.xxx

(Optional) Specifies the host IP address of the HP Web Jetadmin server where HP WS Pro Proxy Agent sends WS Probe Hello packets when the service starts and when the service detects that IP addresses on the host machine have changed. This parameter keeps PC-connected devices up-to-date in HP Web Jetadmin device lists without requiring another discovery.

If this parameter is not specified, the HP Web Jetadmin host IP address is not configured for HP WS Pro Proxy Agent to use.

- WJADISCOVERYPORT=xxxxx

(Optional) Specifies the port where HP WS Pro Proxy Agent sends WS Probe Hello packets. The port specified for this parameter must be the same as the port where HP Web Jetadmin is configured to listen for PC-connect WS Hello messages. The default is port 27893.

- LEDMDISCOVERYPORT=xxxxx

(Optional) Specifies the UDP port on which HP WS Pro Proxy Agent listens for discovery probe requests. The port specified for this parameter must be the same as the port that HP Web Jetadmin is configured to use when sending PC-connect WS probes. The default is port 27893.

The installer then guides you through a series of dialogs.

The following are examples of the standalone installation command:

- To install HP WS Pro Proxy Agent with the default values for the optional parameters, enter the following command:

```
HPWSProxyService_10_5_10.exe
```

- To install HP WS Pro Proxy Agent by specifying values for the optional parameters, enter the following command:

```
HPWSProxyService_10_5_10.exe WJAHOSTIP=1.2.3.4 WJADISCOVERYPORT=27893  
LEDMDISCOVERYPORT=27893
```

Silent installation

The silent installation mode (without a UI) is provided for push-based installations. A silent installation can be initiated when User Account Control (UAC) is enabled.

To initiate a silent installation of HP WS Pro Proxy Agent, run the following command:

```
HPWSProxyService_10_5_10.exe /S /v/qn /V"WJAHOSTIP=xxx.xxx.xxx.xxx  
WJADISCOVERYPORT=xxxxxx LEDMDISCOVERYPORT=xxxxxx"
```

For more information about the optional parameters and default values, see [Standalone installation on page 9](#).

The following is an example of the silent installation command that uses the default values for the optional parameters:

- `HPWSProxyService_10_5_10.exe /S /v/qn /V`

The following are examples of the silent installation command that specify values for the optional parameters:

- `HPWSProxyService_10_5_10.exe /S /v/qn /V"WJADISCOVERYPORT=27893"`
- `HPWSProxyService_10_5_10.exe /S /v/qn /V"WJAHOSTIP=1.2.3.4
WJADISCOVERYPORT=27983 LEDMDISCOVERYPORT=27983"`

Install HP WS Pro Proxy Agent with User Account Control enabled

If User Account Control (UAC) is enabled, you must run the installation command from the elevated (administrator) Command Prompt.

Uninstall HP WS Pro Proxy Agent from the command line

You can uninstall HP WS Pro Proxy Agent from the command line.

The following is the command syntax:

```
msiexec.exe /qn /uninstall <ProductCode>
```

The `<ProductCode>` command-line parameter specifies the product code for the version of HP WS Pro Proxy Agent you are uninstalling. The following are the product codes.

Table 3-1 Product code for the uninstallation command

HP WS Pro Proxy Agent version	Product code
HP WS Pro Proxy Agent 10.3.6	{3BF03BC8-8B49-4082-AF2D-F159A827FD74}
HP WS Pro Proxy Agent 10.3.8	{E1A6D281-7D99-4946-ACD7-C1A3D60B9E03}
HP WS Pro Proxy Agent 10.4.1	{716FB540-940E-4A8F-92C0-2B063C480251}
HP WS Pro Proxy Agent 10.4.2	{358F8677-A281-424A-81B4-0B03B3AAC849}
HP WS Pro Proxy Agent 10.4.3	{014D70E8-BOCB-4E59-99E4-17FBC69075FA}
HP WS Pro Proxy Agent 10.4.5	{2F9CFB69-8B68-4505-9DB0-329CE47FC0F4}
HP WS Pro Proxy Agent 10.4.7	{46F466D4-A8A7-4569-BA01-C7773734A457}

Table 3-1 Product code for the uninstallation command (continued)

HP WS Pro Proxy Agent version	Product code
HP WS Pro Proxy Agent 10.4.8	{519BC246-F92C-4275-B350-A36A3F6154DB}
HP WS Pro Proxy Agent 10.4.9	{B7B817BC-4881-46B7-9577-702AB74ACE4B}
HP WS Pro Proxy Agent 10.5	{8B7ED8AA-2CF1-47C6-92AE-E906CC361D7C}
HP WS Pro Proxy Agent 10.5.1	{E27CF7AC-4A71-4286-ABDF-05D0DFAC0A70}
HP WS Pro Proxy Agent 10.5.2	{447DA6E2-FAB0-41E3-87F8-169215970B15}
HP WS Pro Proxy Agent 10.5.4	{31FB1EDD-F861-4824-9C7B-D81C4AD4FBE7}
HP WS Pro Proxy Agent 10.5.5	{E6FF33D8-06B6-41A3-93F9-6DB00BDDF3EA}
HP WS Pro Proxy Agent 10.5.6	{1E3C7ED6-1091-4DEE-A666-97F83301696B}
HP WS Pro Proxy Agent 10.5.7	{286FA3BE-B50F-4DD6-8ADE-C07F9DD61443}
HP WS Pro Proxy Agent 10.5.8	{C0DAAE50-6584-4029-9DEE-22A64E7179EC}
HP WS Pro Proxy Agent 10.5.9	{1838ED97-1B3C-449F-90B3-A9590210F27D}
HP WS Pro Proxy Agent 10.5.10	{FC3986A7-A78A-4CC7-8295-B1FAEC25F372}

The following is an example of the uninstallation command:

```
msiexec.exe /qn /uninstall {FC3986A7-A78A-4CC7-8295-B1FAEC25F372}
```

Error logging and troubleshooting

The settings in the ProxyServiceConfig.xml file determine the behavior of HP WS Pro Proxy Agent. You can use this file for error logging and troubleshooting.

The ProxyServiceConfig.xml file and the corresponding log files (HPWSProxyServiceLog.log and DeviceManager.log) are located in one of the following directories:

- On a 32-bit operating system:
C:\Program Files\HP Inc\HPWSProxy\bin\
- On a 64-bit operating system:
C:\Program Files (x86)\HP Inc\HPWSProxy\bin\



NOTE: For HP WS Pro Proxy Agent 10.3.8 or earlier, these files are located in one of the following directories:

- On a 32-bit operating system:
C:\Program Files\Hewlett-Packard Company\HPWSProxy\bin\
- On a 64-bit operating system:
C:\Program Files (x86)\Hewlett-Packard Company\HPWSProxy\bin\

Validate that HPWSProxyService can communicate with a USB-connected printer

If the HPWSProxyServiceLog.log file contains endpoints, the proxy server can communicate with a USB-connected device.

The following is an example of the endpoints that must be in the log:

```
ProcessID:1944, Time:6/14/2016 6:26:58 PM, MustWrite] Hosted Endpoints are
[ProcessID:1944, Time:6/14/2016 6:26:58 PM, MustWrite]
https://10.10.10.20:8020/564E4333-4230-3032-3538-308D99AD1AE6
[ProcessID:1944, Time:6/14/2016 6:26:58 PM, MustWrite]
http://10.10.10.20:8021/564E4333-4230-3032-3538-308D99AD1AE6/transfer
```

Validate that the HP Embedded Web Server password is cleared

The HP Embedded Web Server admin password must be cleared to guarantee communication between the device and HP WS Pro Proxy Agent.

If the device is protected with an admin password, some items—such as the device status—might not be shown completely. In this case, the HPWSProxyServiceLog.log file has endpoints that do not have a UUID. The following is an example of an endpoint:

```
[ProcessID:1352, Time:1/14/2019 1:58:48 PM, MustWrite] Hosted Endpoints are
[ProcessID:1352, Time:1/14/2019 1:58:48 PM, MustWrite]
https://10.10.10.20:8020/
[ProcessID:1352, Time:1/14/2019 1:58:48 PM, MustWrite]
http://10.10.10.20:8021//transfer
```

Validate the hosted IP address in an environment with multiple network interfaces

HP WS Pro Proxy Agent can run on multi-homed PCs or PCs with multiple network interfaces. In many cases, multi-homed servers are connected to multiple networks and have multiple IP addresses. Multi-homed PCs with multiple IP addresses might cause problems because HP WS Pro Proxy Agent uses only one address.

HP WS Pro Proxy Agent runs on primary network interfaces, which means the lowest priority order of network adapters. The HPWSProxyServiceLog.log file shows the network interfaces and IP address that HP WS Pro Proxy Agent hosts. The following is an example of the log message that contains the hosted IP address:

```
ProcessID:1944, Time:6/14/2016 6:26:58 PM, MustWrite] Hosted Endpoints are [ProcessID:1944, Time:6/14/2016 6:26:58 PM, MustWrite] https://
10.10.10.10:8020/564E4333-4230-3032-3538-308D99AD1AE6
[ProcessID:1944, Time:6/14/2016 6:26:58 PM, MustWrite] http://
10.10.10.10:8021/564E4333-4230-3032-3538-308D99AD1AE6/transfer
```

To run HP WS Pro Proxy Agent on different network interfaces, you can change the priority order of the network adapters. For more information, see the *Configure the Order of Network Interfaces* document on the [Microsoft Documentation](#) website.

Validate that remote communication with USB-connected HP LaserJet Pro and HP OfficeJet Pro devices is possible outside of HP Web Jetadmin

To test whether the endpoint for HP LaserJet Pro and HP OfficeJet Pro devices is accessible via the network, add /DevMgmt/ProductConfigDyn.xml to the URL provided in the example in the previous section.

The following is an example of the URL:

```
https://10.10.10.20:8020/564E4333-4230-3032-3538-308D99AD1AE6/DevMgmt/  
ProductConfigDyn.xml
```

A user name and password are requested. The user name and password must be for a user who has access to the PC to which the device is connected. For this example, the PC has an IP address of 10.10.10.20. If no data is displayed, the network is blocking the traffic or HPWSProxyService has been stopped.

The endpoint contains the device UUID that the printer generates. The last digits of the UUID are the MAC address of the printer.

Validate that the devices HP WS Pro Proxy Agent does not support and non-HP devices are connected to the proxy agent PC via USB

HP WS Pro Proxy Agent tries to communicate with all USB-connected printers on the PC where HP WS Pro Proxy Agent is installed. HP recommends that you do not have multiple USB-connected printers on the same PC.

If there are any devices that HP WS Pro Proxy Agent does not support or non-HP devices connected via USB, pages with the following message might be printed from those devices periodically:

```
GET /DevMgmt/DiscoveryTree.xml HTTP/1.1  
HOST: localhost
```

If this occurs, unplug the USB cable from those devices.

Default ProxyServiceConfig.xml file

Review the settings in the default ProxyServiceConfig.xml file.

```
<?xml version="1.0" encoding="utf-16"?>  
<ProxyServiceConfig xmlns:xsd="http://www.w3.org/2001/XMLSchema"  
xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance">  
  <SimulatedMode>false</SimulatedMode>  
  <UseAug2004Addressing>true</UseAug2004Addressing>  
  <EnableHTTPS>true</EnableHTTPS>  
  <LogLevel>Error</LogLevel>  
  <DefaultRegistryPath>SOFTWARE\Wow6432Node\Hewlett-  
Packerd\HPLedmProxyAgent</DefaultRegistryPath>  
  <RegistryPath>SOFTWARE\Hewlett-Packard\HPLedmProxyAgent</  
RegistryPath>  
  <RegistryPathToGetWJAHostIP>SOFTWARE\Hewlett-  
Packerd\HPLedmProxyAgent</RegistryPathToGetWJAHostIP>  
  <EnableTestingIPAddressChange>false</EnableTestingIPAddressChange>  
  <DefaultPort>8082</DefaultPort>  
  <DefaultWSTransferPort>8083</DefaultWSTransferPort>  
  <AssignedPort>8020</AssignedPort>
```

```

    <EnableCustomDiscovery>true</EnableCustomDiscovery>
    <CustomPassword></CustomPassword>
    <CustomInstantOnPort></CustomInstantOnPort>
    <FirmwareBundlesPath>$INSTALLDIR\FirmwareBundles</
FirmwareBundlesPath>
    <EnableFirmwareUpgradePCAgentUI>>false</
EnableFirmwareUpgradePCAgentUI>
    <EnableFirmwareDowngrade>>false</EnableFirmwareDowngrade>
    <DeleteOlderFirmwareBundles>true</DeleteOlderFirmwareBundles>
    <RemindTimeInMinutes>30</RemindTimeInMinutes>
    <EnableActiveDeviceDetection>true</EnableActiveDeviceDetection>
    <UseCustomPathLog>>false</UseCustomPathLog>
    <CustomPathDomain></CustomPathDomain>
    <CustomPath></CustomPath>
    <CustomPathUsername></CustomPathUsername>
    <CustomPathPassword></CustomPathPassword>
    <LogDetectedPrinterInfo>>false</LogDetectedPrinterInfo>
    <LogLedmAdapterClientIPLogging>>false</LogLedmAdapterClientIPLogging>
</ProxyServiceConfig>

```

- CustomInstantOnPort

The port HP Web Jetadmin uses for the Instant-On discovery feature for USB-connected printers.

- CustomPassword

The password of the connected Common Data Model (CDM) device required to obtain the access token the device uses to communicate.

- CustomPath

The path of the custom sharepath. The default value is empty.

- CustomPathDomain

The domain of the custom sharepath. The default value is empty.

- CustomPathPassword

The password required to access the custom sharepath. The default value is empty.

- CustomPathUsername

The user name required to access the custom sharepath. The default value is empty.

- EnableActiveDeviceDetection (HP WS Pro Proxy Agent 10.4.1 or later)

The default value is `true`. HPWSProxyService actively checks to detect whether printers are attached to the PC.



NOTE: This functionality was introduced in HP WS Pro Proxy Agent 10.4.1. Earlier versions of HP WS Pro Proxy Agent used only passive listening for Windows events to detect newly attached printers.

The following is an example of a log message:

```
[ProcessID:4516, Time:6/27/2016 3:16:09 PM, Message]
OnDevicePresenceCheckEvent() fired
```

When HP WS Pro Proxy Agent detects a new printer, HPWSProxyService is restarted and the following log messages are in the log file:

```
DetectedDeviceCount = 1 HostedDeviceCount = 0
Detected mismatch in detected device count and Proxy hosted device
count. Restarting proxy...
```

- `EnableFirmwareDowngrade`

Specifies if firmware downgrades are enabled in the FW Upgrade Proxy Agent. The default value is false.

- `LogDetectedPrinterInfo` (HP WS Pro Proxy Agent 10.4.1 or later)

If you change the value of `LogDetectedPrinterInfo` to `true`, you must change the value of `LogLevel` to `All`. After you make these changes and restart HPWSProxyService, the information about the USB-connected printer received from Windows is logged in the `DeviceManager.log` file.

The following is an example of the log data:

```
[ProcessID:5136, Time:6/27/2016 5:54:11 PM, Message] USB Printer
Name : HP LaserJet Pro M402-M403 n-dne PCL.6
[ProcessID:5136, Time:6/27/2016 5:54:11 PM, Message] USB Printer
Port : USB002
[ProcessID:5136, Time:6/27/2016 5:54:11 PM, Message] USB Printer
Driver Name : HP LaserJet Pro M402-M403 n-dne PCL.6
[ProcessID:5136, Time:6/27/2016 5:54:11 PM, Message] USB Printer
Printer Status : Ready
```

- `LogLedmAdapterClientIPLogging` (HP WS Pro Proxy Agent 10.4.1 or later)

If you change the value of `LogLedmAdapterClientIPLogging` to `true` and restart HPWSProxyService, the `HPWSProxyLog.log` file shows the IP address of the requestor, which is normally HP Web Jetadmin.

The value of `LogLedmAdapterClientIPLogging` is set to the off state by default because IP address resolution *might* cause a delay on an LEDM adapter that receives numerous requests.

Due to the nature of various network setups, the IP address might not reflect the true IP address of the source. For example, the address in the log might not be the actual address of the HP Web Jetadmin host.

The following is an example of a message:

```
[ProcessID:5136, Time:6/27/2016 4:58:16 PM, All] Received request
from the (may not be accurate) IP : 10.20.18.196
```

- `LogLevel` (all versions of HP WS Pro Proxy Agent)

The default log level is `Error`. To change the log level, edit the `ProxyServiceConfig.xml` file in one of the directories listed previously. After you change the log level, you must restart HPWSProxyService.

If you set the log level to `All`, HPWSProxyService creates a second log file called `DeviceManager.log`.

- `RemindTimeInMinutes`

The default value is 30 minutes. The maximum value is 1440 (2 hours).

The value of the `RemindTimeInMinutes` setting is used for the **Remind me in** field in the Firmware Upgrade Proxy Agent wizard. You can use the **Remind me in** field to postpone a firmware upgrade until after the specified time period.

- `UseCustomPathLog`

The default value is `false`. To write the log files to the custom sharepath, change this value to `true`.

UIO test tool

HPWSProxyService uses Universal I/O DLLs (UIO DLLs) to communicate with PC-connected devices over USB. You can use the UIO test tool to determine if the UIO DLLs, device, or other proxy components cause a problem.

Use the following steps to execute the UIO test tool:

1. Double-click the `UIOTest.exe` file. This file is located in the `HPWSProxy\bin\` directory.
2. From the **Select Printer** list, select the USB-connected printer.

This list includes the printers that were previously connected, but are now disconnected. This list is the same as the list shown in **Control Panel > Hardware and Sound > Devices and Printers**.

3. Select one of the following printer types:
 - **LEDm** (for non-FutureSmart devices): Continue with Step 4.
 - **FutureSmart**: Continue with Step 6.
4. From the **Select LEDm Tree** list, select a tree element.
5. Click the **Get On All the Trees** or **Get On A Selected Tree** button.
6. Select a service URN from the drop-down list.



NOTE: The drop-down list might include elements that are not supported or available on single-function devices, such as `/copy`.

7. Click **Get**.

The results are written in the `UIOLog.txt` file. This file is in the same directory as the `UIOTest.exe` file. Prior to HP WS Pro Proxy Agent 10.3.8, this file was created in the `C:\temp` directory. For HP WS Pro Proxy Agent 10.4.1 or later, the results are also written in the display pane.

The following are examples of log entries:

```
Time:24/06/2016 11:11:08,    The tree is: /DevMgmt/
MediaHandlingDyn.xml And The Response is null
Time:24/06/2016 11:09:26,    The tree is: /DevMgmt/
DiscoveryTree.xml    And The Response Status Code is : 200
Time:24/06/2016 11:09:33,    The tree is: /TestNode/ExpectFailure
```

And The Response Status Code is : 404

Response Status Code null means: printer is connected

Response Status Code 200 means: printer is responding correctly

Response Status Code 404 means: endpoint not existing (while printer is connected)

Other Response Status Code might be different per device model.

Configure the HP WS Pro Proxy Agent service behind a firewall

The proxy service uses two TCP ports for HTTP or HTTPS communication with HP Web Jetadmin and one UDP port for discovery. For the HP WS Pro Proxy Agent service to work behind a firewall, you must add the proxy service and/or the TCP and UDP ports to the firewall exception list.



NOTE: At this time, the two TCP ports are dynamic. The HP WS Pro Proxy Agent service requests the two TCP ports on the first startup.

Use the following steps to add the proxy service and ports to the firewall exception list:

1. Add the HPDeviceProxyService.exe file from the proxy installation directory to the firewall exception list. The HPDeviceProxyService.exe file is located in one of the following directories:

- For a default installation on a 32-bit operating system:

C:\Program Files\HP Inc\HPWSProxy\bin\

- For a default installation on a 64-bit operating system:

C:\Program Files (x86)\HP Inc\HPWSProxy\bin\

In many cases, adding an exception or rule to the firewall to allow a specific service also allows an HP Web Jetadmin discovery to take place. If the ports must be added to the firewall, continue with Step 2.

2. Add the TCP and UDP ports the HP WS Pro Proxy Agent service uses to the firewall exception list. The TCP and UDP port numbers are defined in the following registry entries:

- For a 32-bit operating system:

HKEY_LOCAL_MACHINE\SOFTWARE\Hewlett-Packard\HPLedmProxyAgent

- For a 64-bit operating system:

HKEY_LOCAL_MACHINE\SOFTWARE\Wow6432Node\Hewlett-Packard\HPLedmProxyAgent

The values of Port and WSTransferPort must be added to the firewall exception list as TCP ports. The values for Port and WSTransferPort might vary from one host PC to another, depending on the availability of free ports on the host system. By default, the HP WS Pro Proxy Agent service finds free ports starting at port 8020.

The value of LEDMDiscoveryPort must be added to the firewall exception list as the UDP port. The value of LEDMDiscoveryPort is the same as the value the administrator set while installing HP WS Pro Proxy Agent.

Supported devices

HP Web Jetadmin uses HP WS Pro Proxy Agent to discover a wide variety of devices.

For a complete list of the devices HP Web Jetadmin can discover, see the *HP Web Jetadmin - Discovering PC-Connected Devices* white paper (in English). This white paper is available from the [HP Web Jetadmin Software - Setup & User Guides](#) website.

Questions and answers

This table provides the answers to some common questions about HP WS Pro Proxy Agent.

Table 3-2 Questions and answers for HP WS Pro Proxy Agent

Question	Answer
How do I detect whether a proxy is installed and which proxy is installed?	You can access Add/Remove Programs to see which proxy is installed, but Add/Remove Programs might not provide the version of the installed proxy.
Does HP Web Jetadmin use ICMP to discover devices through HP WS Pro Proxy Agent?	Yes. HP Web Jetadmin does an initial test on the IP address to determine if it is active. The hosting system must respond or HP Web Jetadmin cannot discover devices. In some cases, a firewall might block ICMP, but should be enabled to ensure that the discovery works. You can issue a simple Windows command at the administrator command window to add ICMP to the protocols that the Windows firewall allows. The following is an example: <pre>"netsh firewall set icmpsetting type = all mode = enable"</pre> CAUTION: Before you issue a Windows command to change the firewall settings, make sure that you read and understand all the related Windows documentation.
Why can I see the following message in the DeviceManager.log file? <pre>WIA dll Access denied. Kindly run the WS proxy service in Local user mode.</pre>	When HP WS Pro Proxy Agent runs as a network service, HP WS Pro Proxy Agent cannot access the HP Web Jetadmin DLL. HP WS Pro Proxy Agent does not detect the USB-connected HP ScanJet 8500 and HP ScanJet N9120 devices. All the other devices HP WS Pro Proxy Agent supports are discovered when HP WS Pro Proxy Agent runs as a network service.
I successfully discovered my device with HP WS Pro Proxy Agent. However, in the Engine Cycle Count column, HP Web Jetadmin displays <Not supported>. How can I see the page counts?	USB-connected devices discovered in HP Web Jetadmin with HP WS Pro Proxy Agent use the WS* communication protocol. The engine cycle count is an SNMP object and cannot be queried via HP WS Pro Proxy Agent. To obtain the printer page counts in HP Web Jetadmin via HP WS Pro Proxy Agent, use other counters, such as the following: • Total Impressions (Print Usage Counters) • Total Equivalent Impressions (Print Usage Counters) • Total Equivalent Mono Impressions (Print Usage Counters)
Why are garbage pages printed on a USB-connected printer after HP WS Pro Proxy Agent is installed?	HP WS Pro Proxy Agent tries to communicate with all USB-connected printers on the PC where HP WS Pro Proxy Agent is installed. HP recommends that you do not have multiple USB-connected printers on the same PC. If there are any devices that HP WS Pro Proxy Agent does not support or non-HP devices connected via USB, pages with the following message might be printed on those devices periodically: <pre>GET /DevMgmt/DiscoveryTree.xml HTTP/1.1 HOST: localhost</pre> If this occurs, unplug the USB cable from those devices.

Revision history (partial)

This table provides a partial history of the improvements and fixes made for HP WS Pro Proxy Agent.

Table 3-3 Revision history for HP WS Pro Proxy Agent (partial)

Proxy version	Release date	Improvements and fixes
10.5.10	HP Web Jetadmin 10.5 SR10 (10.5.119546) 3-April-2026	- Added support to downgrade firmware from the FW Upgrade Proxy Agent. - Added support to upgrade firmware for the HP OfficeJet 200 Mobile Printer series and HP OfficeJet 250 Mobile All-in-One Printer series. - Added support to treat USB-connected Common Data Model (CDM) devices as trusted devices.
10.5.9	HP Web Jetadmin 10.5 SR9 (10.5.119500) 15-August-2025	Added the Instant-On USB Device Discovery feature. This feature enables HP Web Jetadmin to automatically discover USB-connected printers without manual intervention.
10.5.8	HP Web Jetadmin 10.5 SR8 (10.5.119312) 28-February-2025	Updated the proxy version number to match the current version of HP Web Jetadmin.
10.5.7	HP Web Jetadmin 10.5 SR7 (10.5.118922) 7-November-2024	Added support for HP proprietary assets. There are no improvements or fixes. For more information, see the improvements and fixes for HP WS Pro Proxy Agent 10.5.6. This version of the proxy agent should be installed only if you are using HP WS Pro Proxy Agent 10.5.5 or earlier.
10.5.6	HP Web Jetadmin 10.5 SR6 (10.5.118521) 26-July-2024	- For devices that support the Common Data Model (CDM), added support for PC-connected firmware upgrades. - Added support to write the logs to a custom sharepath. - Added support to close the firmware upgrade UI after the firmware upgrade is successful. - Added support to use the encrypted password the encryption tool generates in the custom password specified in the default ProxyServiceConfig.xml file.
10.5.5	HP Web Jetadmin 10.5 SR5 (10.5.117720) 29-January-2024	Added support for devices that support the Common Data Model (CDM).
10.5.4 Update 1	HP Web Jetadmin 10.5 SR4 (10.5.116926) 12-October-2023	- Added support for Windows 11. - Changed the polling interval to a setting in a configuration file. You can increase the polling interval to reduce how often HP Web Jetadmin communicates with devices and reduce network traffic.
10.5.4	HP Web Jetadmin 10.5 SR4 (10.5.116926) 17-July-2023	Updated the proxy version number to match the current version of HP Web Jetadmin.

Table 3-3 Revision history for HP WS Pro Proxy Agent (partial) (continued)

Proxy version	Release date	Improvements and fixes
10.5.2	HP Web Jetadmin 10.5 SR2 (10.5.115586) 19-August-2022	Added the <RemindTimeInMinutes> setting to the ProxyServiceConfig.xml file.
10.5.1	HP Web Jetadmin 10.5 SR1 (10.5.114911) 29-April-2022	Updated the proxy version number to match the current version of HP Web Jetadmin.
10.5	HP Web Jetadmin 10.5 (10.5.113341) 10-September-2021	Updated the proxy version number to match the current version of HP Web Jetadmin.
10.4.9	HP Web Jetadmin 10.4 SR9 (10.4.111315) 10-December-2020	REQ 7509: HP WS Pro Proxy Agent now supports the firmware upgrade functionality without HP Web Jetadmin. The following devices have been verified: • HP PageWide Pro 477dn MFP, HP PageWide Pro 477dw MFP, HP PageWide Pro 577dw MFP, HP PageWide Pro 577z MFP • HP PageWide Pro 452dn Printer, HP PageWide Pro 452dw Printer, HP PageWide Pro 552dw Printer • HP OfficeJet Pro 8730 (PDL), HP OfficeJet Pro 8740 (PDL Hi) • HP OfficeJet Pro 8210, HP OfficeJet Pro 8216 • HP OfficeJet Pro 8630 • HP OfficeJet Pro 9010, HP OfficeJet Pro 9020
10.4.8	HP Web Jetadmin 10.4 SR8 (10.4.110231) 10-July-2020	REQ 7208: A PC-connected firmware upgrade over USB is now available for the following devices: • HP PageWide Pro 477dn MFP, HP PageWide Pro 477dw MFP, HP PageWide Pro 577dw MFP, HP PageWide Pro 577z MFP • HP PageWide Pro 452dn Printer, HP PageWide Pro 452dw Printer, HP PageWide Pro 552dw Printer • HP OfficeJet Pro 8730 (PDL), HP OfficeJet Pro 8740 (PDL Hi) • HP OfficeJet Pro 8210, HP OfficeJet Pro 8216 • HP OfficeJet Pro 8630 • HP OfficeJet Pro 9010, HP OfficeJet Pro 9020 IMPORTANT: HP has not tested other devices and they are not supported for USB upgrades using the HP WS Pro Proxy Agent server.

Table 3-3 Revision history for HP WS Pro Proxy Agent (partial) (continued)

Proxy version	Release date	Improvements and fixes
10.4.7	HP Web Jetadmin 10.4 SR7 (10.4.106859) 12-December-2019 NOTE: In Microsoft Windows, version 10.4.00.70 is displayed in the Add/Remove Programs section.	12618: During the HP WS Pro Proxy Agent installation, the installer no longer blocks the installation if Microsoft .NET Framework 3.5x is not installed. Microsoft .NET Framework 3.5x is required for HP SNMP Proxy Agent. 12659: TLS was not working on HP WS Pro Proxy Agent port 8020 because HP WS Pro Proxy Agent did not uninstall the self-signed certificate correctly during an uninstallation or upgrade. - REQ 7140: HP WS Pro Proxy Agent no longer requires Microsoft .NET Framework 3.5x.
10.4.5	HP Web Jetadmin 10.4 (10.4.105723) 28-January-2019	11810: HP Web Jetadmin now shows the actual MAC address of a USB-connected device instead of EXIT when HP WS Pro Proxy Agent runs on Microsoft Windows 10. 11841: During the startup of HP WS Pro Proxy Agent, the proxy creates the default ProxyServiceConfig.xml file again if the file was corrupted.
10.4.3	HP Web Jetadmin 10.4 SR3 (10.4.103054) 16-November-2017	- Added support for HP ScanJet 8500 fn2 and HP ScanJet Flow N9120 fn2 devices. - Support of HP WS Pro Proxy Agent with USB-connected HP ScanJet 8500/9120 devices requires HP Web Jetadmin 10.4 SR3 or later and special configuration steps. For more information, see Configuration steps required for the HP ScanJet 8500/N9120 device on page 22.
10.4.2	HP Web Jetadmin 10.4 SR2 (10.4.101715) 28-April-2017	- Added support for HP FutureSmart 4 devices with firmware 24.5 or later. - Support of HP WS Pro Proxy Agent with USB-connected HP FutureSmart devices requires HP Web Jetadmin 10.4 SR2 or later.
10.4.1	HP Web Jetadmin 10.4 SR1 (10.4.99821) 7-September-2016 NOTE: This version of HP WS Pro Proxy Agent was released independently of HP Web Jetadmin.	- Fixed the issue with HP WS Pro Proxy Agent crashing. - Changed the installation directory path from Hewlett-Packard Company\HPWSProxy to HP Inc\HPWSProxy. - Changed the directory where the UIOlog.txt file is saved to the same directory as the UITest.exe file. - Added additional logging. - HP WS Pro Proxy Agent now actively and passively checks for USB-connected printers. Previously HP WS Pro Proxy Agent only passively checked for USB-connected printers.
10.3.8	HP Web Jetadmin 10.3 SR8 (10.3.96073) 25-February-2015	- HP WS Pro Proxy Agent is now delivered as an EXE file instead of an MSI file. - The HP WS Pro Proxy Agent service can now be started or reinstalled via a silent installation when User Account Control (UAC) is enabled.

Table 3-3 Revision history for HP WS Pro Proxy Agent (partial) (continued)

Proxy version	Release date	Improvements and fixes
10.3.6	HP Web Jetadmin 10.3 SR6 (10.3.93671) 16-May-2014	- Updated the UIO version to fix device communication errors that occur for the following PC-connected devices: - HP LaserJet Pro 200 color M251 - HP LaserJet Pro 400 Printer M401 - HP LaserJet Pro 400 MFP M425 - HP LaserJet Pro 200 color MFP M276 - Added the ability to manage the new HP OfficeJet Pro 8610, HP OfficeJet Pro 8620, and HP OfficeJet Pro 8630 devices with the HP OfficeJet Pro MFP Universal Plug-in (UPI). - Updated HP WS Pro Proxy Agent to detect a printer when the VMware Workstation is installed on the same machine.

Configuration steps required for the HP ScanJet 8500/N9120 device

The HP ScanJet 8500/N9120 device requires specific configuration steps.

- If HP WS Pro Proxy Agent runs under the local account, perform the following steps:
 - Open **Services**, right-click **HPWSProxyService**, and then select **Stop**.
 - Right-click **HPWSProxyService**, and then select **Properties**.
 - On the **Log On** tab, select **Local System Account**, and then click **OK**.
 - Restart HPWSProxyService.
- If HP Universal Print Driver (UPD) 6.4 or later is installed and HP ScanJet is listed under devices, perform the following steps:
 - Install UPD 6.4 or later.
 - After the UPD driver is installed, wait until the Digital Sender displays on Windows in Devices and Printers.
- If all the hardware NULL drivers for the HP ScanJet devices have been updated (no more NULL drivers are available), perform the following steps:
 - In the **Devices and Printers** folder, right-click the **Digital Sender** icon, and then select **Properties**.
 - On the **Hardware** tab, select the first HP Digital Sender (NULL) driver in the list, and then click **Properties**.
 - In the **Properties** window, select the **Driver** tab, and then click **Update Driver**.
 - In the **Update Driver** window, click **Browse My Computer for Driver Software**.

- e. Perform one of the following actions:
 - If the **HP Printer (BIDI)** option is not listed, continue with Step j.
 - If the **HP Printer (BIDI)** option is listed, select the option, and then continue with Step f.
- f. Clear the **Show compatible hardware** check box.
- g. Under **Manufacturer**, select **HP Inc.**
- h. Under **Model**, select the first model in the list that has HP Printer (BIDI).
- i. Click **Next**.
- j. Click **Close**.
- k. For each HP Digital Sender (NULL) driver, repeat steps a through j.

When all the HP Digital Sender (NULL) drivers are updated, communication with HP WS Pro Proxy Agent is possible.

HP Web Jetadmin Instant-On USB Device Discovery

The Instant-On USB Device Discovery feature enables HP Web Jetadmin to discover USB-connected printers without manual intervention. HP WS Pro Proxy Agent uses configurable model-based filtering and device limits to detect USB-connected printers instantly and register them on the designated HP Web Jetadmin servers.

If the device limit on a specified server is reached, HP WS Pro Proxy Agent directs the discovery to the next available server.



TIP: For optimal performance, HP recommends that you configure a maximum of 3,000 devices per HP Web Jetadmin server.

Instant-On Filter Capabilities Tool

The Instant-On Filter Capabilities Tool provides a graphical user interface (GUI) for configuring the ProxyFilterCapabilitiesConfig.xml file. You can use this tool to add and remove servers, set device limits, and specify filter criteria (model name). The specified filters are applied to USB-connected printers in real time.

The changes you make using the Instant-On Filter Capabilities Tool automatically update the ProxyFilterCapabilitiesConfig.xml file.

To open the Instant-On Filter Capabilities Tool, double-click the InstantOn Filter Capabilities.exe file. This EXE file is available in the following directory:

C:\Program Files (x86)\HP Inc\HPWSProxy\bin

Instant-On Configuration File

The XML-based Instant-On Configuration file stores server IP addresses, device limits, filter type (currently the model name), and filter values. You can configure the Instant-On Configuration file to forward information about printers that meet the filter criteria to specific HP Web Jetadmin servers.

The ProxyFilterCapabilitiesConfig.xml file is available in the following directory:

C:\Program Files (x86)\HP Inc\HPWSProxy\bin

The following is an example of the ProxyFilterCapabilitiesConfig.xml file:

```
<ProxyFilterCapabilitiesConfig>
  <Servers>
    <Server_1>
      <IpAddress>192.168.10.151</IpAddress>
      <DeviceLimit>3000</DeviceLimit>
      <CapabilityType>Model Name</CapabilityType>
      <CapabilityValue>HP Color LaserJet Pro MFP 4301</CapabilityValue>
    </Server_1>
  </Servers>
</ProxyFilterCapabilitiesConfig>
```