Semester Project

Chanel Dobler

July 2026

Contents

1 SMC EX260-SDN1 DeviceNet **1**
1.1 Physical Switch Settings 1
1.1.1 Communication Speed 1
1.1.2 DeviceNet Address 2
1.2 Messaging Protocol 2
1.2.1 Connection ID (CID) 2
1.2.2 Data Field 2
1.3 Duplicate MAC ID Check 3
1.4 Master/Slave Connection Management 3
1.5 Master's Explicit Request 5

2 Keller PAA-4LD I²C **6**
2.1 Request Measurement 6
2.2 Read Measurement 6

3 Autonics TM4-N2SB RS485 **6**

1 SMC EX260-SDN1 DeviceNet

1.1 Physical Switch Settings

1.1.1 Communication Speed

The communication speed is set with the physical switches No. 3 and 4. The default value is 125kbps.

Bitrate	Switch No.	
kbps	3	4
125	0	0
250	0	1
500	1	0

Table 1: Bitrate corresponding to switch settings

1.1.2 DeviceNet Address

The DeviceNet address is set with the physical switches No. 5 to 10. The default address setting is 63.

Address	Switch No.					
-	5	6	7	8	9	10
0	0	0	0	0	0	0
1	0	0	0	0	0	1
2	0	0	0	0	1	0
...				...		
62	1	1	1	1	1	0
63	1	1	1	1	1	1

Table 2: Address corresponding to switch settings

1.2 Messaging Protocol

A message consists of a connection ID and a data field. The first message is always a duplicate MAC ID check. A master/slave connection can be established after the duplicate check is passed. Wait $\geq 1s$ for a response when you send a message.

1.2.1 Connection ID (CID)

The connection ID counts 11 bits. The structure depends on the message group. Only group 2 is relevant for this project. The connection ID for group 2 contains the group ID (2 bits), the MAC ID (6 bits) and the message ID (3 bits).

	Group ID		MAC ID						Message ID		
Bit No.	10	9	8	7	6	5	4	3	2	1	0

Table 3: Group 2 CID Structure

Message ID	Function
4	Master's Explicit Request
6	Master/Slave Connection Management
7	Duplicate MAC ID Check

Table 4: Relevant Group 2 Message IDs

1.2.2 Data Field

The data field may include some flags. The R flag indicates a request or response. The F flag indicates a complete or fragmented message. The X flag is

a transaction ID echoed in a response to match to a request.

Flag	0	1
R	Request	Response
F	Complete	Fragmented
X	-	-

Table 5: Data Field Flags

1.3 Duplicate MAC ID Check

It's inevitable that two modules on the same link will be assigned the same address. It requires human intervention to configure a unique Pi address. The Pi address is written to the CID MAC ID for the duplicate check.

Group 2		Pi Address						Message 7		
1	0	0	0	0	0	0	0	1	1	1

Table 6: Duplicate MAC ID Check CID

Byte No.		
0	R	Physical Port Number
1	Vendor ID	
2		
3	Serial Number	
4		
5		
6		

Table 7: Duplicate MAC ID Check Data Field

Important: The duplicate MAC ID check has to be transmitted two consecutive times without receiving a subsequent request or response message before establishing a connection.

1.4 Master/Slave Connection Management

Group 2		DeviceNet Address						Message 6		
1	0	1	1	1	1	1	1	1	1	0

Table 8: Master/Slave Connection Management CID

The Pi address is written to the MAC ID in the data field. The service code 0x4B indicates the allocation of a master/slave connection and 0x4C the release. The Class ID 3 directs the message at the DeviceNet object. There exists exactly one DeviceNet object per physical attachement to the DeviceNet. Therefore, the instance ID is always 1. The allocation choice byte denotes an explicit message and I/O connections from the predefined master/slave connection set. The acknowledge suppression bit has to be set to 0 for the release choice.

Byte No.			
0	F	X	MAC ID
1	R	Service Code [0x4B]	
2	Class ID [0x03]		
3	Instance ID [0x01]		
4	Allocation Choice		
5	Allocator's MAC ID		

Table 9: Master/Slave Connection Allocation Data Field

Byte No.			
0	F	X	MAC ID
1	R	Service Code [0x4C]	
2	Class ID [0x03]		
3	Instance ID [0x01]		
4	Release Choice		

Table 10: Master/Slave Connection Release Data Field

Bit No.	Connection
7	Reserved
6	Acknowledge Suppression
5	Cyclic
4	Change of State
3	Multicast Polling
2	Bit Strobed
1	Polled
0	Explicit Message

Table 11: Allocation/Release Choice

A master's explicit request message can be transmitted once a master/slave connection is established.

1.5 Master's Explicit Request

Explicit request messages are used to perform operations such as reading and writing attributes. The Pi address is written to the MAC ID in the data field. The service code 0x10 is used to write to a single attribute and the code 0x0E to read from a single attribute. The class ID 9 represents the discrete output points. The instance ID corresponds to the channel.

Group 2		DeviceNet Address						Message 4		
1	0	1	1	1	1	1	1	0	1	0

Table 12: Master's Explicit Request CID

Byte No.		
0	F	X MAC ID
1	R	Service Code [0x10]
2		Class ID [0x09]
3		Instance ID
4		Attribute ID [0x03]
5		Value

Table 13: Master's Explicit Set Single Value Data Field

Byte No.		
0	F	X MAC ID
1	R	Service Code [0x0E]
2		Class ID [0x09]
3		Instance ID
4		Attribute ID [0x03]

Table 14: Master's Explicit Get Single Value Data Field

Byte No.			
0	F	X	MAC ID
1	R	Service Code [0x10]	
2	Class ID [0x09]		
3	Instance ID		
4	Attribute ID [0x03]		
5	Value		

Table 15: Master's Explicit Set Multiple Values Data Field

Byte No.			
0	F	X	MAC ID
1	R	Service Code [0x0E]	
2	Class ID [0x09]		
3	Instance ID		
4	Attribute ID [0x03]		

Table 16: Master's Explicit Get Multiple Values Data Field

2 Keller PAA-4LD I^{2}C

The Keller addresses are set from 0x40 to 0x49. The absolute pressure ranges from 0 bar to 3 bar.

2.1 Request Measurement

The command to request a measurement is 0xAC. Wait $\geq 8ms$ before reading the measurement.

2.2 Read Measurement

Read 3 bytes
- Scale
- Status carries a checksum error indicator

3 Autonics TM4-N2SB RS485

The default address is 1. The default baudrate is 9600 bps.