

plan44 vdcd external device API

Contents

About vdcd external device API	2
External Device API operation	2
Message Format	3
Init Message	3
Init message structure	3
Button object in the buttons field of the init message	6
Input object in the inputs field of the init message	7
Sensor object in the sensors field of the init message	8
Messages from vdcd to device(s)	9
Messages from device(s) to vdcd	10
Experimenting	12
Light button simulation.....	12
Light dimmer simulation.....	12
Temperature sensor simulation.....	13
A light dimmer and a button sharing one API connection	14

About vdc external device API

This document describes the socket based API included in the [plan44.ch vdcd](http://plan44.ch/vdcd) ([virtual device connector daemon](http://plan44.ch/vdcd)).

The external device API allows external scripts and programs to register themselves to the *vdcd* to implement custom digitalSTROM devices with very little effort.

To host external devices, *vdcd* must be started with the *--externaldevices* option, providing a port number or absolute unix socket path for device implementation to connect to. For security reasons, it is recommended to run the scripts and programs implementing devices on the same device as *vdcd* itself, however for development purposes the *--externalnonlocal* command line option can be specified to allow device API connections from non-local clients.

The plan44.ch digitalSTROM products P44-DSB-DEH and P44-DSB-E support the *external device API* from version 1.5.0.8 onwards. Multiple devices sharing a single connection is supported from version 1.5.2.0 onwards. However, at the time of writing the *external device API* is active only for devices enabled for "testing"/beta (available upon request). In the free "[P44-DSB-X](http://plan44.ch)" [plan44.ch image](http://plan44.ch) for RaspberryPi, the *external device API* is always enabled. By default, *vdcd* uses port 8999 for the *external device API*

External Device API operation

Each external device implementation needs to

- open a connection to the TCP port or unix socket specified with the *--externaldevices* *vdcd* command line option (default is port 8999).
- send a *init* message declaring the properties of the device (specifying outputs, inputs, names, default group membership etc.). The *init* message uses JSON syntax. However, no JSON support is actually needed in a device implementation, because the *init* message can specify to use a extremely simple text protocol for any communication beyond the *init* message itself. And the *init* message is usually a constant string that can be sent easily using any programming language.
- enter a loop, waiting for messages from the *vdcd* indicating output channel changes, or sending messages to the *vdcd* indicating input changes.
- When connection closes (due to error or when *vdcd* explicitly closes it), the device implementation should restart, see first bullet point. This can be achieved within the device implementation itself, or by having the device implementation run as a daemon under control of a daemon supervisor like *runit*, which re-starts daemons when they terminate.
- from version 1.5.2.0 onwards, multiple devices can be created on the same TCP connection. To distinguish them, each one must be assigned a *tag* in the *init* message, which must/will then be used in all further messages to/from that device.

Message Format

Messages consist of strings, delimited by a single LF (0x0A) character. The *init* message must always be in JSON format. Further messages are either JSON or simple text messages, depending on the *protocol* option in the *init* message (see below).

Init Message

The init message is sent by a external device implementation as the first message after opening the socket connection. It needs to be formatted as a single line JSON object. It describes the device's outputs and inputs and other properties, such that vdc can instantiate an appropriate digitalSTROM device with all standard behaviour required.

To initialize multiple devices sharing the same connection, multiple *init* messages can be put into a JSON array. This is required in particular to create multiple devices that are meant to communicate via the simple text API - because after the first message, the protocol will be switched to simple text and would not allow further JSON init messages.

A simple init message for a light dimmer might look like (on a single line):

```
{'message':'init','protocol':'simple','output':'light','name':'ext dimmer','uniqueid':'myUniqueID1234'}
```

A init message for two light dimmers on the same connection might look like (on a single line):

```
[ {'message':'init', 'tag':'A', 'protocol':'simple', 'output':'light', 'name':'ext dimmer A', 'uniqueid':'myUniqueID1234_A'}, {'message':'init', 'tag':'B', 'protocol':'simple', 'output':'light', 'name':'ext dimmer B', 'uniqueid':'myUniqueID1234_B'} ]
```

The following tables describes all possible fields of the *init* message JSON object:

Init message structure

Field	Type	Description
<i>message</i>	string	identifies the message type, must be init for the <i>init</i> message
<i>protocol</i>	optional string	Can be set to simple to use the simple text protocol for all further communication beyond the <i>init</i> message. This allows implementing devices without need for any JSON parsing. If set to json (default), further API communication are JSON messages. Note: <i>protocol</i> can be specified only in the first <i>init</i> message. It is ignored if present in any subsequent <i>init</i> messages.
<i>tag</i>	optional string	When multiple devices are created on the same connection, each device needs to have a <i>tag</i> assigned. The <i>tag</i> must not contain '=' or ':'. The <i>tag</i> is used to identify the device in further communication.

<i>uniqueid</i>	string	<p>This string must uniquely define the device at least among all other external devices connected to the same vdc, or even globally.</p> <p>To identify the device globally, use a UUID string (XXXXXXXX-XXXX-XXXX-XXXX-XXXXXXXXXXXX) or a valid 34 hex digit digitalSTROM dSUID.</p> <p>To identify the device uniquely among all other devices in the same vdc, use any other string.</p>
<i>group</i>	optional integer	<p>defines the primary color (group) of the device:</p> <ul style="list-style-type: none"> 1: yellow/light, 2: grey/shadow 3: blue/heating 4: cyan/audio 5: magenta/video 6: red/security 7: green/access 8: black/joker 9: white/cooling 10: ventilation 11: windows
<i>output</i>	optional string	<p>Defines the type of output:</p> <ul style="list-style-type: none"> light: dimmer output with light behaviour colorlight: 6-channel digitalSTROM color light (brightness, hue, saturation, colortemp, cieX, cieY) movinglight: color light with additional X and Y position channels heatingvalve: 0..100% heating valve shadow: jalousie type device with position and angle channel. Also see <i>move</i> field. basic: basic 0..100% output with no special behaviour. Can be used for relay outputs. <p>Default is no output.</p>
<i>kind</i>	optional string for "shadow" output type	<p>Defines the kind of shadow device</p> <ul style="list-style-type: none"> roller: simple roller blind, no angle sun: sunblind jalousie: jalousie with blade angle control
<i>endcontacts</i>	optional boolean for "shadow" output type	<p>If set to true, device implementation must report reaching top and bottom positions by updating channel value to 100 or 0, resp. (using the "channel" message). Otherwise, the shadow behaviour uses move time settings to derive actual positions from timing alone.</p>
<i>move</i>	optional boolean	<p>If set to true, the device must support the "move" or "MV" message (see below), which is issued by the device to start or stop a movement (increase, decrease) of the output value. The move semantic might be more useful for blind type devices than channel output values.</p> <p>Default is false (no move semantics)</p>

<i>sync</i>	optional boolean	if set to true, the device must support the "sync" message and must respond to "sync" with the "synced" message. "sync" is issued by the vdc when it needs to know current output values (e.g. for a saveScene operation). "synced" is sent by the device when updated output channel values have been sent to the vdc. Default is false (no output value sync requests)
<i>groups</i>	optional array of integers	can be used to specify output group membership different from the defaults of the specified <i>output</i> type.
<i>hardwarename</i>	optional string	a string describing the type of output hardware, such as "dimmer" or "relay" etc. Default is the string specified in <i>output</i> .
<i>modelname</i>	optional string	a string describing the device model. This will be displayed by the dSS as "HW Info".
<i>iconname</i>	optional string	a string that is used as a base to construct a file name to be displayed for the device. vdc will first try to load a icon named " <i>iconname_groupcolor</i> " (with <i>groupcolor</i> being the color of the device). If such a file does not exist, vdc tries to load " <i>iconname_other</i> ". Default for <i>iconname</i> is "ext".
<i>name</i>	optional string	the default name the device will have in the digitalSTROM system. Note that this can be changed by the user via dSS Web interface.
<i>buttons</i>	optional array of objects	Defines the buttons of the device. See table below for fields in the button objects
<i>inputs</i>	optional array of objects	Defines the binary inputs of the device. See table below for fields in the input objects
<i>sensors</i>	optional array of objects	Defines the sensors of the device. See table below for fields in the sensor objects

Button object in the buttons field of the init message

Field	Type	Description
<i>id</i>	optional integer	identifies the hardware button this button input belongs to. Two-way or multi-way buttons will have multiple button definitions with the same id. Defaults to 0
<i>buttontype</i>	optional integer	Defines the type of button: 0: kind of button not defined by device hardware 1: single pushbutton 2: two-way pushbutton or rocker (Note: if you use this, the first button must be the the down element and the second button must be the up element. 3: 4-way navigation button 4: 4-way navigation with center button 5: 8-way navigation with center button 6: On-Off switch Defaults to 1 (single pushbutton)
<i>element</i>	optional integer	Defines which element of a multi-element button is represented by this button input: 0: center element / single button 1: down, for 2,4,8-way 2: up, for 2,4,8-way 3: left, for 2,4,8-way 4: right, for 2,4,8-way 5: upper left, for 8-way 6: lower left, for 8-way 7: upper right, for 8-way 8: lower right, for 8-way Default is 0 (single button)
<i>group</i>	optional integer	defines the primary color (group) of the button: 1: yellow/light, 2: grey/shadow 3: blue/heating 4: cyan/audio 5: magenta/video 6: red/security 7: green/access 8: black/joker Defaults to primary device group
<i>hardwarename</i>	optional string	a string describing the button element, such as "up" or "down" etc.

Input object in the inputs field of the init message

Field	Type	Description
<i>inputtype</i>	optional integer	Defines the type of input: 0: no system function 1: Presence 2: Light 3: Presence in darkness 4: twilight 5: motion 6: motion in darkness 7: smoke 8: wind 9: rain 10: solar radiation (sun light above threshold) 11: thermostat (temperature below user-adjusted threshold) 12: device has low battery 13: window is open 14: door is open 15: window handle 16: garage door is open 17: protect against too much sunlight 18: frost detector Defaults to 0 (no system function)
<i>usage</i>	optional integer	Defines usage: 0: undefined 1: room (indoors) 2: outdoors 3: user interaction Default is 0 (undefined)
<i>group</i>	optional integer	defines the primary color (group) of the button: 1: yellow/light, 2: grey/shadow 3: blue/heating 4: cyan/audio 5: magenta/video 6: red/security 7: green/access 8: black/joker Defaults to primary device group
<i>updateinterval</i>	optional double	defines the expected update interval of this input, i.e. how often the actual state is reported by the device. Defaults to 0, which means no fixed interval
<i>hardwarename</i>	optional string	a string describing the button element, such as "up" or "down" etc.

Sensor object in the sensors field of the init message

Field	Type	Description
<i>sensortype</i>	optional integer	Defines the type of sensor: 0: undefined 1: temperature in degrees celsius 2: relative humidity in % 3: illumination in lux 4: supply voltage level in Volts 5: CO (carbon monoxide) concentration in ppm 6: Radon activity in Bq/m3 7: gas type sensor 8: dust, particles <10µm in µg/m3 9: dust, particles <2.5µm in µg/m3 10: dust, particles <1µm in µg/m3 11: room operating panel set point, 0..1 12: fan speed, 0..1 (0=off, <0=auto) 13: wind speed in m/s 14: Power in W 15: Electric current in A 16: Energy in kWh 17: Electric Consumption in VA 18: Air pressure in hPa 19: Wind direction in degrees 20: Sound pressure level in dB 21: Precipitation in mm/m2 22: CO2 (carbon dioxide) concentration in ppm Defaults to 0 (undefined)
<i>usage</i>	optional integer	Defines usage: 0: undefined 1: room (indoors) 2: outdoors 3: user interaction Default is 0 (undefined)
<i>group</i>	optional integer	defines the primary color (group) of the button: 1: yellow/light, 2: grey/shadow 3: blue/heating 4: cyan/audio 5: magenta/video 6: red/security 7: green/access 8: black/joker Defaults to primary device group
<i>updateinterval</i>	optional double	defines the expected update interval in seconds of this sensor, i.e. how often the actual value is reported by the device. Defaults to 5 seconds
<i>hardwarename</i>	optional string	a string describing the button element, such as "up" or "down" etc.
<i>min</i>	optional double	minimal value, defaults to 0
<i>max</i>	optional double	maximal value, defaults to 100
<i>resolution</i>	optional double	sensor resolution, defaults to 1

Messages from vdc d to device(s)

vdc d sends (depending on the features selected in the *init* message) the messages shown in the table below.

If devices were created with a *tag* (which is required when creating multiple devices on a single connection), all JSON protocol messages will include the *tag* field, and all simple text protocol messages will be prefixed by *tag* plus a colon.

JSON protocol	Simple protocol	Description
<pre>{ 'message':'status', 'status':s, 'errorcode':e, 'errormessage':m, 'errordomain':d 'tag':t }</pre>	OK or ERROR= m	Status for <i>init</i> message. If ok, s is the string "ok" in the JSON protocol. m is a textual error message e is the vdc d internal error code d is the vdc d internal error domain t is the tag (only present if device was created with a tag in the <i>init</i> message)
<pre>{ 'message':'channel', 'index':i, 'type':ty, 'value':v, 'tag':t }</pre>	Ci= v or with tag: t :Ci= v	Output channel index i has changed its value to v . v is a double value. The device implementation should forward the new channel value to the device's output. The JSON variant of this message additionally reports the channel type as ty : 0: undefined 1: brightness for lights 2: hue for color lights 3: saturation for color lights 4: color temperature for lights with variable white point 5: X in CIE Color Model for color lights 6: Y in CIE Color Model for color lights 7: vertical position 8: horizontal position 9: opening angle position 10: permeability t is the tag (only present if device was created with a tag in the <i>init</i> message)
<pre>{ 'message':'move', 'index':i, 'direction':d, 'tag':t }</pre>	MVi= d or with tag: t :MVi= d	When the init message has specified <i>move=true</i> , the vdc d can request starting or stopping movement of channel i as follows: 0: stop movement 1: start movement to increase channel value -1: start movement to decrease channel value t is the tag (only present if device was created with a tag in the <i>init</i> message)
<pre>{ 'message':'sync', 'tag':t }</pre>	SYNC or with tag: t :SYNC	When the init message has specified <i>sync=true</i> , the vdc d can request updating output channel values by sending <i>sync</i> . The device is expected to update channel values (using the "channel"/"C" message, see below) and then sending the <i>synced</i> message. t is the tag (only present if device was created with a tag in the <i>init</i> message)

Messages from device(s) to vdc

the device(s) can send (depending on the features selected in the *init* message) the messages shown in the table below.

If devices were created with a *tag* (which is required when creating multiple devices on a single connection), all JSON protocol messages must include the *tag* field, and all simple text protocol messages must be prefixed by *tag* plus a colon to identify the device.

JSON protocol	Simple protocol	Description
<pre>{ 'message':'bye', 'tag':t }</pre>	BYE or with tag: t:BYE	The device can send this message to disconnect from the vdc, for example when it detects its hardware is no longer accessible. Just closing the socket connection has the same effect as sending <i>bye</i> (in case of multiple tagged devices, closing socket is like sending <i>bye</i> to each device) t is the tag (only needed if device was created with a tag in the <i>init</i> message)
<pre>{ 'message':'log', 'level':n, 'text':logmessage, 'tag':t }</pre>	Ln=logmessage or with tag: t:Ln=logmessage	The device can send a logmessage to the vdc log. n is the log level (by default, levels above 5 are not shown in the log - 7=debug, 6=info, 5=notice, 4=warning, 3=error, 2=critical, 1=alert, 0=emergency) t is the tag (only needed if device was created with a tag in the <i>init</i> message)
<pre>{ 'message':'channel', 'index':i, 'value':v, 'tag':t }</pre>	Ci=v or with tag: t:Ci=v	The device should send this message when its output channel index i has changed its value to v for another reason than having received a channel message (e.g. after initialisation, or for devices that can be controlled directly). Devices that cannot immediately detect output changes can specify <i>sync=true</i> in the <i>init</i> message, so the vdc will request updating output channel values by sending <i>sync</i> only when these values are actually needed. t is the tag (only needed if device was created with a tag in the <i>init</i> message)
<pre>{ 'message':'button', 'index':i, 'value':v, 'tag':t }</pre>	Bi=v or with tag: t:Bi=v	The device should send this message when the state of its button at index i has changed. If the button was pressed, v must be set to 1, if the button was released, v must be set to 0. To simulate a button press+release with a single message, set v to the press duration in milliseconds. t is the tag (only needed if device was created with a tag in the <i>init</i> message)
<pre>{ 'message':'input', 'index':i, 'value':v, 'tag':t }</pre>	Ii=v or with tag: t:Ii=v	The device should send this message when the state of its input at index i has changed. If the input has changed to active v must be set to 1, if the input has changed to inactive, v must be set to 0. t is the tag (only needed if device was created with a tag in the <i>init</i> message)

<pre>{ 'message':'sensor', 'index':i, 'value':v, 'tag':t }</pre>	<p>Si=v</p> <p>or with tag: t:Si=v</p>	<p>The device should send this message when the value of its sensor at index i has changed. v is the new value (double) and should be within the range specified with <i>min</i> and <i>max</i> in the <i>init</i> message. t is the tag (only needed if device was created with a tag in the <i>init</i> message)</p>
<pre>{ 'message':'synced', 'tag':t }</pre>	<p>SYNCED</p> <p>or with tag: t:SYNCED</p>	<p>The device must send this message after receiving <i>sync</i> and having updated output channel values. t is the tag (only needed if device was created with a tag in the <i>init</i> message)</p>

Experimenting

The external device API can be experimented easily with by connecting via telnet, then pasting an *init* message and then simulating some I/O.

The following paragraphs show this for different device types. Please also refer to the sample code in different languages contained in the *external_devices_samples* folder of the [vdcd project](#).

Light button simulation

Connect to the device API with telnet:

```
telnet localhost 8999
```

Now copy and paste (single line!!) a simple *init* message defining a light button:

```
{'message':'init','protocol':'simple','uniqueid':'experiment42','buttons':  
[{'buttontype':1,'group':1,'element':0}]}
```

The vdcd responds with:

```
OK
```

Now, the vdcd has created a light button device. If this is the vdcd of a P44-DSB, you can see the device in the P44-DSB web interface, and if the vdcd is connected to a digitalSTROM system, a new button device will appear in the dSS. By default, it will be in the default room for the “external devices” vdc, but you can drag it to an existing room with digitalSTROM light devices.

Now you can switch lights by simulating a button click (250ms active) with

```
B0=250
```

For dimming, the button can be held down...

```
B0=1
```

...and later released

```
B0=0
```

Light dimmer simulation

Connect to the device API with telnet:

```
telnet localhost 8999
```

Now copy and paste (single line!!) a simple *init* message defining a dimmer output:

```
{'message':'init','protocol':'simple','uniqueid':'experiment42b','output':'  
light'}
```

The vdcd responds with:

OK

Now, the vdc has created a light dimmer device. If this is the vdc of a P44-DSB, you can see the device in the P44-DSB web interface, and if the vdc is connected to a digitalSTROM system, a new light device will appear in the dSS

Now you can call scenes in the room that contains the light device (or use the sprocket button in the P44-DSB web interface to directly change the brightness). You will see channel value changes reported from the external device API:

```
C0=3.120000
C0=8.190000
C0=14.040000
C0=21.840000
C0=30.810000
C0=40.950000
C0=56.160000
C0=63.960000
C0=69.810000
C0=78.000000
C0=79.950000
C0=78.000000
C0=65.130000
C0=53.040000
C0=42.120000
C0=33.150000
C0=26.910000
C0=40.950000
C0=53.040000
C0=58.110000
C0=63.180000
```

Temperature sensor simulation

Connect to the device API with telnet:

```
telnet localhost 8999
```

Now copy and paste (single line!!) a simple *init* message defining a light button:

```
{'message':'init','protocol':'simple','group':
3,'uniqueid':'experiment42c','sensors':[{ 'sensortype':1,'usage':1,'group':
48,'min':0,'max':40,'resolution':0.1}]}
```

The vdc responds with:

OK

Now, the vdc has created a temperature sensor device.

Now you can simulate temperature changes with

```
S0=22.5
```

e.g. to report a room temperature of 22.5 degree celsius.

A light dimmer and a button sharing one API connection

Connect to the device API with telnet:

```
telnet localhost 8999
```

Now copy and paste (single line!!) two *init* messages packaged into a JSON array, defining the dimmer and the button device:

```
[ {'message':'init', 'tag':'DIMMER', 'protocol':'simple', 'group':3,
  'uniqueid':'experiment42d', 'output':'light'}, {'message':'init',
  'tag':'BUTTON', 'uniqueid':'experiment42e', 'buttons':[{'buttontype':1,
  'group':1, 'element':0}]] ]
```

The vdc d responds with:

```
OK
```

Now simulate a button click (250ms active) with

```
BUTTON:B0=250
```

As both dimmer and button are initially in the same room, the button acting (by default) as a room button will switch on the light, so you will see:

```
DIMMER:C0=100.000000
```