

```

1.Please read: https://www.xenesis.jp/2022/05/altair-680-basic/ esp. POLCAT, INCH.
2.Please read: https://github.com/simple-circuit/picobug/blob/main/sim680b\_rev1.ino
// UART Status 0xF000 Read Only, Bit-1 Transmit Ready, Bit-0 Receive Ready
//      Use: LDAA $F000 or LDAB $F000
// UART Write Data 0xF001
//      Use: STAA $F001 or STAB $F001
// UART Read Data 0xF003
//      Use: LDAA $F003, LDAB $F003, or ANDB $F003
3.All in the one code!
//HERE(HEAD of CODE)
MF000 EQU $F000
MF001 EQU $F001
MF003 EQU $F003
M00F3 EQU $00F3
STACK EQU $00F1

      ORG $0100
START
      JSR HELLO
      JSR ECHOB
      RTS

HELLO LDX #MSG
HELSTA LDAB 0,X
      NOP
      NOP
      NOP
      NOP
      BEQ HELEXT
      JSR OUTCH
      INX
      BRA HELSTA
HELEXT RTS

ECHOB LDX #MSG2
LOOP LDAB 0,X
      NOP
      NOP
      NOP
      NOP
      BEQ XXXXX
      JSR OUTCH
      INX
      BRA LOOP
XXXXX JSR INCH;MYINCH
      NOP
      NOP

```

```

      NOP
      NOP
      ;BEQ XXXXX
      JSR OUTCH
      BRA XXXXX
Z0112 RTS

MSG FCB 13,10
      FCC 'HELLO, WORLD'
      FCB 13,10,4,0,0

OUTCH PSHB
ZFF85 LDAB MF000
      RORB
      RORB
      BCC ZFF85
      PULB
      ANDB #$7F
      STAB MF001
      RTS

*POLE FOR CHARACTER
*SETS CARRY IF CHARACTER IS IN BUFFER CLOBBERS B REG
POLCAT LDAB MF000 ;ACIA STATUS TO B
      ASRB ;ROTATE RDRF BIT INTO CARRY
      RTS ;RETURN

*INPUT ONE CHARACTER ACC B
INCH BSR POLCAT
      BCC INCH
      LDAB MF003 ;GET CHAR
      CMPB #'a'
      BCS UPE
      CMPB #'z'+1
      BCC UPE
      ADDB #'A'-'a'
UPE:
      RTS

MSG2 FCB 13,10
      FCC 'ECHO BACK TEST'
      FCB 13,10,4,0,0

      END
//HERE(HEAD of CODE)

```