程序代写代做 CS编程辅导

Examination 2021

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

Question 1.a

程序代写代做 CS编程辅导

(a) A frequency shift keying (FSK) coon system transmits $s_o(t)$ to represent binary 1 (mark) and $s_1(t)$ to represent binary 0 (s[illegible]e

$$s_o(t) = A\cos 2\pi f_o t \qquad 0 \leq t \leq T$$

$$s_1(t) = A\cos 2\pi f_1 t \qquad 0 \leq t \leq T$$

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

Assuming that $T \gg 1/f_o$ and $T \gg 1/f_1$

(i) Find the energy per bit.

(ii) Find an expression for the correlation coefficient, ρ between the mark and space signals.

(iii) Deduce the relationship that gives zero correlation coefficient.

Solution

程序代写代做 CS编程辅导

Energy per bit is found from either space signal as

$$E = \int_0^T A^2 cos^2 2\pi f_o t dt = \int_0^T \left(\frac{A^2}{2} + \frac{A^2}{2} cos 4\pi f_o t\right) dt$$

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

The integral becomes equal to

$$E = \left(\frac{A^2 T}{2} + \frac{A^2}{8\pi f_o} sin 4\pi f_o T\right)$$

For $T \gg \frac{1}{f_o}$

The second term is much smaller than the first term which gives the energy per bit as

$$E = \frac{A^2 T}{2}$$

Solution Cont.

程序代写代做 CS编程辅导

The correlation coefficient is

$$\rho = \frac{\int_0^T cos2\pi f_o t.cos2\pi f_1 t.dt}{E = A^2T/2} \text{ X } A^2$$

$$\rho = \frac{T}{2E}\left(\frac{sin2\pi(f_o + f_1)T}{2\pi(f_o + f_1)T} + \frac{sin2\pi(f_1 - f_0)T}{2\pi(f_1 - f_o)T}\right) \text{ X } A^2$$

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

Solution Cont.

程序代写代做 CS编程辅导

$$\rho = \frac{T}{2E}\left(\frac{sin2\pi(f_o + f_1)T}{2\pi(f_o + f_1)T} + \frac{sin2\pi(f_o - f_1)T}{2\pi(f_o - f_1)T}\right) \text{ X } A^2$$

For $T \gg \frac{1}{f_o}$

The first term is much smaller than the second term

$$\rho = \frac{T}{2E}\frac{sin2\pi(f_1 - f_0)T}{2\pi(f_1 - f_o)T} \text{ X } A^2$$

For zero correlation

$sin2\pi(f_1 - f_0)T = sin\pi n$ or equivalently

$f_1 - f_0 = n/2T$

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

Q. 1.b

程序代写代做 CS编程辅导

- Assume binary coded informa[illegible]nsmitted at 10 kb/s using FSK signal. The received amplitude of each to[illegible]10^{-2} V. The additive single sided noise power density spectrum is 10×10^{-9} W/Hz. Find the bit error rate of a coherent detector using the table of the complementary error function for correlation coefficients of (i) 0 and (ii) 0.3 and comment on the result.

WeChat: cstutorcs
Assignment Project Exam Help
Email: tutorcs@163.com
QQ: 749389476
https://tutorcs.com

$$P_e = \frac{1}{2} erfc \sqrt{\frac{E(1-\rho)}{2N_o}} \quad \text{and} \quad \rho = \frac{\int_0^T s_{mark}(t) s_{space}(t) dt}{\sqrt{\int_0^T s(t)^2_{mark} dt \int_0^T s(t)^2_{space} dt}}$$

$$\cos(2\pi f_1 t) . \cos(2\pi f_2 t) = \frac{1}{2}\{\cos(2\pi f_1 + 2\pi f_2) t + \cos(2\pi f_1 - 2\pi f_2) t\}$$

Solution 1.b

程序代写代做 CS编程辅导

$$P_e = \frac{1}{2} erfc \sqrt{\frac{E(1-\rho)}{2N_o}}$$

For zero correlation

$$P_e = \frac{1}{2} erfc \sqrt{\frac{E}{2N_o}}$$

$$E = \frac{A^2 T}{2}$$

The bit duration is 1/10,000

Substituting for the amplitude and T the Energy = 2×10^{-8}

$$P_e = \frac{1}{2} erfc\ (1) = (0.1572992)/2 = 0.0786$$

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

Solution 1.b cont

程序代写代做 CS编程辅导

$$For\ 0.3\ correlation$$

$$P_e = \frac{1}{2} erfc \sqrt{\frac{0.7\ E}{2N_o}}$$

$$= \frac{1}{2} erfc\ (0.8367)$$

From the error function tables
For 0.8 the value is 0.2578990 and for 0.85 the value is 0.2293319
which gives =0.1184

The error rate has increased due the correlation being greater than zero.

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

Question 1.c

程序代写代做 CS编程辅导

A time division multiplexi analogue modulated system transmits eight audio tele ignals with baseband bandwidth equal to 3.4 kHz and two music signals with baseband bandwidth equal to 15 kHz. For an 8-bit analogue to digital converter determine the required bandwidth of transmission for

WeChat: cstutorcs
Assignment Project Exam Help
Email: tutorcs@163.com
QQ: 749389476
https://tutorcs.com

(i) Unipolar non return to zero (NRZ).

(ii) Unipolar return to zero (RZ).

(iii) Manchester code.

Solution Q.1.c

程序代写代做 CS编程辅导

For equal sampling the number of samples is equal to

15x10x2=300 k samples per second.

Each sample is represented by 8 bits so the total number of bits per second is equal to 300x8=2400 kbps

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

Solution cont.

程序代写代做 CS编程辅导

Unipolar NRZ is represented by one +V for mark signal and 0 for space.

WeChat: cstutorcs

For binary NRZ the highest data rate is when we transmit alternate ones and zeros.

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

In this case the spectrum is that of a square wave and has sinx/x function with the first null at 1/Tb which in this case is equal to 2400 kHz.

https://tutorcs.com

Solution cont.

程序代写代做 CS编程辅导

Unipolar return to zero would represent the mark by +V for half the bit and 0 for the second half while the space is represented by 0 for the duration of the bit.

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

For bandwidth requirements the Unipolar RZ would require twice the bandwidth assuming a long sequence of mark bits.

For RZ the bandwidth would be twice that of NRZ at 4800 kHz.

Solution Cont.

程序代写代做 CS编程辅导

The Manchester code has +V for half the bit duration followed by -V for the second half.

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

So for a mark it could be +V followed by -V and the complement for a space i.e. -V followed by +V.

So the bandwidth requirements are similar to the Unipolar RZ.

Question 2.a

程序代写代做 CS编程辅导

A mobile user is travelling at a [illegible] 50 km/hr as shown in Figure Q.2.1.a-b. Assume that the mobile phon[illegible]s a signal to noise ratio of 18 dB and that the noise floor of the receiver is -1[illegible]

Assume that both base stations transmit 20 dBm and use antennas with 3 dB gain, while the mobile uses an antenna with 0 dB gain and that the foliage attenuation is 10 dB. The base stations have dual frequency bands at 900 MHz and 1800 MHz.

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

i. Find the antenna gains in linear scale.

ii. Find the transmit power in mW for the base station.

Solution

程序代写代做 CS编程辅导

(i)

Gain in linear scale is 2 for the base station and 1 for the mobile computed on the basis of 10log(G)=3, 0

WeChat: cstutorcs
Assignment Project Exam Help
Email: tutorcs@163.com
QQ: 749389476
https://tutorcs.com

(ii)

Power of the transmitter at base station is 10log(p)=20 dBm

gives 100 mW

Question 2.a

程序代写代做 CS编程辅导

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

Question 2.a

程序代写代做 CS编程辅导

Given the relationship in equation 2 [illegible] space path loss, determine the time at which the mobile phone would need to be har[illegible]rom base station 1 BS1 to base station 2 BS2 for 900 MHz and 1800 MHz operating frequ[illegible]igures Q2.1.a and Q.2.1.b for a 2 dB margin for hand off.

$$\frac{P_R}{P_T} = G_T G_R \left[\frac{c}{4\pi f d}\right]^2$$

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

where PT and PR are the transmit and receive powers respectively, G_T and G_R are the gains of the transmit and receive antennas respectively,
d is the distance from the transmitter and
f is the transmission frequency.

Solution

程序代写代做 CS编程辅导

For hand off the minimum recnal strength should be

18+2=20 dB above noise floor

So the received signal power is -100+20=-80 dBm

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

$$\frac{P_R}{P_T} = G_T G_R \left[\frac{c}{4\pi f d}\right]^2$$

$$10logP_R = 10logP_T + 10logG_R + 10logG_T + 20log\frac{c}{4\pi} - 20logf - 20logd$$

Solution

程序代写代做 CS编程辅导

For 900 MHz we get

-80=20+3+0+147.55-179-20logd

-71.55=-20logd

This gives a range of 3.78 km from BS1
Travelling at 50 km/hr this would mean a hand off after 4.536 minutes

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

For 1800 MHz we get
-80=20+3+0+147.55-185-20logd

This gives 1.89 km from BS1
Travelling at 50 km/hr this would mean a hand off after 2.268 minutes

Question 2.a

程序代写代做 CS编程辅导

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

(iv) Comment on the success of the handover strategy for both scenarios at the two frequencies.

Solution cont.

程序代写代做 CS编程辅导

- Scenario 1

For the 900 MHz, the handoff would be successful.

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

For the 1800 MHz the distance to BS2 is larger than 1.89 km, then the mobile will lose communication unless the power level is increased to permit longer distance prior to hand off is initiated.

Solution cont.

程序代写代做 CS编程辅导

In the second scenario, the tre[illegible]n the distance of the hand off of the 900 MHz band. This adds another [illegible]ss.

WeChat: cstutorcs

To estimate the point of the hand off we first find the received signal strength at 2 km i.e. at the point of the tree.

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

Path loss at 2 km is equal to 94.566 dB at 900 MHz and 100.566 dB at 1800 MHz

The received signal strength at the tree is then equal to

-74.566 dBm at 900 MHz and -80.566 dBm at 1800 MHz

Solution cont.

程序代写代做 CS编程辅导

- Scenario 2

At 900 MHz, immediately after traveling past the tree, the received signal strength from BS1 will drop to -84.566 which is below the acceptable level for handoff. The received signal strength from BS2 at the tree -78 dBm which is acceptable. However, due to the insufficient hand off margin, the mobile will lose communication resulting in unsuccessful handoff.

WeChat: cstutorcs
Assignment Project Exam Help
Email: tutorcs@163.com
QQ: 749389476
https://tutorcs.com

For the 1800 MHz, the handoff will still occur before the tree but will be unsuccessful due to higher losses.

Question 2.b

程序代写代做 CS编程辅导

A cellular system has 15 c to be multiplexed. Each user has a data rate of 10 kbps. Dete he overall bandwidth required for the system using frequency division multiple access.

WeChat: cstutorcs

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

Solution

程序代写代做 CS编程辅导

For FDMA there are 15 us  each would require 10 kHz bandwidth.

WeChat: cstutorcs

So the overall bandwidth is 150 kHz for the uplink and 150 kHz for the downlink. So overall 300 kHz for the system.

Assignment Project Exam Help

Email: tutorcs@163.com

QQ: 749389476

https://tutorcs.com

Question 2.c

程序代写代做 CS编程辅导

Discuss the different mechanisms o[illegible]on that connect the transmitter and a receiver.

1. Free space which is LoS,
2. diffraction when an obstacle is between the transmitter and receiver.
3. Scattering when the wave is incident on a surface which has undulations which are proportional to the wavelength and in this case the waves scatter in all directions leading to high losses.
4. Reflection is when the wave is incident on a surface where the dimensions are of undulations are much larger than the wavelength and this leads to a relatively stronger received signal than the scattered signal.
5. The other mechanism is refraction like light incident on a prism.

WeChat: cstutorcs
Assignment Project Exam Help
Email: tutorcs@163.com
QQ: 749389476
https://tutorcs.com