

LOST + FOUND

Collection of Curiosities

What are you looking for?

Lost + Found is our first true multi-effect, a little museum of the rare and strange for you to wander around. Tour through 12 modes that can be blended in countless ways, a bit of whatever you need and a whole bunch you're not expecting.

A TIME

Sets the timing of the effects. By default, all modes are synced and this knob will choose the subdivision, allowing you to adjust freely and stay in time. You can turn this off with the **UNSYNC** dip switch.

B MIX

Sets the balance between your input signal and Lost + Found (controls both channels simultaneously).

C MODIFY

A bidirectional control that selects between two different effects and adjusts their character. At noon you will get no effect, allowing you to use the **GLUE** on its own.

D BYPASS

 Tap to engage channel.

 Hold to engage a mode-specific secondary function.



E BLEND

Sets the balance of the two channels. In parallel (**L+R**) it will set which channel is louder in the overall mix. In series (**L>R**, **L<R**) it will control the mix of the second effect in the chain.

F ROUTING

Sets the routing of the two channels, either in parallel or two different series options.

G EFFECT TYPE

Selects the effect type. Full breakdown on the next page.

H PRESETS

The left and right positions each store a preset, while the middle position is live (current settings). There is a second bank accessible via dip switch as well.

Modes

Use the **MODIFY** knob to select between A or B.

LEFT CHANNEL

REVERB

1A.  **Slow-verb**
TIME - SIZE
MODIFY - DECAY
ALT - DIFFUSION

1B.  **Useful Ambience**
TIME - SIZE
MODIFY - DECAY
ALT - DIFFUSION


PITCH

2A.  **Orchestral Swell**
TIME - SWELL TIME
MODIFY - PITCH
ALT - FEEDBACK

2B.  **Pitch Repeater**
TIME - DELAY
MODIFY - PITCH
ALT - NUMBER OF REPEATS

WARP


3A.  **Pinging Phaser**
TIME - RATE
MODIFY - POLES
ALT - RESONANCE

3B.  **Spectral Modulator**
TIME - RATE
MODIFY - DEPTH
ALT - RESONANCE

RIGHT CHANNEL


DELAY

4A.  **Tape Echo**
TIME - DELAY TIME
MODIFY - FEEDBACK
ALT - STABILITY

4B.  **Grain Tumbler**
TIME - GRAIN SIZE
MODIFY - FEEDBACK
ALT - GRAIN SHAPE

SYNTH

5A.  **Impulse Synthesizer**
TIME - PORTAMENTO
MODIFY - TEXTURE
ALT - ATTACK / RELEASE

5B.  **Sympathic Resonator**
TIME - ONSET
MODIFY - FEEDBACK
ALT - OCTAVE

BEND

6A.  **Ensemble Expander**
TIME - RATE
MODIFY - DEPTH
ALT - NUMBER OF VOICES

6B.  **Gen Lite**
TIME - RATE
MODIFY - DEPTH
ALT - DROPS AND SNAGS

I CUSTOMIZE

You can use Lost + Found's various dip switches to configure things to your liking:

MISO

Mono In, Stereo Out. Splits a mono input signal into a stereo output.

SPREAD

Turns on stereo processing to generate movement and create an expansive stereo image.

LATCH

Changes the hold function for each footswitch from momentary to latching, so that it will remain engaged until the footswitch is held again.

L SWAP

Replaces the effects in the Left Channel with those from the Right Channel.

R SWAP

Replaces the effects in the Right Channel with those from the Left Channel.

UNSYNC

Disconnects the tempo of the two channels, allowing you to explore free, asynchronous effects and a smoother response from the TIME knob.

TRAILS

Allows the effects to naturally fade out after the pedal is bypassed.

BANK

Switches over to an alternate bank of internal presets, giving you access to two additional slots on the pedal (Presets 3 and 4).



J HIDDEN OPTIONS

Hold down both footswitches to fine tune various aspects of Lost + Found.

ALT

Accesses a third, mode specific parameter for each effect.

EQ

A two-sided EQ. Rotate clockwise to remove low frequencies and thin out the signal. Rotate counter-clockwise to remove high frequencies and to darken the overall signal.

SPILL

When using Lost + Found in series (L>R or L<R), use SPILL to apply the second effect in the series to your dry signal as well.

GLUE

An end of chain compressor / saturator combo. The first portion of the sweep will gradually add compression, and beyond that your signal will start to overload.

SPREAD ROUTING

Lets you apply stereo SPREAD to only one channel. This might be helpful, for example, if you want a wide stereo reverb with a delay cutting through the middle. Point the toggle towards the channel you want to have stereo movement.

