POWER ENTRY (7-pin XLR NC7MD-LX on the rear panel. two 5 A contacts per rail. 18 AWG to this terminal: +-17 V PSU)

DISTRIBUTION (PTC per wing per rail. 1.85 A hold. 7Z V: local branches VA audio. VP phones. VM meters. VL logic)

MOTHERBOARD (master in the center: CN1 = left wing. CN2 = right wing. Delta pinout)

GROUND CANCEL BUFFER (feeds every re-inverter. summing amps use the raw GCANCEL line: 100K keeper)

MIX L: summing amp (GCANCEL-referenced). re-inverter. master insert

MIX R: summing amp (GCANCEL-referenced). re-inverter. master insert

MASTER FADER (dual 100 mm A10K. pin 1 = GNDA) + post-amps +10 dB

MONO: inverting sum of POST L+R. re-inverter

MAIN OUTPUTS: DRV134 -> 10k NP in the Sense loop -> XLR mate. pin 2 hot

POWER-ON MUTE: rails > -14 V for ~2.7 s closes all six relays: either rail low opens them at once

AUX MASTER 5: OPA4612 sum (2X || 100p) + re-invert. level. buffer. DRV134 out. AFL

AUX MASTER 6: OPA4612 sum (2X || 100p) + re-invert. level. buffer. DRV134 out. AFL

HEADPHONES: PHONES dual A10K. OPA4612 + LME49600 composite (+9.9 dB). 2R2 out. mute relay. PHONES\GND

CONTROL ROOM: C/ROOM dual A10K. followers. DRV134. mute relays. TRS outs

REMOTE METER HEADER (tor a meter bridge)

EXT INPUT (2-track / DAW) and MIX / EXT monitor select (SW latched = EXT)

PFL DETECT (0.92 V per press vs 0.50 V. 2 x 1N4148 clamp. 1u debounce) and DG413 logic. beside the switcher

RUDE SOLO: ~2 Hz flasher. PFL ACTIVE LED. held off through FLiN while no key is pressed

METER L: full-wave rectifier. precision peak / average. follower (TL072). 2 dB ladder. 2 x 10-LED strings

METER R: full-wave rectifier. precision peak / average. follower (TL072). 2 dB ladder. 2 x 10-LED strings

LINK CABLE (2x20 IDC ribbon to the master jack board (9 jacks. 3 XLRs)

Notes joined by label(s): refs auto-assigned
Generated by tools/gen_master.py from master_section_spec.md v0.9

Sheet / File	master_section.kicad_sch
Title	Master section — goa Console
Size	E (34 x 22 in)
Date	2026-10-19
Rev	0.9
KiCad	8.0
Id	1/1