GROUND CANCEL BUFFER  (feeds every re-inverter: summing amps use the raw GCANCEL line; 100K keeper)

MIX L: summing amp (GCANCEL-referenced), re-inverter, master insert

MIX R: summing amp (GCANCEL-referenced), re-inverter, master insert

MASTER FADER (dual 100 mm A10K; pin 1 = GNDA) + post-amps +10 dB

MONO: inverting sum of POST L+R, re-inverter

MAIN OUTPUTS: DRV134 -> 10u NP in the Sense loop -> mute relay (NO: NC grounds the line) -> XLR male, pin 2 hot

POWER-ON MUTE: rails > -14 V for ~2.7 s closes all six relays; either rail low opens them at once

AUX MASTER 5: OPA1612 sum (22K || 100p) + re-invert, level, buffer, DRV134 out, AFL

AUX MASTER 6: OPA1612 sum (22K || 100p) + re-invert, level, buffer, DRV134 out, AFL

EXT INPUT (2-track / DAW) and MIX / EXT monitor select  (SW latched = EXT)

PFL / AFL: OPA1656 sum (22K || 100p) + re-invert, SOLO LEVEL, follower

PFL SWITCHER: DG413 (PFL pressed = SW1/SW4, else SW2/SW3; break-before-make) -> CRS L/R OPA1656 followers

PFL DETECT (0.92 V per press vs 0.50 V: 2 x 1N4148 clamp, 1u debounce) and DG413 logic, beside the switcher

RUDE SOLO: ~2 Hz flasher, PFL ACTIVE LED; held off through FL_N while no key is pressed

CONTROL ROOM: C/ROOM dual A10K, followers, DRV134, mute relays, TRS outs

HEADPHONES: PHONES dual A10K, OPA1612 + LME49600 composite (+9.9 dB), 2R2 out, mute relay, PHONESGND

METER L: full-wave rectifier, precision peak / average, follower (TL072), 2 dB ladder, 2 x 10-LED strings

METER R: full-wave rectifier, precision peak / average, follower (TL072), 2 dB ladder, 2 x 10-LED strings

POWER ENTRY  (7-pin XLR NC7MD-LX on the rear panel, two 5 A contacts per rail, 18 AWG to this terminal: +-17 V PSU)

DISTRIBUTION  (PTC per wing per rail, 1.85 A hold, 72 V; local branches VA audio, VP phones, VM meters, VL logic)

MOTHERLOOM  (master in the centre: CN1 = left wing, CN2 = right wing; Delta pinout)

REMOTE METER HEADER (for a meter bridge)

MOTHERBOARD LINK  2x20 IDC ribbon to the master jack board (9 jacks, 3 XLRs)