Fake-Peak Artificial Noise for Sensing-Location Privacy in Cell-Free Massive MIMO ISAC

***Abstract*—Multi-static cell-free massive MIMO integrated sensing and communication is vulnerable to internal sensing leakage, since a served user can reconstruct transmit beampatterns and fuse their dominant directions to infer a target location. Conventional artificial noise (AN) under strict per-access-point (AP) physical-channel nulling is absent from the raw observations used by this internal adversary. We instead exploit the receive-processing asymmetry between legitimate post-combining detection and raw-sample reconstruction. Network-wide effective-channel nulling cancels the AN at the combiner outputs while preserving it in the adversary's multi-antenna observations. Within the resulting null space, the AN is shaped to generate AP-dependent dominant directions consistent with a common virtual location. A joint beam design maximizes the sensing signal-to-noise ratio under communication quality and per-AP power constraints. Simulations show that, at an AN-power ratio of approximately 0.50, the proposed design lowers the target-localization success rate from 35.8% without AN to 2.8%, with a 3.6 dB sensing-SNR loss.**

***Index Terms*—Cell-free massive MIMO, integrated sensing and communication, sensing privacy, artificial noise, internal adversary.**

I. Introduction

Integrated sensing and communication (ISAC) is a key technology for sixth-generation networks, enabling data transmission and environmental sensing through shared spectrum and hardware [1]. Cell-free massive MIMO (CF-mMIMO) is especially suitable for ISAC, since geographically distributed access points (APs) coordinated by a central processor form a virtual array that jointly illuminates targets [2], [3]. The same distributed configuration, however, enlarges the attack surface for sensing-information leakage.

Physical-layer security has long been used to protect confidential messages against eavesdropping. In the seminal artificial-noise (AN) design of Goel and Negi [4], noise is radiated in the null space of the legitimate channel, so that the eavesdropper is degraded while the intended user is unaffected. These ideas have been extended to secure ISAC, where the illuminated target is treated as an information eavesdropper and the precoding and AN covariance are optimized to degrade its channel [5]–[7]. A complementary line of work protects the sensing function itself. Low-probability-of-intercept power allocation has been studied for integrated multi-static radar and communication systems [8], and the target-location distribution has been exploited as prior knowledge in secure ISAC beamforming [9]. Notably, Zou *et al.* [10] model a served communication user as a sensing eavesdropper and design AN-aided beamforming to limit its sensing mutual information, while Han *et al.* [11] shape the ISAC ambiguity function to create ghost targets in an unauthorized receiver's range profile.

This correspondence addresses the internal threat identified in [12], where a served user reconstructs the transmit beampattern of each AP and then fuses the AP-dependent directions to localize the target. We refer to this as the *reconstruction attack*. Such an adversary is difficult to defend against because it is indistinguishable from an ordinary user at the protocol level. In particular, classical AN designs suppress the AN on the legitimate users' channels so that intended reception is unaffected [4], [6]. However, when the adversary is itself a served user, such nulling also removes the AN from its own received samples and therefore provides no protection.

The contributions of our study are twofold. First, we find that data detection operates on post-combining scalar observations, whereas the reconstruction attack exploits raw samples before combining. Exploiting this receive-processing asymmetry, we null the AN on the network-wide effective channels rather than on the physical channels, thereby retaining the AN in the adversary's raw observations. Second, within this subspace we design a fake-peak AN beam whose AP-dependent deceptive directions are generated from a common virtual location, and jointly optimize the communication, sensing, and AN beams by an alternating concave-convex procedure (CCCP)–minimum mean square error (MMSE) algorithm under quality-of-service (QoS) and per-AP power constraints.

Notation: Boldface upper- and lower-case letters denote matrices and vectors, and $\mathbb{C}$ is the complex field. $(\cdot)^*$, $(\cdot)^H$, $(\cdot)^T$, $(\cdot)^\dagger$, $\mathrm{Tr}(\cdot)$, $\|\cdot\|$, and $\|\cdot\|_F$ are the conjugate, conjugate transpose, transpose, pseudoinverse, trace, Euclidean norm, and Frobenius norm. $\mathbf{I}_N$ is the $N\times N$ identity matrix, $\mathcal{N}(\cdot)$ the null space, $\Re\{\cdot\}$ the real part, $\angle(\cdot)$ the phase angle, $\mathbb{E}\{\cdot\}$ the expectation, $\Pr\{\cdot\}$ the probability, and $\jmath=\sqrt{-1}$. $\mathbf{A}\succ\mathbf{0}$ and $\mathbf{A}\succeq\mathbf{0}$ mean positive definite and positive semidefinite, and $\mathcal{CN}(\mathbf{0},\mathbf{R})$ denotes a circularly symmetric complex Gaussian distribution.

II. System and Threat Model

We consider a CF-mMIMO ISAC network with N_{tx} transmit APs, N_{rx} receive APs, and N_{UE} multi-antenna users. Each transmit AP employs an M_{tx}-element uniform linear array with half-wavelength spacing, and each user has M_{UE} antennas. The APs are coordinated by a central processor to serve the users and illuminate a point target. Accordingly, the signal emitted by AP k at time index n can be expressed as

$$\mathbf{x}_k[n]=\sum_{i=1}^{N_{\mathrm{UE}}}\mathbf{w}_{i,k}s_i[n]+\mathbf{w}_{t,k}s_t[n], \tag{1}$$

where $\mathbf{w}_{i,k}\in\mathbb{C}^{M_{\mathrm{tx}}\times 1}$ is the beam for user i, $\mathbf{w}_{t,k}\in\mathbb{C}^{M_{\mathrm{tx}}\times 1}$ is the sensing beam, and the symbols $\{s_i[n]\}_{i=1}^{N_{\mathrm{UE}}}$ and $s_t[n]$ are mutually independent with zero mean and unit variance. The AP–user channel is modeled as $\mathbf{H}_{i,k}=\sqrt{\beta_{i,k}}\,\mathbf{G}_{i,k}\in\mathbb{C}^{M_{\mathrm{UE}}\times M_{\mathrm{tx}}}$, where $\mathbf{G}_{i,k}$ has i.i.d. $\mathcal{CN}(0,1)$ entries and $\beta_{i,k}$

denotes the large-scale fading coefficient. The system operates in time-division duplex mode. Exploiting channel reciprocity, each transmit AP estimates $\mathbf{H}_{i,k}$ from τ_{p}-length orthogonal uplink pilots of per-antenna power $p_i^{\mathrm{p}} = P_{\mathrm{p}}/M_{\mathrm{UE}}$, where P_{p} is the total pilot power per user, received with i.i.d. $\mathcal{CN}(0, \sigma_{\mathrm{p}}^2)$ noise. This yields the linear minimum mean square error (LMMSE) estimate $\widehat{\mathbf{H}}_{i,k}$ used for beam design.

In the downlink transmission, the received signal at user i and time index n is $\mathbf{y}_i[n] = \sum_k \mathbf{H}_{i,k}\mathbf{x}_k[n] + \mathbf{n}_i[n]$, where $\mathbf{n}_i[n] \sim \mathcal{CN}(\mathbf{0}, \sigma_i^2\mathbf{I}_{M_{\mathrm{UE}}})$ denotes the noise, and user i applies a combiner $\mathbf{u}_i \in \mathbb{C}^{M_{\mathrm{UE}}\times 1}$. For multi-static sensing, AP k illuminates the target at angle ϕ_k with steering vector $\mathbf{a}(\phi) = [1, e^{\jmath\pi\sin\phi}, \ldots, e^{\jmath\pi(M_{\mathrm{tx}}-1)\sin\phi}]^T$. With $\mathbf{W}_k \triangleq [\mathbf{w}_{1,k}, \ldots, \mathbf{w}_{N_{\mathrm{UE}},k}, \mathbf{w}_{t,k}]$, the average sensing SNR is

$$\gamma_t = \sum_{k=1}^{N_{\mathrm{tx}}} c_k \left\|\mathbf{a}^H(\phi_k)\mathbf{W}_k\right\|_F^2, \quad c_k = \frac{\sum_{r=1}^{N_{\mathrm{rx}}} \xi_{r,k}^2 g_{r,k}}{N_{\mathrm{rx}}\sigma_{\mathrm{rx}}^2}, \quad (2)$$

where $g_{r,k} = \lambda_c^2/[(4\pi)^3 d_{t,k}^2 d_{t,r}^2]$ is the two-way path gain, in which λ_c is the carrier wavelength and $d_{t,k}$ and $d_{t,r}$ denote the transmit-AP-k–target and target–receive-AP-r distances, $\xi_{r,k}^2$ is the scattering power absorbing the target radar cross section and the receive array gain, and σ_{rx}^2 is the receive noise power.

One served user, indexed by a, is treated as an internal adversary. It knows its own pilots, data symbols, combiner $\mathbf{u}_a$, and the transmit-AP positions, and can form its own estimate $\widehat{\mathbf{H}}_{a,k}^{\mathrm{adv}}$ of its channel $\mathbf{H}_{a,k}$. Following [12], it is assumed to separate its received samples into per-AP components. The attack must operate on the raw multi-antenna samples, since applying $\mathbf{u}_a$ would collapse each snapshot into a scalar and leave the M_{tx}-dimensional transmit-vector recovery underdetermined. After decoding its own data symbol $s_a[n]$, the adversary subtracts its data component using its channel estimate $\widehat{\mathbf{H}}_{a,k}^{\mathrm{adv}}$, which leaves $\widetilde{\mathbf{y}}_{a,k}[n] = \widehat{\mathbf{H}}_{a,k}^{\mathrm{adv}}\widetilde{\mathbf{x}}_k[n] + \widetilde{\mathbf{n}}_{a,k}^{\mathrm{adv}}[n]$ with the non-self transmit component $\widetilde{\mathbf{x}}_k[n] = \sum_{j\neq a}\mathbf{w}_{j,k}s_j[n] + \mathbf{w}_{t,k}s_t[n]$, and $\widetilde{\mathbf{n}}_{a,k}^{\mathrm{adv}}[n]$ collecting the receiver noise and the residual caused by adversary-side channel-estimation errors. It then applies an expectation-maximization routine to obtain $\widehat{\mathbf{x}}_k[n] \approx \widetilde{\mathbf{x}}_k[n]$, and forms the AP-dependent beampattern from the sample covariance over the available snapshots, i.e.,

$$\widehat{B}_k(\theta) = \mathbf{a}^H(\theta)\mathbf{R}_{\widehat{\mathbf{x}}_k}\mathbf{a}(\theta), \quad \mathbf{R}_{\widehat{\mathbf{x}}_k} = \frac{1}{N}\sum_{n=1}^{N}\widehat{\mathbf{x}}_k[n]\widehat{\mathbf{x}}_k^H[n], \quad (3)$$

where θ denotes the search angle scanned by the adversary and N is the number of available snapshots. The target position is then estimated by fusing the direction lines emanating from each AP along the dominant angle of $\widehat{B}_k(\theta)$, taking the cell of a search grid of resolution Δ_{g}.

III. Channel-Nulling-Based Fake-Peak AN Design

A. Receive-Processing Asymmetric Nulling

We augment the transmit signal at AP k as

$$\mathbf{x}_k[n] = \sum_{i=1}^{N_{\mathrm{UE}}}\mathbf{w}_{i,k}s_i[n] + \mathbf{w}_{t,k}s_t[n] + \mathbf{z}_k s_z[n], \quad (4)$$

where $\mathbf{z}_k \in \mathbb{C}^{M_{\mathrm{tx}}\times 1}$ is the AN beam, and $s_z[n]$ is a common AN symbol with zero mean and unit variance, mutually independent of $\{s_i[n], s_t[n]\}$. Legitimate detection of user i is performed after the receive combiner $\mathbf{u}_i$, which reduces the AP–user channel to the effective row vector $\mathbf{g}_{i,k}^H \triangleq \mathbf{u}_i^H\mathbf{H}_{i,k} \in \mathbb{C}^{1\times M_{\mathrm{tx}}}$. Accordingly, the downlink SINR in this situation is

$$\gamma_i^{\mathrm{AN}} = \frac{\left|\sum_k \mathbf{g}_{i,k}^H\mathbf{w}_{i,k}\right|^2}{\mathcal{D}_i + \left|\sum_k \mathbf{g}_{i,k}^H\mathbf{z}_k\right|^2}, \quad (5)$$

where $\mathcal{D}_i \triangleq \sum_{j\neq i}\left|\sum_k \mathbf{g}_{i,k}^H\mathbf{w}_{j,k}\right|^2 + \left|\sum_k \mathbf{g}_{i,k}^H\mathbf{w}_{t,k}\right|^2 + \sigma_i^2$. By contrast, the reconstruction attack relies on raw multi-antenna samples. This asymmetry motivates nulling the AN at the legitimate combiner outputs rather than on the physical channels. We therefore compare two nulling levels.

Let $\widehat{\mathbf{g}}_{i,k}^H \triangleq \mathbf{u}_i^H\widehat{\mathbf{H}}_{i,k}$ denote the estimated effective channel. Strict per-AP physical-channel nulling imposes $\widehat{\mathbf{H}}_{i,k}\mathbf{z}_k = \mathbf{0}$ for every user i and AP k. Network-wide effective-channel nulling instead imposes

$$\sum_{k=1}^{N_{\mathrm{tx}}}\widehat{\mathbf{g}}_{i,k}^H\mathbf{z}_k = 0, \quad \forall i, \quad (6)$$

which nominally cancels the AN at each legitimate combiner output while generally leaving $\widehat{\mathbf{H}}_{i,k}\mathbf{z}_k$ nonzero in the per-AP raw observations, as illustrated in Fig. 1.




Fig. 1. Nominal network-wide effective-channel nulling.

For comparison, define the stacked AN beam $\overline{\mathbf{z}} \triangleq [\mathbf{z}_1^T, \ldots, \mathbf{z}_{N_{\mathrm{tx}}}^T]^T$ and the network-wide effective-channel matrix $\widehat{\overline{\mathbf{G}}}$, whose ith row is $[\widehat{\mathbf{g}}_{i,1}^H, \ldots, \widehat{\mathbf{g}}_{i,N_{\mathrm{tx}}}^H]$. Then the network-wide constraint (6) is equivalent to $\widehat{\overline{\mathbf{G}}}\overline{\mathbf{z}} = \mathbf{0}$. For fixed combiners, the implication $\widehat{\mathbf{H}}_{i,k}\mathbf{z}_k = \mathbf{0} \Rightarrow \widehat{\mathbf{g}}_{i,k}^H\mathbf{z}_k = 0$ places strict physical-channel nulling inside network-wide effective-channel nulling. The rank–nullity theorem gives the corresponding dimensions

$$d_{\mathrm{phys}} = N_{\mathrm{tx}}[M_{\mathrm{tx}} - N_{\mathrm{UE}}M_{\mathrm{UE}}]^+, \quad d_{\mathrm{eff}} = [N_{\mathrm{tx}}M_{\mathrm{tx}} - N_{\mathrm{UE}}]^+, \quad (7)$$

where $[x]^+ \triangleq \max(x, 0)$. Network-wide effective-channel nulling imposes fewer nulling constraints than its per-AP counterpart, because it exploits cross-AP cancellation rather than requiring each AP to null its AN independently. The larger feasible shaping space leaves more freedom for geometry-consistent fake-peak shaping.

B. Fake-Peak Design and Alternating Optimization

Under (4), the non-self transmit component seen by the adversary becomes $\widetilde{\mathbf{x}}_k[n] = \sum_{j\neq a}\mathbf{w}_{j,k}s_j[n] + \mathbf{w}_{t,k}s_t[n] + \mathbf{z}_k s_z[n]$. Since the data, sensing, and AN symbols are mutually independent, the beampattern reconstructed in (3) decomposes as $\widehat{B}_k(\theta) \approx \sum_{j\neq a}|\mathbf{a}^H(\theta)\mathbf{w}_{j,k}|^2 + |\mathbf{a}^H(\theta)\mathbf{w}_{t,k}|^2 + |\mathbf{a}^H(\theta)\mathbf{z}_k|^2$.

Within the effective-channel null space, we place the AN response along $\phi_{\mathrm{fake},k} = \angle(\mathbf{p}_{\mathrm{f}} - \mathbf{p}_k) \neq \phi_k$, where $\mathbf{p}_{\mathrm{f}}$ is a prescribed virtual location and $\phi_k = \angle(\mathbf{p}_t - \mathbf{p}_k)$ is the true direction determined by the target position $\mathbf{p}_t$. When the two directions are resolvable and the fake response dominates, the resulting AP-dependent direction lines remain consistent with $\mathbf{p}_{\mathrm{f}}$ and shift the fused estimate toward it.

Let Γ_{comm} denote the minimum required user SINR, P_T the per-AP transmit-power budget, and ρ the ratio between the fake-direction AN response and the useful-beam power in the true direction. Collect the transmit variables as $\mathcal{W} \triangleq \{\mathbf{W}_k\}_{k=1}^{N_{\mathrm{tx}}}$ and $\mathcal{Z} \triangleq \{\mathbf{z}_k\}_{k=1}^{N_{\mathrm{tx}}}$. Since the central processor designs the beams from the estimated CSI, define $h_i(\mathcal{W}) \triangleq \sum_k \widehat{\mathbf{g}}_{i,k}^H \mathbf{w}_{i,k}$ and

$$\widehat{\gamma}_i = \frac{|h_i(\mathcal{W})|^2}{\mathcal{I}_i(\mathcal{W}, \mathcal{Z})}, \tag{8}$$

where $\mathcal{I}_i(\mathcal{W}, \mathcal{Z}) = \sum_{j \neq i} \left|\sum_k \widehat{\mathbf{g}}_{i,k}^H \mathbf{w}_{j,k}\right|^2 + \left|\sum_k \widehat{\mathbf{g}}_{i,k}^H \mathbf{w}_{t,k}\right|^2 + \left|\sum_k \widehat{\mathbf{g}}_{i,k}^H \mathbf{z}_k\right|^2 + \sigma_i^2$. On this basis, the secure beam design can be formulated as

$$\max_{\{\mathbf{W}_k, \mathbf{z}_k, \mathbf{u}_i\}} \quad \sum_{k=1}^{N_{\mathrm{tx}}} c_k \left\|\mathbf{a}^H(\phi_k)\mathbf{W}_k\right\|_F^2 \tag{9a}$$

$$\text{s.t.} \quad \widehat{\gamma}_i \geq \Gamma_{\mathrm{comm}}, \ \forall i, \tag{9b}$$

$$\|\mathbf{u}_i\| = 1, \ \forall i, \tag{9c}$$

$$\textstyle\sum_{j=1}^{N_{\mathrm{UE}}} \|\mathbf{w}_{j,k}\|^2 + \|\mathbf{w}_{t,k}\|^2 + \|\mathbf{z}_k\|^2 \leq P_T, \ \forall k, \tag{9d}$$

$$\textstyle\sum_{k=1}^{N_{\mathrm{tx}}} \widehat{\mathbf{g}}_{i,k}^H \mathbf{z}_k = 0, \ \forall i, \tag{9e}$$

$$\textstyle\sum_{k=1}^{N_{\mathrm{tx}}} \widehat{\mathbf{g}}_{i,k}^H \mathbf{w}_{t,k} = 0, \ \forall i, \tag{9f}$$

$$\left|\mathbf{a}^H(\phi_{\mathrm{fake},k})\mathbf{z}_k\right|^2 \geq \rho \left\|\mathbf{a}^H(\phi_k)\mathbf{W}_k\right\|_F^2, \ \forall k. \tag{9g}$$

Constraint (9b) enforces communication QoS, (9d) limits the per-AP power, and (9e)–(9f) place the stacked AN and sensing beams in $\mathcal{N}(\widehat{\mathbf{G}})$, thereby removing both terms at the prescribed legitimate combiners. Although the adversary subtracts its own stream, (9g) retains the full $\mathbf{W}_k$, because the adversary is indistinguishable from an ordinary user and the central processor therefore cannot identify a. The constraint is thus enforced conservatively for every candidate adversary. With $\mathbf{W}_{-a,k}$ denoting $\mathbf{W}_k$ without $\mathbf{w}_{a,k}$, define $S_k = \|\mathbf{a}^H(\phi_k)\mathbf{W}_{-a,k}\|_F^2$, $F_k = |\mathbf{a}^H(\phi_{\mathrm{fake},k})\mathbf{z}_k|^2$, and $T_k = |\mathbf{a}^H(\phi_k)\mathbf{z}_k|^2$. Then (9g) gives $S_k \leq F_k/\rho$. If $T_k/F_k \leq 1/M_{\mathrm{tx}}$, the ideal covariance decomposition yields

$$\widehat{B}_k(\phi_{\mathrm{fake},k}) - \widehat{B}_k(\phi_k) \geq F_k - S_k - T_k \geq F_k \left(1 - \frac{1}{\rho} - \frac{1}{M_{\mathrm{tx}}}\right). \tag{10}$$

Hence, $\rho > M_{\mathrm{tx}}/(M_{\mathrm{tx}} - 1)$ is sufficient for the fake-direction response to exceed the true-direction response. The prescribed $\mathbf{p}_{\mathrm{f}}$ must therefore yield resolvable true and fake directions. Since $s_z[n]$ is known at the sensing receivers and independent of $s_t[n]$, ideal matched filtering separates their echoes.

For fixed combiners, the transmit subproblem is nonconvex. Define $\mathbf{A}_k = \mathbf{a}(\phi_k)\mathbf{a}^H(\phi_k)$, $\mathbf{A}_{\mathrm{f},k} = \mathbf{a}(\phi_{\mathrm{fake},k})\mathbf{a}^H(\phi_{\mathrm{fake},k})$, and, for $\mathbf{A} \succeq \mathbf{0}$,

$$\mathcal{L}_{\mathbf{A}}(\mathbf{X}; \mathbf{X}_0) \triangleq 2\Re\{\mathrm{Tr}[(\mathbf{A}\mathbf{X}_0)^H \mathbf{X}]\} - \mathrm{Tr}(\mathbf{X}_0^H \mathbf{A} \mathbf{X}_0), \tag{11}$$

which lower-bounds $\mathrm{Tr}(\mathbf{X}^H \mathbf{A} \mathbf{X})$ at $\mathbf{X}_0$. At CCCP iteration v, every convex quadratic that is maximized or subtracted is replaced by its affine lower bound at the current iterate. For the sensing objective this gives the surrogate $\widetilde{f}_0^{(v)}(\mathcal{W}) = \sum_k c_k \mathcal{L}_{\mathbf{A}_k}(\mathbf{W}_k; \mathbf{W}_k^{(v)})$, and for the fake-direction response it gives $\widetilde{\zeta}_k = \mathcal{L}_{\mathbf{A}_{\mathrm{f},k}}(\mathbf{z}_k; \mathbf{z}_k^{(v)})$. Since h_i is a scalar aggregating all APs rather than a per-AP quadratic form, (11) does not apply directly, and the affine lower bound of $|h_i(\mathcal{W})|^2$ is written out as $\widetilde{h}_i = 2\Re\{h_i^*(\mathcal{W}^{(v)}) h_i(\mathcal{W})\} - |h_i(\mathcal{W}^{(v)})|^2$. The CCCP transmit update [13] is

$$\max_{\{\mathbf{W}_k, \mathbf{z}_k\}} \quad \widetilde{f}_0^{(v)}(\mathcal{W}) \tag{12a}$$

$$\text{s.t.} \quad \Gamma_{\mathrm{comm}} \mathcal{I}_i(\mathcal{W}, \mathcal{Z}) - \widetilde{h}_i \leq 0, \ \forall i, \tag{12b}$$

$$\text{(9d), (9e), (9f)}, \tag{12c}$$

$$\rho\,\mathrm{Tr}(\mathbf{W}_k^H \mathbf{A}_k \mathbf{W}_k) - \widetilde{\zeta}_k \leq 0, \ \forall k. \tag{12d}$$

This is a convex quadratically constrained problem because its objective is affine and all negative convex terms have been replaced by their affine lower bounds. For fixed combiners, tightness preserves feasibility of the current point. Thus, letting $f_0(\mathcal{W}) \triangleq \sum_k c_k \mathrm{Tr}(\mathbf{W}_k^H \mathbf{A}_k \mathbf{W}_k)$ and assuming that the surrogate problem is solved exactly, we obtain

$$f_0(\mathcal{W}^{(v+1)}) \geq \widetilde{f}_0^{(v)}(\mathcal{W}^{(v+1)}) \geq \widetilde{f}_0^{(v)}(\mathcal{W}^{(v)}) = f_0(\mathcal{W}^{(v)}), \tag{13}$$

where the two inequalities and the equality follow from global minorization, subproblem optimality, and tangency, respectively. Hence, each feasible fixed-combiner CCCP update is non-decreasing in the original objective.

For fixed transmit beams, let $\mathbf{q}_{i,j} = \sum_k \widehat{\mathbf{H}}_{i,k} \mathbf{w}_{j,k}$, $\mathbf{q}_{i,t} = \sum_k \widehat{\mathbf{H}}_{i,k} \mathbf{w}_{t,k}$, $\mathbf{q}_{i,z} = \sum_k \widehat{\mathbf{H}}_{i,k} \mathbf{z}_k$, $\mathbf{Q}_i = [\mathbf{q}_{i,z}, \mathbf{q}_{i,t}]$, and

$$\mathbf{R}_i = \sum_{j \neq i} \mathbf{q}_{i,j}\mathbf{q}_{i,j}^H + \mathbf{q}_{i,t}\mathbf{q}_{i,t}^H + \mathbf{q}_{i,z}\mathbf{q}_{i,z}^H + \sigma_i^2 \mathbf{I}_{M_{\mathrm{UE}}}. \tag{14}$$

Since $\mathbf{R}_i \succ \mathbf{0}$, maximizing $|\mathbf{u}_i^H \mathbf{q}_{i,i}|^2/(\mathbf{u}_i^H \mathbf{R}_i \mathbf{u}_i)$ subject to $\mathbf{Q}_i^H \mathbf{u}_i = \mathbf{0}$ and $\|\mathbf{u}_i\| = 1$ gives the MMSE update

$$\widetilde{\mathbf{u}}_i = \mathbf{R}_i^{-1}\mathbf{q}_{i,i} - \mathbf{R}_i^{-1}\mathbf{Q}_i \left(\mathbf{Q}_i^H \mathbf{R}_i^{-1} \mathbf{Q}_i\right)^{\dagger} \mathbf{Q}_i^H \mathbf{R}_i^{-1} \mathbf{q}_{i,i}, \tag{15}$$

where $\mathbf{u}_i = \widetilde{\mathbf{u}}_i/\|\widetilde{\mathbf{u}}_i\|$. To verify the optimality, let $\boldsymbol{\alpha}_i = (\mathbf{Q}_i^H \mathbf{R}_i^{-1} \mathbf{Q}_i)^{\dagger} \mathbf{Q}_i^H \mathbf{R}_i^{-1} \mathbf{q}_{i,i}$. Then we have $\mathbf{Q}_i^H \widetilde{\mathbf{u}}_i = \mathbf{0}$ and $\mathbf{R}_i \widetilde{\mathbf{u}}_i = \mathbf{q}_{i,i} - \mathbf{Q}_i \boldsymbol{\alpha}_i$. Thus, for any feasible $\mathbf{u}_i$, Cauchy–Schwarz in the $\mathbf{R}_i$-inner product gives

$$\frac{|\mathbf{u}_i^H \mathbf{q}_{i,i}|^2}{\mathbf{u}_i^H \mathbf{R}_i \mathbf{u}_i} = \frac{|\mathbf{u}_i^H \mathbf{R}_i \widetilde{\mathbf{u}}_i|^2}{\mathbf{u}_i^H \mathbf{R}_i \mathbf{u}_i} \leq \widetilde{\mathbf{u}}_i^H \mathbf{R}_i \widetilde{\mathbf{u}}_i, \tag{16}$$

with equality when $\mathbf{u}_i$ is proportional to $\widetilde{\mathbf{u}}_i$. Therefore, the vector in (15) is globally optimal whenever $\widetilde{\mathbf{u}}_i \neq \mathbf{0}$ and the constraint null space is nonempty.

The transmit beams are initialized along the dominant user-channel, true, and fake steering directions. If the first update (12) is solvable, its global lower bounds ensure original feasibility, which the constrained-MMSE step preserves by keeping the preceding combiner feasible. Each exact transmit update is non-decreasing in f_0 by (13), the MMSE step leaves f_0 unchanged, and per-AP power constraints bound f_0 above, so its values converge. Iterations stop once the relative change in f_0 falls below $\varepsilon_{\mathrm{tol}}$, and convergence of the variables or to a joint KKT point is not claimed.

C. Imperfect-CSI Extension

Channel-estimation errors could destroy the nominal null. Write $\mathbf{H}_{i,k} = \widehat{\mathbf{H}}_{i,k} + \mathbf{E}_{i,k}$ and let $\widehat{\mathcal{H}}$ collect all channel estimates. Under the LMMSE model, $\mathbf{E}_{i,k}$ is independent of $\widehat{\mathcal{H}}$ and across links, with i.i.d. $\mathcal{CN}(0, \widetilde{\beta}_{i,k})$ entries, where $\widetilde{\beta}_{i,k} = \epsilon^2_{i,k}\beta_{i,k}$ and $\epsilon^2_{i,k} = \sigma^2_{\mathrm{p}}/(\tau_{\mathrm{p}} p^{\mathrm{p}}_i \beta_{i,k} + \sigma^2_{\mathrm{p}})$. If the unit-norm combiner $\mathbf{u}_i$ and beams $\{\mathbf{v}_k\}$ depend only on $\widehat{\mathcal{H}}$, then

$$\begin{aligned}\mathbb{E}\left\{ \left| \sum_k \mathbf{u}_i^H \mathbf{H}_{i,k} \mathbf{v}_k \right|^2 \middle| \widehat{\mathcal{H}} \right\} \\ = \left| \sum_k \mathbf{u}_i^H \widehat{\mathbf{H}}_{i,k} \mathbf{v}_k \right|^2 + \sum_{k=1}^{N_{\mathrm{tx}}} \widetilde{\beta}_{i,k} \|\mathbf{v}_k\|^2,\end{aligned} \tag{17}$$

because the conditional error term is zero mean with variance $\sum_k \widetilde{\beta}_{i,k}\|\mathbf{v}_k\|^2$, so its cross term with the estimated-channel component vanishes. Setting $\mathbf{v}_k = \mathbf{z}_k$ and applying (9e) gives

$$\mathbb{E}\left\{ \left| \sum_k \mathbf{u}_i^H \mathbf{H}_{i,k} \mathbf{z}_k \right|^2 \middle| \widehat{\mathcal{H}} \right\} = \sum_{k=1}^{N_{\mathrm{tx}}} \widetilde{\beta}_{i,k} \|\mathbf{z}_k\|^2. \tag{18}$$

Thus, for fixed per-AP AN powers, the residual is independent of the AN direction under the isotropic error model. Summing (17) over all data, sensing, and AN beams gives the CSI-error interference floor

$$L_i^{\mathrm{csi}} = \sum_{k=1}^{N_{\mathrm{tx}}} \widetilde{\beta}_{i,k}\, P_k, \quad P_k \triangleq \sum_{j=1}^{N_{\mathrm{UE}}} \|\mathbf{w}_{j,k}\|^2 + \|\mathbf{w}_{t,k}\|^2 + \|\mathbf{z}_k\|^2, \tag{19}$$

which includes the useful-beam estimation error and depends on each AP's total radiated power.

Since L_i^{csi} is a convex quadratic form, define the updated interference-plus-noise $\overline{\mathcal{I}}_i(\mathcal{W}, \mathcal{Z}) = \mathcal{I}_i(\mathcal{W}, \mathcal{Z}) + L_i^{\mathrm{csi}}$ and the corresponding robust SINR $\overline{\gamma}_i = |h_i(\mathcal{W})|^2/\overline{\mathcal{I}}_i(\mathcal{W}, \mathcal{Z})$. The resulting robust formulation of (9a)–(9g) is

$$\max_{\{\mathbf{W}_k, \mathbf{z}_k, \mathbf{u}_i\}} \quad \sum_{k=1}^{N_{\mathrm{tx}}} c_k \left\| \mathbf{a}^H(\phi_k) \mathbf{W}_k \right\|_F^2 \tag{20a}$$

$$\text{s.t.} \quad \overline{\gamma}_i \geq \Gamma_{\mathrm{comm}}, \ \forall i, \tag{20b}$$

$$(9c),\ (9d),\ (9e),\ (9f),\ (9g). \tag{20c}$$

The same CCCP–MMSE updates apply by replacing $\mathcal{I}_i$ with $\overline{\mathcal{I}}_i$ in (12) and $\sigma_i^2 \mathbf{I}_{M_{\mathrm{UE}}}$ with $(\sigma_i^2 + L_i^{\mathrm{csi}})\mathbf{I}_{M_{\mathrm{UE}}}$ in (14). The added positive quadratic term preserves convexity of the transmit update. Moreover, $\overline{\gamma}_i \leq \widehat{\gamma}_i$, so the robust feasible set is contained in the nominal one and the two coincide as $\epsilon^2_{i,k} \to 0$. Under the same feasibility and exact-solve assumptions, the preceding objective-value convergence argument remains valid. This error-averaged formulation controls conditional mean interference under the adopted isotropic LMMSE model.

IV. Simulation Results

A. Simulation Setup and Metrics

Table I lists the default parameters. Throughout, the beams are designed from LMMSE channel estimates, whereas the adversary's reconstruction and the realized SINRs are evaluated on the actual channels. The realized AN-power ratio is $\eta = \sum_k \|\mathbf{z}_k\|^2 / \sum_k \big(\sum_i \|\mathbf{w}_{i,k}\|^2 + \|\mathbf{w}_{t,k}\|^2 + \|\mathbf{z}_k\|^2\big)$.

Five candidate designs are included for comparison. The *no-AN* baseline maximizes the sensing objective under the QoS and power constraints. The *null-space-only AN* baseline projects Gaussian AN onto $\mathcal{N}(\widehat{\mathbf{G}})$ without fake-peak shaping, whereas the *MI-minimizing AN* baseline adapts [10] to minimize true-direction leakage within the same null space. The proposed nominal and robust designs solve (9a)–(9g) and (20), respectively. Localization succeeds when the fused estimate lies in the target's grid cell of size Δ_{g}, while localization error is its Euclidean distance from the target.

TABLE I
Default Simulation Parameters

Parameter	Value
Network size $(N_{\mathrm{tx}}, N_{\mathrm{rx}}, N_{\mathrm{UE}})$	$(8, 4, 4)$
Antenna counts $(M_{\mathrm{tx}}, M_{\mathrm{UE}})$	$(16, 16)$
Carrier frequency	1.9 GHz
Power/SINR $(P_T, \Gamma_{\mathrm{comm}})$	$(30$ dBm, 10 dB$)$
Noise powers $(\sigma_i^2, \sigma_{\mathrm{rx}}^2, \sigma_{\mathrm{p}}^2)$	$(-94, -94, -94)$ dBm
Transmit/receive AP coordinates	Tx: $(\pm200, \pm200), (0, \pm200)$ $(\pm200, 0)$ m; Rx: $(\pm150, \pm150)$ m
True/fake coordinates	$(-75, 75)/(5, -25)$ m
Pilot length/total power $(\tau_{\mathrm{p}}, P_{\mathrm{p}})$	$(64, 20$ dBm$)$
Snapshots/grid cell (N, Δ_{g})	$(128, 10$ m $\times$ 10 m$)$




Fig. 2. Target-localization success rate versus the realized AN-power ratio η.

B. Results Discussion

For $M_{\mathrm{tx}} = 16$, (10) gives the sufficient condition $\rho > 1.07$. Sweeping ρ over $[0.05, 3.5]$ traces the realized AN-power ratio η reported on the horizontal axis. Fig. 2 reports the target-localization success rate versus η, at the estimation quality implied by the tabulated pilot configuration. Without AN the adversary succeeds in 35.8% of the channel realizations. At $\eta \approx 0.50$, the null-space-only and MI-minimizing baselines still give 26.0% and 23.6%, whereas the proposed design drops to 2.8% and reaches 0% at $\eta \approx 0.58$. The MI-minimizing design requires $\eta \approx 0.78$ to approach a comparable level. The key difference is geometry-consistent shaping. Unstructured or leakage-minimizing AN perturbs individual beampatterns but does not force the residual peaks to intersect at one false position, whereas the proposed constraints couple fake directions through the common virtual location, drawing multi-AP fusion toward a coherent alternative.




Fig. 3. Target sensing SNR versus the realized AN-power ratio η at the same paired operating points.




Fig. 4. Communication outage probability $\Pr\{\min_i \gamma_i^{\mathrm{AN}} < \Gamma_{\mathrm{comm}}\}$ on the actual channel versus the CSI NMSE for four design variants.

Fig. 3 reports the sensing cost at the same paired operating points. The no-AN reference is 14.7 dB. At $\eta \approx 0.50$, the proposed, null-space-only, and MI-minimizing designs yield 11.1, 11.4, and 11.5 dB, a 3.6 dB loss for the proposed design relative to the no-AN reference and only 0.3–0.4 dB additional loss relative to the baselines while achieving a much lower localization success rate. At larger η the proposed curve decreases faster due to the more restrictive fake-peak shaping constraint. Jointly, at $\eta \approx 0.50$ all three schemes sacrifice similar sensing SNR, yet only the proposed design reduces localization success to 2.8%, identifying this as a favorable operating region.

Fig. 4 evaluates QoS on the actual channels, now sweeping a common link NMSE directly rather than fixing it through the pilot configuration, so as to isolate the effect of CSI accuracy. At -10 dB NMSE, the no-AN baseline already incurs 75.1% outage, whereas the robust design reduces outage from 18.6% (nominal) to 1.6% at a cost of 0.19 dB in sensing SNR relative to the nominal design. The high outage of the no-AN baseline arises because it attains a higher sensing SNR by operating with a smaller communication-SINR margin, making it more vulnerable to channel uncertainty. The advantage widens at larger NMSE, where at -4 dB the robust design still holds outage to 31.6% while the other three variants all exceed 99%.

V. Conclusion

This correspondence proposed a fake-peak AN design for CF-mMIMO ISAC that exploits the receive-processing asymmetry between post-combining detection and raw-sample reconstruction. Network-wide effective-channel nulling preserves the AN in the adversary's observations, and geometry-consistent shaping displaces the reconstructed dominant peaks away from the target. At $\eta \approx 0.50$, the design lowers localization success from 35.8% to 2.8% with a 3.6 dB sensing-SNR loss and a 20-percentage-point margin over the MI-minimizing baseline.

References

[1] F. Liu, Y. Cui, C. Masouros, J. Xu, T. X. Han, Y. C. Eldar, and S. Buzzi, "Integrated sensing and communications: Toward dual-functional wireless networks for 6G and beyond," *IEEE J. Sel. Areas Commun.*, vol. 40, no. 6, pp. 1728–1767, 2022.

[2] U. Demirhan and A. Alkhateeb, "Cell-free ISAC MIMO systems: Joint sensing and communication beamforming," *IEEE Trans. Commun.*, vol. 73, no. 6, pp. 4454–4468, 2025.

[3] Z. Behdad, Ö. T. Demir, K.-W. Sung, E. Björnson, and C. Cavdar, "Multi-static target detection and power allocation for integrated sensing and communication in cell-free massive MIMO," *IEEE Trans. Wireless Commun.*, vol. 23, no. 9, pp. 11 580–11 596, 2024.

[4] S. Goel and R. Negi, "Guaranteeing secrecy using artificial noise," *IEEE Trans. Wireless Commun.*, vol. 7, no. 6, pp. 2180–2189, 2008.

[5] N. Su, F. Liu, and C. Masouros, "Secure radar-communication systems with malicious targets: Integrating radar, communications and jamming functionalities," *IEEE Trans. Wireless Commun.*, vol. 20, no. 1, pp. 83–95, 2021.

[6] S. Rivetti, E. Björnson, and M. Skoglund, "Secure spatial signal design for ISAC in a cell-free MIMO network," in *Proc. IEEE Wireless Commun. Netw. Conf. (WCNC)*, 2024, pp. 1–6.

[7] Z. Ren, J. Xu, L. Qiu, and D. W. K. Ng, "Secure cell-free integrated sensing and communication in the presence of information and sensing eavesdroppers," *IEEE J. Sel. Areas Commun.*, vol. 42, no. 11, pp. 3217–3231, 2024.

[8] C. Shi, F. Wang, M. Sellathurai, J. Zhou, and S. Salous, "Low probability of intercept-based optimal power allocation scheme for an integrated multistatic radar and communication system," *IEEE Syst. J.*, vol. 14, no. 1, pp. 983–994, 2020.

[9] K. Hou and S. Zhang, "Optimal beamforming for secure integrated sensing and communication exploiting target location distribution," *IEEE J. Sel. Areas Commun.*, vol. 42, no. 11, pp. 3125–3139, 2024.

[10] J. Zou, C. Masouros, F. Liu, and S. Sun, "Securing the sensing functionality in ISAC networks: An artificial noise design," *IEEE Trans. Veh. Technol.*, vol. 73, no. 11, pp. 17 800–17 805, 2024.

[11] K. Han, K. Meng, and C. Masouros, "Sensing-secure ISAC: Ambiguity function engineering for impairing unauthorized sensing," *IEEE Trans. Wireless Commun.*, vol. 25, pp. 5386–5400, 2026.

[12] I. W. G. da Silva, D. P. M. Osorio, and M. Juntti, "Multi-static ISAC in cell-free massive MIMO: Precoder design and privacy assessment," in *Proc. IEEE Globecom Workshops (GC Wkshps)*, 2023, pp. 461–466.

[13] G. Scutari, F. Facchinei, and L. Lampariello, "Parallel and distributed methods for constrained nonconvex optimization—part I: Theory," *IEEE Trans. Signal Process.*, vol. 65, no. 8, pp. 1929–1944, 2017.