

Contoso Electronics

Equipment Reference & Maintenance Guide

Function / Arbitrary Waveform Generator

Contoso SignalGen FG-2200

Asset Identification

Field	Detail
Asset ID	CE-FGN-1300
Category	Test & Measurement
Manufacturer	Contoso Instruments Division
Location	Electrical Test Lab - Bench 5
Installation Date	2023-05-20
Warranty Expiry	2027-05-20
Support Contact	test.equipment.support@contoso.com ext. 4210

Overview

The Contoso SignalGen FG-2200 is a dual-channel function and arbitrary waveform generator used to stimulate circuits under test, generate clocks and modulation, and replay custom waveforms during design verification and production test.

Technical Specifications

Parameter	Value
Channels	2 independent
Max Frequency	80 MHz (sine)
Sample Rate	500 MSa/s
Arb Waveform Length	16 Mpts/channel
Amplitude Range	1 mVpp - 10 Vpp (50 Ω)
Modulation	AM, FM, PM, FSK, PWM, sweep, burst
Power	100-240 VAC, 50/60 Hz

Preventive Maintenance Schedule

Interval	Task
Monthly	Verify output amplitude against calibrated meter.
Quarterly	Update firmware; clean ventilation.
Annual	Full calibration by accredited metrology lab.

As needed	Inspect BNC connectors for wear.
-----------	----------------------------------

Safety Guidelines

- Do not exceed rated output into low-impedance loads.
- Never apply external voltage to output terminals.
- Ensure proper grounding before connecting to DUT.
- Use correctly rated coaxial cables.

Common Issues & Troubleshooting

Symptom	Recommended Action
No output	Verify channel is enabled and output is turned on; check load setting.
Incorrect amplitude	Check output load impedance setting (50 Ω vs High-Z).
Distorted waveform	Reduce amplitude for high frequency; check cable/termination.
Frequency error	Allow warm-up; recalibrate timebase.

Contoso Electronics internal maintenance documentation. For service requests, contact test.equipment.support@contoso.com | ext. 4210 or submit a work order through the maintenance portal.