

AnyCam 3.7.1 Audit Report

Release audit - 05 October 2026 - short absences, two-way audio, decoder report, network - tag 3.7.1

Scope confirmed by CrystalHeeler on 2026-10-06: version 3.7.1 with B27 (short absences only, 60 s), B31 (#backchannel=0 for every camera), B34, and the false overlay warning of B11. B33 was taken out on CrystalHeeler's order, to be investigated first. Not field-tested.

Changes

#	Cause (from the logs)	Change
B27	The live players close their streams 5 s after the page is hidden, and a return waits for a new connection and keyframe: about 2 s of black (CrystalHeeler: black, Chrome, seen since 3.7.0-rc1.0).	While the page is hidden, a player keeps its stream for 60 s (LIVE_HIDDEN_GRACE_MS), in the cards, the MJPEG cards and Enhanced View. Off screen and Enhanced View's pause of the cards keep 5 s.
B31	Two older Hikvision cameras on test system C reset go2rtc's connection about once a second (about 900 resets) while AnyCam's probes and fprobe worked. go2rtc requests the ONVIF backchannel unless told not to; its README: #backchannel=0 is "important for some glitchy cameras".	_go2rtc_rtsp_src adds #backchannel=0 to every RTSP source given to go2rtc: cards, Enhanced View, the RTSP-over-WebSocket source and the relay for AnyCam's ffmpeg. A direct address to ffmpeg never carries it.
B34	On test system C (3.0.0) `ip route` timed out; AnyCam scanned a fixed 192.168.1.0/24.	Retry at 15 s, then the add-on's own address with a /24, logged; an unknown network stops the scan with a message.
B11	3.7.0's report looked for the name rpidv; newer kernels say rpi-hevc-dec. With Protection mode off (test system B, 2026-10-06) all 19 devices open.	rpi-hevc-dec counts as the HEVC decoder; a blocked device note names Protection mode; hevc_drm is unavailable when /dev/video19 or /dev/media0 does not open.

Tests run

Suite	Result	Scope
Release gate	PASS	Eight gates; 17 files; build inputs checked online.
Python integration	PASS	581 of 581; 9 new in section AJ; 11 source checks now expect #backchannel=0.
JavaScript behaviour	PASS	166 of 166.
Not run	NOTED	No field test. The B31 cause is the likely one, from go2rtc's documentation, not yet confirmed on the cameras. The 60 s timer was not watched in a real browser.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*. Rows this change touches; the rest carry from the 3.7.0 audit.

Standard	Check applied	Result	Note
1.10 Exceptions	Failure paths	PASS	No guessed network; a clear scan message.
1.12 Logging	Truth	PASS	No false overlay warning; the blocked-device note names the fix.
1.18 Testing	New tests	PASS	9 server checks.
6.1 Security	Requests to cameras	PASS	AnyCam no longer asks cameras for a two-way audio channel it never used.
Rule 9 (privacy)	New text	PASS	Made-up addresses only.

Known issues

- **B11:** hardware decode needs Protection mode off; whether to declare the devices instead is open.
- **B33:** one Amcrest camera can get two cards; under investigation.
- **B32:** the Microseven waits about 30 s on "Loading feed".
- **B29, B30:** sound, and an empty user name, wait for logs.

Acceptance (field test)

- Switch to another program for 10 s and back: the cards are live at once.
- Test system C: the two older Hikvision cameras play live and in the classic view; the go2rtc "connection reset by peer" lines stop.
- With Protection mode off: the start-up report has no overlay warning, and the classic view logs "hw first frame".

Files changed

File	Change
anycam_go2rtc.py	_go2rtc_rtsp_src and its uses.
anycam_scan.py	get_local_subnet, _own_ipv4; the scan stops on no network.
camera_discovery.py	The decoder report and the hevc_drm check; version 3.7.1.
page_script.py	The 60 s grace for hidden pages.
tests/	Section AJ; updated source checks.
CHANGELOG.md, config.yaml, docs	3.7.1; build plan (header and phases rewritten).