AnyCam 3.8.2 Audit Report

Release audit - 19 October 2026 - B65, B66, B67, B64 (first step), B62 report - tag 3.8.2

A fix release for a 3.8.1 regression found in CrystalHeeler's log of 2026-10-16, with the scope CrystalHeeler confirmed on 2026-10-19: B65 (the regression), a fake-go2rtc check, a quieter pre-warm log, B66 (the log link in the HA app), the first step of B64, B67 (view cleanup, with the new rule 10) and the B62 WebRTC report.

B65: the 3.8.1 regression

3.8.1 sent the connection gate to go2rtc as an exec: source through go2rtc's API. go2rtc 1.9.14 refuses an API source whose scheme is exec, echo or expr, or that holds a space (internal/streams/handlers.go, Validate), so every registration of the Microseven's streams failed ("source from insecure producer", 596 lines in one log). The Microseven lost go2rtc: its card showed pictures from AnyCam's own ffmpeg, Enhanced View used the classic engine, and the card's ffmpeg opened the camera directly. The tests missed it because the fake go2rtc accepted every source.

Part	3.8.2
Source	Rate-limited cameras get go2rtc's own ffmpeg: copy source again (accepted by the API). AnyCam records each one's cooldown in the gate's record.
Gate	AnyCam's inline go2rtc config sets go2rtc's ffmpeg program (ffmpeg.bin) to anycam_gate.py, made executable in the Dockerfile. For an -i address with a cooldown on record it takes the camera's turn, then os.execvp's the real ffmpeg with the same arguments; every other run, including ffmpeg -version, passes straight through; a broken record never stops ffmpeg.
No squeezed turns	go2rtc gives such a command 30 s to start. A turn further away than 25 s is not taken: the gate exits without opening the camera and go2rtc retries later. The 3.8.1 code capped the wait instead, which could give two queued openers the same moment under a 30 s escalation; found while testing, fixed here.
Tests	The fake go2rtc now applies Validate; AR1 shows 3.8.1's source refused and 3.8.2's accepted.

The other items

Item	Change
Quieter log	A pre-warm stream go2rtc refuses is logged once (and once when it starts), not every 30 s; the card's own registration still warns at once.
B66	The log link navigates inside the HA frontend as its navigate() does: pushState on the HA window with the page it came from, then a location-changed event. A full page load stays as the fallback. Inside the HA app the old full load opened the phone's browser.
B64, first step	12 prefixes registered to Ubiquiti and TP-Link left the non-camera list, which B55 uses to skip hosts unprobed.
B67, rule 10	Dialogs: height capped to the screen with their own scrolling, width capped in vw, buttons sticky at the bottom. The Enhanced View bar: min-height, wraps, safe-area padding, the camera name on its own row and the short Quality Switch line on phones. The toast: max-width. The release gate checks these styles (R10) and names every fixed overlay; it fails on 3.8.1's styles (dialog scroll, bar, toast).

Item	Change
B62 report	The live player reads WebRTC's statistics and reports the outcome, the candidates each side offered, the pair checks and the route used, once per camera, place and outcome, to POST /api/live_diag, which checks every field and logs one line (LIVE-DIAG).

Tests run

Suite	Result	Scope
Release gate	**PASS**	Eight gates, with the new R10 check and the contracts moved to the go2rtc source, the go2rtc config and the gate.
Python integration	**PASS**	729 of 729. New section AR; AQ and AM1 updated for the 3.8.2 gate.
JavaScript behaviour	**PASS**	201 of 201: B66 navigation and fallback, the B62 summary.
Visual (rule 10)	**PASS**	The built page in the browser pane at 375x812, 812x375 and 1366x768, the settings dialog with eight zones and a long title, the bar with a long label, Sound and the Quality Switch: every box inside the screen, the dialog scrolls, its buttons visible. Measured from the page; screenshots at phone size.
Field	**NOTED**	Not run yet; see the next section.

Not tested

- **go2rtc running the gate as its ffmpeg on the Pi.** No Linux system or go2rtc here. The command line is checked against go2rtc's own parsing (the ffmpeg: redirect, QuoteSplit) and the API's Validate, read from go2rtc's source, not run.
- **The file lock and the executable bit.** Linux only; set by the Dockerfile.
- **B66 inside the HA app.** The navigation is HA's own method, read from the frontend's source; the app itself was not available here.
- **The B62 report on a phone.** Its first field log is the test.
- **An intermittent test.** Q2 (the home-location re-check timer, untouched by this build) failed once in one run and passed in the next three; a timing check, to be looked at separately.

Best-practices compliance

Standard	Check applied	Result	Note
8 (regressions)	Our code first	**PASS**	B65 was AnyCam's; fixed, and the test fake now matches go2rtc.
6 Security	Validate at the boundary	**PASS**	/api/live_diag checks camera, place and shape, and cuts every field.
1.10 Exceptions	Narrow excepts	**PASS**	The gate catches OSError, ValueError, TypeError only, then runs ffmpeg.

Standard	Check applied	Result	Note
Rule 10	Overlays fit	**PASS**	New rule; gate R10 and a visual check.
Rule 9 (privacy)	New text	**PASS**	Made-up addresses only.

Known issues

- **Phone live view (B62):** where WebRTC does not connect, MSE can fall behind; the new report will show why.
- **Extra connections:** each camera holds one or two all the time; the prewarm setting turns them off.

Files changed

File	Change
anycam_gate.py	Runs as go2rtc's ffmpeg; set_cooldown; no squeezed turns; shebang.
anycam_go2rtc.py	ffmpeg: source for gated cameras, cooldown record, ffmpeg.bin, quiet registration, pre-warm failure logged once, /api/live_diag.
anycam_brand.py	12 prefixes off the non-camera list.
page_script.py	B66 navigation, B62 report.
anycam_page.py	B67 styles.
camera_discovery.py, Dockerfile	Route for /api/live_diag; chmod for the gate; 3.8.2.
verify_release.py	R10 check; contracts moved.
tests/	Fake go2rtc Validate; sections AQ (updated) and AR; page tests.
CHANGELOG.md, config.yaml, CLAUDE.md, docs	3.8.2; rule 10; build plan.