

AnyCam 3.7.5-rc2.0 Audit Report

Release audit - 08 October 2026 - start-up traffic and fragile cameras - tag 3.7.5-rc2.0

Scope confirmed by CrystalHeeler on 2026-10-08: B53 for every brand, with CrystalHeeler's design for removed cameras (scannable again, details kept so a scan gives the card back without probing), and the Quality Switch's failure notice. Not field-tested.

Cause (from the 2026-10-08 log)

AnyCam's one-connection RTSP check got "Connection reset by peer" at all 32 checks from 2026-10-07 20:12 to 22:47, also while nothing else contacted the camera: the Microseven was stuck. Both times it got stuck, AnyCam had just run its start-up or rescan checks on it: a 28-path RTSP walk (20 answers "400 Bad Request"), and on 2026-10-07 ONVIF requests sent over HTTP to its RTSP port 554. In the 23 hours between, with no start-up scan and many live and classic tries, it stayed healthy.

Changes

#	Change
Known cameras	Every scan pass skips a host where a saved camera has a working stream (credentials, an unauthenticated probe, or status ready).
Removed cameras	Remove keeps the card's details without its password in removed_cameras.json; a scan that finds the address gives the card back (needs a password) without probing; the copy is dropped once the camera is set up again.
ONVIF port	_onvif_media_url never uses an RTSP or RTMP port; port 80 when no XAddrs are saved.
Cooldown	The start-up RTSP check waits out the brand's cooldown.
Quality Switch	"failed" state: the toggle says the smoother stream gave no picture.
Correction	AnyCam's probe already sends TEARDOWN after SETUP; the earlier claim that it did not was wrong.

Tests run

Suite	Result	Scope
Release gate	PASS	Eight gates.
Python integration	PASS	666 of 666; section AO new (10 checks), AO6 runs the real scan with stand-in network calls.
JavaScript behaviour	PASS	193 of 193.
Not run	NOTED	No field test; the Microseven needs a power cycle first. Whether the scan was the only trigger is a strong pattern in two events, not proof.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*. Rows this change touches; the rest carry from the 3.7.0 audit.

Standard	Check applied	Result	Note
6.1 Security	Secrets at rest	PASS	The removed-cameras file holds no password and no password in any URL.
1.10 Exceptions	Corrupt file	PASS	A bad removed_cameras.json is logged and ignored.
1.12 Logging	Truth	PASS	"known camera ... not probed" and "card given back ... not probed" lines.
1.18 Testing	New tests	PASS	10 server checks.
Rule 9 (privacy)	New text	PASS	Made-up addresses only.

Known issues

- **Microseven**: stuck until power-cycled; then the ffmpeg copy gets its test.
- **B48**: go2rtc's local RTSP server does not ask local programs for a password.
- **B33**: one Amcrest camera can get two cards.

Files changed

File	Change
anycam_scan.py	Known-camera skip, removed-camera restore, the cooldown.
camera_discovery.py	removed_cameras.json; Remove keeps the details; version.
anycam_probe.py	ONVIF never to an RTSP port.
anycam_snap.py, page_script.py, anycam_page.py	Quality Switch failure notice.
tests/	Section AO.
CHANGELOG.md, config.yaml, docs	3.7.5-rc2.0; build plan.