

AnyCam 3.0.0-rc1.3 Audit Report

Release audit - 02 October 2026 - probe_http_identity restored - tag 3.0.0-rc1.3

3.0.0-rc1.3 carries one change, build plan B19. Scope confirmed by CrystalHeeler on 2026-10-02: B19 alone, after 3.0.0-rc1.2 passed his field test on both systems; the unused `is_camera_positive` and `probe_http_for_camera` stay. `camera_discovery.py`: 6 lines added, 2 removed (the `def` line, a 4-line comment, blank lines).

The defect and the fix

Fact	Detail
Cause	Commit 2.4.0-rc1.0 added <code>_rtsp_options_fingerprint</code> directly above <code>probe_http_identity</code> and lost the line <code>'def probe_http_identity(ip: str, port: int, timeout: int = 5) -> dict:'. The 117-line body stayed as unreachable code after that function's return.</code>
Fix	The <code>def</code> line is back in the same place.
Proof of identity	The restored function's source equals the function in the commit before 2.4.0-rc1.0, compared as text by the restore script, which refuses to write otherwise.
Callers	<code>run_scan</code> , in the branch for a device that answers ONVIF discovery and has no card from the port scan. <code>probe_http_for_camera</code> , whose only caller <code>is_camera_positive</code> has no caller.
Effect on the scan	For such a device the scan now requests its web page on port 80 (several paths, http then https, 4 s timeout each) and takes the brand from the title or Server header.

Expected effect on the two test systems

Evidence	Value
Logs of 2026-10-02, both systems	8 scans, 2,849 DEBUG lines
Times the step ran (its failure logs at DEBUG)	0
Reason	Every ONVIF device there (10.0.0.22, 10.0.0.33, 192.168.50.217) already had a card from the port scan
Expectation	The same devices and cards as the scans of 10:40

Correction carried from the 3.0.0-rc1.0 audit: that report first said the step failed on every device and that a second step failed too. Both statements were wrong and were corrected the same day.

Tests run

Suite	Result	Scope
Release gate	PASS	Eight gates; 7 files; 212 top-level definitions, no duplicates; 48 contracts.
Undefined names	PASS	7 files, 0 undefined names. The list of known defects is empty for the first time.

Suite	Result	Scope
Python integration	PASS	294 of 294, 5 new: a local web server with a Microseven title and a Hipcam Server header is identified as Hipcam/Microseven; an ordinary page is not a camera; the wrapper; a closed port; <code>_rtsp_options_fingerprint</code> now ends at its return.
JavaScript behaviour	PASS	110 of 110.
Not run	NOTED	No scan was run on the build PC. No test drives run_scan into the ONVIF-only branch; the scan has no tests yet (E1). The field test (A17) compares the scan logs.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*, Parts 1 to 6. Rows this change touches; the rest carry from the 3.0.0-rc1.2 audit.

Standard	Check applied	Result	Note
1.1 Truncated function	AST, contracts, undefined names	PASS	B19 closed. This row failed in the three audits before this one.
1.2 Syntax	compile() per file	PASS	7 files.
1.10 Exceptions	Broad catches	NOTED	The restored function and its caller use 'except Exception'. That is what hid the defect at DEBUG level. Not changed here: one change per build.
1.16 Refactoring	Dead code	NOTED	<code>is_camera_positive</code> and <code>probe_http_for_camera</code> are unused (about 150 lines); kept at CrystalHeeler's request.
1.18 Testing	Regression test	PASS	5 checks, with a real HTTP server on localhost.
6.1 Security	New outbound requests	NOTED	HTTP GET to a discovered device's port 80, certificate checks off (cameras use self-signed certificates), 16 KB read limit, timeout.
6.3 Version control	Commits and gate	PASS	One commit; the gate run before it; tag after.

Known issues carried forward

- **B20** (late pictures, sub-stream retries): right after 3.0.0.
- **C17** (detection zones): requirements saved, design discussion next.
- **E1**: the scan, password entry, the snapshot loop and the Enhanced View engine are still in the main file and have no tests.
- The Lorex DVR answers 404 for the sub-stream of its channels.

- Skip Non-Reference Frames breaks H.264 cameras (B3).

Acceptance (field test A17)

- After the update, the start-up scan finds the same devices and cards as on 2026-10-02 10:40, on both systems.
- No line with 'not defined' in the log.
- A line 'HTTP identity : ...' is new and means the step ran.

Files changed

File	Change
camera_discovery.py	The def line of probe_http_identity. Version 3.0.0-rc1.3.
tests/	5 new checks; the known-defects list emptied.
docs	Build plan; detection zones requirements (Detection_Zones_Plan.md).
CHANGELOG.md	3.0.0-rc1.3 entry; earlier entries corrected.