

AnyCam 3.7.5-rc1.0 Audit Report

Release audit - 07 October 2026 - the ffmpeg copy for any camera, the Quality Switch - tag 3.7.5-rc1.0

Scope confirmed by CrystalHeeler on 2026-10-07: B49 (option A2), B50, B51 with a Quality Switch, as a release candidate in case the Microseven still fails. CrystalHeeler also asked that fixes work for other camera systems, not only these, so B47's ffmpeg copy and B51's sub-stream are found generally. Not field-tested.

Changes

#	Cause (from the 3.7.4 field test)	Change
B49	Every Microseven stream: "unsupported scheme: exec:ffmpeg ...". go2rtc runs an ffmpeg: source through its exec module, which AnyCam did not load.	exec loaded, behind the API password required from every caller (3.7.4).
B47	The copy was tied to one brand entry; another brand with the same flaw would still fail.	The page sends the browser's media error; a stream description error switches that camera to the copy, saved, and live view retries once.
B50	After go2rtc's failure, the Microseven was marked stuck (20:07:37).	No stuck mark while go2rtc failed for the camera; reasons naming go2rtc never count.
B51	LibreWolf, Lorex channel 7 at 3840x2160: about 4.5 decoded pictures a second of 7; grey pictures every 5 to 10 s.	Keyframes only at full size (rule for 4K H.265 in software, and a measured switch below 80% of the stream's rate); a Quality Switch to the sub-stream when one is found.

Tests run

Suite	Result	Scope
Release gate	PASS	Eight gates; the module list now pins exec.
Python integration	PASS	656 of 656; section AN new (18 checks).
JavaScript behaviour	PASS	193 of 193; the repair flow new.
Not run	NOTED	No field test: go2rtc's exec and ffmpeg sources ran only against a stand-in; the browser error texts are Chrome's from the 2026-10-06 media log, Firefox's are unknown; the sub-stream rules were not tried on cameras.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*. Rows this change touches; the rest carry from the 3.7.0 audit.

Standard	Check applied	Result	Note
6.1 Security	Least privilege	NOTED	exec can run any command as a stream source; only callers with the API password (AnyCam) can add sources. Accepted by CrystalHeeler (A2).
6.1 Security	Input at the boundary	PASS	/api/live_repair accepts a known camera and a description error only; /quality_switch refuses a camera with no sub-stream.
1.12 Logging	Truth	PASS	Repair, keyframes-only and sub-stream decisions are logged with reasons.
1.18 Testing	New tests	PASS	18 server and 2 page checks.
Rule 9 (privacy)	New text	PASS	Made-up addresses only.

Known issues

- **B48:** go2rtc's local RTSP server does not ask local programs for a password. Decision open.
- **B33:** one Amcrest camera can get two cards; under investigation.

Acceptance (field test)

- The Microseven plays live in Chrome and LibreWolf.
- LibreWolf, Lorex channel 7, classic view: sharp full-size pictures, no grey, "keyframes only" in the info bar; the Quality Switch appears and switches to the sub-stream.
- A camera whose stream description the browser rejects is repaired once, logged.

Files changed

File	Change
anycam_go2rtc.py	exec module; /api/live_repair; _classic_sub_stream; B50.
anycam_snap.py	Keyframes only, the rate check, the sub-stream mode, headers.
anycam_focus.py	/quality_switch; per-session resets.
page_script.py	Media error reports, the repair retry, the Quality Switch.
anycam_page.py	The switch's style.
camera_discovery.py	Routes; quality_switch in the camera list; version.
verify_release.py	Module list with exec.
tests/	Section AN; page checks; updated config checks.

File	Change
CHANGELOG.md, config.yaml, docs	3.7.5-rc1.0; build plan.