AnyCam 3.8.3 Audit Report

Release audit - 20 October 2026 - C27, D5, B64 - tag 3.8.3

A feature release with the scope CrystalHeeler confirmed on 2026-10-20: C27 (save and restore the motion and zone settings, designed with CrystalHeeler on 2026-10-16), D5 (a recorder's new channel cards next to it) and the rest of B64 (the camera MAC prefix list rebuilt from the IEEE registry).

C27: save and restore the motion and zone settings

Decision (2026-10-16)	3.8.3
1. Where the copy lives	Both: every save of motion.json also writes anycam-motion--.json into /settings (default /media/anycam/settings), newest 20 kept; Save Motion & Zone Settings in the Storage tab downloads one (GET /api/motion/copy). A copy with no camera settings, or equal to the newest, is not written, so a lost settings file never pushes the good copies out. Written to a .tmp file, then renamed. The Storage tab skips the folder.
2. What it holds	Per camera with anything to keep: card key, MAC, channel, name, brand, picture size, its own settings (level, cooldown, tail, clip, folder), its zones with detection in zones only, and the armed state.
3. Restore	Restore Motion & Zone Settings in the Storage tab. Sources: the settings folder; a folder on the HA machine under /media or /share (resolved, then checked against the two roots); a folder on the device through the browser's folder picker, where the page sends at most the newest 20 copies under 900,000 characters (the add-on's request limit is 1 MB). The user never picks a file.
5. Matching	By card key; else by MAC address and channel when the address changed; the newest copy that holds the camera wins.
6. The dialog	Every camera with the date found, or "no saved settings"; notes a MAC match; warns when the picture's width/height changed by more than 2% (zones are kept in fractions of the picture). All, None, or any group.
7. Apply	Settings through the same check as the settings dialog, zones through the zone check, then the armed state; motion restarts per camera; one save at the end. A camera whose saved zones fail the check gets its settings and a reported problem.
8. Folder pickers	Offered where the browser has webkitdirectory; otherwise a note points to a folder under /media or /share. The HA phone app has no folder picker in its latest release.

D5 and B64

Item	Change
D5	After channel enumeration registers new cards, _card_order_after_parent puts them right after the recorder's card in the saved order (runtime.json), in channel order; a later channel goes after the recorder's existing channel cards; the recorder's key, which gains #chN when its channel is set, is renamed in the order. With no saved order one starts from the current order.

Item	Change
B64 list	_CAMERA_OUI_VENDORS rebuilt from the IEEE registry (Wireshark's manuf copy, 2026-10-20) by company: 165 blocks (MA-L, MA-M /28, MA-S /36) of 28 camera-only makers. 37 of the old 57 prefixes belonged to other companies (Apple, Dell, Intel, HP, Raspberry Pi, D-Link, Huawei, Ubiquiti, LG, Texas Instruments and others); 44:A9:2C is a Registration Authority prefix that 15 companies share, of which Luxonis holds one /28.
B64 matching	camera_oui_block matches 9, 7 and 6 hex digits, longest first. With the downloaded table, which holds only 24-bit prefixes, a camera block inside a Registration Authority prefix gets the camera label.
B64 left out	Makers that also make routers, phones or other network devices: Ubiquiti, TP-Link, D-Link, Bosch, Sony, Panasonic, Samsung Electronics, Wyze, Ring, EZVIZ, Verkada, Kedacom, Speco, Honeywell.
B64 not findable	No registry block: Foscam, Annke, Vstarcam, Wansview, Tenvis, Sricam, Zosi, LaView, Hiseeu, Q-See, Pelco, Illustra, Oncam, IndigoVision, VideoIQ. The Hipcam family, the Microseven too, uses its Wi-Fi module maker's prefix (Shenzhen Bilian, 42 blocks, in many other devices).
B64 test	tests/build_oui_extract.py makes the list and tests/data/oui_camera_extract.txt (the registry lines); test AS10 checks every prefix's owner against its brand, both ways.
Live effect	Small, as recorded in the build plan: the list is lookup_oui's fallback label before the IEEE table loads, and oui_is_camera's True answer has no live caller.

Tests run

Suite	Result	Scope
Release gate	**PASS**	Eight gates, with new contracts for the copy write, the folder check and the card placement.
Python integration	**PASS**	772 of 772. New section AS (AS1-AS12); the V2, V3 and B55 scan checks use a real Hikvision prefix (the old 1C:C3:16 is Milesight IoT).
JavaScript behaviour	**PASS**	207 of 207: the copies sent from a device folder, the dialog's list, the apply request.
Visual (rule 10)	**PASS**	The built page in the browser pane at 375x812, 812x375 and 1366x768, the restore dialog with 14 cameras and a long name: inside the screen, scrolls inside, buttons in view, no sideways scroll; the Storage bar wraps. The check found the rows' checkbox above the name and the style was fixed.
Field	**NOTED**	Not run yet; see the next section.

Not tested

- **The copy folder on the Pi.** Writing under /media/anycam/settings and the rename were run on Windows only.
- **A folder on a phone.** The folder picker was not run in a phone browser; the HA app has none in its latest release.
- **Channel placement with a real recorder.** Run through the function and checked at its call site, not through a full channel enumeration.

- **Earlier field items.** The 3.8.2 gate through go2rtc, the B66 link in the HA app and the calibration log are still untested in the field.

Best-practices compliance

Standard	Check applied	Result	Note
6 Security	Validate at the boundary	**PASS**	Restore: source allowlist, folder roots, copy size and count, ids as strings; the settings and zones go through the existing checks.
1.11 Resources	Atomic write	**PASS**	Copies are written to .tmp, then renamed.
P4 Async	No blocking I/O on the loop	**PASS**	Folder reads and saves run in a thread.
Rule 10	Overlays fit	**PASS**	The new dialog uses the shared .modal styles; visual check at three sizes.
Rule 9 (privacy)	New text	**PASS**	Made-up addresses in tests; the registry extract is public data.

Known issues

- **Brands without a MAC block** are still found by the camera's answers only.
- **Phone live view (B62):** waiting for the LIVE-DIAG lines from the field.

Files changed

File	Change
anycam_backup.py (new)	Copy write, prune, read, folder check, matching.
anycam_motion.py	The copy at every save; /api/motion/copy and /api/motion/restore.
anycam_page.py, page_script.py	Two Storage-bar buttons, the restore dialog.
anycam_storage.py	Skips the settings folder.
camera_discovery.py, anycam_credentials.py	Routes; D5 card placement; 3.8.3.
anycam_brand.py	The rebuilt camera list; block matching.
anycam_modules.py, Dockerfile, CLAUDE.md	The new file.
verify_release.py	Four contracts.
tests/	Section AS, page checks, build_oui_extract.py, data/oui_camera_extract.txt.

File	Change
CHANGELOG.md, config.yaml, docs	3.8.3; build plan.