

AnyCam 3.7.2 Audit Report

Release audit - 06 October 2026 - card fallbacks, last picture, frozen hardware picture, login hints - tag 3.7.2

Scope confirmed by CrystalHeeler on 2026-10-06: version 3.7.2 with B35, B36, B39, B30, B40 (15 s) and B37 (detect and fall back, plus a diagnostic). Left out: the C items, B6, B33, B32 (to test on 3.7.2 first), B29 (CrystalHeeler's test later) and B38 (the Oak-D add-on's session). B11 moved to Done: Protection mode was the cause, confirmed in the field. Not field-tested.

Changes

#	Cause (from the logs)	Change
B35	The Oak-D card in LibreWolf stayed black. Each live attempt closed after 1 to 2 s; the card's timer counted only while a socket was open, and VideoRTC waits up to 15 s to reconnect, so the timer never ran out.	A card counts the time its player is trying, the reconnect wait included. A hidden page, an open Enhanced View and a player paused off screen do not count.
B36	Classic view of the Oak-D: "entering enhanced view", then "idle 664s - stopping". A live card asks for no pictures, so the request time was old.	Entering the classic view marks the camera as just asked for.
B39	CrystalHeeler: after more than 60 s away, a card is black for about 2 s.	The live player keeps its last picture as the video's poster when its stream closes or starts again (at most 1280 wide). MJPEG cards already kept theirs.
B30	Test system C: four failed logins with the user name left empty; the grey "admin" hint looked like a value.	No placeholder in the user name and password fields of the three login forms.
B40	The 30 s limit came from the Oak-D add-on, whose encoder set no keyframe interval. Normal settings: a keyframe every 1 to 2 s; Hikvision H.265+: 8 to 12 s (Hikvision's H.265+ white paper).	15 s. A timeout names the camera settings to change, on screen and in the add-on log (new POST <code>/api/live_fail</code>).
B37	Lorex channel 7, Protection mode off: hevc_drm, then 2,183 JPEGs of exactly 48,806 bytes (green).	After 50 hardware pictures of one size, software until AnyCam restarts, and a one-time picture test of four ways (software, hardware as now, no format filter, <code>drm_prime</code> with <code>hwdownload</code>) with the kernel's CMA memory; also <code>/api/diagnostics/hwtest/<camera></code> .

Tests run

Suite	Result	Scope
Release gate	PASS	Eight gates; 17 files; build inputs checked online.
Python integration	PASS	603 of 603; section AK new (22 checks); G4 now expects 15 s.
JavaScript behaviour	PASS	176 of 176; B35, B39 and B40 checks new; the watchdog section moved to 15 s.
Not run	NOTED	No field test. The picture test ran only against a stand-in ffmpeg: its hardware ways are unproven on a Pi. The poster capture was not watched in a real browser.

Best-practices compliance

Measured against *docs/AnyCam_Coding_Best_Practices.md*. Rows this change touches; the rest carry from the 3.7.0 audit.

Standard	Check applied	Result	Note
1.3 Async	Blocking calls	PASS	/proc/meminfo is read through <code>asyncio.to_thread</code> .
1.10 Exceptions	Task cleanup	PASS	<code>asyncio.wait</code> for the <code>stderr</code> reader: a reader cancelled before it ran no longer reads as the loop cancelled.
1.12 Logging	Truth	PASS	Live view fallbacks and frozen hardware pictures are now in the add-on log.
1.18 Testing	New tests	PASS	22 server and 9 page checks.
6.1 Security	Input at the boundary	PASS	<code>/api/live_fail</code> takes known cameras and two places only; the reason is cut to one line of 200 characters. The picture test strips passwords.
Rule 9 (privacy)	New text	PASS	Made-up addresses only.

Known issues

- **B37:** the hardware picture is still wrong; the fix waits for the "HW TEST" lines from a field log.
- **B32:** the Microseven waits on "Loading feed" while its RTSP is broken; to test on 3.7.2.
- **B33:** one Amcrest camera can get two cards; under investigation.
- **B29:** sound, waits for CrystalHeeler's test.

Acceptance (field test)

- LibreWolf: the Oak-D card shows still pictures within 15 s.
- Open the Oak-D's classic view after its live card: pictures start.
- Leave the page for 2 minutes and come back: each card shows its last picture until live video starts.
- Protection mode off, Lorex channel 7 in the classic view: the log shows the frozen-picture line, the view turns to software, and "HW TEST" lines follow.

Files changed

File	Change
<code>anycam_snap.py</code>	Frozen hardware detection, the picture test and its route handler; the <code>stderr</code> reader wait.
<code>anycam_focus.py</code>	B36: the request time on classic entry.

File	Change
anycam_go2rtc.py	B40: /api/live_fail.
page_script.py	B35, B39, B40; B30 in the card's login form.
anycam_page.py	B30 in the two dialogs.
camera_discovery.py	Two routes; the decoder report lists frozen decoders and picture tests; version 3.7.2.
tests/	Section AK; page checks.
CHANGELOG.md, config.yaml, docs	3.7.2; build plan.