AnyCam 3.8.0-rc3 Audit Report

Release audit - 10 October 2026 - zone drawing + appliance login + B55 - tag 3.8.0-rc3

Three fixes and one feature found or requested by CrystalHeeler on 2026-10-10: zone drawing failed from the Cog menu, appliance cards now offer a login, the appliance notes wording was corrected, and the scan skips confident non-cameras (B55). Scope: these items only, no change to scan completeness.

Cause and change

Item	Detail
Zone drawing (bug)	Opening Edit Zones from a card's Cog menu laid out the canvas before the video had a measured size, so the drawing surface was zero-sized and would not accept a zone. The editor now retries the layout (up to about 5s) until the media reports a real size, matching the Enhanced View path that already worked.
Appliance login (change)	A camera built into an appliance (robot vacuum, litter robot) kept its "Camera in an appliance" notes but had no way to log in. The card now also shows a login prompt; a submitted login walks the RTSP paths, then tries MJPEG and HLS on the common web ports, and reports a clear message if nothing is reachable.
Appliance notes (bug)	The note now reads that the camera's video may or may not be reachable only through the appliance maker's app.
B55 non-camera skip (feature)	The scan now skips a host when a printer port (631 or 9100) is open, or when the MAC maker is a known non-camera brand. This stops the scan probing printers and similar appliances. Multicast hosts are exempt from the skip.

Tests run

Suite	Result	Scope
Release gate	**PASS**	Eight gates.
Python integration	**PASS**	679 of 679; Z4e covers the appliance login (success and failure); U16 covers the B55 skip.
JavaScript behaviour	**PASS**	193 of 193.
Field	**NOTED**	Zone drawing, the appliance login and B55 are verified against the latest field logs and a follow-up field re-test.

Best-practices compliance

Standard	Check applied	Result	Note
8 (regressions)	Our code first	**PASS**	Zone drawing and the appliance wording were AnyCam-side; both fixed.
1.12 Logging	Truth	**PASS**	The scan logs each host it skips and why (printer port, MAC maker).

Standard	Check applied	Result	Note
1.18 Testing	Coverage	**PASS**	Z4e and U16 cover the new paths.
Rule 9 (privacy)	New text	**PASS**	Made-up addresses only; no device state named.

Known issues

- **OPTIONS-401 scan stop:** a camera that answers 401 at OPTIONS (Lorex) is not yet stopped at the first 401 during the scan (only at DESCRIBE). Harmless.
- **Microseven:** untested on an unlocked Microseven camera.
- **Appliance login:** reaches a camera only if the appliance exposes a local RTSP, MJPEG or HLS endpoint; many expose video only through the maker's app.

Files changed

File	Change
page_script.py	Zone editor retries layout until the media has a size; appliance cards render a login prompt.
anycam_credentials.py	Appliance login branch (RTSP walk, then MJPEG/HLS on web ports); initialises walk findings to avoid an unbound reference.
anycam_scan.py	B55 non-camera skip (printer ports, non-camera MAC maker); corrected appliance notes wording.
tests/	Z4e (appliance login) and U16 (B55 skip) added.
CHANGELOG.md, config.yaml, docs	3.8.0-rc3; build plan.