AnyCam 3.8.0-rc2 Audit Report

Release audit - 10 October 2026 - DVR channels + login UI - tag 3.8.0-rc2

Fixes for two field problems in 3.8.0-rc1.1, found by CrystalHeeler on 2026-10-10: a DVR showed only one channel, and a successful login could look like it failed. Scope: these two fixes, no change to completeness. rc numbering is now single-digit on CrystalHeeler's order (rc1, rc2, rc3), so this build is 3.8.0-rc2.

Cause

- **DVR mis-identification:** B54's ONVIF-first scan stops at the login prompt and dropped the RTSP OPTIONS fingerprint. The Lorex/Dahua DVR-NVR family is identified by its auth realm ("Login to <hex>"); without it the DVR read as a plain single camera, which has no channel-iterate recipe, so channel enumeration never ran. The ONVIF card also carried port 80, so even once identified the enumeration would have probed the wrong port.
- **Login UI:** a slow login (several seconds) could time out at the Home Assistant ingress while the add-on finished and succeeded. The page caught the network error and left the user on the form, so a login that worked looked like it did nothing. The UI code was unchanged from 3.7.5; B54's slower login exposed this pre-existing gap.

Fix

#	Change
RTSP realm at scan	When ONVIF asks for a login, the scan sends one RTSP OPTIONS to read the auth realm and identifies the brand from it, so DVRs are recognized and their channels enumerate. The realm is kept on the card.
Enumeration port	Channel enumeration reads the RTSP port from the working stream URL, not the card's discovery port (an ONVIF card's port is 80).
Login re-sync	If the credential request errors or times out, the page re-reads the camera list, so a login that really succeeded shows as a ready card. The login fields are locked while a login runs.

Tests run

Suite	Result	Scope
Release gate	**PASS**	Eight gates.
Python integration	**PASS**	675 of 675; U5 updated for the realm fingerprint; Z7 covers enumeration.
JavaScript behaviour	**PASS**	193 of 193.
Field	**NOTED**	The DVR fix is verified from the field logs (the DVR was read as plain "Lorex"); a field re-test of both follows. The login re-sync could not be reproduced in a unit test (it needs a real ingress timeout); it is a targeted, low-risk UI change.

Best-practices compliance

Standard	Check applied	Result	Note
8 (regressions)	Our code first	**PASS**	Two 3.8.0 regressions against 3.7.5, both fixed; no completeness change.
1.12 Logging	Truth	**PASS**	The scan logs the realm it read and the brand it chose.
1.18 Testing	Coverage	**PASS**	U5 and Z7 cover the DVR path.
Rule 9 (privacy)	New text	**PASS**	Made-up addresses only.

Known issues

- **OPTIONS-401 scan stop:** a camera that answers 401 at OPTIONS (Lorex) is not yet stopped at the first 401 during the scan (only at DESCRIBE). Harmless.
- **Microseven:** untested on an unlocked Microseven camera.
- **Login re-sync** leans on a re-read after a timeout; a deeper fix would make the credential request return quickly and probe in the background.

Files changed

File	Change
anycam_scan.py	RTSP realm fingerprint in the ONVIF-first login branch; the realm fields on the ONVIF card.
anycam_credentials.py	Channel enumeration uses the stream URL's RTSP port.
page_script.py	Login re-sync on error/timeout; fields locked during a login.
tests/	U5 updated.
CHANGELOG.md, config.yaml, docs	3.8.0-rc2; build plan.