AnyCam 3.8.0-rc1.1 Audit Report

Release audit - 10 October 2026 - login hotfix - tag 3.8.0-rc1.1

A hotfix for a login regression in 3.8.0-rc1.0, found by CrystalHeeler in the field on 2026-10-10 (both test systems: no camera could log in). Scope: one bug fix plus its regression test. Found from the field logs.

Cause

B54 added the 0/1/2 rule: at password entry the walk looks for up to two streams (want_streams=2) on one connection. After the first stream succeeded, the walk kept going for a second. Cameras that close the connection after the first stream (Hikvision, Lorex and Dahua recorders, the Hipcam/Microseven family) then reset the next request; the walker's socket-death handlers returned None, throwing away the stream already found. Every login on those cameras failed with "no working stream". In 3.7.5 the walk returned on the first stream, so the second request never happened.

Fix

#	Change
Sub-stream kept	When a camera drops the connection after the first stream, the sub-stream is now found on a fresh connection (as before B54), so the card still offers it.
Keep the found stream	The five socket-death returns in the single-socket walker (OPTIONS, DESCRIBE, DESCRIBE-auth and SETUP exceptions, and the outer handler) now return the first stream already found, not None. Looking for a second stream is best-effort; a dropped connection no longer loses the first.
Regression tests	AP8: a camera serves one stream then drops the connection; the walk must still return it. Z4d: the sub-stream then comes from a fresh-connection probe.

Tests run

Suite	Result	Scope
Release gate	**PASS**	Eight gates.
Python integration	**PASS**	675 of 675; AP8 and Z4d added.
JavaScript behaviour	**PASS**	193 of 193.
Field	**NOTED**	The failure was reproduced from the 2026-10-10 logs (Hikvision and Lorex). The fix is verified by AP8; a field re-test follows.

Best-practices compliance

Standard	Check applied	Result	Note
1.10 Exceptions	No silent data loss	**PASS**	Socket-death handlers preserve the found result.
1.18 Testing	Regression test first	**PASS**	AP8 covers the exact case.

Standard	Check applied	Result	Note
8 (regressions)	Our code first	**PASS**	A 3.8.0-rc1.0 regression against 3.7.5, fixed.

Known issues

- **OPTIONS-401 scan stop:** a camera that answers 401 at OPTIONS (Lorex) is not yet stopped at the first 401 during the scan (only at DESCRIBE). Harmless; tracked for a later build.
- **Microseven:** the new scan and the ffmpeg copy are untested on an unlocked Microseven camera.

Files changed

File	Change
anycam_probe.py	Five socket-death returns keep the found stream.
anycam_credentials.py	Fresh-connection sub-stream probe when the walk found none.
tests/test_server.py	AP8 and Z4d.
CHANGELOG.md, config.yaml, docs	3.8.0-rc1.1; build plan.