小程序抓包指导

抓包主要调用以下三个接口完成蓝牙数据的抓包：

wx.openBluetoothAdapter 开启蓝牙初始化；

wx.onBluetoothDeviceFound 监听扫描到的蓝牙数据；

wx.startBluetoothDevicesDiscovery 搜寻附近的蓝牙外围设备

使用 wx.startBluetoothDevicesDiscovery 接口扫描蓝牙设备时，应当把 allowDuplicatesKey 设置成 true，保证能够实时更新蓝牙信标 RSSI 值。而 interval 上报间隔在这可以当成是蓝牙数据刷新间隔，可根据实际情况来进行设置。

对于蓝牙信标而言，主要是针对 wx.onBluetoothDeviceFound 接口下获取到的参数，以下是使用该接口打印出来的内容样例：

```
{
  "deviceId": "C3:00:00:09:04:97",
  "name": "MBS02",
  "RSSI": -26,
  "connectable": true,
  "advertisData": "<ArrayBuffer: byteLength=25>",
  "advertisServiceUUIDs": [
    "0000FDA5-0000-1000-8000-00805F9B34FB"
  ],
  "localName": "MBS02",
  "serviceData": {
    "0000FDA5-0000-1000-8000-00805F9B34FB": "<ArrayBuffer: byteLength=11>"
  }
}
```

安卓的是可以拿到iBeacon里的自定义数据，IOS的因为被自动屏蔽，这里是没有的

这里是扫描回复包里的自定义数据，安卓和IOS都可以拿到

在这里，由于 IOS 系统的原因，蓝牙信标中的标准 iBeacon 帧是会被自动屏蔽掉的，只有安卓系统可以直接获取到。advertisData 里的数据是标准 iBeacon 帧里的数据，并且安卓系统也只能获取到 25 个字节(广播格式中从 4C00 开始到最后一个)。

扫描回复包中的自定义数据，只能获取到以下的自定义格式数据

offset	Length	Type	Data	Details
0	1	Data Length	0x02	/
1	1	Data Type	0x0A	AD 类型为 Tx Power Level
2	1	Power Data	0x00	Tx Power, 0x00 => 0dBm
3	1	Data Length	3	/
4	1	Complete list of 16-bit Service UUIDs	0x03	/
5	2	UUID data	0xF1FF	(little-endian) 0xF1FF
7	1	Data Length	14	/
8	1	Service data	0x16	/
9	2	UUID data	0xF1FF	(little-endian) 0xF1FF
11	1	Battery level	0x64	Battery level is 100%
12	2	Major	0x2715	(big-endian) 10005
14	2	Minor	0xD350	(big-endian)54096
16	6	Mac address	0x0100003F23AC	(little-endian) AC:23:3F:00:00:01
22	1	Data Length	6	/