

µOS++ Harness / Board Test — Cheat Sheet

- µOS++ Harness / Board Test — Cheat Sheet
 - 1. Layout
 - 2. One-time setup
 - 3. The platform (tests/platforms/<arch>-rpi-zero-2w/)
 - 4. A HARNESS TEST (a suite in tests/sources/)
 - 5. A BOARD TEST (a port test in <port>/test/<board>/)
 - 5b. A HARDWARE board test (no QEMU)
 - 5c. A HARNESS SUITE on a hardware platform
 - 6. Rules you must not break
 - 7. Commands
 - 8. Quick troubleshooting

µOS++ Harness / Board Test — Cheat Sheet

Condensed from WORK-SMP-AARCH32-AARCH64-HARNESS-GUIDE.md . For an architecture repository (like micro-os-plus-iii-aarch32 / -aarch64) that ships its **own** tests under test/<board>/ and is driven by the xPack harness in the SMP kernel's tests/ .

1. Layout

Layout (workspace root)

```
~/Work-smp/micro-os-plus-iii/  
├─ micro-os-plus-iii.git/          # SMP kernel (cloned from -smp) ← harness lives here  
│   └─ tests/                    # the xPack harness  
│       └─ package.json          # added by hand (greetings)  
├─ micro-os-plus-iii-devices.git/  
├─ micro-os-plus-iii-<arch>.git/   # the port: test/boards/<board>/, test/<board>/  
├─ micro-os-plus-iii-smp          -> micro-os-plus-iii.git  
└─ micro-os-plus-iii-devices     -> micro-os-plus-iii-devices.git
```

The two symlinks let the port find its kernel/devices siblings.

2. One-time setup

Setup — commands (cwd: ~/Work-smp/micro-os-plus-iii)

```
# cwd: ~/Work-smp/micro-os-plus-iii  
# clone  
git clone <smp>.git      micro-os-plus-iii.git  
git clone <devices>.git  micro-os-plus-iii-devices.git  
git clone <arch>.git     micro-os-plus-iii-<arch>.git  
ln -s micro-os-plus-iii.git micro-os-plus-iii-smp  
ln -s micro-os-plus-iii-devices.git micro-os-plus-iii-devices  
  
# harness
```

```
git -C <plain-iii>.git archive HEAD tests | tar -x -C micro-os-plus-iii.git

# C++20
sed -i 's/CMAKE_CXX_STANDARD 23/CMAKE_CXX_STANDARD 20/' micro-os-plus-iii.git/tests/CMakeLists.txt
```

tests/cmake/tests-main.cmake — pick the port by platform (replaces `add_subdirectory("../")`):

File: `micro-os-plus-iii.git/tests/cmake/tests-main.cmake`

```
# micro-os-plus-iii.git/tests/cmake/tests-main.cmake
set (UOS_AARCH32_DIR "${CMAKE_SOURCE_DIR}/../../micro-os-plus-iii-aarch32.git" CACHE PATH "")
set (UOS_AARCH64_DIR "${CMAKE_SOURCE_DIR}/../../micro-os-plus-iii-aarch64.git" CACHE PATH "")
if (PLATFORM_NAME MATCHES "^aarch32")
    add_subdirectory ("${UOS_AARCH32_DIR}" "port-bin")
elseif (PLATFORM_NAME MATCHES "^aarch64")
    add_subdirectory ("${UOS_AARCH64_DIR}" "port-bin")
else ()
    add_subdirectory (".." "top-bin")
endif ()
```

Kernel `package.json` (the harness greeting reads `../package.json`):

File: `micro-os-plus-iii.git/package.json`

```
{ "name": "@micro-os-plus/micro-os-plus-iii-smp", "version": "7.1.0", "license": "MIT" }
```

3. The platform (tests/platforms/<arch>-rpi-zero-2w/)

Platform layout

<code>cmake/definitions.cmake</code>	# platform macro + toolchain 15.2 guard
<code>cmake/dependencies-folders.cmake</code>	# test sources (+ validator xpack)
<code>cmake/platform-library.cmake</code>	# micro-os-plus::platform + ::platform-support
<code>CMakeLists.txt</code>	# executables + <code>add_test</code>
<code>include/cmsis-plus/platform.h</code>	# stub (+ <code>OS_USE_SEMIHOSTING_SYSCALLS</code> for AArch32)
<code>src/platform-support.cpp</code>	# hooks + strong <code>main()</code> + <code>exit/syscalls</code>

Platform split (see §5) — `platform-library.cmake`:

File: `micro-os-plus-iii.git/tests/platforms/aarch32-rpi-zero-2w/cmake/platform-library.cmake`

```
# micro-os-plus-iii.git/tests/platforms/aarch32-rpi-zero-2w/cmake/platform-library.cmake
# base: flags, linker, port, C library
add_library (platform-<arch>-interface INTERFACE EXCLUDE_FROM_ALL)
target_include_directories (platform-<arch>-interface INTERFACE "include")
target_compile_definitions (platform-<arch>-interface INTERFACE
    "${xpack_platform_compile_definition}" OS_NCPU=${UOS_BOARD_NCPU} OS_USE_SMP_SCHEDULER=1
    TRACE SEMIHOST QEMU_BUILD <arch-macros>)
target_link_options (platform-<arch>-interface INTERFACE
    -nostartfiles -WL,--gc-sections "-T${UOS_BOARD_LINKER_QEMU}")
target_link_libraries (platform-<arch>-interface INTERFACE micro-os-plus::aarch32) # AArch32 also:
    iii-newlib-reent iii-semihosting
```

```
add_library (micro-os-plus::platform ALIAS platform-<arch>-interface)

# support: hooks + main, for harness suites only
add_library (platform-<arch>-support-interface INTERFACE EXCLUDE_FROM_ALL)
target_sources (platform-<arch>-support-interface INTERFACE "src/platform-support.cpp")
target_link_libraries (platform-<arch>-support-interface INTERFACE platform-<arch>-interface)
add_library (micro-os-plus::platform-support ALIAS platform-<arch>-support-interface)
```

package.json — add hidden blocks, configs and an action:

File: [micro-os-plus-iii.git/tests/package.json](#)

```
// micro-os-plus-iii.git/tests/package.json
{
  "<arch>-actions": { "hidden": true, "actions": {
    "install": [ "xpm install --config {{ configuration.name }}" ] } },
  "<arch>-dependencies": { "hidden": true, "devDependencies": {
    "@xpack-dev-tools/<toolchain>": "15.2.1-1.1.1",
    "@xpack-dev-tools/qemu-arm": "9.2.4-1.1" } },
  "<arch>-rpi-zero-2w-cmake-gcc-debug": {
    "inherit": [ "<arch>-actions", "cmake-actions", "<arch>-dependencies", "short-win-paths-properties" ],
    "properties": { "buildType": "Debug", "platformName": "<arch>-rpi-zero-2w",
      "toolchainFileName": "<toolchain>.cmake", "shortConfigurationName": "..." } },
  "<arch>-rpi-zero-2w-cmake-gcc-release": {
    "inherit": [ "<arch>-rpi-zero-2w-cmake-gcc-debug" ],
    "properties": { "buildType": "MinSizeRel" } },
  "test-<arch>-rpi-zero-2w-cmake": [
    "xpm run prepare --config <arch>-rpi-zero-2w-cmake-gcc-debug",
    "xpm run build --config <arch>-rpi-zero-2w-cmake-gcc-debug",
    "xpm run test --config <arch>-rpi-zero-2w-cmake-gcc-debug",
    "xpm run prepare --config <arch>-rpi-zero-2w-cmake-gcc-release",
    "xpm run build --config <arch>-rpi-zero-2w-cmake-gcc-release",
    "xpm run test --config <arch>-rpi-zero-2w-cmake-gcc-release" ]
}
```

4. A HARNESS TEST (a suite in tests/sources/)

A. tests/sources/<name>/CMakeLists.txt

File: micro-os-plus-iii.git/tests/sources/<name>/CMakeLists.txt

```
# micro-os-plus-iii.git/tests/sources/<name>/CMakeLists.txt
cmake_minimum_required (VERSION 3.20)
add_library (test-<name>-interface INTERFACE EXCLUDE_FROM_ALL)
target_include_directories (test-<name>-interface INTERFACE "include")
target_sources (test-<name>-interface INTERFACE src/main.cpp)
add_library (test::<name> ALIAS test-<name>-interface)
```

The test defines `int os main(int argc, char* argv[])` and returns 0/non-zero.

B. Register the sources — add to the platform `cmake/dependencies-folders.cmake`:

File: `micro-os-plus-iii.git/tests/platforms/aarch32-rpi-zero-2w/cmake/dependencies-folders.cmake`

```
# micro-os-plus-iii.git/tests/platforms/aarch32-rpi-zero-2w/cmake/dependencies-folders.cmake
"${CMAKE_SOURCE_DIR}/sources/<name>"
```

C. Build + run — add to the platform CMakeLists.txt :

File: [micro-os-plus-iii.git/tests/platforms/aarch32-rpi-zero-2w/CMakeLists.txt](#)

```
# micro-os-plus-iii.git/tests/platforms/aarch32-rpi-zero-2w/CMakeLists.txt
if (ENABLE_<NAME>_TEST)
  add_test_executable (<name>-test)
  target_link_libraries (<name>-test PRIVATE
    micro-os-plus::common-options
    test::<name>
    micro-os-plus::iii
    micro-os-plus::platform
    micro-os-plus::platform-support) # harness suites link the SUPPORT
  add_test (NAME "${PLATFORM_NAME}-<name>-test" COMMAND
    qemu-system-aarch64 --machine raspi3b -smp 4 --nographic --serial none
    --semihosting-config enable=on,target=native
    --kernel "${TARGET_FILE:<name>-test}.bin") # AArch32: use the shim instead
  set_tests_properties ("${PLATFORM_NAME}-<name>-test" PROPERTIES TIMEOUT 1200)
endif ()
```

5. A BOARD TEST (a port test in <port>/test/<board>/)

The port test ships its **own** strong `main()` + startup hooks, so it links the **base** platform, not the support.

A. The port test (already in the port):

Port test layout

```
<port>/test/<board>/<name>/main.cpp      # defines main, hooks, os_main, RESULT:
<port>/test/<board>/src/test-smp-boot.cpp
<port>/test/<board>/include/              # test-console.hpp, test-smp-boot.hpp
```

B. Build + run — add to the platform CMakeLists.txt :

File: [micro-os-plus-iii.git/tests/platforms/aarch32-rpi-zero-2w/CMakeLists.txt](#)

```
# micro-os-plus-iii.git/tests/platforms/aarch32-rpi-zero-2w/CMakeLists.txt
set (_port_test_dir "${UOS_AARCH<NN>_DIR}/test/rpi-zero-2w")
add_executable (<name>
  "${_port_test_dir}/<name>/main.cpp"
  "${_port_test_dir}/src/test-smp-boot.cpp")
target_include_directories (<name> PRIVATE "${_port_test_dir}/include")
target_link_libraries (<name> PRIVATE
  micro-os-plus::common-options
  micro-os-plus::iii
  micro-os-plus::platform          # base ONLY — no platform-support
  micro-os-plus::devices)         # only if it touches the SD card
add_test (NAME "${PLATFORM_NAME}-<name>" COMMAND
  qemu-system-aarch64 --machine raspi3b -smp 4 --nographic --serial none
  --semihosting-config enable=on,target=native)
```

```
--drive "file=${_disk},if=sd,format=raw"          # only if it touches the SD card
--kernel "${_shim_img}"                          # AArch32; AArch64 uses the .bin
--device "loader,file=${<TARGET_FILE:<name>>.bin,addr=0x10000}"
set_tests_properties ("${PLATFORM_NAME}-<name>" PROPERTIES TIMEOUT 1200)
```

SD-backed tests need a blank image first:

File: micro-os-plus-iii.git/tests/platforms/aarch32-rpi-zero-2w/CMakeLists.txt

```
# micro-os-plus-iii.git/tests/platforms/aarch32-rpi-zero-2w/CMakeLists.txt
set (_disk "${CMAKE_CURRENT_BINARY_DIR}/<name>.disk.img")
add_custom_command (OUTPUT "${_disk}" COMMAND truncate -s 4G "${_disk}" VERBATIM)
add_custom_target (<name>-disk ALL DEPENDS "${_disk}")
```

Tests that need `micro-os-plus::devices` (the `BOARD_TEST_NEED_DEVICES` list): `sd_test smp-mat-sdcard-test smp-num-test smp-pipeline-test usb_test`.

Per-test actions. The VS Code plugin lists xpm **actions**, and the inherited `test` action is one per configuration, so every test shows as `<config>-test`. Give each test a named action in the config (same pattern as the hardware platform, §5b):

```
"actions": {
  "test-mutex-stress": "{{ properties.commandCMakePrepareWithToolchain }}" &&
    "{{ properties.commandCMakeBuild }}" && cd "{{ properties.buildFolderRelativePath }}" &&
    ctest -V -R mutex-stress",
  "test-smp-pipeline": "{{ properties.commandCMakePrepareWithToolchain }}" &&
    "{{ properties.commandCMakeBuild }}" && cd "{{ properties.buildFolderRelativePath }}" &&
    ctest -V -R smp-pipeline",
  "test-smp-pro-cons": "{{ properties.commandCMakePrepareWithToolchain }}" &&
    "{{ properties.commandCMakeBuild }}" && cd "{{ properties.buildFolderRelativePath }}" &&
    ctest -V -R smp-pro-cons"
}
```

`aarch32-rpi-zero-2w` and `aarch64-rpi-zero-2w` carry the same three.

5b. A HARDWARE board test (no QEMU)

Some boards have no useful emulator — the Luckfox Lyra is the case: QEMU models none of the RK3506's blocks, so an emulated Lyra would be a generic Cortex-A7 wearing the name. Such a board builds **one image per test** (`hwd`) and is run on silicon through OpenOCD. In the harness it is a **separate platform** whose CTest entry invokes the port's `hw.sh`.

A. New platform `tests/platforms/<arch>-<board>/`:

- `cmake/definitions.cmake` — select the board **before** the port is added (the port reads `BOARD` to pick its `board.cmake`):

```
set (BOARD "luckfox-lyra" CACHE STRING "" FORCE)
```

- `cmake/platform-library.cmake` — defines the **base** (no `QEMU_BUILD`); a **support** interface is added for the harness suites (§5c):

```
target_compile_definitions (... INTERFACE
    OS_NCPU=${UOS_BOARD_NCPU} OS_USE_SMP_SCHEDULER=1
    TRACE SEMHOST HW_BUILD __ARM_EABI__ __ARM_ARCH_7A__ _GNU_SOURCE)
target_link_options (... INTERFACE
    -nostartfiles -WL,--gc-sections "-T${UOS_BOARD_LINKER_HW}")
```

The board tests link the **base only** — they bring their own strong `main()` and hooks. The support (a second strong `main()`, for the harness suites) is a separate interface; see §5c.

- `CMakeLists.txt` — a small helper builds each port test and, opt-in, registers its run. The helper sets what the port's own `test/CMakeLists.txt` would set for an `hwd` application: output name `<app>-hwd`, runtime dir `<binary>/test`, the port flags, and the base platform only.

```
option (ENABLE_HW_TESTS "Register the hardware tests (needs the board)" OFF)

function (add_hw_test _app)
    cmake_parse_arguments (T "" "SECONDS" "SOURCES;INCLUDES;LIBRARIES" ${ARGN})
    add_executable (${_app} ${T_SOURCES})
    target_include_directories (${_app} PRIVATE ${T_INCLUDES})
    set_target_properties (${_app} PROPERTIES OUTPUT_NAME "${_app}-hwd"
        RUNTIME_OUTPUT_DIRECTORY "${CMAKE_CURRENT_BINARY_DIR}/test" SUFFIX "")
    target_link_libraries (${_app} PRIVATE micro-os-plus::iii
        micro-os-plus::platform ${T_LIBRARIES})

    if (ENABLE_HW_TESTS)
        set (_secs "${T_SECONDS}")
        if (_secs STREQUAL "")
            set (_secs 600) # run budget passed to run-hw.sh
        endif ()
        add_test (NAME "${PLATFORM_NAME}-${_app}"
            COMMAND bash "${_port_hw}" ${_app} ${_secs})
        math (EXPR _timeout "${_secs} + 600")
        set_tests_properties ("${PLATFORM_NAME}-${_app}" PROPERTIES
            ENVIRONMENT "BUILD=${CMAKE_CURRENT_BINARY_DIR}" TIMEOUT ${_timeout})
    endif ()
endfunction ()

# smp_test4: shared test-smp-boot.cpp, no devices.
add_hw_test (smp_test4
    SOURCES "${_port_test_dir}/smp_test4/main.cpp"
            "${_port_test_dir}/src/test-smp-boot.cpp"
    INCLUDES "${_port_test_dir}/include" "${_port_test_dir}/smp_test4")

# smp-mat-sdcard-test: shared test-smp-boot.cpp + devices (SD / FatFs).
add_hw_test (smp-mat-sdcard-test
    SOURCES "${_port_test_dir}/smp-mat-sdcard-test/main.cpp"
            "${_port_test_dir}/src/test-smp-boot.cpp"
    INCLUDES "${_port_test_dir}/include" "${_port_test_dir}/smp-mat-sdcard-test"
    LIBRARIES micro-os-plus::devices-rk3506
    SECONDS 1800) # the SD solver runs for many minutes

# smp_test5: self-contained (own boot threads) + C++ FatFs + SD host.
add_hw_test (smp_test5
    SOURCES "${_port_test_dir}/smp_test5/main.cpp" ${_fatfs_sources}
    INCLUDES "${_fatfs_dir}" "${_port_test_dir}/smp_test5")
```

```
LIBRARIES micro-os-plus::devices-rk3506
SECONDS 900)
```

`hw.sh` runs `run-hw.sh "$BUILD/test" <app>`, so each image must sit in `<binary>/test/` named `<app>-hwd` — hence the output name, runtime dir and cleared suffix. `SECONDS` is the run budget; the `CTest TIMEOUT` is that plus a margin, so `CTest` never kills a run the runner would still allow.

- **The tests come from the port clone, not from `tests/`.** `_port_test_dir` is `${UOS_AARCH32_DIR}/test/<board>`, and `UOS_AARCH32_DIR` is `../../micro-os-plus-iii-aarch32.git` — the Work-smp **port clone**, whose origin is the TMP7 working copy. Write and commit the test in TMP7; it reaches Work-smp with a `git pull` in the clone. Nothing is copied into the harness. The harness does **not** glob the port's tests — `add_hw_test(...)` lists the ones to build, so a new test needs a line here too.
- `package.json` — one **named action per test**, so the xPack VS Code plugin (which lists actions, not `CTest` tests) shows each test by name:

```
"actions": {
  "test": "cd {{ properties.buildFolderRelativePath }} && ctest -V -LE hw",
  "test-mutex-stress": "{{ properties.commandCMakePrepareWithToolchain }} && {{ properties.commandCMakeBuild }} && cd {{ properties.buildFolderRelativePath }} && ctest -V -R mutex-stress",
  "test-smp_test4": "{{ properties.commandCMakePrepareWithToolchain }} && {{ properties.commandCMakeBuild }} && cd {{ properties.buildFolderRelativePath }} && ctest -V -R smp_test4",
  "test-smp-mat-sdcard-test": "{{ properties.commandCMakePrepareWithToolchain }} && {{ properties.commandCMakeBuild }} && cd {{ properties.buildFolderRelativePath }} && ctest -V -R smp-mat-sdcard-test",
  "test-smp_test5": "{{ properties.commandCMakePrepareWithToolchain }} && {{ properties.commandCMakeBuild }} && cd {{ properties.buildFolderRelativePath }} && ctest -V -R smp_test5"
}
```

Every hardware test carries `LABELS hw`, and the generic `test` action runs `ctest -LE hw`: on the Lyra that selects **nothing** (all four tests are hardware tests), so a stray `test` cannot start a board run — use the named `test-*` actions, one per power cycle. The QEMU platforms keep the inherited `test` action unchanged.

Each `test-*` action configures the build tree with `commandCMakePrepareWithToolchain` — the pinned `-D CMAKE_TOOLCHAIN_FILE` — before it builds, so a rebuild picks up the right compiler. A fresh configuration still needs `xpm run install` once.

B. Three hardware quirks. All are read at run time (no rebuild):

- **SWD clock** — `hw.sh` (`UOS_HW_ADAPTER_KHZ`) and `openocd.cfg` (`adapter speed`), raised from 1000 to 4000 kHz. If you see `Invalid ACK / DEBUG LINK LOST`, drop it back (`UOS_HW_ADAPTER_KHZ=2000`).
- **Console throughput** — the port's `uart.hpp` mirrors the console **line-buffered**: `putc/operator<<` accumulate and emit one `SYS_WRITE0` per line, not one `SYS_WRITEC` per character. A partial line needs `uart::uart1.flush()`.

- **OpenOCD log noise** — `openocd.cfg`'s `examine_secondaries` runs once, silently, wrapped in `log_output /dev/null ... log_output default`, so the `Info : [<target>] hardware has N breakpoints` lines do not shred the console.

C. The strong semihosting paradigm. A hardware run has **no process status**:

OpenOCD is a debugger, not a parent. So the verdict is a line the runner greps, and the exit is what *stops* the run. The port's `include/semihosting.hpp` picks the trap by build:

File: micro-os-plus-iii-aarch32.git/include/semihosting.hpp

```
// micro-os-plus-iii-aarch32.git/include/semihosting.hpp
#ifdef(QEMU_BUILD)           // emulator: SVC + reason-by-VALUE
#elif defined(SEMIHOST_TRAP_HLT) // Pi under an aarch64 OpenOCD target
#else                       // Lyra: cortex_a -> Angel SVC + reason-by-POINTER
#endif
```

and adds the verdict-and-stop the hardware tests end with:

File: micro-os-plus-iii-aarch32.git/include/semihosting.hpp

```
// micro-os-plus-iii-aarch32.git/include/semihosting.hpp
[[noreturn]] inline void report_result (bool pass) noexcept {
    write_str (pass ? "\nRESULT: PASS\n" : "\nRESULT: FAIL\n"); // the verdict (semihosting)
    pass ? exit_success () : exit_failure ();                  // the stop (SYS_EXIT)
}
```

The strong `_Exit()` (`src/semihosting-exit.cpp`) routes `std::exit()` through the same path. A hardware test ends with `semihosting::report_result (true)` after its checks; every failure path calls `report_result (false)`.

Getting the trap wrong is not a missing console. `hlt #0xF000` is UNDEFINED on ARMv7-A: the word is an Undefined Instruction, so the first character faults and, if the fault handler also prints, the board loops printing fault dumps. The board's `board.cmake` picks HLT vs SVC; the build variant picks value vs pointer.

D. Build and run.

Commands (cwd: `~/Work-smp/micro-os-plus-iii/micro-os-plus-iii.git/tests`)

```
# cwd: ~/Work-smp/micro-os-plus-iii/micro-os-plus-iii.git/tests
cd ~/Work-smp/micro-os-plus-iii/micro-os-plus-iii.git/tests
xpm run install --config aarch32-luckfox-lyra-cmake-gcc-debug
xpm run prepare --config aarch32-luckfox-lyra-cmake-gcc-debug
xpm run build   --config aarch32-luckfox-lyra-cmake-gcc-debug

# register the run (needs the board attached; one power cycle per test)
PATH="$PWD/build/aarch32-luckfox-lyra-cmake-gcc-debug/xpacks/.bin:$PATH" \
  cmake -DENABLE_HW_TESTS=ON build/aarch32-luckfox-lyra-cmake-gcc-debug
ctest --test-dir build/aarch32-luckfox-lyra-cmake-gcc-debug -V -R smp_test5

# or by hand
```

```
BUILD=$PWD/build/aarch32-luckfox-lyra-cmake-gcc-debug/platform-bin \
../../micro-os-plus-iii-aarch32.git/test/boards/luckfox-lyra/hw.sh smp_test5
```

Expected: RESULT: PASS in the OpenOCD log, then [hw] smp_test5 PASSED.

One test per power cycle: the secondaries are released once, and no run can un-release them. run-hw.sh refuses to run a suite for exactly this reason.

5c. A HARNESS SUITE on a hardware platform

A board test brings its own `main()`; a **harness suite** (from `tests/sources/`) does not. To run one on a hardware platform you add a `platform-support` for the board — a hardware variant of the support the QEMU platforms already have.

A. `src/platform-support.cpp` — startup hooks + a strong `main()`:

File: `micro-os-plus-iii.git/tests/platforms/aarch32-luckfox-lyra/src/platform-support.cpp`

```
// micro-os-plus-iii.git/tests/platforms/aarch32-luckfox-lyra/src/platform-support.cpp
void os_startup_initialize_hardware_early (void) {}
void os_startup_initialize_hardware (void) {
    uart::uart1.init ();
    os_startup_initialize_free_store (__heap_start, __heap_end - __heap_start);
    exception::init ();
    // AFTER the free store: setvbuf() allocates the stdout buffer, and there is
    // no heap before os_startup_initialize_free_store().
    setvbuf (stdout, nullptr, _IOLBF, 0);
}

[[noreturn]] static void harness_main_trampoline (void) {
    // Opens the semihosting fds (initialise_monitor_handles) so the C library's
    // _write finds fd 1; without it every printf in the suite is discarded.
    int argc = 0;
    char** argv = nullptr;
    os_startup_initialize_args (&argc, &argv);

    int code = os_main (argc, argv);           // no command line -> argc <= 1
    uart::uart1 << (code == 0 ? "\nRESULT: PASS\n" : "\nRESULT: FAIL\n");
    uart::uart1.flush ();                     // the verdict the runner greps
    std::exit (code);                         // -> strong _Exit -> SYS_EXIT
}
```

The suites print through the C library (`printf`). Its `_write` needs fd 1 in the semihosting table, which `os_startup_initialize_args()` fills (via `initialise_monitor_handles()`); without that call every `printf` is dropped with `EBADF`, while the kernel's own unbuffered trace (the `./!` tick markers) still appears.

B. `cmake/platform-library.cmake` — a support interface that adds the hooks and the kernel's C library (the suites use `printf`, `gettimeofday`):

File: [micro-os-plus-iii.git/tests/platforms/aarch32-luckfox-lyra/cmake/platform-library.cmake](#)

```
# micro-os-plus-iii.git/tests/platforms/aarch32-luckfox-lyra/cmake/platform-library.cmake
add_library (platform-<board>-support-interface INTERFACE EXCLUDE_FROM_ALL)
target_sources (platform-<board>-support-interface INTERFACE "src/platform-support.cpp")
target_link_libraries (platform-<board>-support-interface INTERFACE
    platform-<board>-interface
    micro-os-plus::iii-newlib-reent micro-os-plus::iii-semihosting)
add_library (micro-os-plus::platform-support ALIAS platform-<board>-support-interface)
```

platform.h must define `OS_USE_SEMIHOSTING_SYSCALLS` (plus `__disable_irq`), and the base needs `_GNU_SOURCE` (the syscall layer uses `S_IREAD`).

C. The suite target — link the base + **support** + the suite + common-options:

File: [micro-os-plus-iii.git/tests/platforms/aarch32-luckfox-lyra/CMakeLists.txt](#)

```
# micro-os-plus-iii.git/tests/platforms/aarch32-luckfox-lyra/CMakeLists.txt
add_executable (mutex-stress-test)
target_link_libraries (mutex-stress-test PRIVATE
    micro-os-plus::common-options test::mutex-stress
    micro-os-plus::iii micro-os-plus::platform micro-os-plus::platform-support)
set_target_properties (mutex-stress-test PROPERTIES
    OUTPUT_NAME "mutex-stress-test-hwd"
    RUNTIME_OUTPUT_DIRECTORY "${CMAKE_CURRENT_BINARY_DIR}/test" SUFFIX "")
```

Add `sources/mutex-stress` to `dependencies-folders.cmake`, register the run like any board test, and add a `test-mutex-stress` action.

The suite source is unchanged: it returns a code from `os_main()`, and the **support trampoline** turns that into the `RESULT`: line — so the same source runs under QEMU (exit code) and on the board (log line).

6. Rules you must not break

Rule	Why
One <code>micro-os-plus::iii</code> — add only the port; never the kernel too	duplicate alias fails
Platform split : base = flags/port/linker; support = hooks/main + kernel C-lib	port tests bring their own <code>main</code> ; two strong mains collide
Harness suite links base + support ; board test links base only	as above
QEMU_BUILD on the platform	AArch32 port selects SVC + reason-by-value; else QEMU exits 1
AArch32 links the kernel's <code>iii-newlib-reent</code> + <code>iii-semihosting</code> ; AArch64 does not (port provides its own HLT)	the kernel groups are AArch32-only

Rule	Why
<code>OS_USE_SEMIHOSTING_SYSCALLS</code> in <code>platform.h</code> (AArch32)	else <code>c-syscalls-semihosting.cpp</code> compiles to nothing
C++20	harness/port standard
Unique test names + project name per <code>platform (\${PLATFORM_NAME}-...)</code>	runners cannot tell aarch32 from aarch64 otherwise
install → prepare → build → test	<code>build/<config>/</code> holds the pinned toolchain
arm-none-eabi-gcc 15.2 guard	the system 16.2 must not be picked
Hardware board: no <code>QEMU_BUILD</code> , define <code>HW_BUILD</code> , run via <code>hw.sh</code> ; the verdict is the <code>RESULT:</code> line, not an exit code	OpenOCD has no process status
Harness suite on hardware: needs a board <code>platform-support (+ iii-newlib-reent/iii-semihosting)</code> ; board tests link the base only	the suite has no <code>main()</code> /hooks

7. Commands

Commands (cwd: `~/Work-smp/micro-os-plus-iii/micro-os-plus-iii.git/tests`)

```
# cwd: ~/Work-smp/micro-os-plus-iii/micro-os-plus-iii.git/tests
cd ~/Work-smp/micro-os-plus-iii/micro-os-plus-iii.git/tests

# first time
npm install
xpm install
xpm run install --config <arch>-rpi-zero-2w-cmake-gcc-debug

# lifecycle
xpm run prepare --config <arch>-rpi-zero-2w-cmake-gcc-debug
xpm run build --config <arch>-rpi-zero-2w-cmake-gcc-debug
xpm run test --config <arch>-rpi-zero-2w-cmake-gcc-debug

# debug + release
xpm run test-<arch>-rpi-zero-2w-cmake

# one test only (xpm's PATH provides qemu-system-aarch64)
B=build/<arch>-rpi-zero-2w-cmake-gcc-debug
PATH="$PWD/$B/xpacks/.bin:$PWD/xpacks/.bin:$PATH" \
  ctest --test-dir "$B" -R <name> -V

# list registered tests
PATH="$PWD/$B/xpacks/.bin:$PATH" ctest --test-dir "$B" -N
```

Expected:

Output

```
1/3 Test #1: aarch32-rpi-zero-2w-mutex-stress-test ... Passed
2/3 Test #2: aarch32-rpi-zero-2w-smp-pipeline-test ... Passed
```

```
3/3 Test #3: aarch32-rpi-zero-2w-smp-pro-cons-test ... Passed
100% tests passed, 0 tests failed out of 3
```

From TMP7 instead

TMP7's working copies have **no .git suffix**, so the harness's fixed `../../micro-os-plus-iii-aarch32.git` does not resolve. Symlink the ports once, then the same lifecycle runs from `TMP7/micro-os-plus-iii-smp/tests`:

```
cd /home/dan/Downloads/luckfox_lyra/TMP7
ln -s micro-os-plus-iii-aarch32 micro-os-plus-iii-aarch32.git
ln -s micro-os-plus-iii-aarch64 micro-os-plus-iii-aarch64.git

cd micro-os-plus-iii-smp/tests
xpm run install --config aarch32-luckfox-lyra-cmake-gcc-debug
xpm run test-mutex-stress --config aarch32-luckfox-lyra-cmake-gcc-debug
```

TMP7 is where a port test is written; Work-smp is where the harness builds it — they meet at the bare (`GIT/micro-os-plus-iii-smp.git`), so commit + push in TMP7, then `git pull` in the Work-smp clone. Full chapter: guide §21.

8. Quick troubleshooting

Symptom	Fix
alias <code>micro-os-plus::iii</code> already exists	add only the port
undefined reference to <code>os_startup_initialize_hardware*</code>	harness suite must link <code>platform-support</code>
multiple definition of <code>_write/...</code> (AArch64)	the port already defines them; don't redefine
undefined reference to <code>_write/_gettimeofday</code>	AArch32: link <code>iii-newlib-reent</code> + <code>iii-semihosting</code>
test hangs after <code>scheduler::start()</code>	strong <code>main()</code> must set the interrupts stack
<code>***Failed, QEMU exit 1</code>	AArch32: use <code>QEMU_BUILD</code> (SVC + value)
toolchain guard fires (16.2)	<code>rm -rf build/<config></code> then <code>install</code> → <code>prepare</code> → <code>build</code>
<code>test_smpl</code> -era path errors	apps live in <code><port>/test/<board>/</code> , runners in <code>test_smpl/</code>
hardware run faults / no output	wrong trap: HLT for the Pi, SVC for the Lyra; never <code>hlt</code> on ARMv7-A
hardware test never ends (TIMEOUT)	the test must call <code>semihosting::report_result()</code> ; an infinite demo has no verdict
hardware test killed at the budget	raise its <code>SECONDS</code> in <code>add_hw_test</code> (e.g. <code>smp-mat-sdcard-test = 1800</code>)
<code>S_IREAD</code> was not declared building <code>c-syscalls-semihosting.cpp</code>	the base needs <code>_GNU_SOURCE</code>

Companion to `WORK-SMP-AARCH32-AARCH64-HARNESS-GUIDE.md` (full detail) and `TESTS-XPACK-SYSTEM.md` (upstream harness).