



LESTER B. PEARSON
Pearson Electrotechnology Centre

Installation and Repair of Telecommunications Equipment

Module 21 Telephone network systems

VOIP lab experiment#3

Setting up the extensions in FreePBX

Installation and Repair of Telecommunications Equipment

Name of student: _____

Group Number: _____

Date: _____



LESTER B. PEARSON
Pearson Electrotechnology Centre

Installation and Repair of Telecommunications Equipment

Module 21 Telephone network systems

The purpose of the lab is to demonstrate the ability of the students to configure the PBX by creating different extensions.

[FreePBX Support](#)[ISymphony Panel](#)[User Panel](#)

FreePBX Administration



User Control Panel



Operator Panel



Get Support

Click FreePBX Administration

Username: admin

Password: admin



1- This will allow to access your PBX, Elastix. In the main page click on **PBX**



FreePBX System Status

FreePBX Notices

- Default Asterisk Manager Password Used
- Collecting Anonymous Browser Stats

[show all](#)

FreePBX Statistics

Total active calls	0
Internal calls	0
External calls	0
Total active channels	0

FreePBX Connections

Uptime

System Uptime: 4 minutes
Asterisk Uptime: 0 minutes
Last Reload: 0 minutes

System Statistics

Processor

Load Average	0.00
CPU	0%

Memory

App Memory	9%
Swap	0%

Disks

/	10%
/dev/shm	0%
/boot	11%

Networks

eth0 receive	0.64 KB/s
eth0 transmit	105.47 KB/s

Server Status

Asterisk	OK
MySQL	OK
Web Server	OK
SSH Server	OK



Add an Extension

Please select your Device below then click Submit

- Device

Device

Click on **Applications** then **extensions**

2- In device, choose: **generic SIP device**, then click on submit



- Add Extension

User Extension	1000
Display Name	Central Office
CID Num Alias	
SIP Alias	

- Extension Options

Outbound CID	
Asterisk Dial Options	Ttr ☐ Override
Ring Time	Default
Call Forward Ring Time	Default
Outbound Concurrency Limit	No Limit
Call Waiting	Enable
Internal Auto Answer	Disable
Call Screening	Disable
Pinless Dialing	Disable
Emergency CID	
Queue State Detection	Use State

- Assigned DID/CID

DID Description	
Add Inbound DID	
Add Inbound CID	

- Device Options

This device uses sip technology.

secret	pec123
dtmfmode	RFC 2833

3- Create the following information to create the first extension:

User extension: **1000**

Display Name: **Main Office**

Secret: **pec123**



- Voicemail

Status	Enabled
Voicemail Password	
Email Address	
Pager Email Address	
Email Attachment	yes no
Play CID	yes no
Play Envelope	yes no
Delete Voicemail	yes no
VM Options	
VM Context	default

- iSymphony Extension Settings

- 4- Enable the voiceMail
- 5- Go to the end of the page and click on "submit"
- 6- The extension is now created as you can see on the right side of the screen. Create the 2 following extension as well by repeating the steps 2-4:

User extension	Display Name	Secret
2000	xxxx	pec123
3000	Boss	pec123

*****You have to click on "apply config" in order to finalize the extension. If you do not, the extension will not be created*****