

# OpenJukebox

Benjamin Fus

December 19, 2013

## Contents

<b>1</b>	<b>Hardware</b>	<b>1</b>
1.1	Carambola2 . . . . .	1
1.2	USB-Sound . . . . .	1
1.3	LCD-Display . . . . .	2
1.4	Power supply . . . . .	2
1.5	Front panel control . . . . .	2
<b>2</b>	<b>Software</b>	<b>3</b>
2.1	OpenWRT . . . . .	3
2.1.1	Patch for MPD-full . . . . .	3

## Abstract

There are several network player on the market, which all based on proprietary software. Because of this proprietary the network player is mostly uncomfortable in use and it is not usable from every network device. To improve this weakness the goal of this project is to build a network player which is controllable via the Music Player Daemon (MPD). MPD uses a extreme simple protocol which based on ascii Strings. This simple protocol allows to interact via a telnet client with the mpd server. The network player will get a own hard drive and will be able to play internet radio and audio from other sources.

## 1 Hardware

Existing development boards has been chosen to build the network player with a minimal effort of development. The power supply will be build in a classic way with a toroidal transformer, bridge rectifiers and a reservoir capacitor. After this simple power supply two different voltages will be provided by two step-down transformer. The core of the network player will be a Carambol2 2.

## 1.1 Carambola2

The Carambola2 is a System On Chip (SoC) Module which has a MIPS processor with 400 MHz clock, 16 MB of SPI-Flash and 64 MB of RAM. The SoC provides 2 Ethernet connectors and a Wifi module as well as UART access and buses like inter circuit communication (i2c). Especially for audio playback the Carambola2 is equipped with the Inter-IC Sound(i2s) bus which is a bus for serielle digital audio transmission as well as Sony/Philips Digital Interface (S/PDIF) which is a interface specification for a digital audio interface for stereo or multi-channel audio. Unfortunately, there is no driver to use either i2s nor S/PDIF under openWRT because of this a USB sound card must be used to provide an audio output. The Carambola2 development board provides two




Figure 1: Carambola2

lines of holes for pinheaders and they provide the following assignment.




Figure 2: Carambola2 Pinheader assignement

## 1.2 USB-Sound

In the selection of the chipset for the USB-Soundchip the choice falls on the PCM2704 from Texas Instruments. The PCM2704 provides direkt analog audio output via Burr Brown Digital Analog Converter as well as digital audio output over S/PDIF and Toslink. In this case the referencedesing for the PCM2704 is available as an development board and that is used in this project. The

PCM2704 operates directly as Human Interface Device(HID) which means that no special driver is needed. If there is a driver for the Carambola2 i2s and SPDIF available in the future, this hardware component will be obsolete.




Figure 3: PCM2704

### 1.3 LCD-Display

To display informations like title or artist there will be used a common lcd display with a hd4478 chipset with 16 columns and 2 rows or 20 clumns and 4 rows. To controll the display the circuit "LCD2USB" from Dr. Till Harbaum will be used. This circuit consist of an Atmel ATMEGA8 and uses the Avrusb library to communicate directly via USB with the LCD display. As alternative we will test a circuit which controls the LCD display via i2c. This has the advantage that the USB hub has one device less to manage.

### 1.4 Power supply

Goal of the power supply is to provide the internal voltage with a minimum of noise. The power supply is designed in a classic way with an toroidal transformer and step-down transformer to provide 5V and 3.3V as output voltage. In the first step the torodial transformer transforms the 220V alternating current voltage into 12V alternating current voltage which feeds an bridge rectifier to get direct current voltage. The direct current voltage from the bridge rectifier fluctuate. To smooth the voltage a reservoir capacitor is used. The capacity of the capacitor can be calculated with the following formula.

$$C = I * \frac{\Delta t}{\Delta U} \quad (1)$$

In this case  $\Delta t$  stands for the netfrequency diviced by two which means at a 50Hz we have  $\Delta t = 10ms$ .  $\Delta U$  stands for the amount of voltage which can be lost during  $\Delta t$ . The toroiadal transformer can provide a current of 2.5A.

$$C = 2.5A * \frac{10*10^{-3}s}{0.1V} = 0.25F$$

Because we use half-wave rectification the capacity must be doubled. The reservoir capacitor must have 0.5F

## 1.5 Front panel control

As input device will be used a rotary encoder on the front panel.




Figure 4: Rotary Encoder

A fast test lets see a mapping of  
 right: 00  $\rightarrow$  01  $\rightarrow$  11  
 1/0  $\rightarrow$  00  
 left: 00  $\rightarrow$  10  $\rightarrow$  11  
 01  $\rightarrow$  00




Figure 5: Rotary encoder states

## 2 Software

### 2.1 OpenWRT

#### 2.1.1 Patch for MPD-full

In order to compile the package mpd-full it is necessary to patch the package with the following patch

### Listing 1: mpd-patch

```
diff --git a/sound/mpd/Makefile b/sound/mpd/Makefile
index 19f9b06..baa8059 100644
--- a/sound/mpd/Makefile
+++ b/sound/mpd/Makefile
@@ -8,12 +8,12 @@
    include $(TOPDIR)/rules.mk

    PKG_NAME:=mpd
    -PKG_VERSION:=0.16.5
    +PKG_VERSION:=0.16.8
    PKG_RELEASE:=2

    PKG_SOURCE:=$(PKG_NAME)-$(PKG_VERSION).tar.bz2
    -PKG_SOURCE_URL:=@SF/musicpd
    -PKG_MD5SUM:=f7564cff12035f6a1112cce770655df7
    +PKG_SOURCE_URL:=http://www.musicpd.org/download/mpd/0.16/
    +PKG_MD5SUM:=b412a9d0b3457bea1bb87904a8f80c04

    PKG_BUILD_DIR:=$(BUILD_DIR)/$(PKG_NAME)-$(BUILD_VARIANT)/$(PKG_NAME)-$(PKG_VERSION)
    PKG_BUILD_PARALLEL:=1
```

## List of Tables

## List of Figures

1	Carambola2 . . . . .	1
2	Carambola2 Pinheader assignement . . . . .	2
3	PCM2704 . . . . .	2
4	Rotary Encoder . . . . .	2
5	Rotary encoder states . . . . .	2