



Amlogic Linux BSP Openlinux Release Note

AMLOGIC, Inc.

2518 Mission College Blvd
Santa Clara, CA 95054
U.S.A.
www.amlogic.com

AMLOGIC reserves the right to change any information described herein at any time without notice.
AMLOGIC assumes no responsibility or liability from use of such information.

Amlogic Openlinux Release Notes

Content

1. Basic Information.....	3
1.1. INTRODUCTION.....	3
1.1.1. Kernel Version.....	3
1.1.2. List of Supported Drivers.....	3
1.1.3. List of Not Supported Drivers.....	3
1.2. CHIP INFORMATION.....	3
1.3. HOW TO GET CODE.....	4
1.4. REFERENCE PLATFORM.....	4
1.5. HOW TO BUILD CODE.....	5
1.5.1. Kernel Toolchain.....	5
1.5.2. Build.....	5
1.6. HOW TO UPGRADE.....	5
2. Test Report.....	5
2.1. STABILITY TEST.....	5
2.2. VIDEO FORMAT TEST REPORT FOR GSTPLAYER.....	6
2.3. VIDEO FORMAT TEST REPORT FOR KPLAYER.....	7
3. Recent Changes.....	8
4. Known Issue.....	8

1. Basic Information

1.1. Introduction

This document provides the Openlinux notes for Amlogic Linux BSP reference source code release running on Amlogic reference hardware. To obtain Amlogic Linux BSP reference source code, you will need to have an account to access Amlogic GIT source code repository.

1.1.1. Kernel Version

Kernel version is 3.10.33:

```
commit 6969595f011b46b49c3f1b9e0bd7da27768c1fd9
Author: Greg Kroah-Hartman <gregkh@linuxfoundation.org>
Date: Thu Mar 6 21:58:45 2014 -0800
```

Linux 3.10.33

1.1.2. List of Supported Drivers

- 1) Timer / Interrupts
- 2) Clocks
- 3) Pinmux/GPIO/GPIO IRQ
- 4) Remote
- 5) Hdmi
- 6) UART
- 7) USB Host
- 8) CPU DVFS
- 9) System Thermal (IPA)
- 10) CPU Hotplug
- 11) SD/SDHC/SDXC
- 12) NAND
- 13) eFuse
- 14) SARADC/ADCKEY
- 15) I2C
- 16) PWM
- 17) SDIO WiFi/USB WiFi
- 18) LED
- 19) Ethernet

1.1.3. List of Not Supported Drivers

- 1) SPI

1.2. Chip Information

Item	S805
CPU	Quad Cortex-A5
Max CPU Freq.	1.5G Hz
GPU	Mali-450
Security	TrustZone & TVP
Memory	DDR3/3L, LPDDR2/3

Amlogic Openlinux Release Notes

Video decoding	1080P H265
Video Encoding	1080P H264
HDMI-Tx	1080P
Ethernet	10/100/1000M
AV output	CVBS
IP License	Dolby,DTS

1.3. How to Get Code

1) repo command

You can download Linux BSP source code by running the following repo commands:

- **China openlinux server**

```
$ cd ~/<your-repo-dir>/
$ repo init -u ssh://git@openlinux.amlogic.com/buildroot/platform/manifest.git
$ repo init -m buildroot-openlinux-20170731.xml
$ repo sync
```

- **Overseas openlinux server**

```
$ cd ~/<your-repo-dir>/
$ repo init -u ssh://git@openlinux2.amlogic.com/buildroot/platform/manifest.git
$ repo init -m buildroot-openlinux-20170731.xml
$ repo sync
```

2) download tar package

You can download the tar package freely, but it has no git info:

```
$ wget -c
http://openlinux.amlogic.com:8000/download/ARM/filesystem/Linux_BSP/buildroot_openlinux_kernel_3.10_wayland_20170731.tar.gz
$ tar xvfz buildroot_openlinux_kernel_3.10_wayland_20170731.tar.gz
```

1.4. Reference Platform

- **M201(S805)**
NAND,WIFI AP6210 ,DDR 1GB

1.5. How to Build Code

1.5.1. Kernel Toolchain

The cross-compile tool used for kernel 3.10 is : gcc-linaro-6.3.1-2017.02-x86_64_aarch64-linux-gnu/, and it should be pre-installed before kernel build.

```
aarch64-linux-gnu-gcc -v
gcc version 4.9.2 20140904 (prerelease) (crosstool-NG linaro-1.13.1-4.9-2014.09 -
Linaro GCC 4.9-2014.09)
```

1.5.2. Build

You can find corresponding Buildroot setenv config and kernel config for the reference hardware by doing the following:

1) Mbox M201

```
. buildroot/build/setenv.sh
choose meson8b_m201_release config option
make
Note: Do not use make -jN here as Buildroot does not support top-level parallel
make. This does not mean that Buildroot does not support parallel compilation, but
just that it will handle this inside the Buildroot compilation system.

Uboot compile:
cd bootloader/uboot
./mk m8b_m201_v1
(uboot/fip/u-boot.bin for nand and EMMC, uboot/fip/u-boot.bin.sd.bin for making
bootcard)
```

The upgrade file aml_upgrade_package.img will be generated in output/[config_build_folder]/images/.

1.6. How to Upgrade

- For Windows: Upgrade with USB burn tool.
- For Linux: Upgrade with bash script aml_update_whole_package.sh. Make sure usb driver has been installed correctly.
 - 1) plugin power cable, at the same time, hold down the POWER key.
 - 2) plugin the usb cable within 5 seconds.
 - 3) cd the script directory.
 - 4) ./aml_update_whole_package.sh path/to/aml_upgrade_package.img.

2. Test Report

2.1. Stability test

Test Platform	Test Case	Total test time	Test Result	
M201#064	dvfs stress	0H	Fail	
M201#097	H264&H265	12H	Pass	
M201#064	H264&H265	15H	Pass	

Amlogic Openlinux Release Notes

M201#064	Auto reboot	3000 times	Fail	
M201#097	Auto reboot	3000 times	Pass	

2.2.Video Format Test Report For GSTplayer

Extension	Codec Detail	Tested Resolution	S805
.3g2	H263	704x576	Support
.3gp	MPEG-4 Visual	640x480	Support
	H263	704x576	Support
	MPEG-4	320x240	Support
.asf	WMV3	320x240	Support
.avi	AVC	1920x1080	Support
	DivX5	1280x720	Support
	M-JPEG	1024x576	Support
	MS MPEG-4 V1	352x218	Support
	RealMagic	720x480	Support
	MPEG-4	720x576	Support
	h264	1920x1080	Support
	FF mpeg	640x480	Support
	MPEG4	640x480	Support
	XVID	640x480	Support
	S-Mpeg 4 v3	720x400	Support
	DivX3	720x576	Support
	DivX4	1920x1080	Support
.dat	MPEG-1	352x288	Support
.divx	DivX5	1280x720	Support
.f4v	AVC(H264)	1280x720	Support
.flv	Sorenson Spark	1920x1080	Support
.mp4	AVC(H264)	1920x1080	Support
	HEVC(H265)	1920x1080	Support
	H263	176x144	Support
	MPEG-4 Visual	640x480	Support
.m2ts	AVC	1920x1080	Support
.m2v	MPEG-2	480x576	Support
.m4v	AVC	1280x720	Support
.mkv	WMV3	1280x720	Support
	MPEG-4 Visual	1920x1080	Support
	AVC	1920x1080	Support
.mov	MPEG-4 Visual	1280x720	Support
	mjpa	640x480	Support
	H263	320x240	Support
	M-JPEG	640x480	Support
	AVC	1920x1080	Support
	MPEG-4 Visual	640x480	Support
.mpeg	MPEG-2	1920x1080	Support
	MPEG-1	720x576	Support
.mts	AVC	1440x1080	Support
.ogm	DivX5	640x336	Support
	XVID	640x480	Support
.tp	MPEG-2	1920x1088	Support
.ts	HEVC(H265)	1920x1080	Support

Amlogic Openlinux Release Notes

	MPEG-1	1920x1080	Support
	AVC	1920x1080	Support
	MPEG-2	1920x1080	Support
.vob	MPEG-2	720x576	Support
.h265	HEVC(H265)	1920x1080	Support

2.3.Video Format Test Report For Kplayer

Extension	Codec Detail	Tested Resolution	S805
.3g2	H263	704x576	Support
.3gp	MPEG-4 Visual	640x480	Support
	H263	704x576	Support
	MPEG-4	320x240	Support
.asf	WMV3	320x240	Support
.avi	AVC	1920x1080	Support
	DivX5	1280x720	Support
	M-JPEG	1024x576	Support
	MS MPEG-4 V1	352x218	Support
	RealMagic	720x480	Support
	MPEG-4	720x576	Support
	h264	1920x1080	Support
	FF mpeg	640x480	Support
	MPEG4	640x480	Support
	XVID	640x480	Support
	S-Mpeg 4 v3	720x400	Support
	DivX3	720x576	Support
	DivX4	1920x1080	Support
.dat	MPEG-1	352x288	Support
.divx	DivX5	1280x720	Support
.f4v	AVC(H264)	1280x720	Support
.flv	Sorenson Spark	1920x1080	Support
.mp4	AVC(H264)	1920x1080	Support
	HEVC(H265)	1920x1080	Support
	H263	176x144	Support
	MPEG-4 Visual	640x480	Support
.m2ts	AVC	1920x1080	Support
	VC-1	1920x1080	Support
.m2v	MPEG-2	480x576	Support
.m4v	AVC	1280x720	Support
.mkv	WMV3	1280x720	Support
	MPEG-4 Visual	1920x1080	Support
	AVC	1920x1080	Support
.mov	MPEG-4 Visual	1280x720	Support
	mjpa	640x480	Support
	H263	320x240	Support
	M-JPEG	640x480	Support
	AVC	1920x1080	Support
	MPEG-4 Visual	640x480	Support
.mpeg	MPEG-2	1920x1080	Support
	VC-1	1920x1080	Support
	MPEG-1	720x576	Support

Amlogic Openlinux Release Notes

	WMV1	320x240	Support
.mts	AVC	1440x1080	Support
.ogm	DivX5	640x336	Support
	XVID	640x480	Support
.PMP	H264	480x272	Support
.rmvb	RealVideo4	1920x1080	Support
.tp	MPEG-2	1920x1088	Support
.ts	HEVC(H265)	1920x1080	Support
	MPEG-1	1920x1080	Support
	AVC	1920x1080	Support
	AVS	720x576	Support
	AVS+	720x576	Support
	MPEG-2	1920x1080	Support
.vob	MPEG-2	720x576	Support
.mvc	mvc	1920x1080	Support
.h265	HEVC(H265)	1920x1080	Support

3. Recent Changes

- 1) Porting Wayland 1.13 and Weston 2.99.
- 2) Porting Chromium 53.0.

4. Known Issue

- 1) Chromium stability need improve.
- 2) DVFS stability need improve.
- 3) Compatibility of gstreamer need improve.
- 4) Picture has not been tested.