

Juniper Networks[®] vMX Virtual Router Release Notes Release Notes

Release 19.1R2
14 July, 2020

These release notes accompany the Junos OS Release 19.1R2 of the Juniper Networks[®] virtual MX Series router (vMX). They describe new and changed features, limitations, and known problems in the software.

Contents	Introduction 2
	New and Changed Features 2
	Known Issues 2
	Known Issues in 19.1R2 2
	Known Issues in 19.1R1S2 3
	Known Issues in 19.1R1 3
	Resolved Issues 3
	Resolved Issues in 19.1R2 3
	Resolved Issues in 19.1R1 4
	Upgrade Instructions 4
	System Requirements 5
	Minimum Hardware and Software Requirements for KVM 5
	Minimum Hardware and Software Requirements for VMware 8
	Requesting Technical Support 11
Self-Help Online Tools and Resources 11	
Creating a Service Request with JTAC 12	
Revision History 12	

Introduction

The vMX Virtual Router (vMX) is an MX Series router optimized to run on x86 servers. vMX is supported on Red Hat Enterprise Linux, CentOS, and Ubuntu.

NOTE: See [“System Requirements” on page 5](#) for details on each supported environment.

vMX enables you to leverage Junos OS Release 19.1R2 to provide a quick and flexible deployment. vMX provides the following benefits:

- Optimizes carrier-grade routing for the x86 environment
- Simplifies operations as the management and configuration are the same as for MX Series routers
- Introduces new services without requiring a reconfiguration of the current infrastructure

This release of vMX supports most of the features available on Juniper Networks MX Series routers.

New and Changed Features

There are no new features and enhancements introduced in this release.

Known Issues

Known Issues in 19.1R2

This section lists the known issues in the release 19.1R2.

- On VMX instances, because the host CPU core 0 is not dedicated for virtual instances, it might be used by the other applications. However, VMX's vCPU resource allocation starts from core 0. When the usage of core 0 is high, the VMX instance might get less resource, which might lead to packet drop. [PR1449289](#)

Known Issues in 19.1R1S2

This section lists the known issues in the release 19.1R1S2.

- On vMX instances, IPv6 is using different unicast MAC address when you configure VRRPv3 for IPv6. [PR1449014](#)

Known Issues in 19.1R1

This section lists the known issues in the release 19.1R1.

- On vMX-based platforms including MX150, when you run the **clear pim join instance *instance-name* all** command, it might result in stopping of riot process on the system. [PR1409527](#).

Resolved Issues

IN THIS SECTION

- [Resolved Issues in 19.1R2](#) | 3
- [Resolved Issues in 19.1R1](#) | 4

Resolved Issues in 19.1R2

This section lists the resolved issues in the release 19.1R2.

- On VMX instances deployed in subscriber scenario, RIOT core might be observed on VMX instances. The respective FPC might reboot after generating RIOT core. All the traffic or service related to that FPC are impacted. [PR1393660](#)
- On VMX platform, when the value of the "remote-gateway" is changed (from example, it is changed from a.a.a.a to b.b.b.b) on the device acting as the initiator of IPsec VPN tunnel, the device might still use value a.a.a.a to negotiate the IKE-phase-1 with its peer, which will lead to the failure of the negotiation, thus the establishment of IPsec-VPN tunnel will fail. [PR1421977](#)
- On vMX instances, continuous disk error logs requesting for switchover due to disk failure on ada1 are seen on vCP console. [PR1424771](#)

Resolved Issues in 19.1R1

This section lists the issues fixed in the release 19.1R1.

- On vMX platform, when a physical function (PF) resets, the underlying virtual function (VF) must also be reset to continue data path functionality. There are no options available for registering to receive PF reset notification. Consequently whenever something happens on the PF causing a reset, the data path functionality halts till SR-IOV is restarted (that is FPC restart in order to recover). When PF reset takes place, it sends a reset message to all associated VFs and attempts to stop and restart again. In case of i40e drivers, VFs are not able to reset properly. [PR1382787](#)
- On vMX system, when you configure large number of interfaces, the vFPC CPU utilization might go very high periodically because of interface statistics collection running repeatedly. [PR1385853](#)
- On vMX platform, kernel core files are generated when the kernel state (ifstates) exceptions occur. [PR1398320](#)
- While using the IXGBE driver with SR-IOV, during the interface flap at the peer device, the vMX occasionally stops receiving traffic. You must restart the FPC to recover the functionality on the affected interface. [PR1401672](#)

Upgrade Instructions

You cannot upgrade Junos OS for the vMX router from earlier releases using the **request system software add** command.

You must deploy a new vMX instance using the downloaded software package.

System Requirements

IN THIS SECTION

- [Minimum Hardware and Software Requirements for KVM | 5](#)
- [Minimum Hardware and Software Requirements for VMware | 8](#)

These topics provide system requirements for each supported environment.

Minimum Hardware and Software Requirements for KVM

[Table 1 on page 5](#) lists the hardware requirements for KVM.

Table 1: Minimum Hardware Requirements for KVM

Description	Value
Required CPUs and NICs	For lab simulation and low performance (less than 100 Mbps) use cases, any x86 processor (Intel or AMD) with VT-d capability. For all other use cases, Intel Ivy Bridge processors or later are required. Example of Ivy Bridge processor: Intel Xeon E5-2667 v2 @ 3.30 GHz 25 MB Cache To use single root I/O virtualization (SR-IOV) NIC type on vMX, the following NICs are required and no other NICs are supported with SR-IOV. ● Intel X520 or X540 using 10G ports and ixgbe driver ● Intel X710 or XL710 using 10G ports and i40e driver Only 10G ports are supported. OEM versions of those NICs are also supported when they use the same drivers.

Table 1: Minimum Hardware Requirements for KVM (continued)

Description	Value
Number of cores NOTE: Performance mode is the default mode and the minimum value is based on one port.	For lite mode with lab simulation use case applications: Minimum of 3 • 1 for VCP • 2 for VFP NOTE: If you want to use lite mode when you are running more than 3 vCPUs for the VFP, you must explicitly configure lite mode. For performance mode with low-bandwidth (virtio) or high-bandwidth (SR-IOV) applications: Minimum of 9 • 1 for VCP • 8 for VFP The exact number of vCPUs needed differs depending on the Junos OS features that are configured and other factors, such as average packet size. You can contact Juniper Networks Technical Assistance Center (JTAC) for validation of your configuration and make sure to test the full configuration under load before use in production. For typical configurations, we recommend the following formula to calculate the minimum vCPUs needed by the VFP. NOTE: • Without CoS—$(4 * \text{number-of-ports}) + 4$ • With CoS—$(5 * \text{number-of-ports}) + 4$ NOTE: All VFP vCPUs must be in the same physical non-uniform memory access (NUMA) node for optimal performance. In addition to vCPUs for the VFP, we recommend 2 x vCPUs for VCP and 2 x vCPUs for Host OS on any server running the VMX.
Memory NOTE: Performance mode is the default mode.	For lite mode: Minimum of 3 GB • 1 GB for VCP • 2 GB for VFP For performance mode: • Minimum of 5 GB 1 GB for VCP 4 GB for VFP • Recommended for 16 GB 4 GB for VCP 12 GB for VFP Additional 2 GB recommended for host OS

Table 1: Minimum Hardware Requirements for KVM (continued)

Description	Value
Storage	Local or NAS Each vMX instance requires 30 GB of disk storage.
Other requirements	Intel VT-d capability Hyperthreading (recommended) AES-NI

[Table 2 on page 7](#) lists the software requirements for Ubuntu.

Table 2: Software Requirements for Ubuntu

Description	Value
Operating system	Ubuntu 14.04 Ubuntu 16.04.5 LTS (recommended host OS) Linux 4.4.0-generic
Virtualization	QEMU-KVM 2.0.0+dfsg-2ubuntu1.11
Required packages NOTE: Other additional packages might be required to satisfy all dependencies.	bridge-utils qemu-kvm libvirt-bin python python-netifaces vnc4server libyaml-dev python-yaml numactl libparted0-dev libpciaccess-dev libnuma-dev libyajl-dev libxml2-dev libgl2.0-dev libnl-dev python-pip python-dev libxml2-dev libxslt-dev NOTE: libvirt 1.3.1

[Table 3 on page 7](#) lists the software requirements for Red Hat Enterprise Linux.

Table 3: Software Requirements for Red Hat Enterprise Linux

Description	Value
Operating system	- Red Hat OpenStack Platform 10 - Red Hat Enterprise Linux 7.5
Virtualization	QEMU-KVM 1.5.3

Table 3: Software Requirements for Red Hat Enterprise Linux (*continued*)

Description	Value
Required packages	python27-python-pip python27-python-devel numactl-libs libpciaccess-devel parted-devel yajl-devel libxml2-devel glib2-devel libnl-devel libxslt-devel libyaml-devel numactl-devel redhat-lsb kmod-ixgbe libvirt-daemon-kvm numactl telnet net-tools
NOTE: SR-IOV requires these packages: kernel-devel gcc	NOTE: libvirt 1.2.17 or later

Table 4 on page 8 lists the software requirements for CentOS.

Table 4: Software Requirements for CentOS

Description	Value
Operating system	CentOS 7.2 Linux 3.10.0-327.22.2
Virtualization	QEMU-KVM 1.5.3
Required packages	python27-python-pip python27-python-devel numactl-libs libpciaccess-devel parted-devel yajl-devel libxml2-devel glib2-devel libnl-devel libxslt-devel libyaml-devel numactl-devel redhat-lsb kmod-ixgbe libvirt-daemon-kvm numactl telnet net-tools NOTE: libvirt 1.2.19 To avoid any conflicts, install libvirt 1.2.19 instead of updating from libvirt 1.2.17.

Minimum Hardware and Software Requirements for VMware

Table 5 on page 9 lists the hardware requirements for VMware.

Table 5: Minimum Hardware Requirements for VMware

Description	Value
Number of cores NOTE: Performance mode is the default mode and the minimum value is based on one port.	For performance mode with low-bandwidth (virtio) or high-bandwidth (SR-IOV) applications: Minimum of 9 • 1 for VCP • 8 for VFP The exact number of vCPUs needed differs depending on the Junos OS features that are configured and other factors, such as average packet size. You can contact Juniper Networks Technical Assistance Center (JTAC) for validation of your configuration and make sure to test the full configuration under load before use in production. For typical configurations, we recommend the following formula to calculate the minimum vCPUs needed by the VFP. NOTE: To calculate the optimal number of vCPUs needed by VFP for performance mode: • Without CoS—$(4 * \text{number-of-ports}) + 4$ • With CoS—$(5 * \text{number-of-ports}) + 4$ NOTE: All VFP vCPUs must be in the same physical non-uniform memory access (NUMA) node for optimal performance. In addition to vCPUs for the VFP, we recommend 2 x vCPUs for VCP and 2 x vCPUs for Host OS on any server running the vMX. For lite mode: Minimum of 3 • 1 for VCP • 2 for VFP NOTE: If you want to use lite mode when you are running with more than 3 vCPUs for the VFP, you must explicitly configure lite mode.
Memory NOTE: Performance mode is the default mode.	For performance mode: • Minimum of 5 GB 1 GB for VCP 4 GB for VFP • Recommended for 16 GB 4 GB for VCP 12 GB for VFP For lite mode: Minimum of 3 GB • 1 GB for VCP • 2 GB for VFP

Table 5: Minimum Hardware Requirements for VMware (*continued*)

Description	Value
Storage	Local or NAS Each vMX instance requires 30 GB of disk storage.
vNICs	- SR-IOV NOTE: SR-IOV is only supported with Intel Ivy Bridge CPU (or higher) and Intel 82599 or X710 controller based NICs. Any other NIC models are not supported (for example,; Broadcom QLogic 57810). - VMXNET3 NOTE: See Virtual Network Interfaces for vMX for an overview on the types of virtual network interfaces supported by vMX.

[Table 6 on page 10](#) lists the software requirements.

Table 6: Software Requirements for VMware

Description	Value
Hypervisor	VMware ESXi 5.5 (Update 2), 6.0, or 6.5 NOTE: Due to a DPDK version change in Junos OS Release 18.1R1 or later, ESXi 6.5 is the minimum version required to run the vMX router if you are operating in high-bandwidth mode (performance mode). If you are operating the vMX router in low-bandwidth(lite) mode, you can use ESXi 6.0 or ESXi 5.5.
Management Client	vSphere 5.5 or vCenter Server

Requesting Technical Support

Technical product support is available through the Juniper Networks Technical Assistance Center (JTAC). If you are a customer with an active J-Care or Partner Support Service support contract, or are covered under warranty, and need post-sales technical support, you can access our tools and resources online or open a case with JTAC.

- JTAC policies—For a complete understanding of our JTAC procedures and policies, review the *JTAC User Guide* located at <https://www.juniper.net/us/en/local/pdf/resource-guides/7100059-en.pdf>.
- Product warranties—For product warranty information, visit <http://www.juniper.net/support/warranty/>.
- JTAC hours of operation—The JTAC centers have resources available 24 hours a day, 7 days a week, 365 days a year.

Self-Help Online Tools and Resources

For quick and easy problem resolution, Juniper Networks has designed an online self-service portal called the Customer Support Center (CSC) that provides you with the following features:

- Find CSC offerings: <https://www.juniper.net/customers/support/>
- Search for known bugs: <https://prsearch.juniper.net/>
- Find product documentation: <https://www.juniper.net/documentation/>
- Find solutions and answer questions using our Knowledge Base: <https://kb.juniper.net/>
- Download the latest versions of software and review release notes: <https://www.juniper.net/customers/csc/software/>
- Search technical bulletins for relevant hardware and software notifications: <https://kb.juniper.net/InfoCenter/>
- Join and participate in the Juniper Networks Community Forum: <https://www.juniper.net/company/communities/>
- Create a service request online: <https://myjuniper.juniper.net>

To verify service entitlement by product serial number, use our Serial Number Entitlement (SNE) Tool: <https://entitlementsearch.juniper.net/entitlementsearch/>

Creating a Service Request with JTAC

You can create a service request with JTAC on the Web or by telephone.

- Visit <https://myjuniper.juniper.net>.
- Call 1-888-314-JTAC (1-888-314-5822 toll-free in the USA, Canada, and Mexico).

For international or direct-dial options in countries without toll-free numbers, see <https://support.juniper.net/support/requesting-support/>.

Revision History

14, July 2020—Revision 2, Junos OS Release 19.1R2—vMX

29, November 2019—Revision 1, Junos OS Release 19.1R2—vMX

Copyright © 2020 Juniper Networks, Inc. All rights reserved.

Juniper Networks, the Juniper Networks logo, Juniper, and Junos are registered trademarks of Juniper Networks, Inc. and/or its affiliates in the United States and other countries. All other trademarks may be property of their respective owners.

Juniper Networks assumes no responsibility for any inaccuracies in this document. Juniper Networks reserves the right to change, modify, transfer, or otherwise revise this publication without notice.