

Computing the Areas of IAU Constellations

Dale Dickerhoof

September 3, 2026

Abstract

The areas of the 88 constellations recognized by the International Astronomical Union (IAU) are computed through the use of Stoke's theorem.

1 Formulation of the Problem

The computations here are carried out in a standard spherical coordinate system defined by a radial distance r , a polar angle θ , and an azimuthal angle ϕ .

The constellation boundaries are specified in coordinates of right ascension α and declination δ . These are essentially a kind of spherical coordinates, with an arbitrary radial distance. Instead of a polar angle, declination is measured from the equator.

Since we wish to compute the area within a boundary on the sphere, we utilize Stoke's theorem to convert the surface integral into a line integral along the constellation boundaries (1).

$$\iint_S (\nabla \times \mathbf{A}) \cdot d\mathbf{S} = \oint_{\ell} \mathbf{A} \cdot d\boldsymbol{\ell} \quad (1)$$

In order to utilize this, a vector field $\mathbf{A}$ needs to be found such that $\nabla \times \mathbf{A}$ has a constant radial component on the surface of the unit sphere. Then, the line integral in (1) along the closed constellation boundaries will yield the surface area within.

In spherical coordinates, the radial component of the curl is expressed as (2),

$$(\nabla \times \mathbf{A}) \cdot \hat{\mathbf{r}} = \frac{1}{r \sin \theta} \left(\frac{\partial}{\partial \theta} (A_\phi \sin \theta) - \frac{\partial}{\partial \phi} A_\theta \right). \quad (2)$$

2 Evaluation of Candidate Vector Fields

Two different choices for suitable vector fields were evaluated. Only the A_θ and A_ϕ components need be specified, since A_r does not appear in (2).

One choice for $\mathbf{A}$ is

$$\begin{aligned} A_\phi &= \frac{1}{\sin \theta} \\ A_\theta &= -r\phi \sin \theta. \end{aligned} \quad (3)$$

It is easily shown that the radial component of the curl is unity on the unit sphere.

The constellation boundaries for the 1875 epoch run along paths of constant θ and ϕ values. To evaluate the line integrals from (1), we also need to evaluate $d\ell$. For the choice of $\mathbf{A}$ in (3), paths with constant values of ϕ have $d\ell = r d\theta$, and can be evaluated as

$$\int_{\theta_1}^{\theta_2} \mathbf{A} \cdot d\ell = r^2 \phi (\cos \theta_2 - \cos \theta_1), \quad (4)$$

setting $r = 1$.

Similarly, paths of constant θ , have $d\ell = r \sin \theta d\phi$, and can be evaluated as

$$\int_{\phi_1}^{\phi_2} \mathbf{A} \cdot d\ell = r (\phi_2 - \phi_1). \quad (5)$$

Note that in (5), the line integral does not depend on θ . When integrating the closed constellation boundaries, the sum of the constant- θ paths goes to zero, with the exception of the constellations containing the north and south poles.

The individual line integral terms due to (4) are computing areas from the path back to the $\phi = 0$ meridian. This makes it tricky to properly account for constellations that cross over that line.

Another choice for $\mathbf{A}$ was then considered:

$$\begin{aligned} A_\phi &= -\frac{\cos \theta}{\sin \theta} \\ A_\theta &= 0. \end{aligned} \tag{6}$$

The constant- θ paths are evaluated as

$$\int_{\phi_1}^{\phi_2} A_\phi r \sin \theta d\phi = -r \cos \theta (\phi_2 - \phi_1), \tag{7}$$

And the constant- ϕ paths are conveniently always zero.

With this choice for $\mathbf{A}$ in (6), individual line integral segments of the boundaries are computing areas from the constant- θ paths down to the equator. This works without major difficulties for all but two constellations. For the two constellations that contain the poles, the area computed is the area outside of the constellation to the equator, which is easily rectified by the addition of the area of a half- sphere.

The main complication that occurs in the evaluation of (7) for all constellations is that if $|\phi_2 - \phi_1| > \pi$, it means that the shortest path goes through $\phi = 0$, since $0 \leq \phi < 2\pi$. To correctly evaluate the integral, 2π should be subtracted from the larger value of ϕ_1 and ϕ_2 .

References

- [1] M. Ebada, A. Elkelesh, S. Cammerer and S. ten Brink, "Scattered EXIT Charts for Finite Length LDPC Code Design," 2018 IEEE International Conference on Communications (ICC), Kansas City, MO, USA, 2018, pp. 1-7, doi: 10.1109/ICC.2018.8422961.
- [2] Benedetto, Sergio, and Ezio Biglieri. Principles of Digital Transmission: With Wireless Applications. Kluwer Academic/Plenum Press, 1999.
- [3] Chugg, Keith M., et al. Iterative Detection: Adaptivity, Complexity Reduction, and Applications. Kluwer Academic Publishers, 2001.