

altairsim — Quick Reference

2026-08-03 · 7794848

Getting out, and back in

Key	Does
<code>^E</code>	ATTN — stop the machine and take the keyboard back. Nothing is lost.
<code>RUN</code>	Resume, at the exact instruction it stopped on.
<code>QUIT</code>	Leave. (There is no <code>EXIT</code> .)

Editing the command line

`Tab` completes what you are typing — a command, then a board id, then its property names, then a property's values (`SET mem0 fill=` then `Tab`); a second `Tab` lists the choices. `Up` / `Down` walk the command history, saved per directory in `.altairsim_history`.

Key	Does
<code>Ctrl-A</code> / <code>Ctrl-E</code> (or <code>Home</code> / <code>End</code>)	start / end of line
<code>Alt-B</code> / <code>Alt-F</code> (or <code>Ctrl-Left</code> / <code>Ctrl-Right</code>)	back / forward one word
<code>Ctrl-W</code> / <code>Ctrl-K</code> / <code>Ctrl-U</code>	erase word behind / to end of line / whole line
<code>Backspace</code> / <code>Delete</code>	erase before / under the cursor

Command line

```
altairsim [options] [machine]
```

machine	a built-in name, or a config file (has a '/' or ends .toml). Omitted: ./altairsim.toml if there is one, else `default`.
-m, --machine <n>	ALWAYS a built-in name -- never a file.
-f, --file <path>	ALWAYS a file -- never a built-in name.
-n, --none	empty backplane: no boards, no memory, nothing.
-l, --list	list the built-in machines and exit.
-s, --script <f>	run a command script, then exit with its status.
-x, --exec <cmd>	run one monitor command (repeatable), then exit.
-i, --interactive	after --script/--exec, stay in the monitor.
--mcp	MCP server on stdio.
-v, --version	-h, --help

Monitor commands

Type the part before the bracket.

Command	Usage
D[UMP]	DUMP [<addr> <range>] [WIDTH=16]
S[TEP]	STEP [n]
N[EXT]	NEXT
R[UN]	RUN [addr]
H[ISTORY]	HISTORY [BUS CPU] [n]
M[OUNT]	MOUNT <id>[:<u>] <file> [WP] [CREATE] [extract[=<base>]] [k=v...]
B[REAK]	BREAK [<addr> [IF <expr>] MEM R W <addr> IO R W <port> TAPE STOP] [TRACE ON OFF]
E[DIT]	EDIT <addr> [ROM]
C[ONFIG]	CONFIG LOAD <f.toml> CONFIG SAVE <f.toml>
SE[T]	SET <id>[:<u>] CONSOLE DISPLAY REG BUS <k>=<v>
SH[OW]	SHOW <id> BOARDS BOARD <type> [UNITS] MACHINES MACHINE [<name>] BUS [MAP IO IRQ CONTENTION] ROMS MOUNTS PATHS CONSOLE DISPLAY SYMBOLS VERSION
DE[POSIT]	DEPOSIT <addr> <bytes...>
EX[AMINE]	EXAMINE [<addr>]
I[N]	IN <port>
O[UT]	OUT <port> <byte>
L[OAD]	LOAD <file> [AT <addr>] [FORMAT=BIN HEX] [ROM]
SA[VE]	SAVE <file> <range> [FORMAT=BIN HEX OCTAL PRN]
F[ILL]	FILL <range> <byte>
SEA[RCH]	SEARCH <range> <bytes...> "str"
COM[PARE]	COMPARE <range> <addr>
MOV[E]	MOVE <range> <dest> [ROM]
W[HO]	WHO <addr> WHO IO <port>
BO[ARDS]	BOARDS [LIST] ADD <type> <id> [k=v...] REMOVE <id>
RE[GS]	REGS SET REG <r>=<v>
REGI[ON]	REGION ADD <id> type=ram rom at=<addr> [size= mount=]
DI[SASM]	DISASM [<addr> <range>] [n] [CPU=8080]
SY[MBOLS]	SYMBOLS LOAD <file> [REPLACE] SYMBOLS CLEAR
U[NMOUNT]	UNMOUNT <id>:<u>
DISC[ONNECT]	DISCONNECT <id>:<u>

Command	Usage
CONS[OLE]	CONSOLE [<k>=<v>...]
CONN[ECT]	CONNECT <id>:<u> <endpoint>
RES[ET]	RESET [CPU]
P[OWER]	POWER
T[RACE]	TRACE ON OFF [file] [MASK=IN,OUT,IRQ,DMA,CONTENTION]
TY[PE]	TYPE "text"
SN[APSHOT]	SNAPSHOT <file>
REST[ORE]	RESTORE <file>
NO[BREAK]	NOBREAK [id]
HE[LP]	HELP [<command>]
Q[UIT]	QUIT

Boards

Type	What it is
memory	RAM/ROM board: a list of regions, PHANTOM*, and five banking schemes
8080	MIT 88-CPU: an 8080A at 2 MHz. Decodes nothing -- it drives the bus
z80	Generic Z80 CPU board. Decodes nothing -- it drives the bus. The 88-CPU's twin, with a Z80 core
2sio	MIT 88-2SIO: two 6850 ACIAs, units 'a' and 'b'. Four ports at BASE+0..3
sio	MIT 88-SIO: one COM2502 UART, unit 'tty'. Two ports at BASE+0..1. INVERTED status bits
sbc	SD Systems SBC-100/200: Z80 single-board computer. One 8-port block (78-7F): Intel 8251 console (unit 'tty', data 7C / status 7D, RxD->/DSR auto-baud for MSMONR21), Z80-CTC (78-7B) whose ch1 raises a mode-2 keyboard interrupt (vector 0x82) off the 8251 RxRDY, and a parallel port (7E/7F) whose OUT 7F bit 1 switches the onboard PROM out. Optional onboard boot PROM via [[board.socket]] (at+mount). variant=sbc100 sbc200
dcdd	MIT 88-DCDD: 8" hard-sector floppy, up to 16 drives. Three ports at BASE+0..2. INVERTED status bits
mds	MIT 88-MDS: 5.25" minidisk, 4 drives. Same three ports as the dcdd -- but 300 RPM, 64 us/byte, and a motor that stops after 6.4 s
hdisk	MIT 88-HDSK Datakeeper: Pertec hard disk, 256-byte sectors from a linear .DSK. Eight ports at BASE+0..7 (default A0). Command/handshake protocol, four page buffers
versafloppy	SD Systems VersaFloppy I/II: WD FD177x soft-sector floppy, up to 4 drives. Eight ports at BASE+0..7 (default 60). variant=vfi (FD1771, single density) vfii (FD1791, single+double). Boots SDOS with the SBC-200 + DDBIOS
tarbell	Tarbell #1011: single-density WD FD1771 floppy, up to 4 drives. Eight ports at BASE+0..7 (default F8). Carries a 32-byte boot PROM that shadows 0000 over PHANTOM* -- boots CP/M automatically at reset (bootstrap=on)
tarbelldd	Tarbell #2022: double-density WD FD1791 floppy (mixed-density media, SD track 0), up to 4 drives. The single-density card's twin with a bitmap OUT-FC latch and a port-FD DMA/ext-addr register. Same 32-byte boot PROM
16fdc	Cromemco 16FDC: WD FD1793 soft-sector floppy (single + double density), up to 4 drives. Disk registers at 30-34, a TMS 5501 console UART at 00-09 (unit 'tty'), and a 4K RDOS 2.52 boot PROM at C000 (OUT 40H banks it out, RESET restores it). Boots CDOS
64fdc	Cromemco 64FDC: the 16FDC's 1983 successor -- same FD1793 + TMS 5501, carrying an 8K RDOS 3.12 boot PROM at C000-DFFF (OUT 40H banks it out, RESET restores it). Boots CDOS
acr	MIT 88-ACR: cassette. An 88-SIO B + an FSK modem, unit 'tape'. Brings the WIND/REWIND/EXTRACT verbs and a tape counter
uio	MIT 88-UIO: serial + cassette on one board. A 6850 (unit 'serial', default 0x10) and an 88-ACR cassette section (unit 'tape', default 0x06) with motor control and a SW-1 MITS/Kansas-

Type	What it is
	City modulation switch. Defaults reproduce the standard 0x10 + 0x06 layout
c700	MTS 88-C700: Centronics line-printer controller, unit 'prn'. Two ports at BASE+0..1 (default 02). Output-only; CONNECT it to a file, a socket, or a real printer queue
lpc	MTS 88-LPC: 88-LP line-printer controller, unit 'prn'. Two ports at BASE+0..1 (default 02). Line-buffered: 6-bit codes + PRINT/LINE FEED/CLEAR. CONNECT it to a file, a socket, or a real printer queue
pio	MTS 88-PIO: 8-bit parallel port, units 'out'/'in'. Two ports at BASE+0..1 (default 04). CONNECT a printer, a keyboard, a socket
4pio	MTS 88-4PIO: up to four 6820 PIAs, sections ja/jb.. per port. 16 ports from BASE (default 20). Software-set direction; CONNECT each section
vdm1	Processor Technology VDM-1: memory-mapped 16x64 video, screen RAM at BASE (default CC00), scroll/status port (default CC). Needs a Display
dazzler	Cromemco Dazzler: color graphics from a framebuffer in main RAM. Two ports at BASE+0..1 (default 0E): control/status and format. 32x32 to 128x128, 16 colors/greys. Needs a Display
vdb8024	SD Systems VDB-8024: an 80x24 video terminal on one board -- the video console for an SBC-100/200 (the alternative to the 8251). Two I/O ports at BASE+0..1 (default 00): status/keyboard/display. Unit 'keyboard' (CONNECT). Optional keyboard-strobe interrupt strap (interrupt=vi0..vi7) for the SBC-200's CTC to vector -- what the SD video CBIOS needs; polled by default. Boots sdmonv21. Needs a Display
d7a	Cromemco D+7A: analog + parallel I/O. Eight ports from BASE (default 18): one parallel port + seven two's-complement A/D-in/D/A-out channels. Reads 1-2 JS-1 joysticks from the host
sol	Processor Technology Sol-PC I/O: serial, keyboard, parallel, CUTS tape as one board. Seven ports F8..FE. Units serial/printer/keyboard (CONNECT) and tape1/tape2 (MOUNT). Brings the WIND/REWIND/EXTRACT verbs and a tape counter
fp	Altair front panel: the address switches, SA0..SA15. The top eight double as the SENSE switches, which IN 0FFH reads -- the panel answers no OUT
turnkey	MTS 8800b Turnkey Module: phantom boot PROM (FC00-FFFF), integrated 6850 SIO (unit 'tty', default 0x10), sense switches at FF, and the Auto-Start JMP jam. Sockets via [[board.socket]]
virtc	MTS 88-VI/RTC: vectored interrupts (VI0-VI7 -> RST n) and a real-time clock. One port at FE
hostbridge	Host Bridge: guest <-> host file transfer, sandboxed. OUR OWN BOARD, not a period one. Two ports at BASE+0..1. R.COM/W.COM/HDIR.COM
pmmi	PMMI MM-103: Bell 103 modem on an S-100 card, unit 'line'. Four ports at BASE+0..3 (default C0), read/write different registers. Transmit/receive over a ByteStream; CONNECT it to in:/out: files. No dialer; modem status is a fixed stub

Type	What it is
<code>usio</code>	Universal Serial board: a UART-agnostic serial card, unit 'serial'. Two ports you strap: a status/control port (<code>status_port</code> -- read synthesizes RDR/TDRE at bit positions you pick, write is discarded) and a data port (<code>data_port</code>). Built-in profiles preset the straps: <code>profile=tuart</code> (Cromemco TU-ART) <code>imsai-sio2</code> <code>compupro-if2</code> (CompuPro Interfacer II) <code>compupro-ss1</code> (CompuPro System Support 1). Polled, no interrupts. CONNECT it to a file, socket, serial port, in:/out:

Machines

Machine	What it is
<code>acuter</code>	ACUTER at F000 -- CUTER on a plain Altair, with a terminal instead of a VDM.
<code>altmon</code>	An Altair with a monitor in ROM and a terminal on it.
<code>amon</code>	AMON 3.1 in a 4K EPROM at F000 -- Martin Eberhard's full-featured Altair monitor.
<code>basic4k</code>	The machine Altair 4K BASIC was sold to run on: an 88-SIO Teletype, a cassette in the ACR.
<code>basic8k</code>	The machine Altair 8K BASIC was sold to run on: an 88-2SIO terminal, a cassette in the ACR.
<code>cdbl</code>	The <code>default</code> machine with the Combo Disk Boot Loader in the PROM socket.
<code>cuter</code>	CUTER 1.3 driving a Processor Technology VDM-1 -- the real Sol/CUTS monitor.
<code>dazzler</code>	A Cromemco Dazzler in an Altair -- the bench for the S-100's first color graphics card.
<code>default</code>	The machine you get when you name none: 56K, and the DBL boot PROM at FF00.
<code>lineprinter-lpc</code>	The <code>default</code> machine with an 88-LPC line printer at port 02, captured to a file.
<code>lineprinter</code>	The <code>default</code> machine with an 88-C700 line printer at port 02, captured to a file.
<code>minidisk</code>	The Altair Minidisk: an 88-MDS at 08 and the MDBL boot PROM. You supply the 5.25" disk.
<code>original</code>	The Altair as it actually left Albuquerque.
<code>parallel</code>	The <code>default</code> machine with two MITS parallel boards: an 88-PIO and an 88-4PIO.
<code>ps2</code>	The machine MITS Programming System II ran on: basic8k's cards, but not basic8k's bootstrap.
<code>ps2int</code>	MITS Programming System II, WITH INTERRUPTS. <code>ps2</code> with A9 down and an 88-VI/RTC in it.
<code>rombasic</code>	MITS Extended ROM BASIC 16K -- Extended BASIC that runs directly out of ROM.
<code>sbc200</code>	SD Systems SBC-200 -- a 4 MHz Z80 single-board computer running the MSMONR21 monitor.
<code>sbc200v</code>	The SD Systems SBC-200 with a VDB-8024 VIDEO console: SDMONV21 on an 80x24 screen.
<code>sol20</code>	The Processor Technology Sol-20 -- an integrated 8080 machine, running SOLOS.
<code>tarbell</code>	Tarbell #1011 single-density floppy machine -- boots CP/M 2.2 the moment a disk is in it.
<code>tarbelldd</code>	Tarbell #2022 double-density floppy machine -- boots CP/M 2.2 the moment a disk is in it.

Machine	What it is
turnkey	The MITS 8800bt -- an Altair with a Turnkey Module where the front panel used to be.
vdm1	A Processor Technology VDM-1 in an Altair, and a demo that draws on it.
z80	A minimal Z80 machine: a z80 CPU, 64K of RAM, and a 2SIO console.

A machine file, in one look

```
[machine]
name      = "mine"
base      = "default"      # start from a machine, and say what is DIFFERENT
startup   = ["RUN FF00"]    # the operator's own keystrokes. There is no BOOT verb.

[[board]]                # type + a NEW id      -> ADD the card
type       = "2sio"        # type + an id from the base -> REPLACE it outright
id         = "sio0"        # NO type + an id      -> MODIFY the one already there
port       = 10            # remove = true       -> PULL THE CARD OUT

[board.unit.a]           # a unit's own settings
connect    = "console"

[[board.region]]         # a list the card owns (memory)
type       = "ram"
at         = 0000          # hex: it is an address
size       = "56K"         # decimal: it is a size

[[board.drive]]          # a list the card owns (disk controllers)
unit       = 0
mount      = "cpm.dsk"     # relative to THIS FILE

[console]                # the HOST's terminal -- not a board
strip7out  = true
base       = octal         # read/print the wire class in split octal (MITS style)
```

Paths: a path *inside* a machine file is relative to **that file**. A path you *type* is relative to **your shell**.

Endpoints — `CONNECT <id>:<unit> <endpoint>`

Endpoint	Is
<code>console</code>	the host terminal. Exactly one unit may hold it.
<code>null</code>	nowhere. Writes vanish, reads never come.
<code>loopback</code>	itself — what you write comes back.
<code>socket:PORT</code>	listens — this is telnet-in.
<code>socket:HOST:PORT</code>	calls out .
<code>serial:DEVICE</code>	a real serial port on this host.