MISSION 2

Configuration switch et vérification de la version actuelle avec la commande show version

```
Switch#show version
Cisco IOS Software, C3750 Software (C3750-IPBASE-M), Version 12.2(25)SEB4, RELEASE SOFTWARE (fc1)
Copyright (c) 1986-2005 by Cisco Systems, Inc.
Compiled Tue 30-Aug-05 15:47 by yenanh

ROM: Bootstrap program is C3750 boot loader
BOOTLDR: C3750 Boot Loader (C3750-HBOOT-M) Version 12.2(25r)SEC, RELEASE SOFTWARE (fc4)

 Switch uptime is 14 minutes
System returned to ROM by power-on
System image file is "flash:c3750-ipbase-mz.122-25.SEB4/c3750-ipbase-mz.122-25.SEB4.bin"

cisco WS-C3750-24TS (PowerPC405) processor (revision L0) with 118784K/12280K bytes of memory.
Processor board ID CAT1035NH4J
Last reset from power-on
1 Virtual Ethernet interface
24 FastEthernet interfaces
2 Gigabit Ethernet interfaces
The password-recovery mechanism is enabled.
```

Configuration de l'heure avec System Clock

```
Switch#clock set 9:09:00 05 feb 2025
Switch#
00:17:54: %SYS-6-CLOCKUPDATE: System clock has been updated from 00:17:54 UTC Mon Mar 1 1993 to 09:09:00 UTC Wed Feb 5 2025, configured from console by console.
```

Affichage de la configuration en marche avec show running-config

```
Switch#show running-config
Building configuration...

Current configuration : 1304 bytes
!
! No configuration change since last restart
!
version 12.2
no service pad
service timestamps debug uptime
service timestamps log uptime
no service password-encryption
!
hostname Switch
!
!
no aaa new-model
switch 1 provision ws-c3750-24ts
ip subnet-zero
!
!
!
!
no file verify auto
spanning-tree mode pvst
```

Configuration du mot de passe en conf t et du nom avec hostname

```
Switch(config)#hostname B513-Cisco2960-09
B513-Cisco2960-09(config)#exit
B513-Cisco2960-09#
00:23:10: %SYS-5-CONFIG_I: Configured from console by console
B513-Cisco2960-09#conf t
Enter configuration commands, one per line.  End with CNTL/Z.
B513-Cisco2960-09(config)#line console 0
B513-Cisco2960-09(config-line)#password root
B513-Cisco2960-09(config-line)#login
B513-Cisco2960-09(config-line)#exit
B513-Cisco2960-09(config)#exit
B513-Cisco2960-09#
00:24:18: %SYS-5-CONFIG_I: Configured from console by consoleexit
```

Re vérification pour observer avec show running-config les différents mots de passe

```
B513-Cisco2960-09#show running-config
Building configuration...

Current configuration : 1465 bytes
!
! Last configuration change at 09:20:21 UTC Wed Feb 5 2025
!
version 12.2
no service pad
service timestamps debug uptime
service timestamps log uptime
service password-encryption
!
hostname B513-Cisco2960-09
!
enable secret 5 $1$U8Re$3A7.pYH9Cn8WIXzHScg5M1
enable password 7 071D2E435A
!
no aaa new-model
switch 1 provision ws-c3750-24ts
ip subnet-zero
```

La commande show IP interface brief pour pouvoir observer le statut et les adresses IP pour les vlan et les ports FastEthernet

```
B513-Cisco2960-09#show ip interface brief
Interface              IP-Address      OK? Method Status                Protocol
Vlan1                  10.0.9.254      YES manual up                    down
FastEthernet1/0/1      unassigned      YES unset  down                  down
FastEthernet1/0/2      unassigned      YES unset  down                  down
FastEthernet1/0/3      unassigned      YES unset  down                  down
FastEthernet1/0/4      unassigned      YES unset  down                  down
FastEthernet1/0/5      unassigned      YES unset  down                  down
FastEthernet1/0/6      unassigned      YES unset  down                  down
FastEthernet1/0/7      unassigned      YES unset  down                  down
FastEthernet1/0/8      unassigned      YES unset  down                  down
FastEthernet1/0/9      unassigned      YES unset  down                  down
FastEthernet1/0/10     unassigned      YES unset  down                  down
FastEthernet1/0/11     unassigned      YES unset  down                  down
FastEthernet1/0/12     unassigned      YES unset  down                  down
FastEthernet1/0/13     unassigned      YES unset  down                  down
FastEthernet1/0/14     unassigned      YES unset  down                  down
FastEthernet1/0/15     unassigned      YES unset  down                  down
FastEthernet1/0/16     unassigned      YES unset  down                  down
FastEthernet1/0/17     unassigned      YES unset  down                  down
FastEthernet1/0/18     unassigned      YES unset  down                  down
FastEthernet1/0/19     unassigned      YES unset  down                  down
FastEthernet1/0/20     unassigned      YES unset  down                  down
FastEthernet1/0/21     unassigned      YES unset  down                  down
```

La commande show vlan brief sert à observer les vlan ainsi que leur nom, leur statut et leur port

```
B513-Cisco2960-09#show vlan brief

VLAN Name                             Status    Ports
---- -------------------------------- --------- -------------------
1    default                          active    Fa0/8, Gi0/1
134  VLAN0134                         active    Fa0/7
301  M2L                              active    Fa0/1
314  VoIP                             active    Fa0/3
317  DMZ                              active    Fa0/2
318  WIFI                             active    Fa0/4
319  Sport-Assur                      active    Fa0/5
352  VLAN0352                         active    Fa0/6
1002 fddi-default                     act/unsup
1003 token-ring-default               act/unsup
1004 fddinet-default                  act/unsup
1005 trnet-default                    act/unsup
B513-Cisco2960-09#show ip brief
                        ^
```

Ouverture de PuTTY en SSH avec l'adresse IP associé à un vlan pour pouvoir accéder à PuTTY avec cette adresse à distance (10.187.35.29)

```
10.187.35.29 - PuTTY
login as: btssio
Keyboard-interactive authentication prompts from server:
| Password:
End of keyboard-interactive prompts from server
Acces autorise pour les etudiants et enseignants du BTS SIO seulement !
B513-Cisco2960-09>enable
Password:
Password:
B513-Cisco2960-09#
```

Avec la commande show interfaces vlan nous pouvons voir le port Gigabit et les ports associés :

```
B513-Cisco2960-09#show interfaces trunk

Port        Mode             Encapsulation  Status        Native vlan
Gi0/1       on               802.1q         trunking      1

Port        Vlans allowed on trunk
Gi0/1       1-4094

Port        Vlans allowed and active in management domain
Gi0/1       1,134,301,314,317-319,352

Port        Vlans in spanning tree forwarding state and not pruned
Gi0/1       134,301,314,317-319
B513-Cisco2960-09#
```

```
interface GigabitEthernet0/1
 switchport trunk allowed vlan 134,301,314,317-319,352
 switchport mode trunk
```