SELECTABLE FLOODLIGHT

SPEC SHEET

LC-FL-WS-3CCT-SF / LC-FL-WS-3CCT-Y

DRAFT · NOT FOR RELEASE

PRODUCT DESCRIPTION

A die-cast floodlight with field-selectable wattage and colour temperature: one fixture covers 40, 60 and 80 W and 3000, 4000 and 5000 K, set on site.

Ships with a slipfitter (-SF) or a yoke (-Y) bracket; the head aims from 0 to 90 degrees.

PRODUCT PHOTO

LC photo to be added

OVERVIEW

- Die-cast ADC12 aluminium housing with integrated heat-dissipation fins
- IP65, wet location; drainage groove keeps water off the housing
- Field-selectable wattage: 40 / 60 / 80 W
- Field-selectable CCT: 3000 / 4000 / 5000 K
- 0-10 V dimming
- Interchangeable yoke and slipfitter brackets

WATTAGE	40 / 60 / 80 W
CCT	3000 / 4000 / 5000 K
VOLTAGE	120-277 V

SPECIFICATIONS

Wattage	40 / 60 / 80 W, field selectable
Colour temperature	3000 / 4000 / 5000 K, field selectable
Efficacy	120 lm/W
CRI	Ra > 70
Input voltage	120-277 V AC
Dimming	0-10 V
Ingress / location	IP65, wet location
Operating temperature	-40 to 104 °F (-40 to 40 °C)
Storage temperature	-40 to 158 °F (-40 to 70 °C)
Rated life	30,000 hours
Housing	Die-cast ADC12 aluminium
Finish	Gray-brown or black
Weight	2.25 kg (5.0 lb)
Dimensions	9.61 × 10.07 × 3.23 in
Aiming	0-90°, locked with a hex key
Slipfitter	For a pole up to Ø60 mm (2.36 in)

Specifications subject to change without notice.

SELECTABLE FLOODLIGHT

SPEC SHEET

LC-FL-WS-3CCT-SF / LC-FL-WS-3CCT-Y

DRAFT · NOT FOR RELEASE

ORDERING INFORMATION

SERIES	WATTAGE	CCT	VOLTAGE	MOUNTING
LC-FL LED Flood	**WS** 40 / 60 / 80 W selectable	**3CCT** 30K / 40K / 50K selectable	120-277 V	**SF** Slipfitter **Y** Yoke

EXAMPLE **LC-FL-WS-3CCT-Y**

LC-FL-WS-3CCT-SF	40/60/80 W, 30/40/50 K, 120-277 V, slipfitter bracket
LC-FL-WS-3CCT-Y	40/60/80 W, 30/40/50 K, 120-277 V, yoke bracket

ELECTRICAL CONNECTIONS

Black	Line (L)
White	Neutral (N)
Green	Ground
Purple	Dimming + (0-10 V)
Pink	Dimming - (0-10 V)

FIELD SET-UP: WATTAGE AND CCT

1. Turn the power off. Lay the fixture face down.
2. Unscrew the selector cover on the back with a cross (Phillips) screwdriver and set it aside.
3. Set the wattage and CCT switches to the setting the design calls for.
4. Screw the cover back on before the fixture is powered.

NOTES

- Electrical work by qualified persons only. Ground the fixture.
- Rated 120-277 V: a 480 V circuit needs a step-down transformer ahead of the fixture.
- Do not wipe with water or caustic solutions, and avoid high-pressure washing.

DRAFT

Draft for LED Connection review. Not for customers until approved: certifications (UL/ETL, DLC), delivered lumens, photometry and warranty are added once the documents are on file.

Specifications subject to change without notice.