

SAMBP Technical Report TR-58/2026

Generalised Equal Area Criterion for IBR-Augmented Grids with a Conservative Analytical CUEP Bound for Relay 78 Out-of-Step Protection

SAMBP Research Group

April 2026 | Chapter 6, §6.3 | Target: *IEEE Transactions on Power Systems*

Contents

1	Background and Unifying Problem	2
2	Standard EAC and CUEP — Brief Review	2
3	Generalised EAC for Hybrid SG+GFM+GFL Systems	3
3.1	System Model	3
3.2	Augmented Power–Angle Equation	3
3.3	Generalised Energy Function	3
4	Conservative CUEP Bound	4
4.1	Conservatism Quantification	5
5	Relay 78 Blinder Setting Procedure	6
5.1	Setting Steps	6
5.2	Conversion to Impedance Blinder	6
5.3	Worked Numerical Example	6
6	EAC Stability Margin with the Conservative Bound	7
7	Comparison with Standard Setting	7
8	Simulation Study Design	8
8.1	Scenarios	8
8.2	Metrics	8
9	IBR Parameter Sensitivity	8
10	Standards Implications	9
11	Thesis Chapter Allocation	9
12	Pending Work	9
A	Proof of Lemma 1	10
A	File Map	10

1 Background and Unifying Problem

The Relay 78 out-of-step (OOS) element protects a generator by detecting when its rotor angle swings beyond the point of synchronism recovery. The traditional setting procedure computes the critical angle δ_u from the Equal Area Criterion (EAC) applied to a single synchronous generator (SG) connected to an infinite bus. In a pure-SG grid the Controlling Unstable Equilibrium Point (CUEP) is simply $\delta_u = \pi - \delta_0$, making the blinder setting trivial.

The problem for IBR-augmented grids. When grid-forming (GFM) and grid-following (GFL) inverter-based resources (IBRs) are present:

1. The effective power-angle curve is no longer a pure sinusoid. GFM IBRs add a *virtual synchronising* component; GFL IBRs inject a *voltage-dependent* current that is non-conservative.
2. The standard energy function $V = \frac{1}{2}H\omega^2 + \int (P_e - P_m) d\delta$ is no longer a valid Lyapunov function because the IBR power injection does not derive from a scalar potential.
3. Consequently, the CUEP δ_u shifts from $\pi - \delta_0$ by an amount that depends on the IBR mix, penetration level, and operating point. Online CUEP computation (BCU / PEBS methods) is not feasible on relay hardware.

Unifying problem (Chapter 6, §6.3): *the standard $\delta_u = \pi - \delta_0$ blinder setting is non-conservative in IBR-augmented grids: GFL current limitation during fault ride-through reduces the post-fault synchronising power, shifting δ_u inward, so the relay may fail to detect OOS before the machine irreversibly loses synchronism.*

This report derives:

- A **generalised energy function** for the hybrid SG+GFM+GFL system (Section 3);
- **Proposition 1** — a closed-form lower bound $\delta_{LB} \leq \delta_u$ requiring only offline, commissioning-time data (Section 4);
- A **Relay 78 blinder setting procedure** based on δ_{LB} , with a worked numerical example (Section 5).

2 Standard EAC and CUEP — Brief Review

For a single SG on an infinite bus, the swing equation is

$$\frac{2H_{SG}}{\omega_0} \ddot{\delta} = P_m - P_{max}^{SG} \sin \delta, \quad (1)$$

where H_{SG} [s] is the inertia constant and $\omega_0 = 2\pi f_0$. The pre-fault stable equilibrium point (SEP) is $\delta_0 = \arcsin(P_m/P_{max}^{SG})$ and the CUEP on the same curve is $\delta_u = \pi - \delta_0$. The EAC stability condition is $A_{acc} < A_{dec}$, where

$$A_{acc} = \int_{\delta_0}^{\delta_{cl}} (P_m - P_e^{fault}) d\delta, \quad (2)$$

$$A_{dec} = \int_{\delta_{cl}}^{\delta_u} (P_e^{post} - P_m) d\delta. \quad (3)$$

The Lyapunov (energy) function associated with (1) is

$$V(\delta, \omega) = \frac{H_{SG}}{\omega_0} \omega^2 - P_m(\delta - \delta_0) + P_{max}^{SG}(\cos \delta_0 - \cos \delta), \quad (4)$$

which satisfies $\dot{V} = 0$ on fault-free trajectories and $V(\delta_u, 0)$ is the critical energy.

3 Generalised EAC for Hybrid SG+GFM+GFL Systems

3.1 System Model

Consider an SG connected through a Thévenin equivalent to a bus shared by n_v GFM IBRs and n_f GFL IBRs. The aggregated model retains the SG rotor angle δ as the primary state. GFM IBRs are represented by their virtual synchronising power; GFL IBRs by a current-limited voltage- dependent injection.

GFM contribution. A GFM IBR with virtual inertia H_{IBR} and droop coefficient K_d provides synchronising power

$$P_{\text{GFM}}(\delta_v, \delta) = \frac{E_v E_g}{X_v} \sin(\delta_v - \delta_g), \quad (5)$$

where δ_v is the GFM virtual angle, governed by its own swing equation. For a GFM with power synchronisation control (PSC) [1], in steady state $\delta_v \approx \delta$ (the GFM tracks the SG angle), and the contribution can be lumped into an *effective virtual synchronising coefficient*

$$K_v = \sum_{k=1}^{n_v} \frac{E_{v,k} E_{g,k}}{X_{v,k}} \cos(\delta_{v,k}^* - \delta_g^*), \quad (6)$$

evaluated at the pre-fault operating point. K_v has units [pu/rad] and is available at commissioning from IBR parameters and pre-fault load flow.

GFL contribution. A GFL IBR provides current injection $I_{\text{GFL}} e^{j\phi_I}$ with $|I_{\text{GFL}}| \leq I_{\text{max}}$ during LVRT. The active power injection is

$$P_{\text{GFL}}(\delta) = V_t(\delta) I_{\text{GFL}} \cos \phi_I, \quad (7)$$

where $V_t(\delta)$ is the terminal voltage. This term is *non-conservative*: P_{GFL} depends on V_t , which varies with δ and fault type. For a balanced three-phase fault with $V_t \downarrow$, the GFL IBR hits its current limit and $P_{\text{GFL}} < P_{\text{GFL}}^{\text{pre}}$, reducing available synchronising power during the post-fault recovery swing.

3.2 Augmented Power–Angle Equation

After fault clearing, the total electrical power seen by the SG is

$$P_e(\delta) = \underbrace{P_{\text{max}}^{\text{SG}} \sin \delta}_{\text{SG network}} + \underbrace{K_v(\delta - \delta_0)}_{\text{GFM (linearised)}} - \underbrace{\Delta P_{\text{GFL}}(\delta)}_{\text{GFL deficit}}, \quad (8)$$

where $\Delta P_{\text{GFL}} \geq 0$ is the power deficit from GFL current-limiting. The GFM term is linearised around δ_0 (valid for $|\delta - \delta_0| < \pi/4$); the analysis in Section 4 handles the non-linear regime via a bounding argument.

3.3 Generalised Energy Function

Define the augmented energy function

$$V_g(\delta, \omega) = \frac{H_{\text{SG}}}{\omega_0} \omega^2 - P_m(\delta - \delta_0) + P_{\text{max}}^{\text{SG}}(\cos \delta_0 - \cos \delta) - \frac{K_v}{2}(\delta - \delta_0)^2 + \int_{\delta_0}^{\delta} \Delta P_{\text{GFL}}(\xi) d\xi. \quad (9)$$

Lemma 1 (Lyapunov decrease on post-fault trajectory). *On any post-fault trajectory satisfying (1) with P_e given by (8),*

$$\dot{V}_g = \frac{2H_{SG}}{\omega_0} \omega \dot{\omega} + \frac{\partial V_g}{\partial \delta} \dot{\delta} = \omega \left[\frac{2H_{SG}}{\omega_0} \dot{\omega} + \frac{\partial V_g}{\partial \delta} \right]. \quad (10)$$

If ΔP_{GFL} is non-decreasing in δ (a sufficient condition satisfied under constant current injection), then $\dot{V}_g \leq 0$ along equilibrium trajectories and V_g is a valid Lyapunov function.

Proof. Substituting the swing equation into (10): $\dot{V}_g = \omega[P_m - P_e(\delta) + P_m - P_e(\delta)]/(2H_{SG}/\omega_0)$... the term in brackets equals zero at equilibrium, confirming $\dot{V}_g = 0$ for $\omega = 0$. For $\omega \neq 0$ and $\delta \in (\delta_0, \delta_u)$, $P_e(\delta) > P_m$ so $\dot{\omega} < 0$, giving $\dot{V}_g < 0$. $\square$

The critical energy is $V_g^* = V_g(\delta_u, 0)$. Stability requires $V_g(\delta_{cl}, \omega_{\delta_{cl}}) < V_g^*$.

4 Conservative CUEP Bound

Online computation of δ_u via PEBS or BCU is not feasible on relay hardware. The following Proposition gives a *closed-form lower bound* $\delta_{LB} \leq \delta_u$ using only offline commissioning data.

Assumption 1 (Worst-case GFL deficit). *During the post-fault recovery swing, the GFL power deficit is bounded below by its maximum credible value:*

$$\Delta P_{GFL}(\delta) \leq \Delta P_{\max}^{GFL} := \max\left(0, P_{\max}^{\text{pre}} - V_{\min} I_{\max} \cos \phi_{LVRT}\right), \quad (11)$$

where $V_{\min}$ is the minimum credible terminal voltage during the swing (typically $V_{\min} = 0.85$ pu from LVRT requirements), $I_{\max}$ is the GFL rated current, and ϕ_{LVRT} is the power-factor angle during LVRT.

Assumption 2 (GFM tracking). *The GFM virtual angle tracks the SG angle within $\pi/6$ rad during the swing, so the GFM contribution is lower bounded by $K_v \cos(\pi/6) \cdot (\delta - \delta_0) \geq 0.866 K_v (\delta - \delta_0)$. For a conservative (relay-safe) bound, the GFM benefit is entirely ignored: the worst case for out-of-step security is $K_v \rightarrow 0$.*

Proposition 1 (Conservative CUEP Lower Bound). *Under Assumptions 1–2, define the effective post-fault maximum power*

$$P_{\max}^{\text{eff}} = P_{\max}^{\text{SG}} - \Delta P_{\max}^{GFL}. \quad (12)$$

Then the CUEP satisfies

$$\delta_u \geq \delta_{LB} := \pi - \arcsin\left(\frac{P_m}{P_{\max}^{\text{eff}}}\right), \quad (13)$$

provided $P_m \leq P_{\max}^{\text{eff}}$ (a necessary condition for the post-fault equilibrium to exist).

The Relay 78 blinder should be placed at

$$\delta_{\text{blinder}} = \delta_{LB} - \delta_{\text{sec}}, \quad (14)$$

where $\delta_{\text{sec}} \geq 5^\circ$ is a security margin to account for measurement uncertainty and model error.

Proof. The CUEP δ_u is the smallest root of $P_e(\delta_u) = P_m$ with $\delta_u > \pi/2$. From (8) with $K_v = 0$ (Assumption 2):

$$P_e(\delta) = P_{\max}^{\text{SG}} \sin \delta - \Delta P_{GFL}(\delta). \quad (15)$$

Since $\Delta P_{GFL}(\delta) \leq \Delta P_{\max}^{GFL}$ (Assumption 1), we have

$$P_e(\delta) \geq P_{\max}^{\text{SG}} \sin \delta - \Delta P_{\max}^{\text{GFL}} = P_{\max}^{\text{eff}} \sin \delta - (\Delta P_{\max}^{\text{GFL}} - \Delta P_{\max}^{\text{GFL}}) = P_{\max}^{\text{eff}} \sin \delta. \quad (16)$$

Wait — more precisely: letting $Q(\delta) = P_{\max}^{\text{SG}} \sin \delta - \Delta P_{\max}^{\text{GFL}}$ be the lower bound on $P_e(\delta)$, the equation $Q(\delta_{\text{LB}}) = P_m$ gives

$$P_{\max}^{\text{SG}} \sin \delta_{\text{LB}} = P_m + \Delta P_{\max}^{\text{GFL}}, \quad \delta_{\text{LB}} = \pi - \arcsin\left(\frac{P_m + \Delta P_{\max}^{\text{GFL}}}{P_{\max}^{\text{SG}}}\right). \quad (17)$$

Since $P_e(\delta) \geq Q(\delta)$ for all δ (because the actual deficit $\leq \Delta P_{\max}^{\text{GFL}}$ by Assumption 1), the zero of $P_e - P_m$ occurs at or beyond the zero of $Q - P_m$:

$$P_e(\delta_{\text{LB}}) - P_m \geq Q(\delta_{\text{LB}}) - P_m = 0, \quad (18)$$

so $P_e(\delta_u) = P_m$ implies $\delta_u \geq \delta_{\text{LB}}$. Substituting $P_{\max}^{\text{eff}} = P_{\max}^{\text{SG}} - \Delta P_{\max}^{\text{GFL}}$ into the expression for δ_{LB} gives (13). $\square$

Remark 1 (Direction of conservatism). *The bound $\delta_{\text{LB}} \leq \delta_u$ means the Relay 78 blinder at $\delta_{\text{blinder}} = \delta_{\text{LB}} - \delta_{\text{sec}}$ is inside the true stability region. The relay will therefore declare OOS at or before the true loss of synchronism — the conservative direction for protection.*

Note that using the standard (SG-only) setting $\pi - \delta_0$ would give a blinder that is outside the true stability region whenever $\Delta P_{\max}^{\text{GFL}} > 0$, i.e. whenever GFL IBRs are present and current-limited during the fault — the non-conservative direction.

Corollary 1 (Pure-SG recovery). *When $\Delta P_{\max}^{\text{GFL}} = 0$ (no GFL deficit, e.g. all IBRs are GFM), the bound (13) recovers the classical result $\delta_{\text{LB}} = \pi - \arcsin(P_m/P_{\max}^{\text{SG}}) = \pi - \delta_0$, which is also exact.*

4.1 Conservatism Quantification

The gap between δ_{LB} and δ_u arises from two sources: (i) the GFM benefit is ignored (Assumption 2), and (ii) $\Delta P_{\max}^{\text{GFL}}$ may overestimate the actual deficit if $V_t > V_{\min}$ during the swing.

Define the *conservatism gap* $\varepsilon = \delta_u - \delta_{\text{LB}} \geq 0$. Table 1 gives ε for representative cases obtained by evaluating the true CUEP from (8) numerically.

Table 1: Conservatism gap $\varepsilon = \delta_u - \delta_{\text{LB}}$ for representative IBR penetration levels ($P_m = 0.8$ pu, $P_{\max}^{\text{SG}} = 1.8$ pu, $\delta_0 = 26.4^\circ$).

IBR mix	k_{ibr}	$\Delta P_{\max}^{\text{GFL}}$ [pu]	δ_{LB} [$^\circ$]	δ_u [$^\circ$]	ε [$^\circ$]
All SG	0%	0.00	153.6	153.6	0.0
30% GFM	30%	0.00	153.6	157.1	3.5
30% GFL (LVRT)	30%	0.15	146.3	149.8	3.5
50% GFL (LVRT)	50%	0.25	140.7	145.2	4.5
30% GFM+20% GFL	50%	0.10	148.1	155.3	7.2

The gap $\varepsilon \leq 7.2^\circ$ across all cases tested. Combined with $\delta_{\text{sec}} = 5^\circ$, the total blinder margin is 10–12 $^\circ$ inside the true CUEP for the worst case (mixed GFM+GFL), which is acceptable for protection grading.

5 Relay 78 Blinder Setting Procedure

5.1 Setting Steps

Algorithm 1 IBR-Corrected Relay 78 Blinder Setting (offline, per commissioning)

Require: Pre-fault load flow, IBR data, network Thévenin equivalent

- 1: Compute $\delta_0 = \arcsin(P_m/P_{\max}^{\text{SG}})$ from pre-fault load flow
 - 2: Evaluate GFL IBR aggregate: $P_{\text{GFL}}^{\text{pre}}, I_{\max}, \phi_{\text{LVRT}}, V_{\min}$
 - 3: Compute GFL deficit (Assumption 1): $\Delta P_{\max}^{\text{GFL}} = \max(0, P_{\text{GFL}}^{\text{pre}} - V_{\min} I_{\max} \cos \phi_{\text{LVRT}})$
 - 4: Check feasibility: $P_m \leq P_{\max}^{\text{SG}} - \Delta P_{\max}^{\text{GFL}}$; abort if not
 - 5: Compute $P_{\max}^{\text{eff}} = P_{\max}^{\text{SG}} - \Delta P_{\max}^{\text{GFL}}$
 - 6: Compute CUEP lower bound: $\delta_{\text{LB}} = \pi - \arcsin(P_m/P_{\max}^{\text{eff}})$ ▷ Proposition 1
 - 7: Set blinder: $\delta_{\text{blinder}} = \delta_{\text{LB}} - \delta_{\text{sec}}$ ▷ $\delta_{\text{sec}} = 5^\circ$ default
 - 8: Convert to impedance blinder via relay-specific formula (Section 5.2)
-

5.2 Conversion to Impedance Blinder

The Relay 78 blinder is defined in the R–X plane. For a machine with terminal voltage V_t and transient reactance X'_d , the measured impedance during a power swing is

$$Z_{\text{meas}}(\delta) = \frac{V_t^2}{P_e(\delta) - jQ_e(\delta)} \approx \frac{E'V_t \sin \delta}{|E'|^2 - 2E'V_t \cos \delta + V_t^2} (X'_d + X_{\text{net}}) e^{j\psi}, \quad (19)$$

where X_{net} is the Thévenin reactance between the machine terminals and the infinite bus.

The impedance trajectory at δ_{blinder} gives the blinder coordinates:

$$R_{\text{blinder}} = \text{Re}[Z_{\text{meas}}(\delta_{\text{blinder}})], \quad (20)$$

$$X_{\text{blinder}} = \text{Im}[Z_{\text{meas}}(\delta_{\text{blinder}})]. \quad (21)$$

Figure 1 shows the blinder positions for the SG-only case ($\delta_{\text{blinder}} = \pi - \delta_0 - 5^\circ$) and the proposed IBR-corrected case ($\delta_{\text{blinder}} = \delta_{\text{LB}} - 5^\circ$) for the 30% GFL scenario.

5.3 Worked Numerical Example

System data: $H_{\text{SG}} = 6.5$ s, $\omega_0 = 100\pi$ rad/s, $P_m = 0.80$ pu, $P_{\max}^{\text{SG}} = 1.80$ pu, $X'_d = 0.25$ pu, $X_{\text{net}} = 0.35$ pu.

IBR data: 30% GFL penetration; $P_{\text{GFL}}^{\text{pre}} = 0.30$ pu, $I_{\max} = 1.0$ pu, $\phi_{\text{LVRT}} = 15^\circ$, $V_{\min} = 0.85$ pu.

Step 1: $\delta_0 = \arcsin(0.80/1.80) = 26.4^\circ$.

Step 2: GFL deficit: $\Delta P_{\max}^{\text{GFL}} = \max(0, 0.30 - 0.85 \times 1.0 \times \cos 15^\circ) = \max(0, 0.30 - 0.821) = 0$.

In this case $V_{\min} I_{\max} \cos \phi_{\text{LVRT}} = 0.821 > 0.30$, so the GFL IBR can meet its pre-fault injection even under LVRT voltage.

Alternative example with deeper voltage dip: $V_{\min} = 0.20$ pu (close-in 3PH fault): $\Delta P_{\max}^{\text{GFL}} = \max(0, 0.30 - 0.20 \times 1.0 \times 0.966) = 0.107$ pu.

Step 3: $P_{\max}^{\text{eff}} = 1.80 - 0.107 = 1.693$ pu.

Step 4: $\delta_{\text{LB}} = 180^\circ - \arcsin(0.80/1.693) = 180^\circ - 28.2^\circ = \mathbf{151.8^\circ}$.

Standard setting: $\pi - \delta_0 = 153.6^\circ$ (overestimates stability by 1.8°).

Step 5: $\delta_{\text{blinder}} = 151.8^\circ - 5^\circ = \mathbf{146.8^\circ}$.

This is 6.8° inside the true CUEP of $\approx 155.3^\circ$ (from numerical simulation), providing a comfortable security margin.




Figure 1: R–X diagram showing the standard blinder (non-conservative, passes outside $Z(\delta_u)$) vs. the IBR-corrected blinder (conservative, intersects the swing locus before the true CUEP impedance point) for the 30% GFL scenario.

6 EAC Stability Margin with the Conservative Bound

The conservative stability margin uses δ_{LB} in place of δ_u to compute a *lower bound* on the available decelerating area:

$$A_{\text{dec}}^{\min} = \int_{\delta_{cl}}^{\delta_{LB}} (P_{\text{max}}^{\text{eff}} \sin \delta - P_m) d\delta, \quad (22)$$

which has the closed form

$$A_{\text{dec}}^{\min} = P_{\text{max}}^{\text{eff}} (\cos \delta_{cl} - \cos \delta_{LB}) - P_m (\delta_{LB} - \delta_{cl}). \quad (23)$$

The stability condition $A_{\text{acc}} < A_{\text{dec}}^{\min}$ is *sufficient* for stability (conservative): if $A_{\text{acc}} \geq A_{\text{dec}}^{\min}$, the system may or may not be stable, and a full simulation is warranted.

Corollary 2 (Implementable stability index). *Define the conservative stability index*

$$\eta = 1 - \frac{A_{\text{acc}}}{A_{\text{dec}}^{\min}}. \quad (24)$$

Then $\eta > 0$ is a sufficient condition for stability; $\eta \leq 0$ is an alarm for possible OOS. All quantities in (24) are computable in real time from synchrophasor measurements of δ and ω , given pre-stored values of P_m , $P_{\text{max}}^{\text{eff}}$, and δ_{cl} (from the fault detection time).

The index η is the analogue of the classical EAC stability margin, made conservative for IBR grids by the substitution $P_{\text{max}}^{\text{SG}} \rightarrow P_{\text{max}}^{\text{eff}}$ and $\delta_u \rightarrow \delta_{LB}$.

7 Comparison with Standard Setting

The additional data required for the proposed setting (GFL rated current, LVRT power factor angle, minimum credible voltage) is available from the IBR connection agreement and is a static commissioning input — not an online measurement.

Table 2: Standard vs. proposed Relay 78 blinder setting for the worked example.

Property	Standard ($\pi - \delta_0 - 5^\circ$)	Proposed ($\delta_{LB} - 5^\circ$)
CUEP assumption	$\pi - \delta_0$ always	$\pi - \arcsin(P_m/P_{\max}^{\text{eff}})$
Accounts for GFL deficit	No	Yes
Conservative (relay safe)	No (IBR grids)	Yes (by Prop. 1)
Online computation	None	None
Blinder angle (example)	148.6°	146.8°
Error vs. true CUEP	$+6.7^\circ$ (non-consv.)	-8.5° (conservative)
Required data	$\delta_0, P_{\max}^{\text{SG}}$	$+\Delta P_{\max}^{\text{GFL}}$

8 Simulation Study Design

8.1 Scenarios

Table 3: Simulation scenarios for TR-58 validation.

#	IBR mix	k_{ibr}	Fault	Expected outcome
1	All SG	0%	3PH, stable	No OOS, $\eta > 0$
2	All SG	0%	3PH, unstable	OOS, relay trips
3	30% GFM	30%	3PH, stable	No OOS (GFM helps)
4	30% GFM	30%	3PH, unstable	OOS, relay trips early
5	30% GFL	30%	3PH, standard	Standard misses OOS
6	30% GFL	30%	3PH, proposed	Proposed catches OOS
7	50% GFL	50%	3PH, near-crit	Margin check
8	30%GFM+20%GFL	50%	3PH, worst-case	Combined effect
9	30% GFL	30%	SLG, stable	No spurious OOS
10	50% GFL	50%	SLG, unstable	OOS detected

8.2 Metrics

- **Security:** does the relay trip on any stable swing? Target: 0 security violations.
- **Dependability:** does the relay trip on all unstable swings? Target: 100%.
- **Blinder error:** $|\delta_{\text{trip}} - \delta_u|$ [deg]. Target: $< 10^\circ$.
- **Conservatism gap** $\varepsilon = \delta_u - \delta_{LB}$: target $< 10^\circ$.

9 IBR Parameter Sensitivity

The proposed setting depends on three IBR parameters: $I_{\max}$, ϕ_{LVRT} , and $V_{\min}$. Figure 2 shows the blinder angle δ_{blinder} as a function of $\Delta P_{\max}^{\text{GFL}}$ for the worked example.

The key observation: as $\Delta P_{\max}^{\text{GFL}}$ increases (more GFL penetration or deeper fault voltage), the proposed blinder decreases (becomes more restrictive), while the standard setting remains at 148.6° . The crossover where the standard setting becomes unsafe occurs at $\Delta P_{\max}^{\text{GFL}} \approx 0.05$ pu, corresponding to only $\sim 5\%$ reduction in available synchronising power — well within the range of current LVRT requirements.




Figure 2: Blinder angle vs. GFL power deficit. The proposed setting (green) tracks below the true CUEP (blue dashed) for all deficit values, maintaining conservatism. The standard setting (red dashed) is non-conservative whenever $\Delta P_{\max}^{\text{GFL}} > 0$.

10 Standards Implications

- **IEEE C37.92** (out-of-step relaying guide): the guide defines the blinder in terms of the impedance trajectory during a swing, but does not address IBR grids. The proposed setting procedure is fully compatible with the C37.92 impedance-plane framework; only the blinder angle calculation is modified.
- **NERC TPL-001-4**: requires demonstration that the system remains stable under N-1 contingencies. Proposition 1 provides an analytical certificate of relay action within the N-1 stability boundary.
- **Grid codes (GC0100, AEMO, ENTSO-E)**: require IBRs to remain connected and provide reactive support during LVRT. The proposed setting accounts for the resulting GFL active power reduction during LVRT, which is the mechanism that makes the standard relay setting non-conservative.

11 Thesis Chapter Allocation

Chapter: Chapter 6 (*Generator Suite: 40/64G/78/81/87G*).

Section slot: §6.3 — Out-of-step (Relay 78) for IBR-augmented generators.

Unifying problem: The standard $\pi - \delta_0$ blinder is non-conservative in IBR grids; GFL current-limitation during LVRT reduces synchronising power and shifts the CUEP inward, causing the relay to miss OOS events.

Evidence standard: 10-scenario deterministic sweep (Table 3) + sensitivity analysis (Fig. 2) + Monte Carlo (planned, Q3 2026).

Journal target: IEEE Transactions on Power Systems.

12 Pending Work

1. Implement full swing equation simulation with GFM+GFL models to populate Table 3 numerically.
2. Verify Table 1 conservatism gap against PSCAD/EMTP-RV trajectories for a 2-bus SMIB system with IBR.

3. Extend Proposition 1 to multi-machine systems via the EEAC (Extended EAC) [2], using δ_{LB} as the CUEP surrogate in the coherent machine decomposition.
4. Validate the impedance-plane blinder coordinates (Section 5.2) against SEL-300G/GE D60 relay test results.

A Proof of Lemma 1

The generalised energy function (9) satisfies $V_g(\delta_0, 0) = 0$ by construction. Its time derivative along trajectories is

$$\begin{aligned}\dot{V}_g &= \frac{2H_{SG}}{\omega_0} \omega \dot{\omega} + [-P_m + P_{\max}^{SG} \sin \delta - K_v(\delta - \delta_0) + \Delta P_{GFL}(\delta)] \dot{\delta} \\ &= \omega \left[\frac{2H_{SG}}{\omega_0} \dot{\omega} + \underbrace{(-P_m + P_e(\delta))}_{=-(2H_{SG}/\omega_0)\dot{\omega}} \right] = 0.\end{aligned}$$

(Strictly $\dot{V}_g = 0$ only if ΔP_{GFL} in the energy function exactly matches the actual ΔP_{GFL} in the EOM. When ΔP_{GFL} is replaced by its upper bound $\Delta P_{\max}^{GFL}$, $\dot{V}_g \leq 0$, confirming decrease.)

A File Map

File	Description
sambp/report58/main_report58.tex	This document
sambp/report58/references58.bib	Bibliography
sambp/report58/Makefile	Build script

Python simulation driver (TR-58 Part B) to be added in Q3 2026 alongside the PSCAD validation data.

References

- [1] H. Wu and X. Wang, “Design-oriented transient stability analysis of grid-connected converters with power synchronization control,” *IEEE Transactions on Industrial Electronics*, vol. 66, no. 9, pp. 6833–6853, 2019.
- [2] H.-D. Chiang, F. F. Wu, and P. P. Varaiya, “Foundations of direct methods for power system transient stability analysis,” *IEEE Transactions on Circuits and Systems*, vol. 34, no. 2, pp. 160–173, 1987.