

Appendix B.

Corrected Cramér–Rao Lower Bound under the Dual-Channel AWGN Noise Model for the SAMBPS DTaaS HIF-TF Locator (`fault_location_id`)

Arjundas K., K. Shanthi Swarup
Power Systems Computational Lab, IIT Madras

Issued under WP1.6; v3 Execution Plan deliverable D-B; closes R1, R9

The IEEE Access v1 manuscript reports a Cramér–Rao analysis under a circular complex Gaussian noise model placed directly on the single-bin admittance $H_{\text{meas}} = I_{\text{bin}}/V_{\text{bin}}$. That model is *not* self-consistent with § V-B of the same manuscript, which specifies dual-channel AWGN on the time-domain voltage and current channels. H_{meas} is the ratio of two independent complex Gaussians whose density is the Marsaglia–Nadarajah–Pogány form, not Gaussian. This appendix derives two corrected bounds:

1. the **proper-complex-Gaussian-ratio CRLB** after Kuruoğlu (2018), which uses the high- SNR_V Gaussian approximation of the ratio density and includes the Geary–Hinkley validity test;
2. the **joint dual-channel FIM** in $(V(t), I(t))$ space after Nehorai & Hawkes (2000), projected onto (α, R_x) .

The two are cross-checked at high SNR_V and used to overlay the empirical RMS error from the WP1.5 Monte-Carlo on the 2×4 panel `outputs/phase1_crlb_overlay/`.

Appendix B.1 Ratio-density form (Marsaglia–Nadarajah–Pogány)

For independent complex Gaussian random variables $X = \mu_X + n_X$ and $Y = \mu_Y + n_Y$ with circular complex variances σ_X^2 and σ_Y^2 per real/imag component, the ratio $Z = X/Y$ has a non-Gaussian density [1, ?] that can be written in closed form via Bessel functions but is unwieldy. In the high- SNR_Y regime, defined by the Geary–Hinkley criterion

$$\frac{|\mu_Y|}{\sigma_Y} > \tau, \quad \tau \approx 4, \tag{1}$$

a first-order Taylor expansion in n_Y/μ_Y gives

$$Z \approx \frac{\mu_X}{\mu_Y} + \frac{n_X}{\mu_Y} - \frac{\mu_X}{\mu_Y^2} n_Y, \tag{2}$$

which is itself a complex Gaussian with mean μ_X/μ_Y and *signal-dependent* per-component variance

$$\sigma_Z^2 = \frac{\sigma_X^2 + |Z|^2 \sigma_Y^2}{|\mu_Y|^2}. \tag{3}$$

The $|Z|^2 \sigma_Y^2$ term is the “ratio-shot” contribution that the v1 manuscript drops by treating σ_H^2 as constant.

Appendix B.2 Proper-ratio FIM construction

Substituting $X = I_{\text{bin}}$, $Y = V_{\text{bin}}$, $Z = H_{\text{meas}}$ in (3):

$$\sigma_H^2 = \frac{\sigma_I^2 + |H|^2 \sigma_V^2}{|V_{\text{phase}}|^2}, \quad (4)$$

where $|V_{\text{phase}}|$ is the phasor magnitude of the ideal source at ω_0 and $\sigma_X^2 = 2\sigma_{x_t}^2/N_s$ is the per-real/imag variance of the single-bin DFT phasor of a length- N_s time-domain channel with white Gaussian noise of variance $\sigma_{x_t}^2$.

For complex observations $h(\theta) = H(\theta)$ contaminated by circular complex Gaussian noise of per-component variance σ_H^2 , the Fisher information matrix on $\theta = (\alpha, R_x)$ is [2]

$$F_{kl}^{\text{proper}}(\theta) = \frac{1}{\sigma_H^2} \text{Re}[(\partial_{\theta_k} H)^* \partial_{\theta_l} H]. \quad (5)$$

The CRLB on the variance of any unbiased estimator of θ_k is $(F^{\text{proper}})^{-1}_{kk}$. Substituting (4):

$$F_{kl}^{\text{proper}} = \frac{|V_{\text{phase}}|^2}{\sigma_I^2 + |H|^2 \sigma_V^2} \text{Re}[(\partial_{\theta_k} H)^* \partial_{\theta_l} H]. \quad (6)$$

The partials $\partial H/\partial \alpha$ and $\partial H/\partial R_x$ are computed by the central-finite-difference fallback in `inverse_estimation/f` and will be swapped for the closed-form Phase-2 forms (WP2.2) when those land.

Geary–Hinkley validity. σ_H^2 in (4) is the variance of a Gaussian *approximation* of the Marsaglia density. Equation (4) is a faithful approximation only when the V channel is in the Geary–Hinkley regime (1). Outside that regime the true ratio density carries heavier tails than the Gaussian, and (6) *overestimates* the FIM (i.e. underestimates the true CRLB). The library reports a per-cell boolean `geary_hinkley_valid` flag. Under the project’s $N_s = 200$ single-bin averaging the GH threshold $|V_{\text{phase}}|/\sigma_V > 4$ corresponds to time-domain $\text{SNR}_V \gtrsim -8$ dB; the entire 720-case grid (which starts at 20 dB) is comfortably in the regime.

Appendix B.3 Dual-channel FIM (Nehorai–Hawkes)

The dual-channel FIM treats the raw waveform vector $\mathbf{y} = [v(t_0), \dots, v(t_{N_s-1}), i(t_0), \dots, i(t_{N_s-1})]^T$ as the observation, with $v(t_n) = V_{\text{phase}} \cos(\omega_0 t_n) + n_v(n)$ and $i(t_n) = \text{Re}\{H(\theta) V_{\text{phase}} e^{j\omega_0 t_n}\} + n_i(n)$. Under the project’s ideal-source assumption $\partial v/\partial \theta \equiv 0$, so the V channel contributes zero to the FIM; only the I channel carries information about θ . Defining the Jacobian $[J_i]_{n,k} = \partial i_{\text{clean}}(t_n)/\partial \theta_k$,

$$F_{kl}^{\text{dual}}(\theta) = \frac{1}{\sigma_{i_t}^2} \sum_{n=0}^{N_s-1} \frac{\partial i_{\text{clean}}(t_n)}{\partial \theta_k} \frac{\partial i_{\text{clean}}(t_n)}{\partial \theta_l}. \quad (7)$$

A one-cycle window with N_s samples evaluates the inner sum analytically (cosine–cosine and sine–sine sums each contribute $N_s/2$, cross terms cancel):

$$F_{kl}^{\text{dual}} = \frac{N_s}{2} \frac{V_{\text{phase}}^2}{\sigma_{i_t}^2} \text{Re}[(\partial_{\theta_k} H)^* \partial_{\theta_l} H]. \quad (8)$$

Appendix B.4 Cross-check: proper-ratio vs dual-channel

The same Fisher kernel $\text{Re}[(\partial_k H)^* \partial_l H]$ appears in both (6) and (8); the prefactors differ. Substituting $\sigma_I^2 = 2\sigma_{i_t}^2/N_s$ and $\sigma_V^2 = 2\sigma_{v_t}^2/N_s$:

$$\frac{F^{\text{proper}}}{F^{\text{dual}}} = \frac{\sigma_I^2}{\sigma_I^2 + |H|^2 \sigma_V^2}. \quad (9)$$

Two limiting cases:

- $\sigma_V \rightarrow 0$ (V perfectly known): the two FIMs are *exactly equal*. This is the **WP1.6 brief acceptance regime** (“agree to within 5 % at $\text{SNR}_I \geq 40$ dB in the Geary–Hinkley regime”) verified by `tests/test_crlb_consistency.py::test_crlb_proper_eq_dual_when_V_noiseless`.
- $\sigma_V = \sigma_I/|H|$ (V and I shot noise balanced): $F^{\text{proper}} = F^{\text{dual}}/2$, i.e. a factor of two loss in information by accessing only the ratio instead of the raw waveforms. In RMSE terms, $\text{RMSE}^{\text{proper}} = \sqrt{2} \text{RMSE}^{\text{dual}}$. Verified by `test_crlb_factor_sqrt2_when_snrV_eq_snrI`.

Direction of the inequality. Note $F^{\text{proper}} \leq F^{\text{dual}}$ always, with equality iff $\sigma_V = 0$. The proper-ratio CRLB is therefore $\geq$ the dual-channel CRLB (it represents *less* information about θ because the H-ratio observation discards the absolute magnitudes that the raw V and I waveforms preserve). This is opposite to the v1 “Gaussian-on-H” linearisation, which artificially *tightens* the bound by ignoring the $|H|^2 \sigma_V^2$ term in (4).

Appendix B.5 Headline empirical-vs-CRLB result

The WP1.5 Monte-Carlo (100 trials per cell on the 720-case grid) provides empirical per-cell $\text{RMSE}(\hat{\alpha})$ values that the bounds (6) and (8) are plotted against in the 2×4 overlay panel `outputs/phase1_crlb_overlay/`. The four headline findings this Appendix supports:

1. The proper-ratio bound is the *correct* bound on any unbiased estimator that operates on H_{meas} . It supersedes the v1 “Gaussian-on-H” linearisation, which is invalid outside the asymptotic $|I| \gg \sigma_I$ regime.
2. The dual-channel bound is the ground truth in (V, I) waveform space; it is *tighter* (lower) than the proper-ratio bound by the factor in (9).
3. The two bounds agree to within 5 % (in fact exactly) at $\sigma_V \rightarrow 0$, certified by `test_crlb_proper_eq_dual_when`.
4. The Geary–Hinkley validity flag holds across the full 720-case grid (time-domain SNR_V down to -8 dB), so (4) is a faithful approximation throughout. Outside this regime the proper-ratio FIM *overestimates* the true Marsaglia FIM.

End of Appendix B.

References

- [1] G. Marsaglia, “Ratios of normal variables and ratios of sums of uniform variables,” *Journal of the American Statistical Association*, vol. 60, no. 309, pp. 193–204, 1965.
- [2] S. M. Kay, *Fundamentals of Statistical Signal Processing, Volume I: Estimation Theory*. Prentice Hall, 1993.