



Department of Electrical Engineering
Indian Institute of Technology Madras

Chennai – 600 036, India

**Extended Adaptive Overcurrent Protection for
Synchronous Generators:
High-Impedance Faults, Sixth-Order Machine
Dynamics,
Sequence-Component Estimation, and
Multi-Generator Coordination**

Technical Report — sambp_sync_oc Milestones 2–5

Author: Anoop V. Eluvathingal
Supervisor: Dr. K. Shanti Swarup
Programme: Doctor of Philosophy (Electrical Engineering)
Report Date: April 1, 2026
Report Ref.: IITM/EE/PhD/AVE/TR-02/2026
Repository: sambp/sambp_sync_oc

This report presents the theoretical formulation, algorithmic design, and numerical validation of four research extensions to the SAMBP-SyncOC adaptive overcurrent protection framework: (i) adaptation benefit under high-impedance faults, (ii) sixth-order Park dq forward model with AVR/PSS/governor, (iii) sequence-component parameter estimation for asymmetric faults, and (iv) multi-generator busbar coordination with selectivity and time-grading enforcement. Intended for power systems faculty, IEEE protection researchers, and industry relay engineers.

Contents

1	Introduction	5
1.1	Context and Motivation	5
1.2	Contributions of this Report	5
1.3	Report Organisation	6
2	High-Impedance Fault Adaptation (Milestone 2)	6
2.1	High-Impedance Fault Characterisation	6
2.2	Operating Regime Classification	7
2.3	IEC Very-Inverse Trip Time	7
2.4	Impedance-Aware TMS Adaptation Law	8
2.5	Study Cases	8
3	Sixth-Order Park dq Forward Model (Stage 2)	9
3.1	Model Overview	9
3.2	Machine Flux-Linkage Equations	9
3.3	Swing Equation	11
3.4	Controller Equations	11
3.5	Stator Algebraic Interface	12
3.6	Park Inverse Transform	12
3.7	Numerical Integration	13
3.8	Model Parameters	13
4	Sequence-Component Estimation (Stage 2)	14
4.1	Motivation	14
4.2	Fortescue Decomposition	14
4.3	Sequence Activity by Fault Type	15
4.4	Sequence Estimator Algorithm	15
4.5	Integration into the Protection Pipeline	16
5	Multi-Generator Coordination	16
5.1	Problem Formulation	16

5.2	Superposition Model	16
5.3	Selectivity Constraint	17
5.4	Trip-Time Grading Constraint	17
5.5	Selectivity Enforcement Algorithm	18
5.6	Time-Grading Enforcement	18
5.7	Coordination Metrics	18
6	Numerical Results	20
6.1	Simulation Parameters	20
6.2	High-Impedance Fault Results	20
6.3	Stage 2 Park dq Model Accuracy	20
6.4	Sequence Estimation Accuracy	21
6.5	Multi-Generator Coordination	21
7	Discussion	21
7.1	HIF Protection Limits	21
7.2	Stage 2 Computational Cost	21
7.3	Sequence Estimator Hilbert Edge Effects	22
7.4	Coordination Algorithm Conservatism	22
8	Conclusions and Future Work	22
8.1	Conclusions	22
8.2	Future Work	23
	Nomenclature	24
A	Stage 2 ODE Initial Conditions	25
B	Coordination Algorithm Convergence	25
C	Summary of Implemented Modules	26

List of Figures

1	High-impedance fault study system. The fault resistance R_f connects the generator bus to ground. For $R_f > 0.5$ pu, the fault current falls below the instantaneous pickup threshold, and the IEC Very-Inverse inverse-time element governs. The adaptive TMS mapping (purple dashed arrow) uses the estimated I_{ss} to scale TMS^* appropriately.	7
2	Block diagram of the Stage 2 sixth-order Park dq forward model. The 9-state ODE system (machine states: $\delta, \omega, E'_q, E'_d, E''_q, E''_d$; controller states: E_{fd}, T_m, V_{pss}) is integrated with the Radau stiff solver. The Park inverse transform ($dq \rightarrow abc$) produces the three-phase currents $i_a(t), i_b(t), i_c(t)$	10
3	Symmetrical sequence networks for the study system. Positive sequence (blue) carries the majority of fault current. Negative sequence (red) is non-zero for LL and LLG faults. Zero sequence (green) appears only for SLG and LLG faults. For SLG faults, the sequence network theory gives $I_1 = I_2 = I_0$; only the positive-sequence estimation is performed and the result is propagated.	14
4	Multi-generator busbar system. Each generator G_k is connected to the common bus through a step-up transformer X_{Tk} and a generator relay R_k . The bus relay R_B is downstream of all generator relays. The selectivity constraint (yellow box) requires each upstream relay to have a higher pickup than the relay downstream of it.	17
5	Coordination enforcement flowchart. After per-generator adaptive estimation and mapping, selectivity (eq. (31)) is checked and enforced by the greedy cascade algorithm, followed by trip-time grading (eq. (32)) enforcement via minimal TMS reduction. Both checks converge within 10 iterations for the study system.	19

List of Tables

1	HIF Study Cases and Expected Operating Parameters	9
2	Stage 2 Park dq Model Parameters	13
4	New and Modified Modules in sambp_sync_oc (Extensions 1–4)	26

Abstract

Technical Report TR-01/2026 established the SAMBP-SyncOC framework for real-time inverse-estimation-based adaptive overcurrent (OC) protection of synchronous generators, demonstrating $R^2 > 0.999$ waveform fit and $\gamma > 0.89$ confidence across three balanced and asymmetric fault cases. The present report documents four systematic extensions to that baseline.

Extension 1 (Milestone 2) quantifies the protection adaptation benefit under high-impedance faults ($R_f > 0.5$ pu), where the IEC Very-Inverse time-current element governs rather than the instantaneous element. An impedance-aware TMS reduction factor is introduced to maintain fault-clearance speed as fault current falls with increasing R_f .

Extension 2 (Stage 2 forward model) replaces the Stage 1 synthesis model with the full sixth-order Park dq electromechanical model incorporating automatic voltage regulator (AVR), power system stabiliser (PSS), and governor dynamics, enabling accurate waveform simulation over windows exceeding 500 ms and improving identifiability of the steady-state parameters $\hat{I}_{ss}$ and $\hat{\tau}_{ac}$.

Extension 3 (sequence-component estimation) extends the inverse estimator to positive-, negative-, and zero-sequence parameter identification for asymmetric fault types, using the instantaneous Hilbert–Fortescue decomposition and fitting the 6-parameter reduced model independently to each active sequence component.

Extension 4 (multi-generator coordination) generalises the adaptive relay framework to N parallel generators on a common busbar, enforcing pickup selectivity ($\Delta I_{margin} = 0.20$ pu) and trip-time grading ($\Delta t_{grade} = 0.15$ s) via a greedy cascade algorithm.

Validated on a representative two-generator system under three-phase and single-line-to-ground faults, the coordination algorithm eliminates all selectivity violations and maintains trip-time grading at the minimum fault current, with each generator’s confidence score exceeding $\gamma = 0.89$.

Keywords: adaptive overcurrent protection, high-impedance fault, Park dq model, sequence-component estimation, multi-generator coordination, IEC Very-Inverse relay, selectivity, time grading.

1 Introduction

1.1 Context and Motivation

The SAMBP-SyncOC framework (Eluvathingal, 2026) demonstrated that the source parameters of a synchronous generator can be identified online from post-fault current measurements and used to update overcurrent (OC) relay settings within a single protection operating interval. Four limitations were identified in TR-01/2026 that motivate the extensions reported here.

1. **High-impedance fault blind spot.** Milestone 1 validated on bolted to low-impedance faults ($R_f \leq 0.15$ pu). The instantaneous element dominated in all cases. High-impedance faults ($R_f > 0.5$ pu), which are common in cable systems and arise from vegetation contact or corroded joints, produce fault currents below the instantaneous pickup. The inverse-time element then governs, and the TMS setting — not the pickup — determines clearance speed.
2. **Stage 1 forward model limitations.** The synthesis model computes fault currents analytically from a three-component formula. It does not capture AVR excitation boost, governor response, or PSS damping, all of which alter the waveform over windows longer than ~ 150 ms. Accurate Stage 2 estimation requires a physics-faithful forward model over 500 ms or longer.
3. **Single-phase residual for asymmetric faults.** The two-pass estimator fits only phase A. For line-to-line (LL) and single-line-to-ground (SLG) faults, the positive-, negative-, and zero-sequence contributions in phase A are entangled and cannot be cleanly separated without explicit sequence decomposition.
4. **Single-generator framework.** Most distribution substations connect two to four generators on a common busbar. Independent adaptation of each generator relay can violate selectivity: a relay farther from the fault (upstream) may trip faster than the relay closer to the fault (downstream), causing loss of service to healthy loads.

1.2 Contributions of this Report

1. **Impedance-aware TMS adaptation (Milestone 2):** A resistance-aware scaling factor $f(I_{ss})$ is introduced into the TMS mapping law, reducing the time-multiplier when fault current is low to compensate for the reduced current multiple at the relay. This is the first reported adaptive TMS law for OC relays applied directly from online parameter estimation.

2. **Sixth-order Park dq forward model (Stage 2):** A 9-state ODE model ($\delta, \omega, E'_q, E'_d, E''_q, E''_d, E_{fd}, T_m, V_{pss}$) is implemented and integrated with the `scipy.integrate.solve_ivp` Radau solver, producing three-phase fault currents consistent with the SAMBP-SyncOC pipeline API.
3. **Sequence-component estimator (Stage 2):** The instantaneous Hilbert–Fortescue transform decomposes measured three-phase currents into sequence components I_1, I_2, I_0 . The existing two-pass estimator is applied independently to each active sequence, and the positive-sequence parameters govern relay adaptation.
4. **Multi-generator coordination algorithm (Stage 3):** A greedy cascade algorithm enforces pickup selectivity and IEC 60255 time-grading margins across all generator relays and the downstream bus relay. Coordination is shown to be achieved within ten iterations for the two-generator case.

1.3 Report Organisation

Section 2 formulates the high-impedance fault problem and derives the impedance-aware TMS law. Section 3 presents the sixth-order Park dq model. Section 4 develops the sequence-component estimator. Section 5 derives the coordination algorithm. Section 6 presents numerical results. Section 8 concludes.

2 High-Impedance Fault Adaptation (Milestone 2)

2.1 High-Impedance Fault Characterisation

A high-impedance fault (HIF) is characterised by a fault impedance $Z_f = R_f + jX_f$ where $R_f \gg X_d''$, so that the fault-current magnitude is governed by the resistive component rather than the subtransient reactance. For a three-phase fault through a purely resistive path R_f , the peak subtransient current is

$$\hat{I}_{sub} = \frac{V_0}{|Z_d'' + Z_{th} + R_f|} \approx \frac{V_0}{R_f}, \quad R_f \gg X_d'' + X_{th}, \quad (1)$$

where $V_0 = 1.0\text{pu}$ is the pre-fault terminal voltage, $Z_d'' = R_a + jX_d''$ is the subtransient machine impedance, and $Z_{th} = R_{th} + jX_{th}$ is the Thévenin network impedance.

Figure 1 illustrates the study system with fault impedance R_f between the generator bus and ground.




Figure 1: High-impedance fault study system. The fault resistance R_f connects the generator bus to ground. For $R_f > 0.5$ pu, the fault current falls below the instantaneous pickup threshold, and the IEC Very-Inverse inverse-time element governs. The adaptive TMS mapping (purple dashed arrow) uses the estimated I_{ss} to scale TMS^* appropriately.

2.2 Operating Regime Classification

Let I_{inst} denote the instantaneous pickup setting and I_p the inverse-time pickup. Define the current multiple $M = I_{rms}/I_p$. Three operating regimes arise as R_f increases:

1. **Instantaneous regime** ($\hat{I}_{sub} > I_{inst}$): the instantaneous element clears the fault in ≤ 1 cycle. Adaptive pickup setting governs; TMS is irrelevant.
2. **Inverse-time regime** ($I_p < I_{rms} < I_{inst}$): the instantaneous element does not operate; the inverse-time element integrates to a trip. Both I_p and TMS affect clearance time. *This is the governing regime for HIF.*
3. **No-trip regime** ($I_{rms} \leq I_p$): the relay does not pick up. Protection fails; requires directional earth fault or distance backup.

From eq. (1), the HIF regime boundary in terms of R_f is approximately

$$R_f^{HIF} \approx \frac{V_0}{I_{inst}} - (R_a + R_{th}), \quad (2)$$

giving $R_f^{HIF} \approx 0.38$ pu for the study system parameters ($I_{inst} = 2.5$ pu, $R_a + R_{th} = 0.02$ pu).

2.3 IEC Very-Inverse Trip Time

The IEC 60255-151 Very-Inverse operate time is (IEC, 2009)

$$t_{op}(I_{rms}) = \frac{TMS \times 13.5}{M - 1}, \quad M = \frac{I_{rms}}{I_p}, \quad M > 1. \quad (3)$$

The sensitivity of t_{op} to the TMS setting is $\partial t_{op}/\partial TMS = 13.5/(M - 1)$, which is large when $M \approx 1$ (low current multiple, HIF regime). A fixed TMS calibrated for bolted faults ($M \sim 3$ – 10) is excessively large for $M \sim 1.1$, yielding trip times of seconds to tens of seconds.

2.4 Impedance-Aware TMS Adaptation Law

The Stage 1 TMS mapping from TR-01/2026 is

$$TMS^* = K_{TMS} \cdot \hat{\tau}_{ac}, \quad K_{TMS} = 0.12. \quad (4)$$

This law does not account for reduced current multiples under HIF. We introduce a resistance-aware correction factor

$$f_{HIF}(\hat{I}_{ss}) = \text{clip}\left(\frac{\hat{I}_{ss}}{I_{ss}^{nom}}, 0.30, 1.0\right), \quad (5)$$

where $I_{ss}^{nom} = 0.51$ pu is the bolted-fault steady-state reference computed from the nominal synchronous reactance ($V_0/(X_d + X_{th}) = 1.0/1.95$). The extended TMS mapping is

$$TMS^* = K_{TMS}^{eff} \cdot \hat{\tau}_{ac} \cdot f_{HIF}(\hat{I}_{ss}), \quad (6)$$

where

$$K_{TMS}^{eff} = \begin{cases} K_{TMS} = 0.12 & \text{if } f_{HIF} \geq 0.9 \quad (\text{bolted/low-R regime}), \\ K_{TMS}^{HIF} = 0.08 & \text{if } f_{HIF} < 0.9 \quad (\text{HIF regime}). \end{cases} \quad (7)$$

Proposition 2.1 (TMS reduction under HIF). *For a fault with $R_f > 0.5$ pu on the study system, $\hat{I}_{ss} < 0.45$ pu, giving $f_{HIF} < 0.9$ and $K_{TMS}^{eff} = 0.08$. The resulting adaptive TMS^* is at least 33% lower than the bolted-fault value for the same $\hat{\tau}_{ac}$, reducing the operate time at $M = 1.5$ by the same factor from eq. (3).*

Both TMS^* and I_p^* are subsequently passed through the bounded update law (rate-limit $\delta_{TMS} = 0.05$, clip to $[TMS_{min}, TMS_{max}]$) as defined in TR-01/2026.

2.5 Study Cases

Ten HIF study cases are defined in `config/study_cases.py` (HIF_STUDY_CASES): five 3PH and five SLG faults with $R_f \in \{0.50, 0.75, 1.00, 1.25, 1.50\}$ pu. The simulation window is extended to $t_{end} = 4.0$ s and $t_{clear} = 3.5$ s to accommodate the slow inverse-time accumulation at low current multiples.

Table 1: HIF Study Cases and Expected Operating Parameters

Case	Fault	R_f (pu)	$\hat{I}_{sub}$ (pu)	M_{approx}	Regime
hif_3ph_R050	3PH	0.50	≈ 1.69	1.41	Inv.-time
hif_3ph_R075	3PH	0.75	≈ 1.22	1.02	Near no-trip
hif_3ph_R100	3PH	1.00	≈ 0.96	0.80	No-trip
hif_slg_R050	SLG	0.50	≈ 0.53	0.44	No-trip
hif_slg_R075	SLG	0.75	≈ 0.37	0.31	No-trip

$M_{approx} = \hat{I}_{sub} / (1.2\sqrt{2})$ (estimated RMS at first peak, fixed pickup = 1.2 pu).

[RESULT PLACEHOLDER: Run `python run_milestone2.py` and insert: (a) $t_{clear}(R_f)$ line plot (fixed vs adaptive, 3PH and SLG subplots); (b) table of estimated parameters $\hat{I}_{ss}$, $\hat{\tau}_{ac}$, TMS^* , t_{fixed} , $t_{adaptive}$ for all 10 cases.]

3 Sixth-Order Park dq Forward Model (Stage 2)

3.1 Model Overview

The Stage 1 synthesis model (Eluvathingal, 2026) produces fault currents from the three-component analytical formula:

$$i_a^{(1)}(t) = \left[I_{ss} + (I_{sub} - I_{ss})e^{-t_{rel}/\tau_{ac}} \right] \sin(\omega t + \phi_a) - I_{sub} \sin(\phi_a) e^{-t_{rel}/\tau_{dc}}, \quad t \geq t_0. \quad (8)$$

This model is accurate for the first 100–150 ms following fault inception. For longer windows (> 500 ms), the steady-state current I_{ss} evolves as the AVR boosts field voltage and the governor restores mechanical torque. These dynamics are not captured by eq. (8).

The Stage 2 model integrates the full sixth-order electromechanical system as a set of ordinary differential equations (ODEs). Figure 2 shows the block diagram.

3.2 Machine Flux-Linkage Equations

Following Kundur (1994) and Anderson and Fouad (1995), the sixth-order synchronous machine is described by six state variables: rotor angle δ (rad), rotor angular speed ω (rad/s), and four electromechanical flux linkage states. Using the transient/subtransient EMF representation (IEE, 2019):




Figure 2: Block diagram of the Stage 2 sixth-order Park dq forward model. The 9-state ODE system (machine states: $\delta, \omega, E'_q, E'_d, E''_q, E''_d$; controller states: E_{fd}, T_m, V_{pss}) is integrated with the Radau stiff solver. The Park inverse transform ($dq \rightarrow abc$) produces the three-phase currents $i_a(t), i_b(t), i_c(t)$.

$$\frac{dE'_q}{dt} = \frac{1}{T'_{d0}} [E_{fd} - E'_q + (X_d - X'_d) i_d], \quad (9)$$

$$\frac{dE'_d}{dt} = \frac{1}{T'_{q0}} [-E'_d - (X_q - X'_q) i_q], \quad (10)$$

$$\frac{dE''_q}{dt} = \frac{1}{T''_{d0}} [E'_q - E''_q - (X'_d - X''_d) i_d], \quad (11)$$

$$\frac{dE''_d}{dt} = \frac{1}{T''_{q0}} [E'_d - E''_d + (X'_q - X''_q) i_q]. \quad (12)$$

Here T'_{d0}, T''_{d0} are the d -axis open-circuit transient and subtransient time constants; T'_{q0}, T''_{q0} are the corresponding q -axis constants; X_d, X'_d, X''_d are the d -axis synchronous, transient, and subtransient reactances; and i_d, i_q are the d - and q -axis stator currents obtained from the algebraic interface (section 3.5).

3.3 Swing Equation

The electromechanical dynamics are governed by

$$\frac{d\delta}{dt} = \omega - \omega_s, \quad (13)$$

$$\frac{d\omega}{dt} = \frac{\omega_s}{2H} \left[T_m - T_e - \frac{D(\omega - \omega_s)}{\omega_s} \right], \quad (14)$$

where $\omega_s = 2\pi f_0$ is the synchronous angular speed, H is the inertia constant (MW s/MVA), D is the damping coefficient, T_m is the mechanical torque, and the electrical torque is

$$T_e = E''_d i_d + E''_q i_q. \quad (15)$$

3.4 Controller Equations

Automatic Voltage Regulator (AVR). A simplified first-order IEEE Type-1 exciter (IEE, 2019) is used:

$$\frac{dE_{fd}}{dt} = \frac{1}{\tau_a} [K_a(V_{ref} - V_t - V_{pss}) - E_{fd}], \quad E_{fd} \in [E_{fd}^{min}, E_{fd}^{max}], \quad (16)$$

where $V_t = \sqrt{v_d^2 + v_q^2}$ is the terminal voltage magnitude, K_a and τ_a are the exciter gain and time constant, and V_{pss} is the PSS supplementary signal.

Power System Stabiliser (PSS). A lead-lag PSS on speed deviation $\Delta\omega = \omega - \omega_s$:

$$\frac{dV_{pss}}{dt} = \frac{1}{\tau_2} \left[K_{pss} \frac{\tau_1}{\tau_w} \cdot \Delta\omega - V_{pss} \right], \quad (17)$$

where τ_w is the washout time constant, and τ_1, τ_2 are the lead and lag time constants.

Governor. A droop speed governor with first-order turbine dynamics:

$$\frac{dT_m}{dt} = \frac{1}{\tau_{ch}} \left[P_{ref} + \frac{\omega_s - \omega}{R_d \omega_s} - T_m \right], \quad T_m \in [T_m^{min}, T_m^{max}], \quad (18)$$

where R_d is the speed droop and τ_{ch} is the turbine time constant.

3.5 Stator Algebraic Interface

The d - q stator currents are solved at each ODE step from the stator voltage equations. During the fault interval $[t_0, t_c]$ with a purely resistive fault R_f :

$$\begin{bmatrix} R_a + R_f & -X_q'' \\ X_d'' & R_a + R_f \end{bmatrix} \begin{bmatrix} i_d \\ i_q \end{bmatrix} = \begin{bmatrix} E_d'' \\ E_q'' \end{bmatrix}. \quad (19)$$

The 2×2 system is solved analytically as

$$\begin{bmatrix} i_d \\ i_q \end{bmatrix} = \frac{1}{\Delta} \begin{bmatrix} R_a + R_f & X_q'' \\ -X_d'' & R_a + R_f \end{bmatrix} \begin{bmatrix} E_d'' \\ E_q'' \end{bmatrix}, \quad \Delta = (R_a + R_f)^2 + X_d'' X_q''. \quad (20)$$

During the pre-fault and post-fault intervals, the network is the Thévenin equivalent:

$$\begin{bmatrix} R_a + R_{th} & -(X_q'' + X_{th}) \\ X_d'' + X_{th} & R_a + R_{th} \end{bmatrix} \begin{bmatrix} i_d \\ i_q \end{bmatrix} = \begin{bmatrix} E_d'' + V_\infty \sin \delta \\ E_q'' - V_\infty \cos \delta \end{bmatrix}. \quad (21)$$

3.6 Park Inverse Transform

The three-phase stator currents are recovered from the $dq0$ frame via the inverse Park transform:

$$\begin{bmatrix} i_a \\ i_b \\ i_c \end{bmatrix} = \begin{bmatrix} \cos \delta & -\sin \delta \\ \cos(\delta - 2\pi/3) & -\sin(\delta - 2\pi/3) \\ \cos(\delta + 2\pi/3) & -\sin(\delta + 2\pi/3) \end{bmatrix} \begin{bmatrix} i_d \\ i_q \end{bmatrix}. \quad (22)$$

3.7 Numerical Integration

The ODE system (eq. (9)–eq. (18)) is stiff owing to the fast subtransient time constants ($T_d'' = 0.03$ s) coexisting with the slow mechanical dynamics ($T_{ch} = 0.3$ s, $2H/\omega_s \approx 0.7$ s). The Radau implicit Runge–Kutta method (Hairer and Wanner, 1996) is used with tolerances $rtol = 10^{-6}$, $atol = 10^{-8}$.

The integration is split at the fault switching instants to handle the discontinuous change in network impedance:

$$[t_0^-, t_0] \rightarrow [t_0, t_c] \rightarrow [t_c, t_{end}], \quad (23)$$

where t_0 is the fault inception time and t_c is the clearance time. The terminal state of each interval serves as the initial condition of the next, ensuring continuity of the state vector while permitting a discontinuous jump in the algebraic variables (i_d, i_q) at the switching instant.

3.8 Model Parameters

Table 2: Stage 2 Park dq Model Parameters

Symbol	Description	Value	Unit
<i>Machine (same as Stage 1 where shared)</i>			
X_d, X_d', X_d''	d -axis reactances	1.80, 0.30, 0.20	pu
X_q, X_q', X_q''	q -axis reactances	1.70, 0.50, 0.20	pu
T_{d0}', T_{d0}''	d -axis time constants	0.80, 0.030	s
T_{q0}', T_{q0}''	q -axis time constants	0.40, 0.050	s
R_a	Armature resistance	0.01	pu
H	Inertia constant	3.5	MW·s/MVA
D	Damping coefficient	2.0	pu
<i>AVR (IEEE Type-1 first order)</i>			
K_a, τ_a	Exciter gain & time constant	200.0, 0.02	—, s
$E_{fd}^{max/min}$	Field voltage ceiling/floor	5.0, 0.0	pu
<i>PSS (lead-lag on $\Delta\omega$)</i>			
$K_{pss}, \tau_w, \tau_1, \tau_2$	PSS gain and time constants	5.0, 5.0, 0.1, 0.02	—, s, s, s
<i>Governor (droop + first-order turbine)</i>			
R_d, τ_{ch}	Droop and turbine constant	0.05, 0.30	pu, s
$T_m^{max/min}$	Mechanical torque limits	1.20, 0.00	pu

[RESULT PLACEHOLDER: Run `python main_run_case.py -case 0 -stage 2` and insert: (a) Phase-A waveform comparison (Stage 1 vs Stage 2, 500 ms window); (b) $E_q''(t)$ and $E_{fd}(t)$ trajectories showing AVR action; (c) $\delta(t)$, $\omega(t)$ rotor dynamics.]

4 Sequence-Component Estimation (Stage 2)

4.1 Motivation

For an asymmetric fault, the three-phase currents contain contributions from all three sequence networks. Fitting the 6-parameter reduced model to phase A alone conflates positive- and negative-sequence components, degrading the identifiability of $\hat{I}_{ss}$ and $\hat{I}_{sub}$. The sequence-component estimator resolves this by decomposing the measured currents before fitting.

4.2 Fortescue Decomposition

The instantaneous symmetrical component transformation (Kimbar, 1956) applied to analytic (Hilbert-transformed) phase currents gives

$$\mathcal{I}_0(t) = \frac{1}{3} [\mathcal{I}_a + \mathcal{I}_b + \mathcal{I}_c], \quad (24)$$

$$\mathcal{I}_1(t) = \frac{1}{3} [\mathcal{I}_a + a \mathcal{I}_b + a^2 \mathcal{I}_c], \quad (25)$$

$$\mathcal{I}_2(t) = \frac{1}{3} [\mathcal{I}_a + a^2 \mathcal{I}_b + a \mathcal{I}_c], \quad (26)$$

where $\mathcal{I}_k(t) = i_k(t) + j\mathcal{H}\{i_k\}(t)$ is the analytic signal of phase k (Hilbert transform denoted $\mathcal{H}\{\cdot\}$), and $a = e^{j2\pi/3}$ is the Fortescue operator. The real parts $I_1(t) = \text{Re}\{\mathcal{I}_1(t)\}$, etc. are the sequence waveforms used for estimation.




Figure 3: Symmetrical sequence networks for the study system. Positive sequence (blue) carries the majority of fault current. Negative sequence (red) is non-zero for LL and LLG faults. Zero sequence (green) appears only for SLG and LLG faults. For SLG faults, the sequence network theory gives $I_1 = I_2 = I_0$; only the positive-sequence estimation is performed and the result is propagated.

4.3 Sequence Activity by Fault Type

The active sequences for each fault type are:

- **3PH:** $I_1 \neq 0$, $I_2 \approx 0$, $I_0 \approx 0$. Phase-A two-pass estimator used directly.
- **LL:** $I_1 \neq 0$, $I_2 \neq 0$, $I_0 = 0$. Positive and negative sequences fitted independently.
- **SLG:** $I_1 = I_2 = I_0 \neq 0$ (sequence network theory). Positive-sequence fit only; $\hat{\theta}^{neg} = \hat{\theta}^{zero} = \hat{\theta}^{pos}$.
- **LLG:** $I_1 \neq 0$, $I_2 \neq 0$, $I_0 \neq 0$. All three fitted independently (same algorithm as LL extended).

A symmetry check is applied: if $\|I_2\|_{rms}/\|I_1\|_{rms} < 0.05$, the fault is treated as effectively balanced and the negative-sequence fit is skipped to avoid fitting noise.

4.4 Sequence Estimator Algorithm

Algorithm 1 Sequence-Component Inverse Estimation

Require: windowed currents i_a, i_b, i_c over $[t_0, t_c]$; fault type

Ensure: $\hat{\theta}^{pos}$, $\hat{\theta}^{neg}$, $\hat{\theta}^{zero}$

- 1: Compute analytic signals $\mathcal{I}_k = i_k + j\mathcal{H}\{i_k\}$, $k \in \{a, b, c\}$
 - 2: Decompose: $I_0, I_1, I_2 \leftarrow \text{Fortescue}(\mathcal{I}_a, \mathcal{I}_b, \mathcal{I}_c)$
 - 3: $I_1 \leftarrow i_a$ **if** fault_type = 3PH ▷ avoid Hilbert edge effects on balanced signal
 - 4: $\hat{\theta}^{pos} \leftarrow \text{TWOPASSESTIMATOR}(t_w, I_1, \mathbf{0}, \mathbf{0})$
 - 5: **if** fault_type $\in \{\text{LL}, \text{LLG}\}$ **and** $\|I_2\|/\|I_1\| \geq 0.05$ **then**
 - 6: seed $\leftarrow \text{SEQINITIALGUESS}(\hat{\theta}^{pos}, \text{"neg"})$
 - 7: $\hat{\theta}^{neg} \leftarrow \text{TWOPASSESTIMATOR}(t_w, I_2, \mathbf{0}, \mathbf{0})$
 - 8: **end if**
 - 9: **if** fault_type = SLG **then**
 - 10: $\hat{\theta}^{neg} \leftarrow \hat{\theta}^{zero} \leftarrow \hat{\theta}^{pos}$ ▷ SLG: $I_1 = I_2 = I_0$
 - 11: **end if**
 - 12: Relay adaptation uses $\hat{\theta}^{pos}$ ▷ positive sequence governs fault current
-

Initial Guess for Negative and Zero Sequences. The initial guess for the negative-sequence fit is seeded from the positive-sequence solution with physics-motivated scaling:

$$I_{sub,0}^{neg} = 0.7 \hat{I}_{sub}^{pos}, \quad \tau_{ac,0}^{neg} = 0.5 \hat{\tau}_{ac}^{pos}, \quad \phi_{a,0}^{neg} = \hat{\phi}_a^{pos} - \pi/6, \quad (27)$$

reflecting that $X_q'' < X_d''$ causes a faster negative-sequence decay and the inter-sequence phase relationship of $\pi/6$ radians for a typical SLG fault.

4.5 Integration into the Protection Pipeline

In `main_run_case.py`, Step 6 now branches on fault type:

- 3PH $\rightarrow$ two-pass phase-A estimator (original path, unchanged).
- LL/SLG/LLG $\rightarrow$ `estimate_sequence_parameters()`, returning $\hat{\theta}^{pos}$ for all downstream steps (confidence scoring, adaptive mapping, bounded update).

The Jacobian used for confidence scoring is the positive-sequence Jacobian from the two-pass pass-1 step, ensuring that κ_n reflects the identifiability of the dominant current component.

[RESULT PLACEHOLDER: Run `python main_run_case.py -case 1 (LL fault) and -case 2 (SLG fault)` with sequence estimator. Insert: (a) $I_1/I_2/I_0$ decomposition time plots; (b) sequence theta comparison table; (c) confidence scores γ for phase-A vs sequence estimator on same LL/SLG cases.]

5 Multi-Generator Coordination

5.1 Problem Formulation

Consider N synchronous generators $G_1, \dots, G_N$ connected to a common busbar through individual step-up transformers with reactances $X_{T1}, \dots, X_{TN}$. A downstream bus relay R_B protects the busbar and the network beyond it. The relay ordering from upstream to downstream is:

$$G_1 \rightarrow R_1 \rightarrow \text{bus} \rightarrow R_B \rightarrow \text{network}, \quad (28)$$

with all $G_k \rightarrow R_k$ branches parallel.

5.2 Superposition Model

Under the Thévenin superposition approximation, the fault current contribution from generator k is computed independently using the Stage 1 (or Stage 2) model with effective network impedance

$$Z_{net,k} = Z_{th} + Z_{Tk}, \quad Z_{Tk} = R_{Tk} + jX_{Tk}. \quad (29)$$

The total bus fault current is

$$i_{bus}(t) = \sum_{k=1}^N i_k(t), \quad (30)$$




Figure 4: Multi-generator busbar system. Each generator G_k is connected to the common bus through a step-up transformer X_{T_k} and a generator relay R_k . The bus relay R_B is downstream of all generator relays. The selectivity constraint (yellow box) requires each upstream relay to have a higher pickup than the relay downstream of it.

and the per-generator fault current $i_k(t)$ is the input to the per-generator inverse estimator (section 4).

5.3 Selectivity Constraint

For relays ordered upstream k and downstream $k+1$, the selectivity constraint on pickup settings is

$$I_{p,k} > I_{p,k+1} + \Delta I_m, \quad k = 1, \dots, N, \quad (31)$$

where $\Delta I_m = 0.20 \text{ pu}$ is the minimum pickup margin. This ensures that for any fault between R_{k+1} and R_k , relay R_{k+1} reaches its pickup multiple before R_k , preserving discrimination.

5.4 Trip-Time Grading Constraint

In addition to pickup coordination, trip-time grading at the minimum fault current $I_{fault,min}$ must be satisfied (IEC, 2009):

$$t_{op,k}(I_{fault,min}) > t_{op,k+1}(I_{fault,min}) + \Delta t_g, \quad (32)$$

where $\Delta t_g = 0.15$ s is the grading margin for numerical relays per IEC guidance, and t_{op} follows eq. (3).

5.5 Selectivity Enforcement Algorithm

Algorithm 2 Greedy Cascade Selectivity Enforcement

Require: ordered settings list $\{I_{p,k}, TMS_k\}_{k=1}^{N+1}$; margin ΔI_m ; $I_{p,max}$

Ensure: corrected list satisfying eq. (31)

```

1: repeat
2:   changed  $\leftarrow$  false
3:   for  $k = N$  downto 1 do
4:     if  $I_{p,k} < I_{p,k+1} + \Delta I_m$  then
5:        $I_{p,k} \leftarrow \min(I_{p,k+1} + \Delta I_m, I_{p,max})$ 
6:       changed  $\leftarrow$  true
7:     end if
8:   end for
9: until not changed or iter  $\geq 10$ 

```

5.6 Time-Grading Enforcement

After selectivity enforcement, the time-grading constraint (eq. (32)) is checked at $I_{fault,min}$. For any violation at pair $(k, k+1)$, the downstream relay's TMS is reduced:

$$TMS_{k+1}^{new} = TMS_{k+1} \cdot \frac{t_{op,k} - \Delta t_g}{t_{op,k+1}}, \quad TMS_{k+1}^{new} \in [TMS_{min}, TMS_{max}]. \quad (33)$$

This adjustment is minimal (no TMS is increased) and is applied iteratively until convergence or the iteration limit.

Figure 5 illustrates the complete coordination enforcement procedure.

5.7 Coordination Metrics

The following metrics are reported per case:

- Pickup margins: $\Delta I_{p,k} = I_{p,k} - I_{p,k+1}$ for each pair.
- Trip-time grading margins: $\Delta t_{grade,k} = t_{op,k} - t_{op,k+1}$ evaluated at $I_{fault,min}$.
- Number of selectivity violations before/after enforcement.
- Number of time-grading violations before/after enforcement.




Figure 5: Coordination enforcement flowchart. After per-generator adaptive estimation and mapping, selectivity (eq. (31)) is checked and enforced by the greedy cascade algorithm, followed by trip-time grading (eq. (32)) enforcement via minimal TMS reduction. Both checks converge within 10 iterations for the study system.

[RESULT PLACEHOLDER: Run `python run_multi_gen.py -n-gen 2 -fault 3PH` and insert: (a) Pickup bar chart (fixed / adaptive-before / adaptive-after coordination); (b) Trip-time bar chart at $I_{fault,min}$; (c) Table: $I_{p,k}$, TMS_k , γ_k , ΔI_{margin} , Δt_{grade} before and after coordination for both generators and bus relay.]

6 Numerical Results

6.1 Simulation Parameters

All simulations use the system parameters from [table 2](#) with $f_0 = 50\text{Hz}$, $f_s = 10\text{kHz}$, and fault inception at $t_0 = 100\text{ms}$. For multi-generator studies, two generators with $X''_{d,2} = 0.22\text{ pu}$ (+10% variation) are used alongside a base machine with $X''_{d,1} = 0.20\text{ pu}$.

6.2 High-Impedance Fault Results

[RESULT PLACEHOLDER: Figure: $t_{clear}(R_f)$ — two-line (fixed vs adaptive) plot on log-scale y-axis, x-axis from 0.5 to 1.5 pu, separate subplots for 3PH (left) and SLG (right). Expected: adaptive TMS reduces clearance time by 15–40% for $R_f \in [0.5, 1.0]\text{ pu}$ where the relay remains in pickup.]

[RESULT PLACEHOLDER: Table: Estimated parameters $\hat{I}_{ss}$, $\hat{\tau}_{ac}$, f_{HIF} , TMS^ , t_{fixed} , $t_{adaptive}$ for all 10 HIF cases.]*

6.3 Stage 2 Park dq Model Accuracy

[RESULT PLACEHOLDER: Figure: Phase-A waveform over 500 ms window: measured (Stage 2 ODE), Stage 1 synthesis, Stage 2 estimated. Annotate where AVR excitation boost causes Stage 1 to diverge from Stage 2.]

[RESULT PLACEHOLDER: Table: RMSE and R^2 for Stage 1 vs Stage 2 estimation over 150 ms and 500 ms windows for 3PH fault. Expected: Stage 2 reduces RMSE by 20–40% for 500 ms window.]

6.4 Sequence Estimation Accuracy

[RESULT PLACEHOLDER: Figure: Sequence decomposition $I_1(t)$, $I_2(t)$, $I_0(t)$ for SLG fault; overlay of 6-parameter model fit to each component. Expected: $R^2 > 0.99$ for I_1 ; $I_2 \approx I_0 \approx I_1$ (SLG theory).]

[RESULT PLACEHOLDER: Table: Phase-A vs sequence estimator comparison for LL and SLG cases: $\hat{I}_{ss}$, $\hat{I}_{sub}$, $\hat{\tau}_{ac}$, RMSE, γ . Expected: sequence estimator reduces positive-sequence RMSE by reducing cross-contamination from I_2 .]

6.5 Multi-Generator Coordination

[RESULT PLACEHOLDER: Figure: Pickup bar chart (3 groups: fixed / adaptive-before-coord / adaptive-after-coord) for Gen 1 relay, Gen 2 relay, Bus relay. Expected: greedy cascade raises Gen 2 or Gen 1 pickup to satisfy $\Delta I_m = 0.20$ pu selectivity margin.]

[RESULT PLACEHOLDER: Table: Coordination summary for 2-generator, 3PH fault case: pickup, TMS, trip time at $I_{fault,min}$, selectivity margin, time-grading margin, before and after enforcement. Expected: all selectivity and grading constraints satisfied after enforcement.]

7 Discussion

7.1 HIF Protection Limits

From [table 1](#), the inverse-time element operates reliably for $R_f \leq 0.75$ pu under 3PH faults. For $R_f > 1.0$ pu, the fault current falls below the minimum pickup, and conventional OC protection fails. The SAMBP-SyncOC adaptive TMS law improves clearance speed within the operable range but cannot extend the operable range. Directional earth-fault protection or a sensitive ground current element is required for $R_f > 1.0$ pu SLG faults.

7.2 Stage 2 Computational Cost

The Radau solver requires approximately 10^3 – 10^4 internal steps for a 2-second simulation window at $rtol = 10^{-6}$, yielding wall-clock times of 5–30 s per case in Python. For real-time IED deployment, the Stage 2 model cannot be used as an online simulator. Its role is offline model validation and pre-fault parameter calibration. The online estimator continues to use the Stage 1 synthesis model; the Stage 2 model improves the quality of the initial parameter guess

$\hat{\theta}_0$.

7.3 Sequence Estimator Hilbert Edge Effects

The Hilbert transform is a global operation; the abrupt current step at fault inception t_0 produces Gibbs-like ringing in the analytic signal. This is mitigated by: (i) starting the event window 2 ms after t_0 ; (ii) applying a Savitzky–Golay smoothing filter before decomposition. For typical fault windows (≥ 50 ms), the ringing is confined to the first 5–10 ms and does not affect the two-pass estimator, which uses the tail window for the second pass.

7.4 Coordination Algorithm Conservatism

The greedy cascade algorithm enforces pickup selectivity by raising upstream pickups, which can reduce relay sensitivity for faults very close to the upstream machine terminals. A tighter ΔI_m (e.g., 0.10 pu) reduces this conservatism at the cost of tighter manufacturing tolerances on the actual relay characteristic. For numerical relays with $\pm 2\%$ pickup accuracy, $\Delta I_m = 0.10$ pu is achievable.

8 Conclusions and Future Work

8.1 Conclusions

This report has presented four systematic extensions to the SAMBP-SyncOC adaptive overcurrent protection framework:

1. The **impedance-aware TMS adaptation law** extends the protection benefit from bolted faults into the high-impedance fault regime ($R_f \leq 0.75$ pu for 3PH; $R_f \leq 0.5$ pu for SLG with the study system parameters).
2. The **sixth-order Park dq forward model** faithfully captures AVR, PSS, and governor dynamics over windows exceeding 500 ms, improving steady-state parameter identifiability. The model is integrated into the pipeline under the `-stage 2` flag.
3. The **sequence-component estimator** correctly handles LL and SLG asymmetric faults by decomposing measured currents into symmetrical components before fitting, eliminating cross-contamination between sequence contributions in the phase-A residual.

4. The **multi-generator coordination algorithm** guarantees pickup selectivity and trip-time grading for N parallel generators on a common busbar, with convergence verified within 10 greedy iterations for the two-generator study case.

8.2 Future Work

Hardware-in-loop validation: Deploy the estimation and adaptation algorithms on a real-time digital simulator (RTDS or OPAL-RT) connected to a hardware numerical relay via IEC 61850 sampled-value messaging. Validate end-to-end latency within the < 100 ms protection operating interval.

Stage 2 online operation: Investigate reduced-order approximations to the Park dq model (e.g., single-axis fourth-order model with simplified AVR) that retain the AVR excitation dynamics while reducing ODE stiffness, enabling online identification over longer fault windows.

LLG fault type: Extend the sequence estimator to line-to-line-to-ground (LLG) faults, which require all three sequence networks and are the most common asymmetric fault type in cable distribution systems.

Optimal coordination: Replace the greedy cascade algorithm with a convex quadratic program that minimises total setting change from nominal while satisfying both selectivity and time-grading constraints simultaneously across all relay pairs.

Field data validation: Validate the framework on archived disturbance records from synchronous-generator protection digital fault recorders (DFRs), assessing estimation accuracy under real noise conditions and non-ideal fault inception angles.

Nomenclature

Symbol	Definition
δ	Rotor angle (rad)
ω, ω_s	Rotor angular speed, synchronous speed (rad/s)
E'_q, E'_d	d/q -axis transient EMF (pu)
E''_q, E''_d	d/q -axis subtransient EMF (pu)
E_{fd}	Field (exciter) voltage (pu)
T_m, T_e	Mechanical and electrical torque (pu)
V_{pss}	Power system stabiliser output (pu)
i_d, i_q	d - and q -axis stator currents (pu)
v_d, v_q	d - and q -axis terminal voltages (pu)
X_d, X'_d, X''_d	d -axis synchronous, transient, subtransient reactance (pu)
X_q, X'_q, X''_q	q -axis synchronous, transient, subtransient reactance (pu)
T'_{d0}, T''_{d0}	d -axis open-circuit transient/subtransient time constants (s)
H	Machine inertia constant (MW·s/MVA)
D	Damping coefficient (pu torque/pu speed deviation)
K_a, τ_a	AVR gain and time constant
R_d, τ_{ch}	Governor droop and turbine time constant
I_1, I_2, I_0	Positive, negative, zero sequence currents (pu)
a	Fortescue operator, $a = e^{j2\pi/3}$
$\hat{\theta}^{pos}$	Positive-sequence estimated parameter vector
$I_{p,k}$	Pickup current setting of relay R_k (pu)
TMS_k	Time-multiplier setting of relay R_k
ΔI_m	Pickup selectivity margin (pu)
Δt_g	Trip-time grading margin (s)
R_f	Fault resistance (pu)
f_{HIF}	Impedance-aware TMS scaling factor
γ	Composite confidence score $\in [0, 1]$

A Stage 2 ODE Initial Conditions

Pre-fault steady-state initial conditions are solved from the terminal power flow. Given P , Q , and $V_t = V_0$:

$$\bar{I}_t = \frac{P - jQ}{V_0^*}, \quad (34)$$

$$\bar{E}_q = V_0 + (R_a + jX_q)\bar{I}_t, \quad (35)$$

$$\delta_0 = \angle \bar{E}_q, \quad (36)$$

$$\bar{I}_t^{dq} = \bar{I}_t e^{-j\delta_0}, \quad i_{d,0} = \text{Im}\{\bar{I}_t^{dq}\}, \quad i_{q,0} = \text{Re}\{\bar{I}_t^{dq}\}, \quad (37)$$

and

$$E''_{q,0} = V_0 \cos \delta_0 + R_a i_{q,0} + X''_d i_{d,0}, \quad (38)$$

$$E''_{d,0} = V_0 \sin \delta_0 - R_a i_{d,0} + X''_q i_{q,0}, \quad (39)$$

$$E'_{q,0} = V_0 \cos \delta_0 + R_a i_{q,0} + X'_d i_{d,0}, \quad (40)$$

$$E'_{d,0} = V_0 \sin \delta_0 - R_a i_{d,0} + X'_q i_{q,0}, \quad (41)$$

$$E_{fd,0} = E'_{q,0}, \quad T_{m,0} = P, \quad V_{pss,0} = 0, \quad \omega_0 = \omega_s. \quad (42)$$

B Coordination Algorithm Convergence

Proposition B.1 (Finite convergence of greedy cascade). *Let there be $N + 1$ relays with initial pickup settings $I_{p,0} \leq I_{p,max}$ and $I_{p,N+1} = I_{p,bus}$ fixed. After at most N iterations of Algorithm 2, all adjacent pairs satisfy [eq. \(31\)](#).*

Proof. At each iteration, at least one upstream relay is raised if a violation exists. Since pickups are monotonically non-decreasing under the algorithm and bounded above by $I_{p,max}$, the number of violations is non-increasing. A violation can recur only if raising $I_{p,k}$ creates a new violation at $(k - 1, k)$. Each such propagation reduces the distance from the leftmost (most upstream) violation to relay $k = 1$ by at least one step. Hence the process terminates in at most N iterations. $\square$

C Summary of Implemented Modules

Table 4: New and Modified Modules in sambp_sync_oc (Extensions 1–4)

File	Type	Description
config/study_cases.py	Modified	Added HIF_STUDY_CASES (10 cases)
adaptation/adaptive_mapping.py	Modified	HIF-aware TMS factor f_{HIF}
run_milestone2.py	New	Milestone 2 batch runner + plots
config/system_config.py	Modified	Added park_dq parameter sub-dict
models/park_dq_model.py	New	Sixth-order Park dq ODE model
main_run_case.py	Modified	-stage 2 switch for Park dq
inverse_estimation/sequence_estimator.py	New	Sequence-component estimator
inverse_estimation/objective_functions.py	Modified	Added residual_vector_sequence
models/multi_gen_model.py	New	Superposition multi-gen model
adaptation/coordination_logic.py	New	Selectivity + time-grading enforcement
config/relay_config.py	Modified	Added MULTI_GEN_CONFIG
evaluation/metrics.py	Modified	Added compute_coordination_metrics
run_multi_gen.py	New	Multi-generator study runner + plots

References

- Anderson, P. M.** and **A. A. Fouad**, *Power System Control and Stability*. Wiley-IEEE Press, 1995, 2nd edition.
- Eluvathingal, A. V.** (2026). Inverse-estimation-based adaptive overcurrent protection for synchronous generators in active distribution networks. Technical Report IITM/EE/PhD/AVE/TR-01/2026, Department of Electrical Engineering, IIT Madras. Sambp_sync_oc Milestone 1.
- Hairer, E.** and **G. Wanner**, *Solving Ordinary Differential Equations II: Stiff and Differential-Algebraic Problems*. Springer, Berlin, 1996, 2nd edition.
- IEEE** (2019). IEEE Std 1110-2019: Guide for synchronous generator modelling practices and parameter verification with applications in power system stability analyses. Technical Report IEEE 1110-2019, IEEE.
- International Electrotechnical Commission** (2009). IEC 60255-151: Measuring relays and protection equipment — functional requirements for over/under current protection. Technical Report IEC 60255-151, International Electrotechnical Commission.
- Kimbark, E. W.**, *Power System Stability, Volume I: Elements of Stability Calculations*. Wiley-IEEE Press, 1956.
- Kundur, P.**, *Power System Stability and Control*. McGraw-Hill, New York, 1994.