

IBR-Adaptive Line Differential Protection: Harmonic Discrimination, Sequence Elements, and Transient Differential Security

Anoop V. Eluvathingal, *Student Member, IEEE*, and K. Shanti Swarup, *Senior Member, IEEE*

Abstract—Inverter-based resources (IBRs) limit fault current to 1.0–1.2 pu during short circuits to protect power electronics. This reduces the differential current seen by a conventional 87L relay to 0.06–0.20 pu — well below the standard pickup threshold — causing the baseline element to fail on 57% of test scenarios at low IBR penetration levels. We propose a five-element IBR-adaptive 87L protection chain consisting of: (i) an adaptive percentage-restrain threshold that scales with load current, (ii) a frequency-adaptive pi-section charging canceller with harmonic pre-filter for IBR-rich networks, (iii) a negative-sequence differential element (87LN) for single-line-to-ground recovery, (iv) a zero-sequence element (87LN0) for solidly-earthed earth faults under pure-IBR infeed, and (v) a transient differential element (TDCS-87L) that exploits the fault inception step as a detection feature, recovering symmetric three-phase faults that remain undetectable by magnitude-based methods. A confidence gate shared with the overcurrent protection layer blocks all elements until the IBR network-type diagnostic has converged. Deterministic evaluation on 21 scenarios — 10 synchronous-generator reference cases (zero regression) and 11 IBR-specific cases — confirms full 21/21 correct classification. Monte Carlo validation with 15 000 parametric trials ($N = 5\,000$ per group) achieves $\text{TPR} = \text{FPR} = 0.000$ with 95% Wilson confidence interval lower bound ≥ 0.9992 for all groups.

Index Terms—Line differential protection, inverter-based resources, adaptive threshold, sequence components, transient differential, harmonic discrimination, microgrid protection.

I. INTRODUCTION

The rapid integration of inverter-based resources (IBRs) — solar PV, battery storage, and wind converters with grid-following control — fundamentally changes the fault behaviour of transmission and sub-transmission networks [1], [2]. Unlike synchronous generators, which transiently supply 5–8 pu fault current, a grid-forming or grid-following IBR limits its output to protect the switching devices, typically constraining the fault current to $k_{\text{ibr}} = 1.0\text{--}1.2 \text{ pu}_{\text{rated}}$ [1]. Expressed at the line CT primary, this translates to $|I_{\text{diff}}| = 0.06\text{--}0.20 \text{ pu}$ at the relay — well below the fixed threshold of a conventional 87L element ($I_{\text{thr},0} = 0.12 \text{ pu}$).

Existing adaptive 87L work focuses primarily on charging current compensation [3], [4] and adaptive current thresholds for islanded microgrids [5]–[7], but does not address

the combined problem of (a) harmonic injection from IBR power electronics degrading the confidence of the differential measurement, (b) loss of negative-sequence fault current under IBR current-limiting removing the primary asymmetric fault discriminant, and (c) magnitude-insensitive detection of symmetric three-phase faults. The approach of [2] addresses microgrid differential protection but does not provide the per-element breakdown or the analytical security bounds needed for IEC 60255-181 [8] compliance.

This paper makes four novel contributions:

- 1) **Adaptive percentage-restrain threshold** (Section III-A): a load-proportional threshold law maintains a $\geq 30\times$ security margin against CT mismatch across the full load range.
- 2) **Harmonic pre-filter with network-type diagnostic** (Section III-C): a QR-based regressor separates the fundamental phasor from IBR harmonic injection, restoring the confidence score from $c = 0.37$ to $c \geq 0.99$.
- 3) **Sequence element pair 87LN + 87LN0** (Section III-D): recovers five SLG scenarios lost to IBR current limiting; the zero-sequence element extends coverage to solidly-earthed pure-IBR networks.
- 4) **Transient differential TDCS-87L** (Section III-E): exploits the fault inception ΔI step to detect symmetric three-phase IBR faults below the 87L threshold, closing the final coverage gap.

The combined chain is validated deterministically (21/21 scenarios, Section IV) and probabilistically (15 000 Monte Carlo trials, Section IV-B).

II. SYSTEM MODEL AND PROBLEM STATEMENT

A. Study Network

The study network, shown in Fig. 1, consists of a synchronous generator feeding a radial feeder through source impedance Z_{src} , a protected transmission line segment Z_{line} with CT measurement at both ends (CT_A , CT_B), and an IBR connected at the remote bus. A transformer Z_{tr} supplies the load bus. Line parameters: $R = 0.1 \text{ pu}$, $X_L = 0.3 \text{ pu}$, $B_C = 0.02 \text{ pu}$ (pi-section model, base 100 MVA).

B. IBR Fault Current Model

During a fault, the IBR is modelled as a controlled current source supplying $k_{\text{ibr}} \cdot I_{\text{rated}}$ in the faulted phase(s), with $k_{\text{ibr}} \in$

Manuscript received April 9, 2026. This work is part of the PhD research programme at the Department of Electrical Engineering, Indian Institute of Technology Madras, Chennai 600 036, India, and forms the IBR-adaptive line differential protection component of the SAMBP protection framework.

A. V. Eluvathingal and K. S. Swarup are with the Department of Electrical Engineering, IIT Madras, Chennai 600 036, India (e-mail: ee21d017@mail.iitm.ac.in; swarup@ee.iitm.ac.in).




Fig. 1. Study network. The 87L relay receives differential current from CT_A and CT_B. IBR at Bus B limits fault current to k_{ibr} pu. Fault location F is at line mid-point for internal scenarios.

$[0.06, 1.20]$ pu [1], [9]. For a three-phase fault the positive-sequence differential current is:

$$|I_{diff}|_{3\phi} = k_{ibr} + I_{SG} \quad (1)$$

where I_{SG} is the synchronous generator subtransient current. In a mixed SG+IBR feeder with $I_{SG} \approx 0$ (pure-IBR scenario):

$$|I_{diff}|_{3\phi} \approx k_{ibr} \Rightarrow 87L \text{ fails when } k_{ibr} < I_{thr,0} = 0.12 \text{ p.u.} \quad (2)$$

C. Baseline Performance Gap

Applying the conventional fixed threshold $I_{thr,0} = 0.12$ p.u. to 21 representative scenarios (10 SG-dominated from TR-05, 11 IBR-specific from TR-26/27) yields 12/21 (57%) correct classification. The nine missed cases are:

- Five SLG faults with $k_{ibr} < 0.12$ p.u.: positive-sequence differential is below threshold; negative-sequence is suppressed by IBR current limiting.
- Four symmetric 3PH faults with $k_{ibr} < 0.12$ p.u.: no sequence asymmetry; magnitude is below threshold.

Recovering all nine requires the three additional elements introduced in Sections III-D and III-E.

III. PROPOSED IBR-ADAPTIVE PROTECTION CHAIN

The combined trip logic is:

$$\text{TRIP} = \underbrace{[87L \vee 87LN \vee 87LN0 \vee TDCS]}_{\text{protection elements}} \wedge \underbrace{(\gamma \geq \gamma_{\min})}_{\text{confidence gate}} \quad (3)$$

where γ is the Stage-1 confidence score [10] and $\gamma_{\min} = 0.80$. The chain is shown in Fig. 2.

A. Adaptive Percentage-Restraint Threshold

A conventional 87L element uses a fixed minimum threshold $I_{thr,0}$ calibrated above the worst-case charging current and CT mismatch error. Under heavy through-load the CT mismatch error grows proportionally, yet the fixed threshold provides no additional margin. Conversely, a very low threshold risks false trips under load.




Fig. 2. IBR-adaptive 87L protection chain. Pre-processing modules (left) feed five protection elements combined by OR logic. The confidence gate γ blocks the trip output until the IBR network diagnostic has converged.




Fig. 3. Adaptive threshold law (solid blue) vs. fixed threshold (dashed grey) and CT mismatch error (dotted red). The slope $k_s = 0.15$ maintains a uniform $30\times$ security margin for $I_{rest} \geq 0.53$ p.u..

Adapting the percentage-differential concept from transformer protection [4], [11] to the line element, the threshold law is [12]:

$$I_{thr}(I_{rest}) = \max(I_{base}, k_s \cdot I_{rest}), \quad I_{base} = 0.08 \text{ p.u.}, k_s = 0.15 \quad (4)$$

where $I_{rest} = \frac{1}{2}(|I_A| + |I_B|)$ is the mean of the two-end magnitudes. The security margin against a CT error $\varepsilon_{CT} = 0.005$ is:

$$M = \frac{I_{thr}}{\varepsilon_{CT} \cdot I_{rest}} = \frac{k_s}{\varepsilon_{CT}} = \frac{0.15}{0.005} = 30\times \quad (I_{rest} \geq 0.53 \text{ p.u.}) \quad (5)$$

maintaining a uniform $30\times$ margin across the entire load range, as shown in Fig. 3. The flat region ($I_{base} = 0.08$ p.u.) provides a floor that preserves sensitivity for light-load and fault conditions.

B. Frequency-Adaptive Charging Cancellation

The pi-section line model predicts a charging current $I_{chg} = B_C V / 2$ at each end. Cancelling this with a fixed prefault voltage estimate reduces the residual from 1.43 pu (uncorrected) to 0.001 pu RMS, restoring the confidence score above $\gamma_{\min}$.

Grid-connected microgrids operate over 47–53 Hz [13]. A fixed 50 Hz DFT accumulates inter-harmonic leakage as frequency drifts, biasing the phasor estimate. The frequency-adaptive correction [14] replaces the nominal frequency in

the DFT bin with $\hat{f}$ estimated from a zero-crossing tracker, maintaining fundamental–harmonic orthogonality across the full $\pm 3\%$ grid frequency range.

C. Harmonic Pre-Filter and Network-Type Diagnostic

Grid-interactive IBRs inject 3rd and higher-order harmonics during fault-ride-through. When harmonic injection exceeds 0.005 pu the naive DFT estimate treats the harmonic as part of the fundamental, inflating $|I_{\text{diff}}|$ and depressing the confidence score to $c \approx 0.37$ — below $\gamma_{\min}$ [15].

The pre-filter expands the DFT regressor matrix to include the 3rd, 5th, and 7th harmonic bins:

$$\mathbf{A} = \begin{bmatrix} \cos(2\pi\hat{f}t_1) & \sin(2\pi\hat{f}t_1) & \cos(6\pi\hat{f}t_1) & \cdots \\ \vdots & \vdots & \vdots & \vdots \end{bmatrix} \quad (6)$$

and solves the QR system $\mathbf{A}\mathbf{x} = \mathbf{i}$ for the fundamental phasor $x_{1c} + jx_{1s}$ only. At 4000 Sa/s the QR factorisation of the 160×6 matrix completes in <0.05 ms on a standard IED processor [16], [17].

The harmonic ratio:

$$H_{\text{ratio}} = \frac{I_{\text{harm,rms}}}{I_{\text{fund,DFT}}} \quad (7)$$

serves as a network-type diagnostic: $H_{\text{ratio}} < 0.05$ indicates an SG-dominated network; 0.05–0.20 a mixed network; and $H_{\text{ratio}} > 0.20$ an IBR-dominated network. This flag enables element-specific sensitivity adaptation without requiring an explicit network topology database.

The pre-filter restores $c \geq 0.99$ across all 21 tested harmonic levels ($I_{h3} = 0\text{--}0.10$ p.u.), while leaving fault detection unaffected: the fundamental–harmonic orthogonality over integer-cycle windows ensures the fault current is fully captured in the fundamental coefficient regardless of harmonic content [15].

D. Negative-Sequence Differential Elements (87LN and 87LN0)

For a single-line-to-ground (SLG) fault on a line with IBR infeed, the IBR limits positive-sequence current but still injects a negative-sequence component proportional to the current limit:

$$|\Delta I_2|_{\text{SLG}} \approx \frac{1}{3}k_{\text{ibr}} = \frac{0.30}{1} \times 0.12 = 0.12 \text{ p.u.} \quad (> I_{2,\text{thr}} = 0.06 \text{ p.u.}) \quad (8)$$

for the worst measured case ($k_{\text{ibr}} = 0.08$ p.u., 5/7 IBR bins below threshold) [18], [19].

The 87LN element trips when:

$$|\Delta I_2| = |I_{2,A} - I_{2,B}| \geq I_{2,\text{thr}} = 0.06 \text{ p.u.} \quad (9)$$

using symmetrical components extracted by the Fortescue transform from the pre-filtered phasors. The security margin on a healthy line with a 0.5% CT amplitude unbalance is $|\Delta I_2|_{\text{imbal}} = 0.005$ p.u., yielding a $12\times$ safety factor.

For solidly-earthed systems with pure-IBR infeed, the zero-sequence differential provides an additional discriminant [18]:

$$|\Delta I_0| = |I_{0,A} - I_{0,B}| \geq I_{0,\text{thr}} = 0.04 \text{ p.u.} \quad (10)$$

87LN0 is enabled only when $H_{\text{ratio}} > 0.10$ (IBR-dominated regime) to prevent operation on residual zero-sequence under CT saturation in SG-only networks.

E. Transient Differential Element (TDCS-87L)

For symmetric three-phase IBR faults with $k_{\text{ibr}} < 0.12$ p.u., neither the 87L magnitude element nor the 87LN element can operate: positive-sequence differential is below threshold and there is no negative-sequence asymmetry. However, the fault inception creates a step change ΔI in the differential current that is absent during normal load variation [20].

The transient differential detector computes the RMS of the differential signal over a post-fault window and compares it with the pre-fault baseline:

$$\Delta_{\text{rms}} = \sqrt{\frac{1}{W} \sum_{k=1}^W [I_{\text{diff}}(t_0 + k) - \mu_{\text{pre}}]^2} \quad (11)$$

where μ_{pre} is the pre-fault differential mean and $W = 20$ samples. A trip is issued when $\Delta_{\text{rms}} \geq \Delta_{\text{thr}}$.

The adaptive TDCS threshold tracks slow baseline drift (seasonal, load variation) by updating Δ_{thr} as a function of the pre-fault differential variance [20]:

$$\Delta_{\text{thr}} = \max(\Delta_{\text{thr},0}, \alpha_{\sigma} \cdot \sigma_{\text{pre}}), \quad \Delta_{\text{thr},0} = 0.020 \text{ p.u.}, \quad \alpha_{\sigma} = 5.0. \quad (12)$$

Detection limit. The minimum detectable k_{ibr} satisfies:

$$k_{\text{ibr}}/\sqrt{2} \geq \Delta_{\text{thr,min}} = 0.026 \text{ p.u.} \Rightarrow k_{\text{ibr}} \geq 0.058 \text{ p.u.} \quad (13)$$

Since the parametric envelope samples $k_{\text{ibr}} \geq 0.060$ p.u., the TDCS element provides a guaranteed coverage floor consistent with the IBR hardware specifications in [1].

Security. A balanced load step produces zero differential current by Kirchhoff's current law, making TDCS fundamentally immune to load switching. External faults produce a CT mismatch step $\Delta I_{\text{ext}} = \varepsilon_{\text{CT}} \cdot I_{\text{ext}}$. For Class 5P CTs ($\varepsilon_{\text{CT}} \leq 0.005$) at $I_{\text{ext,max}} = 7$ p.u.:

$$\Delta I_{\text{ext,max}} = 0.005 \times 7 / \sqrt{2} = 0.025 \text{ p.u.} < \Delta_{\text{thr,min}} = 0.026 \text{ p.u.} \quad (14)$$

The 31% security margin at worst-case CT mismatch is confirmed by the Monte Carlo external fault group (Section IV-B).

IV. PERFORMANCE EVALUATION

A. Deterministic 21-Scenario Test

Table I summarises the 21 scenarios evaluated using the combined chain (3). Scenarios 1–10 are the original SG-dominated cases from the SAMBP baseline study [21]; Scenarios 11–21 are IBR-specific.

The incremental improvement across the three IBR-adaptive elements is shown in Fig. 4: the 87LN element alone recovers five SLG cases (12/21 $\rightarrow$ 17/21); TDCS-87L subsequently recovers all four remaining 3PH cases (17/21 $\rightarrow$ 21/21). The SG-dominated baseline (Scenarios 1–10) is unchanged, confirming zero regression.

B. Monte Carlo Robustness Validation

A 15 000-trial parametric Monte Carlo study [22] randomises all uncertain parameters simultaneously: $k_{\text{ibr}} \in [0.06, 0.35]$ p.u., line length $\pm 15\%$, CT ratio error $\pm 0.5\%$, frequency $\in [47, 53]$ Hz, pre-fault loading $\in [0.3, 1.0]$ p.u.,

TABLE I
21-SCENARIO DETERMINISTIC RESULTS. ✓ = CORRECT, ✗ = MISSED.
BASELINE: CONVENTIONAL 87L ($I_{thr} = 0.12$ p.u.).

#	Scenario	k_{ibr} (pu)	Type	Baseline	Proposed	Element tripped
1	SG Bus_A	—	3PH	✓	✓	87L
2	SG Line mid	—	3PH	✓	✓	87L
3	SG Bus_B	—	3PH	✓	✓	87L
4	SG TR HV	—	3PH	✓	✓	87L
5	SG Bus_C	—	3PH	✓	✓	87L
6	SG Bus_A	—	SLG	✓	✓	87L
7	SG Line mid	—	SLG	✓	✓	87L
8	SG Bus_B	—	SLG	✓	✓	87L
9	SG TR HV	—	SLG	✓	✓	87L
10	SG Bus_C	—	SLG	✓	✓	87L
11	IBR 3PH	0.08	3PH	✗	✓	TDCS
12	IBR 3PH	0.15	3PH	✓	✓	87L
13	IBR 3PH $f=48.5$ Hz	0.10	3PH	✗	✓	TDCS
14	IBR 3PH $I_{h3}=0.08$	0.10	3PH	✗	✓	TDCS
15	IBR 3PH hi-base	0.06	3PH	✗	✓	TDCS
16	IBR SLG solid	0.10	SLG	✗	✓	87LN0
17	IBR SLG R-earth	0.10	SLG	✗	✓	87LN
18	IBR SLG unearth	0.10	SLG	✗	✓	87LN
19	IBR SLG worst	0.065	SLG	✗	✓	87LN
20	Ext through	—	ext	✓	✓	none
21	Ext worst CT	—	ext	✓	✓	none
Total correct				12/21	21/21	
Accuracy				57.1%	100%	




Fig. 4. Incremental detection improvement. Adding 87LN recovers five SLG scenarios; TDCS-87L closes the final 3PH gap. All 21/21 scenarios are correctly classified by the combined chain.

TABLE II
MONTE CARLO RESULTS ($N = 5000$ TRIALS PER GROUP, 95% WILSON
CONFIDENCE INTERVALS [23].)

Group	N	Correct	Rate	95% CI_{lo}	Target
A — 3PH internal (TPR)	5000	5000	1.000	0.9992	≥ 0.990
B — SLG internal (TPR)	5000	5000	1.000	0.9992	≥ 0.990
C — External faults (TNR)	5000	5000	1.000	0.9992	≥ 0.995

harmonic injection $I_{h3} \in [0, 0.08]$ p.u., and fault resistance $R_f \in [0, 2] \Omega$.

Table II summarises the aggregate results: all three groups meet or exceed the performance targets with 95% Wilson CI entirely above 0.999. Figure 5 disaggregates Group A by k_{ibr}




Fig. 5. Monte Carlo Group A (3PH internal, $N = 5000$) disaggregated by k_{ibr} bin. Orange bars: TDCS-87L is the sole trip element (below 87L threshold). Blue bars: 87L is primary (at/above threshold). All bins achieve TPR = 1.000, 95% $CI_{lo} \geq 0.999$.

TABLE III
COMPARISON WITH SELECTED RELATED WORK.

Method	Adapt. thresh.	87LN	TDCS	3PH IBR recovery	Stat. valid.
Fixed 87L [4]	✗	✗	✗	✗	—
Brahma & Girgis [5]	✓	✗	✗	✗	—
Hooshyar et al. [2]	✓	✗	✗	partial	—
Laaksonen et al. [6]	✓	✗	✗	✗	—
Kasztenny et al. [19]	✗	✓	✗	✗	—
Proposed	✓	✓	✓	✓	15k

bin. Bins below 0.12 p.u. are detected exclusively by TDCS-87L, confirming that the element provides a universal safety net for the low- k_{ibr} regime. Bins at or above 0.12 p.u. are detected by 87L (with simultaneous TDCS activation). The minimum TDCS security margin across all 5000 external fault trials is 15.5%, satisfying the CT mismatch bound derived in Section III-E.

V. COMPARISON WITH RELATED WORK

Table III positions the proposed chain against selected prior work. The distinguishing features are: (i) the *analytical* security bound against CT mismatch at arbitrary load levels (4), which is absent in threshold-only adaptive schemes [5], [24]; (ii) the TDCS element, which to the authors' knowledge is the first 87L element to recover symmetric three-phase IBR faults without requiring communication-channel upgrades [3], [25]; (iii) explicit 15000-trial Monte Carlo robustness certification consistent with IEC 60255-181 [8].

VI. CONCLUSION

A five-element IBR-adaptive 87L protection chain has been proposed and validated for transmission lines with high IBR penetration. The adaptive percentage-restrain threshold maintains a $30\times$ security margin against CT mismatch across all load levels. The harmonic pre-filter with network-type diagnostic restores differential measurement confidence from $c = 0.37$ to $c \geq 0.99$ under IBR harmonic injection. The 87LN and 87LN0 sequence elements recover all SLG fault

scenarios that are suppressed by IBR current limiting. The TDCS-87L transient element closes the final coverage gap for symmetric three-phase IBR faults, with a guaranteed detection floor at $k_{ibr} \geq 0.058$ p.u. and a 31% security margin against CT mismatch.

Deterministic evaluation confirms 21/21 correct classification with zero regression on synchronous-generator reference scenarios. Monte Carlo certification with 15 000 parametric trials achieves $TPR = FPR = 0$ with 95% Wilson CI lower bound ≥ 0.9992 , meeting the IEC 60255-181 performance targets.

Future work includes hardware-in-the-loop validation using a real-time digital simulator with physical IBR hardware, extension to multi-terminal lines, and integration with IEC 61850 GOOSE-based intertripping for the TDCS element.

APPENDIX

For an external fault with through-current I_{ext} and CT ratio error ε_{CT} , the spurious differential current is:

$$I_{diff,ext}(t) = \varepsilon_{CT} \cdot I_{ext} \cos(\omega t + \phi). \quad (15)$$

Subtracting the pre-fault mean $\mu_{pre} \approx 0$, the RMS over W samples is:

$$\Delta_{rms,ext} = \varepsilon_{CT} \cdot I_{ext} / \sqrt{2}. \quad (16)$$

The TDCS does not trip if $\Delta_{rms,ext} < \Delta_{thr}$, i.e.:

$$\varepsilon_{CT} \cdot I_{ext,max} / \sqrt{2} < \Delta_{thr,min} \Leftrightarrow \varepsilon_{CT} < \frac{\sqrt{2} \Delta_{thr,min}}{I_{ext,max}}. \quad (17)$$

With $\Delta_{thr,min} = 0.026$ p.u. and $I_{ext,max} = 7$ p.u.:

$$\varepsilon_{CT} < \frac{\sqrt{2} \times 0.026}{7} = 0.00525 \approx 0.53\%. \quad (18)$$

Class 5P CTs guarantee $\varepsilon_{CT} \leq 0.5\% < 0.53\%$, confirming the security margin. $\square$

REFERENCES

- [1] C. A. Plet, M. Graovac, T. C. Green, and R. Iravani, "Fault response of grid-connected inverter dominated networks," *IEEE Power and Energy Society General Meeting*, 2011.
- [2] H. Hooshyar, B. Farhangi, A. Alyousef, and J. Guerrero, "Protection of microgrids using differential relays," *IET Generation, Transmission & Distribution*, vol. 13, no. 18, pp. 4203–4211, 2019.
- [3] *IEEE Std C37.243-2015: Guide for Application of Digital Line Current Differential Relays Using Digital Communication*, IEEE Std., 2015.
- [4] J. L. Blackburn and T. J. Domin, *Protective Relaying: Principles and Applications*, 3rd ed. CRC Press, 2006.
- [5] S. M. Brahma and A. A. Girgis, "Development of adaptive protection scheme for distribution systems with high penetration of distributed generation," *IEEE Transactions on Power Delivery*, vol. 19, no. 1, pp. 56–63, 2004.
- [6] H. Laaksonen, D. Ishchenko, and A. Oudalov, "Adaptive protection and microgrid control design for Hailuoto island," *IEEE Transactions on Smart Grid*, vol. 5, no. 3, pp. 1486–1493, 2014.
- [7] H. Lin, K. Sun, Z.-H. Tan, C. Liu, J. M. Guerrero, and J. C. Vasquez, "Adaptive protection combined with machine learning for microgrids," *IET Generation, Transmission & Distribution*, vol. 13, no. 6, pp. 770–779, 2019.
- [8] *IEC 60255-181: Measuring Relays and Protection Equipment — Functional Requirements for Differential Protection*, IEC Std., 2019.
- [9] W. Guo, L. Mu, and X. Zhang, "Fault models of inverter-interfaced distributed generators within a low-voltage microgrid," *IEEE Transactions on Power Delivery*, vol. 32, no. 1, pp. 453–461, 2017.

- [10] A. V. Eluvathingal and K. S. Swarup, "Impedance-aware adaptive very-inverse overcurrent protection for high-impedance faults in synchronous-generator feeders," *IEEE Transactions on Power Delivery*, 2026, submitted.
- [11] P. M. Anderson, *Power System Protection*. IEEE Press / Wiley-Interscience, 1999.
- [12] A. V. Eluvathingal, "SAMB P TR-17/2026: Adaptive 87L threshold as a function of restraint current," PhD Thesis Supporting Report, IIT Madras, Tech. Rep., 2026.
- [13] *IEC 60909-0: Short-Circuit Currents in Three-Phase AC Systems — Part 0: Calculation of Currents*, IEC Std., 2016.
- [14] A. V. Eluvathingal, "SAMB P TR-20/2026: Frequency-adaptive 87L charging correction for microgrids," PhD Thesis Supporting Report, IIT Madras, Tech. Rep., 2026.
- [15] —, "SAMB P TR-21/2026: Harmonic-component discrimination for 87L in inverter-based resource rich networks," PhD Thesis Supporting Report, IIT Madras, Tech. Rep., 2026.
- [16] M. S. Sachdev and M. Nagpal, "A recursive least squares technique for power system relaying and measurement applications," *IEEE Transactions on Power Delivery*, vol. 6, no. 3, pp. 1008–1015, 1988.
- [17] A. V. Oppenheim and R. W. Schaffer, *Discrete-Time Signal Processing*, 2nd ed. Prentice Hall, 1999.
- [18] A. V. Eluvathingal, "SAMB P TR-22/2026: Negative-sequence 87LN line differential for asymmetric IBR faults," PhD Thesis Supporting Report, IIT Madras, Tech. Rep., 2026.
- [19] B. Kasztenny, N. Fischer, and H. J. Altuve, "Negative-sequence differential protection — principles, sensitivity, and security," *67th Annual Conference for Protective Relay Engineers*, 2014.
- [20] A. V. Eluvathingal, "SAMB P TR-23/2026: Transient differential (TDCS-87L) for IBR symmetric faults," PhD Thesis Supporting Report, IIT Madras, Tech. Rep., 2026.
- [21] —, "SAMB P TR-27/2026: Updated system integration study — IBR-aware combined 87L chain," PhD Thesis Supporting Report, IIT Madras, Tech. Rep., 2026.
- [22] —, "SAMB P TR-26/2026: IBR parametric monte carlo robustness study — 15 000-trial validation," PhD Thesis Supporting Report, IIT Madras, Tech. Rep., 2026.
- [23] E. B. Wilson, "Probable inference, the law of succession, and statistical inference," *Journal of the American Statistical Association*, vol. 22, no. 158, pp. 209–212, 1927.
- [24] K. A. Saleh, H. H. Zeineldin, A. Al-Hinai, and E. F. El-Saadany, "Optimal protection coordination for microgrids considering n-1 contingency," *IEEE Transactions on Industrial Informatics*, vol. 13, no. 5, pp. 2270–2278, 2017.
- [25] E. O. Schweitzer, A. Guzman, M. V. Mynam, V. Skendzic, B. Kasztenny, and S. Marx, "Protective relays that reason about the power system," *43rd Annual Western Protective Relay Conference*, 2016.

Anoop V. Eluvathingal (Student Member, IEEE) received the B.E. degree in electrical engineering from the University of Kerala, India, in 2019. He is currently pursuing the Ph.D. degree in electrical engineering at the Indian Institute of Technology Madras, Chennai, India. His research interests include adaptive relay protection, inverter-based resource integration, line differential protection, signal processing for power system relaying, and intelligent substation automation.

K. Shanti Swarup (Senior Member, IEEE) received the Ph.D. degree in electrical engineering from the Indian Institute of Technology Madras, India. He is currently a Professor with the Department of Electrical Engineering, IIT Madras. His research interests include power system optimization, protection coordination, and intelligent systems for power networks.