CO2035

2. Discrete-Time Signal and System





Contents

- **Discrete-Time Signal**
  - Elementary Discrete-Time Signals
  - Classification of Discrete-Time Signals
  - Simple Manipulation of Discrete-Time Signals
- **Discrete-Time System**
  - Input-Output Description
  - Block Diagram Representation of Discrete-Time Systems
  - Classification of Discrete-Time Systems
- **Analysis of LTI** (Linear Time Invariant) **System in time domain**
  - Resolution of A Discrete-Time Signal Into Impulses
  - Properties of Convolution
  - FIR and IIR System





Contents (con't)


- **Difference Equations**
  - LTI Systems Characterized by Constant-Coefficient Difference Equations.
  - Solve the Constant-Coefficient Difference Equation.
  - Impulse Response of A Recursive LTI System

- **Implementation of Discrete-Time Systems**
  - Direct Form I Structure
  - Direct Form II Structure

Discrete-Time Signals

- Discrete-Time Signal x(n) is a function of an independent variable that is an integer (n € Z)
  - x(n) is not defined for non-integer values of n. It is incorrect to think that x(n) is equal to zero if n is not an integer.

- $x(n) = x_a(nT_s)$
  - x_a: corresponding analog signal
  - T_s: sampling cycle



Discrete-Time Signals

- Functional representation

$$x(n) = \begin{cases} 1, & \text{for } n = 1, 3 \\ 4, & \text{for } n = 2 \\ 0, & \text{elsewhere} \end{cases}$$


- Tabular representation

n	...	-2	-1	0	1	2	3	4	5	...
x(n)	...	0	0	0	1	4	1	0	0	...

- Sequence representation
  - The time origin (n=0) is indicated by symbol ↑ or *.

$$x(n) = \{\ldots 0, \underset{\uparrow}{0}, 1, 4, 1, 0, 0, \ldots\}$$

- Graphical representation




Elementary Discrete-Time Signals

- Unit sample sequence (impulse)

$$\delta(n) = \begin{cases} 1, & \text{for } n = 0 \\ 0, & \text{for } n \neq 0 \end{cases}$$


- Unit step signal

$$u(n) = \begin{cases} 1, & \text{for } n \geq 0 \\ 0, & \text{for } n < 0 \end{cases}$$



- Unit ramp signal

$$u_r(n) = \begin{cases} n, & \text{for } n \geq 0 \\ 0, & \text{for } n < 0 \end{cases}$$



- Note:

$$\begin{aligned} \delta(n) &= u(n) - u(n-1) = u_r(n+1) - 2u_r(n) + u_r(n-1) \\ u(n) &= u_r(n+1) - u_r(n) \end{aligned}$$

Exponential Signal

- Defined as
  - $x(n) = a^n, \forall n$
  - If a is real


    $\rightarrow$ x(n): real signal
  - If a is complex valued, it can be expressed as $a \equiv re^{j\theta}$

    $\rightarrow x(n) = r^n e^{j\theta n}$


    $= r^n(\cos\theta n + j\sin\theta n)$
    - x(n) can be expressed in two forms

$$\begin{cases} x_R(n) = r^n cos\theta n \\ x_I(n) = r^n sin\theta n \end{cases} \qquad \begin{cases} |x(n)| = r^n \\ \angle x(n) = \theta n \end{cases}$$

Exponential Signal




$x(n)=a^n$ (where a=0.9)




$x(n)=a^n$ (where a=1.5)

Exponential Signal



$x_r(n) = (1.5)^n \cos(\pi n/10)$



$x_r(n) = (0.9)^n \cos(\pi n/10)$

Classification of Discrete-Time Signals

- Energy Signal
- Power Signal
- Periodic Signal
- Aperiodic Signal

Energy Signal and Power Signal

- The energy E_x of the signal x(n)

$$E_x = \sum_{-\infty}^{+\infty} |x(n)|^2$$

  - If E_x is finite $(0 < E_x < \infty) \rightarrow$ x(n): Energy signal

- The average power P of the signal x(n)

$$P_x = \lim_{N\to\infty} \frac{1}{2N+1} \sum_{n=-N}^{N} |x(n)|^2$$

  - If P_x is finite $(0 < P_x < \infty) \rightarrow$ x(n): Power signal

- The signal energy of x(n) over a finite interval [-N, N]

  - The signal energy

$$E = \lim_{N\to\infty} E_N$$

$$E_N = \sum_{-N}^{N} |x(n)|^2$$

  - The signal power

$$P = \lim_{N\to\infty} \frac{1}{2N+1} E_N$$

Periodic Signal

- A signal x(n) is periodic with a period N (N>0) if and only if
  - $x(n + N) = x(n), \forall n$

- The signal energy is
  - finite if
    - $0 \le n \le N - 1$
    - x(n) is finite
  - Infinite if
    - $-\infty \le n \le +\infty$

Periodic signals are power signals.


- The signal power is finite

$$\mathbf{P} = \frac{\mathbf{1}}{\mathbf{N}} \sum_{\mathbf{n-0}}^{\mathbf{N-1}} |\mathbf{x(n)}|^{\mathbf{2}}$$


Signal Symmetry

x(n): real signal


- Symmetric signal (even signal)
  - $x(n) = x(-n), \forall n$
- Antisymmetric signal (odd signal)
  - $x(n) = -x(-n), \forall n$





- Any arbitrary signal can be expressed by the sum of two signal components
  - $x(n) = x_e(n) + x_o(n)$, where
  - Even signal component
    - $x_e(n) = (½)[x(n) + x(-n)]$
  - Odd signal component
    - $x_o(n) = (½)[x(n) - x(-n)]$



Quiz


x(n)
2
1
n
-7 -6 -5 -4 -3 -2 -1 0 1 2 3 4 5 6 7


x(n)
2
1
n
-7 -6 -5 -4 -3 -2 -1 0 1 2 3 4 5 6 7


x(n)
2
1
-7 -6 -5 -4 -2 -1 3 4 5 6 7

Simple Manipulations of Discrete-Time Signals


- Transformation of the independent variable (time)
  - Delay
  - Advance
  - Folding

- Addition, Multiplication, and scaling of sequences
  - Addition
  - Multiplication
  - Amplitude Scaling


Simple Manipulations of Discrete-Time Signals

- **Delay**: shifted in time by replacing n by n–k
  - $y(n) = x(n-k) \quad \forall k > 0$
  - y(n) is the time shift result in a delay of the signal by k units of time.
  - Graphically, delay corresponds to **shifting the signal to the RIGHT on the time axis**.

- **Advance**: shifted in time by replacing n by n+k
  - $y(n) = x(n+k) \quad \forall k > 0$
  - y(n) is the time shift result in an advance of the signal by k units of time.
  - Graphically, advance implies **shifting the signal to the LEFT on the time axis**.




Example




(a)

Delay



(b)


Advance




(c)

Simple Manipulations of Discrete-Time Signals


- **Folding**: replace n by –n
  - y(n) = x(–n)
  - y(n) is a folding or a reflection of the signal about the time origin n=0.




Example



(a)





(b)



Simple Manipulations of Discrete-Time Signals

- **Time scaling**: replace n by μn ($\mu \in Z$)
  - $y(n) = x(\mu n)$ where $\mu \in Z$
  - y(n) is the time scaling results of the signal x(n) with the coefficient μ





Simple Manipulations of Discrete-Time Signals

$x_1(n)$ và $x_2(n)$ n: $[-\infty,+\infty]$


- Addition
  - $y(n) = x_1(n) + x_2(n)$ n: $[-\infty,+\infty]$
- Multiplication
  - $y(n) = x_1(n).x_2(n)$ n: $[-\infty,+\infty]$
- Amplitude Scaling
  - $y(n) = ax_1(n)$ n: $[-\infty,+\infty]$

Exercise

- Given two digital signals $x_1 = \{1\ \ -1\hat{}\ \ 0\ \ 0\ \ 2\ \ -4\}$ and $x_2 = \{-2\ \ 3\hat{}\ \ 1\ \ 0\ \ -3\}$, determine
  - $y_1(n) = x_1(n\ -\ 2)$
  - $y_2(n) = x_2(-n + 1)$
  - $y_3(n) = y_1(n) + y_2(n)$
  - $y_4(n) = y_1(n).y_2(n)$



Discrete-Time Systems



- Input-Output Description

$$y(n) = T[x(n)]$$


  - Exact structure of system is unknown or ignored.
  - Black-Box representation

$$x(n) \xrightarrow{T} y(n)$$


Discrete-Time Systems

- **Block Diagram Representation**
  - Interconnect basic blocks to describe the system.


An Adder




A Signal Multiplier



A Unit Delay Element



A Constant Multiplier



A Unit Advance Element




Example

- A system is given by Input-Output Description as follows


$$y(n) = 2x(n) - 3x(n-1) + 1.5y(n-1) + 2y(n-2)$$

- The corresponding block diagram representation of the above system is



Exercise

- Write the input-output description corresponding to the system represented by the block diagram as the following Figure.



Classification of Discrete-Time Systems

- Why is this so important?
  - mathematical techniques developed to analyze systems are often contingent upon the general characteristics of the systems being considered.

- For a system to possess a given property, the property must hold for every possible input to the system.
  - to disprove a property, need a single counter-example.
  - to prove a property, need to prove for the general case.

Classification of Discrete-Time Systems

Common System Properties

- Static vs. Dynamic
- Time-Invariant vs. Time-Variant
- Linear vs. Non-linear
- Causal vs. Non-causal
- Stable vs. Unstable

Static vs. Dynamic Systems

- **A discrete-time system is called static or memoryless if its output at any instant n depends only on the input sample at time n (not on the past or future sample of the input); otherwise the system is said to be dynamic.**
  - NO Z^{-1} in block diagram representation
  - NO x(n–k) or y(n–k) in input-output description

- **Consider the general system**

$$y(n) = \mathcal{T}[x(n-N), x(n-N+1), \cdots, x(n-1), x(n), x(n+1), \cdots, x(n+M-1), x(n+M)], \quad N, M > 0$$

  - For N=M=0, y(n)=T[x(n)] → the system is **static**.
  - 0< N, M < ∞ → the system is said to be **dynamic** with finite memory.
  - N=∞ (M =∞) → the system is said to have infinite memory.

Static vs. Dynamic Systems

- Example: static (memoryless) or not?



Y	$y(n) = A\,x(n),\ A \neq 0$
Y	$y(n) = A\,x(n) + B,\ A, B, \neq 0$
Y	$y(n) = x(n)\cos(\frac{\pi}{25}(n-5))$
N	$y(n) = x(-n)$
N	$y(n) = x(n+1)$
N	$y(n) = \frac{1}{1-x(n+2)}$
Y	$y(n) = e^{3x(n)}$
N	$y(n) = \sum_{k=-\infty}^{n} x(k)$

Time-Invariant vs. Time-Variant Systems

- **Time-Invariant System**
  - input-output characteristics do not change with time
  - **Definition**
    - A relaxed system T is time-invariant or (shift invariant) if and only if

$$x(n) \xrightarrow{T} y(n) \Rightarrow x(n-k) \xrightarrow{T} y(n-k) \qquad \forall x(n), \forall k$$

    - In general, we can write the output as

$$y(n,k) = T[x(n-k)]$$

- **Time-Variant System**
  - The system does not satisfy the above definition.

Time-Invariant vs. Time-Variant Systems

- Example 1
  - The system is described by the input-output equation

$$y(n) = T[x(n)] = x(n) - x(n-1)$$

  - If the input is delayed by k units in time and applied to the system, then the output will be

$$y(n, k) = x(n-k) - x(n-k-1)$$

  - On the other hand, if we delay y(n) by k units in time, we obtain

$$y(n-k) = x(n-k) - x(n-k-1)$$

  - Obviously, y(n, k) and y(n – k) are identical. Therefore, the system is time-invariant.





Time-Invariant vs. Time-Variant Systems

- Example 2
  - The system is described by the input-output equation

$$y(n) = T[x(n)] = nx(n)$$

  - If the input is delayed by k units in time and applied to the system, then the output will be

$$y(n, k) = nx(n - k)$$

  - On the other hand, if we delay y(n) by k units in time, we obtain

$$y(n - k) = (n - k)x(n - k)$$

  - Obviously, y(n, k) and y(n – k) are **different** ($y(n,k) \neq y(n-k)$). Therefore, the system is **time-variant**.





Time-Invariant vs. Time-Variant Systems

- **Quiz:** time-invariant or not?



- Y — $y(n) = A\,x(n),\ A \neq 0$
- Y — $y(n) = A\,x(n) + B,\ A, B, \neq 0$
- N — $y(n) = x(n)\cos(\frac{\pi}{25}n)$
- N — $y(n) = x(-n)$
- Y — $y(n) = x(n+1)$
- Y — $y(n) = \frac{1}{1-x(n+2)}$
- Y — $y(n) = e^{3x(n)}$
- Y — $y(n) = \sum_{k=-\infty}^{n} x(k)$

Linear vs. Non-Linear Systems

- **Linear System**
  - Obey superposition principle
  - **Definition**
    - A system is linear if and only if:

$$T[a_1x_1(n) + a_2x_2(n)] = a_1T[x_1(n)] + a_2T[x_2(n)] \qquad \forall a_i, \forall x_i(n)$$

  - **Homogeneity**
    - Let $a_2 = 0 \rightarrow T[a_1x_1(n)] = a_1T[x_1(n)]$
  - **Additivity**
    - Let $a_1 = a_2 = 1 \rightarrow T[x_1(n) + x_2(n)] = T[x_1(n)] + T[x_2(n)]$
- **Non-Linear System**
  - The system does not obey superposition principle





Linear vs. Non-Linear Systems

- Note:

$$\text{Linearity} = \text{Homogeneity} + \text{Additivity}$$

  - If a system is not homogeneous, it is not linear.
  - If a system is not additive, it is not linear.

Linear vs. Non-Linear Systems

- **Example 1**
  - The system is described by the input-output equation

$$y(n) = T[x(n)] = nx(n)$$

  - For two input sequences $x_1(n)$ and $x_2(n)$, the corresponding output are:

$$y_1(n) = nx_1(n) \quad \text{(I)}$$
$$y_2(n) = nx_2(n) \quad \text{(II)}$$

  - A linear combination of the two input sequences in the output

$$y_3(n) = T[a_1x_1(n)+a_2x_2(n)] = n[a_1x_1(n)+a_2x_2(n)] = na_1x_1(n) + na_2x_2(n)$$

  - On the other hand, a linear combination of the two outputs (I)&(II) results in the output.

$$a_1y_1(n)+a_2y_2(n) = a_1nx_1(n) + a_2nx_2(n)$$

  - Obviously, the system **obeys** superposition principle. Therefore, the system is **Linear**.

Linear vs. Non-Linear Systems

- **Example 2**
  - The system is described by the input-output equation

$$y(n) = T[x(n)] = x^2(n)$$

  - For two input sequences $x_1(n)$ and $x_2(n)$, the corresponding output are:

$$y_1(n) = x_1^2(n) \quad \text{(I)}$$
$$y_2(n) = x_2^2(n) \quad \text{(II)}$$

  - A linear combination of the two input sequences in the output

$$y_3(n) = T[a_1x_1(n)+a_2x_2(n)] = [a_1x_1(n)+a_2x_2(n)]^2 \quad \text{(III)}$$

  - On the other hand, a linear combination of the two outputs (I)&(II) results in the output.

$$a_1y_1(n)+a_2y_2(n)=a_1x_1^2(n) + a_2x_2^2(n) \quad \text{(IV)}$$

  - From (III) & (IV), the system **does not** obey superposition principle. Therefore, the system is **Non-Linear**.

Linear vs. Non-Linear Systems

- **Quiz:** Linear or not?



Y	$y(n) = A\,x(n),\ A \neq 0$
N	$y(n) = A\,x(n) + B,\ A, B, \neq 0$
Y	$y(n) = x(n)\cos(\frac{\pi}{25}n)$
Y	$y(n) = x(-n)$
Y	$y(n) = x(n+1)$
N	$y(n) = \frac{1}{1-x(n+2)}$
N	$y(n) = e^{3x(n)}$
Y	$y(n) = \sum_{k=-\infty}^{n} x(k)$

Causal vs. Noncausal Systems

- Causal System
  - Definition
    - A system T is said to be causal if the output of the system at any time n [i.e. y(n)] **depends only on present and past inputs** [i.e. x(n), x(n – 1), x(n – 2) …]. In mathematical term, the output of a causal system satisfies an equation of the form

$$y(n) = F[x(n), x(n–1), x(n–2), \ldots]$$

- Noncausal System
  - The system is said to be Noncausal if the output of the system does not abbey the above definition.

Causal vs. Noncausal Systems

- **Quiz:** Causal or not?



Y	$y(n) = A\,x(n),\ A \neq 0$
Y	$y(n) = A\,x(n) + B,\ A, B, \neq 0$
Y	$y(n) = x(n)\cos(\frac{\pi}{25}(n+1))$
N	$y(n) = x(-n)$
N	$y(n) = x(n+1)$
N	$y(n) = \frac{1}{1-x(n+2)}$
Y	$y(n) = e^{3x(n)}$
Y	$y(n) = \sum_{k=-\infty}^{n} x(k)$


Stable vs. Unstable Systems

- **Stable System**
  - **BIBO:** Bounded Input-Bounded Output
  - **Definition**
    - A relaxed system is said to be BIBO Stable if and only if every bounded input produces a bounded output.

$$\forall x(n): \ |x(n)| \leq M_x < \infty \quad \rightarrow |y(n)| = |T[x(n)]| \leq M_y < \infty$$

- **Unstable System**
  - A system is said to be unstable if it does not satisfy the above definition.

Discrete-Time Bounded Signals



Stable vs. Unstable Systems

- **Quiz:** Stable or not?



Y	$y(n) = A\,x(n),\ A \neq 0$
Y	$y(n) = A\,x(n) + B,\ A, B, \neq 0$
Y	$y(n) = x(n)\cos(\frac{\pi}{25}n)$
Y	$y(n) = x(-n)$
Y	$y(n) = x(n+1)$
N	$y(n) = \frac{1}{1-x(n+2)}$
Y	$y(n) = e^{3x(n)}$
N	$y(n) = \sum_{k=-\infty}^{n} x(k)$

Final Remarks

- For a system to possess a given property, the property must hold for **every** possible **input** and **parameter** of the system.
  - To disprove a property, need a **single counter-example.**
  - To prove a property, need to **prove for the general case.**

In-Class Problems


- Investigate all the properties of the following systems
  - $y_1(n) = x(n) + nx(n+1)$
  - $y_2(n) = x(2n)$



Interconnection of Discrete-Time Systems

- Discrete-time systems can be interconnected to form larger systems.

- 2 basic interconnections
  - Cascade




$$\left.\begin{aligned} y_1(n) &= T_1[x(n)] \\ y(n) &= T_2[y_1(n)] \end{aligned}\right\} \qquad \begin{aligned} y(n) &= T_2[T_1[x(n)]] \\ &= T_c[x(n)] \end{aligned} \qquad \text{với } T_c \equiv T_2T_1$$

  - $T_2T_1 \neq T_1T_2$
  - If both T_1 and T_2 are linear and time-invariant (LTI).
    - $T_c = T_2T_1$: time-invariant *system*
    - $T_2T_1 = T_1T_2$

  - Parallel

$$\begin{aligned} y(n) &= T_1[x(n)] + T_2[x(n)] \\ &= (T_1+T_2)[x(n)] \\ &= T_p[x(n)] \quad \text{where } T_p \equiv T_1+T_2 \end{aligned}$$



Analysis of Discrete-Time LTI Systems

- **Techniques for the Analysis of Linear System**
  1. Directly solve the input-output equation of the system.
  2. **Decompose or resolve the input signal into a sum of elementary signals** that are selected so that the response of the system to each signal component is predetermined.
     - Then, using the **linearity**, the response of the system to the given input signals are the summation of the responses of the system to each elementary signals.

- **Example**
  - Decompose the input signal
    - where $y_k(n) = T[x_k(n)]$

$$x(n) = \sum_k c_k x_k(n)$$

$$\begin{aligned} y(n) &= T[x(n)] \\ &= T[\sum_k c_k x_k(n)] \\ &= \sum_k c_k T[x_k(n)] \\ \Rightarrow y(n) &= \sum_k c_k y_k(n) \end{aligned}$$

Resolution of A Discrete-Time Signal Into Impulses

- Resolution of A Discrete-Time Signal Into Impulses
  - Select the elementary signals
    - $x_k(n) = \delta(n-k)$
  - And
    - $x(n)\delta(n-k) = x(k)\delta(n-k) \qquad \forall k$
  - Sum all the product sequences, the result will be a sequence equal to sequence x(n)
  - Example

$$x(n) = \sum_{k=-\infty}^{\infty} x(k)\delta(n-k)$$

$$x(n) = \{2 \quad 4 \quad \underset{\uparrow}{3} \quad 1\}$$

$$x(n) = 2\delta(n+2) + 4\delta(n+1) + 3\delta(n) + \delta(n-1)$$

Response of LTI Systems

- The response **y(n,k)** of the system to the input unit sample sequence at n=k is denoted **h(n,k)**
  - $y(n, k) \equiv h(n, k) = T[\delta(n-k)]$ $\quad -\infty < k < \infty$
    - n: time index
    - k: position of corresponding impulse

- If the impulse at the input is scaled by an amount $c_k = x(k)$, the response of the system is also correspondingly scaled by $c_k h(n, k) = x(k)h(n, k)$

The Convolution Sum

The Convolution Sum



$$
\begin{aligned}
y(n) &= T[x(n)] \\
&= T[\sum_{k=-\infty}^{\infty} x(k)\delta(n-k)] \\
&= \sum_{k=-\infty}^{\infty} x(k)T[\delta(n-k)] \\
&= \sum_{k=-\infty}^{\infty} x(k)h(n,k)
\end{aligned}
$$

- For LTI system, if $h(n) = T[\delta(n)]$ then $h(n-k) = T[\delta(n-k)]$

$$y(n) = \sum_{k=-\infty}^{\infty} x(k)h(n-k)$$

The Convolution Sum

- Procedure to determine the response of the system at time instant n_0.

$$y(n_0) = \sum_{k=-\infty}^{\infty} x(k)h(n_0 - k)$$

1. **Folding**: $h(k) \rightarrow h(-k)$
2. **Shifting**: $h(-k) \rightarrow h(-k + n_0)$: shifting $h(-k)$ n_0 units to the **RIGHT** or **LEFT** if n_0 is **positive** or **negative** respectively.
3. **Multiplication**: $v_{n0}(k) = x(k)\, h(-k + n_0)$
4. **Summation**: sum all the sequences $v_{n0}(k)$

The Convolution Sum

- **Example**
  - The impulse response of a LTI system is

$$h(n) = \{1, \underset{\uparrow}{2}, 1, -1\}$$

  - Determine the response of the system to the input signal

$$x(n) = \{\underset{\uparrow}{1}, 2, 3, 1\}$$

$$y(n) = \sum_{k=-\infty}^{\infty} x(k)h(n-k)$$

The Convolution Sum

- In the convolution equation, if replacing m=n–k (i.e. k=n–m), we obtain

$$y(n) = \sum_{m=-\infty}^{\infty} x(n-m)h(m) = \sum_{k=-\infty}^{\infty} x(n-k)h(k)$$


  - Although, the above output y(n) and the result of convolution sum are identical. They are in different arrangement.
  - If

$$\left.\begin{aligned} v_n(k) &= x(k)h(n-k) \\ w_n(k) &= x(n-k)h(k) \end{aligned}\right\} \quad v_n(k) = w_n(n-k)$$

$$\Rightarrow y(n) = \sum_{k=-\infty}^{\infty} v_n(k) = \sum_{k=-\infty}^{\infty} w_n(n-k)$$

The Convolution Sum

- Summary




h(n) : The impulse response of the LTI system

$$y(n) = x(n) * h(n) = \sum_{k=-\infty}^{\infty} x(k)h(n-k)$$


$$y(n) = h(n) * x(n) = \sum_{k=-\infty}^{\infty} x(n-k)h(k)$$

Properties of Convolution

- Commutative $x(n)*h(n) = h(n)*x(n)$




- Associative $[x(n)*h_1(n)]*h_2(n) = x(n)*[h_1(n)*h_2(n)]$



Properties of Convolution

- **Distributive**

$$x(n)*[h_1(n) + h_2(n)] = x(n)*h_1(n) + x(n)*h_2(n)$$



- **Example**: Determine the response of the following systems using convolution.
  - $x(n) = a^n u(n)$ and $h(n) = b^n u(n)$ for two cases **a=b** and **a≠b**
  - $x(n) = \{\ldots 0, 1^*, 2, 1, 1, 0 \ldots\}$ and $h(n) = \delta(n) - \delta(n-1) + \delta(n-4) + \delta(n-5)$

Finite vs. Infinite Impulse Response

- **FIR** (Finite-duration Impulse Response)
  - $h(n) = 0\ \forall n: n < 0$ and $n \geq M$

$$y(n) = \sum_{k=0}^{M-1} h(k)x(n-k)$$

  - An FIR system has a finite memory of length-M samples.

- **IIR** (Infinite-duration Impulse Response)
  - For a causal system

$$y(n) = \sum_{k=0}^{\infty} h(k)x(n-k)$$

  - An IIR system has an infinite memory.

Recursive Discrete-Time Systems

- The cumulative average of a signal x(n) in the interval $0 \le k \le n$.


$$y(n) = \frac{1}{n+1}\sum_{k=0}^{n} x(k)$$

  - The computation y(n) requires the storage of all the input samples x(k) for $0 \le k \le n \Rightarrow$ **since n is increasing, our memory requirements grow linearly with time.**

  - y(n) can be computed by using recursive method

$$(n+1)y(n) = \sum_{k=0}^{n-1} x(k) + x(n) = ny(n-1) + x(n)$$

$$\Rightarrow y(n) = \frac{n}{n+1}y(n-1) + \frac{1}{n+1}x(n)$$




  - A system whose output y(n) at time n depends on any number of past output values y(n – 1), y(n – 2), …is called a **recursive system**.

Nonrecursive Discrete-Time Systems

- The system is **nonrecursive** if

$$y(n) = F[x(n), x(n-1), \ldots, x(n-M)]$$

- Recursive vs. Nonrecursive Systems




- **Notes**
  - If the system is recursive, to compute y(n), we first need to compute all previous (past) values y(0), y(1), … y(n – 1).
  - If the system is nonrecursive, we can compute the output y(n) immediately without having past values y(n – 1), y(n – 2), …
  - Recursive System = Sequential System
  - Nonrecursive system = Combinational System.


Structure for the Realization of LTI Systems

- Given first-order system

$y(n) = a_1 y(n-1) + b_0 x(n) + b_1 x(n-1)$

- Structures






Structure for the Realization of LTI Systems


$$y(n) = -\sum_{k=1}^{N} a_k y(n-k) + \sum_{k=0}^{M} b_k x(n-k)$$

Direct Form I Structure



#memory: M+N

Direct Form II Structure



#memory: Max(M,N)

References

- Textbook "Digital Signal Processing: Principles, Algorithms, and Applications", 4th Edition, Prentice Hall.
  - John G. Proakis, Dimitris G. Manolakis

- Lecture Notes – Digital Signal Processing
  - Professor Deepa Kundur (University of Toronto)
  - http://www.comm.utoronto.ca/~dkundur/course/ece-455-digital-signal-processing/#lectures