

Wang 700 Boards

Slot	P/N	Wang Title	Description
#4	5887	MEMORY CORE 32x32x8	1Kx8 core memory array, physically organized (addressed) as 32x32x8.
#3	5917	X & Y CORE DRIVER	High-current drivers for core memory, with decoders for L,M,N registers (core address).
#8	5918	ALU	4-bit BCD/Binary Arithmetic-Logic Unit
#6	5919	BUS-1	Implements A-Bus and B-Bus
#7(?)	5920	BUS-2	Implements S,T,U,V registers and corresponding part of A-Bus
#5	5921	SENCE AMP. OSC COREBIT DRIVE	Implements RA,RB registers and analog interface to core memory. Also implements main system timing clock.
#10	5922	ROM DECODER	Latches microcode instruction and decodes operand fields (excludes JH,JL,JAD)
#9(?)	5923	JH,JL,JAD (ROM ADDRESS)	Latches JH,JL,JAD and generates next address
#1(?)	5924	TAPE IN & OUT, NIXIE TUBE DECODER	Analog interface to tape read/write head. Refresh decoders for X and Y displays.
#2	5926	KBD, CORE ADDRESS, KEYBOARD REG.	Implements KA,KB registers with I/O Port input override. Digital Tape Data interface. Implements L,M,N registers (core memory address). Only bits 0,1 of L are implemented (1Kx8 core memory).
#11	5927	GENERAL I/O	Implementation of GIOA,GIOB registers and most peripheral control signals. Latching of keyboard special function keys.
#12	5928	BUFFER BOARD	Drivers for signals requiring more current, mostly I/O related.
(#3)	5929	(see 2917)	Appears to be revision/expansion of 2917 (for model 720 – 2Kx8 core). Also appears to implement bit 2 of L register (needed for 2K core).
(#9?)	5930	(see 5923)	Seems to be a revision of 5923, unknown changes. Appears to be functionally identical.
(#4)	6038	MEMORY CORE 32x64x8	2Kx8 core memory array, physically organized (addressed) as 32x64x8. Combined with 5929 to replace (upgrade) 5887/5917.
L505X	5945-X	“X” NIXIE CONTROL ANODE SWITCH	Provides the high voltage drivers for the “X” display Nixie tubes. Connects directly to “X” display assembly through cable assembly.
L505Y	5945-Y	“Y” NIXIE CONTROL ANODE SWITCH	Provides the high voltage drivers for the “Y” display Nixie tubes. Connects directly to “Y” display assembly through cable assembly. Slot does not have “BL” (blink/flash) signal connected.
X/Y	5936	NIXIE DISPLAY	Nixie tube assemblies for “X” and “Y” displays. Two units total.

Numeric slots are number from front to back. Slot #1 is immediately behind the X/Y Nixie displays.