



Smoke Detector

NB802 conventional photoelectric smoke detectors are state-of-the-art detectors suitable for connection to conventional fire detection control and indicating equipment, or to addressable fire detection control and indicating equipment that can accept conventional type detectors.

Advanced electronics in conjunction with a photoelectric smoke sensing chamber and an electronic thermistor provide early detection of fire and high immunity against unwanted alarms. The heat sensor provides fixed-temperature operation when the response threshold value is exceeded.

The NB802 smoke detectors are available in a wide range of variants to suit many applications.

- Dual photoelectric smoke and heat sensors to detect either smoke, heat or a combination of the phenomena.
- Advanced algorithms provide excellent detection discrimination
- High immunity against unwanted alarms
- Stable photoelectric smoke sensing chamber. No adjustment or replacement required
- Easy installation. No programming required
- Sleek low-profile housing design
- Dual LEDs for 360° visibility
- 2-wire and 4-wire models for DC 12 V or DC 24 V operation
- 4-wire models include a N/C or N/O alarm relay output
- 4-wire models available with auto-reset function
- 4-wire models available with an internal sounder
- Connects to zone monitor for use with addressable control and indicating equipment

Specifications Summary

Operating voltage ^a	DC (12 ~ 28) V
Operating voltage ^b	DC (10.2 ~ 13.8) V
Operating voltage ^c	DC (20.4 ~ 27.6) V
Start-up current	≤ 200 µA
Standby current	≤ 60 µA
Alarm current (max) ^d	(35 ~ 80) mA
Reset voltage	≤ 1 V
Reset time	≤ 3 s
Alarm response threshold (smoke)	(0.10 ~ 0.16) dB/m (1.51 ~ 2.73) % / ft obscuration
Operating temperature	-0 °C ~ +50 °C
Operating humidity	0 % ~ 95 % RH, non-condensing
Alarm indicator	Two continuous emitting red LEDs
Dimensions (excluding contacts)	Φ 100 mm × 35 mm
Ingress protection rating	IP-42

^a NB802-2 and NB802-2-LED

^b NB802-4-12, NB802-4-AR-12, NB802-4B-12 and NB802-4B-AR-12

^c NB802-4-24, NB802-4B-24, NB802-4B-AR-24, and NB802-4AR-24

^d Depends on model

- For complete specifications, see product datasheet 31-0074.

Ordering Information

	2-Wire	4-wire	Nominal Operating Voltage	Remote LED Output	Alarm Relay Output	Auto Reset	Sounder
NB802-2	✓	-	DC 24 V	-	-	-	-
NB802-2-LED	✓	-	DC 24 V	✓	-	-	-
NB802-4-12	-	✓	DC 12 V	-	✓	-	-
NB802-4-24	-	✓	DC 24 V	-	✓	-	-
NB802-4-AR-12	-	✓	DC 12 V	-	✓	✓	-
NB802-4-AR-24	-	✓	DC 24 V	-	✓	✓	-
NB802-4B-12	-	✓	DC 12 V	-	✓	-	✓
NB802-4B-24	-	✓	DC 24 V	-	✓	-	✓
NB802-4B-AR-12	-	✓	DC 12 V	-	✓	✓	✓
NB802-4B-AR-24	-	✓	DC 24 V	-	✓	✓	✓

