

Control Commands

RQ25K Series

Model No. PT-RQ25K
PT-SRQ25KC

PT-RZ24K
PT-SRZ24KC

PT-RQ18K
PT-SRQ18KC

PT-RZ17K
PT-SRZ17KC



- Please refer to the Operating Instructions for the serial command format, limitations, connection and other details.
- シリアルコマンドのフォーマット、制限事項、接続方法およびその他詳細につきましては、各モデルの取扱説明書をご覧ください。
- 有关串行控制命令的格式、限制事项、连接方法以及其他详情、请参阅各机型的使用说明书。

Panasonic

(2023-06)

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
BASIC OPERATION REMOTE CONTROL	POWER	ON OFF (STANDBY)		PON POF	QPW	001 000	✓ ✓	✓ ✓
	INPUT SELECT	HDMI1		IIS:HD1	QIN	HD1	✓	✓
		HDMI2		IIS:HD2		HD2	✓	✓
		DisplayPort		IIS:DP1		DP1	✓	✓
	INPUT SELECT (SDM SLOT)	SLOT1 : 12G SDI		IIS:DM1,SD1	QIN	DM1,SD1	✓	✓
		SLOT1 : Digital Link		IIS:DM1,DL1		DM1,DL1	✓	✓
		SLOT1 : PressIT		IIS:DM1,WP1		DM1,WP1	✓	✓
		SLOT1 : 3rd Party Board		IIS:DM1,TP1		DM1,TP1	✓	✓
		SLOT1 : 12G SDI OPT1		IIS:DM1,OP1		DM1,OP1	✓	✓
		SLOT1 : 12G SDI OPT2		IIS:DM1,OP2		DM1,OP2	✓	✓
	INPUT SELECT (SDM SLOT : DIGITAL LINK)	COMPUTER1		IIS:DM1,DL1:PC1	QIN	DM1,DL1:PC1	✓	✓
		COMPUTER2		IIS:DM1,DL1:PC2		DM1,DL1:PC2	✓	✓
		VIDEO		IIS:DM1,DL1:VID		DM1,DL1:VID	✓	✓
		HDMI1		IIS:DM1,DL1:HD1		DM1,DL1:HD1	✓	✓
		HDMI2		IIS:DM1,DL1:HD2		DM1,DL1:HD2	✓	✓
		S-VIDEO		IIS:DM1,DL1:SVD		DM1,DL1:SVD	✓	✓
	FREEZE	OFF		OFZ:0	QFZ	0	✓	✓
		ON		OFZ:1		1	✓	✓
	MENU KEY			OMN			✓	✓
	ENTER KEY			OEN			✓	✓
	UP KEY			OCU			✓	✓
	DOWN KEY			OCD			✓	✓
	LEFT KEY			OCL			✓	✓
	RIGHT KEY			OCR			✓	✓
	DEFAULT KEY			OST			✓	✓
	SHUTTER	OFF		OSH:0	QSH	0	✓	✓
		ON		OSH:1		1	✓	✓
	SHUTTER(Toggle)	OFF		OSH	QSH	0	✓	✓
		ON				1	✓	✓
	FUNCTION KEY			FC1			✓	✓
	SYSTEM SELCTOR KEY			OSL			✓	✓
	ASPECT KEY			VS1			✓	✓
	NUMERIC KEY	0		ONK:0			✓	✓
		1		ONK:1			✓	✓
		2		ONK:2			✓	✓
		3		ONK:3			✓	✓
		4		ONK:4			✓	✓
		5		ONK:5			✓	✓
		6		ONK:6			✓	✓
		7		ONK:7			✓	✓
		8		ONK:8			✓	✓
		9		ONK:9			✓	✓
	LENS HOME POSITION	EXECUTE		VXX:LNSI1=+00001			✓	✓
	ACTIVE FOCUS OPTIMIZER-ACTIVE FOCUS	OFF		VXX:AFOI1=+00000	QVX:AFOI1	AFOI1=+00000	✓	✓
		ON		VXX:AFOI1=+00001		AFOI1=+00001	✓	✓
	ACTIVE FOCUS OPTIMIZER-FOCUS OFFSET BRIGHT	-00299		VXX:FOBI1=-00299	QVX:FOBI1	FOBI1=-00299	-299	-299
		+00299		VXX:FOBI1=+00299		FOBI1=+00299	+299	+299
	ACTIVE FOCUS OPTIMIZER-FOCUS OFFSET DARK	-00299		VXX:FODI1=-00299	QVX:FODI1	FODI1=-00299	-299	-299
		+00299		VXX:FODI1=+00299		FODI1=+00299	+299	+299
	ACTIVE FOCUS OPTIMIZER-INITILIZE	EXECUTE		VXX:FOII1=+00001			✓	✓
LENS SHIFT-HORIZONTAL	SLOW+		VXX:LNSI2=+00000			✓	✓	
	SLOW-		VXX:LNSI2=+00001			✓	✓	
	NORMAL+		VXX:LNSI2=+00100			✓	✓	
	NORMAL-		VXX:LNSI2=+00101			✓	✓	
	FAST+		VXX:LNSI2=+00200			✓	✓	
	FAST-		VXX:LNSI2=+00201			✓	✓	
LENS SHIFT-VERTICAL	SLOW+		VXX:LNSI3=+00000			✓	✓	
	SLOW-		VXX:LNSI3=+00001			✓	✓	
	NORMAL+		VXX:LNSI3=+00100			✓	✓	
	NORMAL-		VXX:LNSI3=+00101			✓	✓	
	FAST+		VXX:LNSI3=+00200			✓	✓	
	FAST-		VXX:LNSI3=+00201			✓	✓	
LENS FOCUS	SLOW+		VXX:LNSI4=+00000			✓	✓	
	SLOW-		VXX:LNSI4=+00001			✓	✓	
	NORMAL+		VXX:LNSI4=+00100			✓	✓	
	NORMAL-		VXX:LNSI4=+00101			✓	✓	
	FAST+		VXX:LNSI4=+00200			✓	✓	
	FAST-		VXX:LNSI4=+00201			✓	✓	
LENS ZOOM	SLOW+		VXX:LNSI5=+00000			✓	✓	
	SLOW-		VXX:LNSI5=+00001			✓	✓	
	NORMAL+		VXX:LNSI5=+00100			✓	✓	
	NORMAL-		VXX:LNSI5=+00101			✓	✓	
	FAST+		VXX:LNSI5=+00200			✓	✓	
	FAST-		VXX:LNSI5=+00201			✓	✓	
LENS POSITION	HORIZONTAL(H)		VXX:LNSI7=*HORIZONTAL	QVX:LNSI7 QVX:LNSI8 QVX:LNSI9 QVX:LNSIA QVX:LNSSB QVX:LNSSC QVX:LNSSD	LNSI7=*HORIZONTAL	✓	✓	
	VERTICAL(V)		VXX:LNSI8=*VERTICAL		LNSI8=*VERTICAL	✓	✓	
	FOCUS(F)		VXX:LNSI9=*FOCUS		LNSI9=*FOCUS	✓	✓	
	ZOOM(Z)		VXX:LNSIA=*ZOOM		LNSIA=*ZOOM	✓	✓	
	H/V		VXX:LNSSB=*H*V		LNSSB=*H*V	✓	✓	
	H/V F		VXX:LNSSC=*H*V*F		LNSSC=*H*V*F	✓	✓	
	H/V F Z		VXX:LNSSD=*H*V*F*Z		LNSSD=*H*V*F*Z	✓	✓	
	*HORIZONTAL(H)	min.	-*****		-*****	*by lens type(-4960)	*by lens type(-4960)	
		max.	+*****		+*****	*by lens type(+4960)	*by lens type(+4960)	
	*VERTICAL(V)	min.	-*****		-*****	*by lens type(-6300)	*by lens type(-6300)	
		max.	+*****		+*****	*by lens type(+6300)	*by lens type(+6300)	
	*FOCUS(F)	min.	+*****		+*****	0	0	
		max.	+*****		+*****	3520	3520	
*ZOOM(Z)	min.	+*****	+*****	*by lens type	*by lens type			
	max.	+*****	+*****	*by lens type	*by lens type			
STATUS KEY			STS			✓	✓	
LENS FOCUS KEY			OLF			✓	✓	
LENS SHIFT KEY			OLH			✓	✓	
LENS ZOOM KEY			OLZ			✓	✓	
DIGITAL LINK KEY			DLK			✓	✓	
INPUT MENU KEY			IPT			✓	✓	
SELF DIAGNOSIS				QVX:ERRS1 QVX:ERRS2	ERRS1=***** ERRS2=*****	✓ ✓	✓ ✓	
	PICTURE MODE	DYNAMIC		VPM:DYN	QPM	DYN	✓	✓
		NATURAL		VPM:NAT		NAT	✓	✓
		STANDARD		VPM:STD		STD	✓	✓
		CINEMA		VPM:CIN		CIN	✓	✓
		GRAPHIC		VPM:GRA		GRA	✓	✓
		DICOM SIM.		VPM:DIC		DIC	✓	✓
		USER		VPM:USR		USR	✓	✓
	PICTURE MODE-NAME SETTING USER	PICTUREMODE		VXX:NCGS0=PICTUREMODE	QVX:NCGS0	NCGS0=PICTUREMODE	✓	✓
	PICTURE MODE-NAME CLEAR USER	PICTUREMODE		VXX:NCLI0=+00000			✓	✓
	CONTRAST	+1		VCN:001	QVR	001	✓	✓
		+63		VCN:063		063	✓	✓
	BRIGHTNESS	+1		VBR:001	QVB	001	✓	✓
		+63		VBR:063		063	✓	✓
	COLOR	+1		VCO:001	QVC	001	✓	✓
		+63		VCO:063		063	✓	✓
	TINT	+1		VTN:001	QVT	001	✓	✓
		+63		VTN:063		063	✓	✓
	SHARPNESS	0		VSR:000	QVS	000	✓	✓
		15		VSR:015		015	✓	✓
COLOR TEMPERATURE	USER1(USER)		OTE:04	QTE	4	✓	✓	
	USER2		OTE:09		9	✓	✓	
	DEFAULT		OTE:10		10	✓	✓	
	3200K		OTE:3200		3200	✓	✓	
	3300K		OTE:3300		3300	✓	✓	
	9200K		OTE:9200		9200	✓	✓	

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
PICTURE		9300K		OTE:9300		9300	✓	✓
		9400K		OTE:9400		9400	✓	✓
		12900K		OTE:12900		12900	✓	✓
		13000K		OTE:13000		13000	✓	✓
	COLOR TEMP-NAME SETTING USER1	COLORTEMP1		VXX:NCGS1=COLORTEMP1	QVX:NCGS1	NCGS1=COLORTEMP1	✓	✓
	COLOR TEMP-NAME SETTING USER2	COLORTEMP2		VXX:NCGS3=COLORTEMP2	QVX:NCGS3	NCGS3=COLORTEMP2	✓	✓
	COLOR TEMP-NAME CLEAR USER1	COLORTEMP1		VXX:NCLI1=+00000			✓	✓
	COLOR TEMP-NAME CLEAR USER2	COLORTEMP2		VXX:NCLI3=+00000			✓	✓
	WHITE BALANCE LOW-RED	-127		VOR:001	QOR	001	✓	✓
		+127		VOR:255		255	✓	✓
	WHITE BALANCE LOW-GREEN	-127		VOG:001	QOG	001	✓	✓
		+127		VOG:255		255	✓	✓
	WHITE BALANCE LOW-BLUE	-127		VOB:001	QOB	001	✓	✓
		+127		VOB:255		255	✓	✓
	WHITE BALANCE HIGH-RED	0		VHR:000	QHR	000	✓	✓
		+255		VHR:255		255	✓	✓
	WHITE BALANCE HIGH-GREEN	0		VHG:000	QHG	000	✓	✓
		+255		VHG:255		255	✓	✓
	WHITE BALANCE HIGH-BLUE	0		VHB:000	QHB	000	✓	✓
		+255		VHB:255		255	✓	✓
	GAMMA	1.0		VGA:1.0	QGA	1.0	✓	✓
		1.8		VGA:1.8		1.8	✓	✓
		2.0		VGA:2.0		2.0	✓	✓
		2.1		VGA:2.1		2.1	✓	✓
		2.2		VGA:2.2		2.2	✓	✓
		2.3		VGA:2.3		2.3	✓	✓
		2.4		VGA:2.4		2.4	✓	✓
		2.5		VGA:2.5		2.5	✓	✓
		2.6		VGA:2.6		2.6	✓	✓
		2.7		VGA:2.7		2.7	✓	✓
		2.8		VGA:2.8		2.8	✓	✓
		USER1		VGA:US1		US1	✓	✓
		USER2		VGA:US2		US2	✓	✓
		DICOM		VGA:DIC		DIC	✓	✓
		HDR HLG		VGA:HD1		HD1	✓	✓
		HDR ST2048-500		VGA:HD2		HD2	✓	✓
		HDR ST2048-1000		VGA:HD3		HD3	✓	✓
		DEFAULT		VGA:DEF		DEF	✓	✓
	GAMMA-HDR HLG SYSTEM GAMMA	min.	(0.1step)	VXX:HLGS1=+1.00	QVX:HLGS1	HLGS1=1.00	✓	✓
		max.		VXX:HLGS1=+1.62		HLGS1=1.62	✓	✓
	GAMMA-NAME SETTING USER1	GAMMAUSER1		VXX:NCGS2=GAMMAUSER1	QVX:NCGS2	NCGS2=GAMMAUSER1	✓	✓
	GAMMA-NAME SETTING USER2	GAMMAUSER2		VXX:NCGS4=GAMMAUSER2	QVX:NCGS4	NCGS4=GAMMAUSER2	✓	✓
	GAMMA-NAME CLEAR USER1	GAMMAUSER1		VXX:NCLI2=+00000			✓	✓
	GAMMA-NAME CLEAR USER2	GAMMAUSER2		VXX:NCLI4=+00000			✓	✓
	DAYLIGHT VIEW FRONT INSTALL	OFF		VXX:DLVI0=+00000	QVX:DLVI0	DLVI0=+00000	✓	✓
		AUTO(1)		VXX:DLVI0=+00001		DLVI0=+00001	✓	✓
		ON(2)		VXX:DLVI0=+00002		DLVI0=+00002	✓	✓
		ON(3)		VXX:DLVI0=+00003		DLVI0=+00003	✓	✓
		4		VXX:DLVI0=+00004		DLVI0=+00004	✓	✓
		5		VXX:DLVI0=+00005		DLVI0=+00005	✓	✓
		6		VXX:DLVI0=+00006		DLVI0=+00006	✓	✓
	NOISE REDUCTION	OFF		VNS:0	QNS	0	✓	✓
		1		VNS:1		1	✓	✓
		2		VNS:2		2	✓	✓
		3		VNS:3		3	✓	✓
		4		VNS:4		4	✓	✓
		5		VNS:5		5	✓	✓
		6		VNS:6		6	✓	✓
	DYNAMIC CONTRAST/IRIS	OFF		OAI:0	QAI	0	✓	✓
		1		OAI:1		1	✓	✓
		2		OAI:2		2	✓	✓
		3		OAI:3		3	✓	✓
		USER		OAI:4		4	✓	✓
	DYNAMIC CONTRAST/AUTO IRIS (AUTO CONTRAST)	OFF		OAI:A000	QAI:A	000	✓	✓
		1		OAI:A001		001	✓	✓
		255		OAI:A255		255	✓	✓
	DYNAMIC CONTRAST (BRIGHT SIGNAL LEVEL)	6%		VXX:DYCI1=+00006	QVX:DYCI1	00006	✓	✓
		50%		VXX:DYCI1=+00050		00050	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT TIMER)	DISABLE		VXX:DYCS2=OFF	QVX:DYCS2	OFF	✓	✓
		0.0s		VXX:DYCS2=0.0		0.0	✓	✓
		10.0s		VXX:DYCS2=10.0		10.0	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT SIGNAL LEVEL)	0		VXX:DYCI3=+00000	QVX:DYCI3	00000	✓	✓
		5		VXX:DYCI3=+00005		00005	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT FADE-IN)	0.0s(OFF)		VXX:DYCS4=0.0	QVX:DYCS4	DYCS4=0.0	✓	✓
		0.5s		VXX:DYCS4=0.5		DYCS4=0.5	✓	✓
		1.0s		VXX:DYCS4=1.0		DYCS4=1.0	✓	✓
		1.5s		VXX:DYCS4=1.5		DYCS4=1.5	✓	✓
		2.0s		VXX:DYCS4=2.0		DYCS4=2.0	✓	✓
		2.5s		VXX:DYCS4=2.5		DYCS4=2.5	✓	✓
		3.0s		VXX:DYCS4=3.0		DYCS4=3.0	✓	✓
		3.5s		VXX:DYCS4=3.5		DYCS4=3.5	✓	✓
		4.0s		VXX:DYCS4=4.0		DYCS4=4.0	✓	✓
		5.0s		VXX:DYCS4=5.0		DYCS4=5.0	✓	✓
		7.0s		VXX:DYCS4=7.0		DYCS4=7.0	✓	✓
		10.0s		VXX:DYCS4=10.0		DYCS4=10.0	✓	✓
	DYNAMIC CONTRAST (LIGHTS OUT FADE-OUT)	0.0s(OFF)		VXX:DYCS5=0.0	QVX:DYCS5	DYCS5=0.0	✓	✓
		0.5s		VXX:DYCS5=0.5		DYCS5=0.5	✓	✓
		1.0s		VXX:DYCS5=1.0		DYCS5=1.0	✓	✓
		1.5s		VXX:DYCS5=1.5		DYCS5=1.5	✓	✓
		2.0s		VXX:DYCS5=2.0		DYCS5=2.0	✓	✓
		2.5s		VXX:DYCS5=2.5		DYCS5=2.5	✓	✓
		3.0s		VXX:DYCS5=3.0		DYCS5=3.0	✓	✓
		3.5s		VXX:DYCS5=3.5		DYCS5=3.5	✓	✓
		4.0s		VXX:DYCS5=4.0		DYCS5=4.0	✓	✓
		5.0s		VXX:DYCS5=5.0		DYCS5=5.0	✓	✓
		7.0s		VXX:DYCS5=7.0		DYCS5=7.0	✓	✓
		10.0s		VXX:DYCS5=10.0		DYCS5=10.0	✓	✓
	DYNAMIC CONTRAST (CONTRAST MODE)	CONTRAST MODE 1		VXX:DYCI6=+00001	QVX:DYCI6	DYCI6=+00001	✓	✓
		CONTRAST MODE 2		VXX:DYCI6=+00002		DYCI6=+00002	✓	✓
	DYNAMIC CONTRAST (BRILLIANT CORRECTION)	OFF		VXX:DYCI7=+00000	QVX:DYCI7	DYCI7=+00000	✓	✓
		BRILLIANT CORRECTION 1		VXX:DYCI7=+00001		DYCI7=+00001	✓	✓
		BRILLIANT CORRECTION 2		VXX:DYCI7=+00002		DYCI7=+00002	✓	✓
		BRILLIANT CORRECTION 3		VXX:DYCI7=+00003		DYCI7=+00003	✓	✓
	DYNAMIC CONTRAST/MANUAL IRIS (MANUAL INTENSITY)	OFF		OAI:M000	QAI:M	000	✓	✓
		1		OAI:M001		001	✓	✓
		255		OAI:M255		255	✓	✓
	DYNAMIC CONTRAST (DYNAMIC GAMMA)	OFF		OAI:D0	QAI:D	0	✓	✓
		1		OAI:D1		1	✓	✓
		2		OAI:D2		2	✓	✓
		3		OAI:D3		3	✓	✓
	COLOR SPACE	NATIVE		VXX:CSPI1=+00000	QVX:CSPI1	CSPI1=+00000	✓	✓
		ITU-709		VXX:CSPI1=+00001		CSPI1=+00001	✓	✓
		DCI-P3		VXX:CSPI1=+00002		CSPI1=+00002	✓	✓
		ITU2020		VXX:CSPI1=+00003		CSPI1=+00003	✓	✓
	SYSTEM SELECTOR HDMI/DIGITAL LINK/DisplayPort/ SLOT-HDMI/SLOT-DIGITAL LINK/ GEOMETRY	RGB		ORF:0	QRF	0	✓	✓
		YPbPr		ORF:1		1	✓	✓
		AUTO		ORF:2		2	✓	✓
	GEOMETRY	OFF		VXX:GMMI0=+00000	QVX:GMMI0	GMMI0=+00000	✓	✓
		KEYSTONE		VXX:GMMI0=+00001		GMMI0=+00001	✓	✓
		CURVED		VXX:GMMI0=+00002		GMMI0=+00002	✓	✓
		PC-1		VXX:GMMI0=+00003		GMMI0=+00003	✓	✓
		PC-2		VXX:GMMI0=+00004		GMMI0=+00004	✓	✓
		PC-3		VXX:GMMI0=+00005		GMMI0=+00005	✓	✓

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
POSITION		CORNER-CORRECTION		VXX:GMMI0=+00010		GMMI0=+00010	✓	✓
	GEOMETRY-KEYSTONE-LENS THROW RATIO	0.7	0.1 step	VXX:GMKS0=+00.7	QVX:GMKS0	GMKS0=+00.7	✓	✓
		16.5		VXX:GMKS0=+16.5		GMKS0=+16.5	✓	✓
	GEOMETRY-KEYSTONE-VERTICAL BALANCE	-60		VXX:GMKI4=-00060	QVX:GMKI4	GMKI4=-00060	✓	✓
		+60		VXX:GMKI4=+00060		GMKI4=+00060	✓	✓
	GEOMETRY-KEYSTONE-HORIZONTAL BALANCE	-30		VXX:GMKI7=-00030	QVX:GMKI7	GMKI7=-00030	✓	✓
		+30		VXX:GMKI7=+00030		GMKI7=+00030	✓	✓
	GEOMETRY-KEYSTONE-VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX:GMKS8=-40.0	QVX:GMKS8	GMKS8=-40.0	✓	✓
		+40.0 (+45.0)*		VXX:GMKS8=+40.0		GMKS8=+40.0	✓	✓
	GEOMETRY-KEYSTONE-HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX:GMKS9=-15.0	QVX:GMKS9	GMKS9=-15.0	✓	✓
		+15.0 (+40.0)*		VXX:GMKS9=+15.0		GMKS9=+15.0	✓	✓
	GEOMETRY-CURVED-LENS THROW RATIO	0.7	0.1 step	VXX:GMCS0=+00.7	QVX:GMCS0	GMCS0=+00.7	✓	✓
		16.5		VXX:GMCS0=+16.5		GMCS0=+16.5	✓	✓
	GEOMETRY-CURVED-VERTICAL ARC	-50 (-100)*		VXX:GMCI3=-00050	QVX:GMCI3	GMCI3=-00050	✓	✓
		+50 (+100)*		VXX:GMCI3=+00050		GMCI3=+00050	✓	✓
	GEOMETRY-CURVED-HORIZONTAL ARC	-50 (-100)*		VXX:GMCI7=-00050	QVX:GMCI7	GMCI7=-00050	✓	✓
		+50 (+100)*		VXX:GMCI7=+00050		GMCI7=+00050	✓	✓
	GEOMETRY-CURVED-VERTICAL BALANCE	-60		VXX:GMCI2=-00060	QVX:GMCI2	GMCI2=-00060	✓	✓
		+60		VXX:GMCI2=+00060		GMCI2=+00060	✓	✓
	GEOMETRY-CURVED-HORIZONTAL BALANCE	-30		VXX:GMCI6=-00030	QVX:GMCI6	GMCI6=-00030	✓	✓
		+30		VXX:GMCI6=+00030		GMCI6=+00030	✓	✓
	GEOMETRY-CURVED-VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX:GMCS8=-40.0	QVX:GMCS8	GMCS8=-40.0	✓	✓
		+40.0 (+45.0)*		VXX:GMCS8=+40.0		GMCS8=+40.0	✓	✓
	GEOMETRY-CURVED-HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX:GMCS9=-15.0	QVX:GMCS9	GMCS9=-15.0	✓	✓
		+15.0 (+40.0)*		VXX:GMCS9=+15.0		GMCS9=+15.0	✓	✓
	GEOMETRY-CURVED-MAINTAIN ASPECT RATIO	OFF		VXX:GMCIA=+00000	QVX:GMCIA	GMCIA=+00000	✓	✓
		ON		VXX:GMCIA=+00001		GMCIA=+00001	✓	✓
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(V)	min.		VXX:GMFI1=+00000	QVX:GMFI1	GMFI1=+00000	0	0
		max.		VXX:GMFI1=+00300		GMFI1=+00300	+300	+300
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(V)	min.		VXX:GMFI2=+00000	QVX:GMFI2	GMFI2=+00000	0	0
		max.		VXX:GMFI2=+00300		GMFI2=+00300	+300	+300
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(V)	min.		VXX:GMFI3=-00300	QVX:GMFI3	GMFI3=-00300	-300	-300
		max.		VXX:GMFI3=+00000		GMFI3=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(V)	min.		VXX:GMFI4=-00300	QVX:GMFI4	GMFI4=-00300	-300	-300
		max.		VXX:GMFI4=+00000		GMFI4=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LINEARITY(V)	min.		VXX:GMFI5=-00127	QVX:GMFI5	GMFI5=-00127	-127	-127
		max.		VXX:GMFI5=+00127		GMFI5=+00127	+127	+127
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(H)	min.		VXX:GMFI6=+00000	QVX:GMFI6	GMFI6=+00000	0	0
		max.		VXX:GMFI6=+00480		GMFI6=+00480	+480	+480
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(H)	min.		VXX:GMFI7=-00480	QVX:GMFI7	GMFI7=-00480	-480	-480
		max.		VXX:GMFI7=+00000		GMFI7=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(H)	min.		VXX:GMFI8=+00000	QVX:GMFI8	GMFI8=+00000	0	0
		max.		VXX:GMFI8=+00480		GMFI8=+00480	+480	+480
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(H)	min.		VXX:GMFI9=-00480	QVX:GMFI9	GMFI9=-00480	-480	-480
		max.		VXX:GMFI9=+00000		GMFI9=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LINEARITY(H)	min.		VXX:GMFIA=-00127	QVX:GMFIA	GMFIA=-00127	-127	-127
		max.		VXX:GMFIA=+00127		GMFIA=+00127	+127	+127
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION UPPER	min.		VXX:GMFIB=-00100	QVX:GMFIB	GMFIB=-00100	✓	✓
		max.		VXX:GMFIB=+00100		GMFIB=+00100	✓	✓
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION LOWER	min.		VXX:GMFIC=-00100	QVX:GMFIC	GMFIC=-00100	✓	✓
		max.		VXX:GMFIC=+00100		GMFIC=+00100	✓	✓
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION LEFT	min.		VXX:GMFID=-00100	QVX:GMFID	GMFID=-00100	✓	✓
		max.		VXX:GMFID=+00100		GMFID=+00100	✓	✓
	GEOMETRY-CORNER/PINCUSHION-PINCUSHION RIGHT	min.		VXX:GMFIE=-00100	QVX:GMFIE	GMFIE=-00100	✓	✓
		max.		VXX:GMFIE=+00100		GMFIE=+00100	✓	✓
	GEOMETRY-CORNER/PINCUSHION-LINEARITY	AUTO		VXX:GMFIF=+00000	QVX:GMFIF	GMFIF=+00000	✓	✓
		MANUAL		VXX:GMFIF=+00001		GMFIF=+00001	✓	✓
	GEOMETRY - FREE GRID(ON/OFF)	OFF		VXX:GMGI1=+00000	QVX:GMGI1	GMGI1=+00000	✓	✓
		ON		VXX:GMGI1=+00001		GMGI1=+00001	✓	✓
	GEOMETRY - FREE GRID - INITIALIZE			VXX:GMGI2=+00001			✓	✓
	GEOMETRY - FREE GRID - GRID RESOLUTION	2x2		VXX:GMGI3=+00002	QVX:GMGI3	GMGI3=+00002	✓	✓
		3x3		VXX:GMGI3=+00003		GMGI3=+00003	✓	✓
		5x5		VXX:GMGI3=+00005		GMGI3=+00005	✓	✓
		9x9		VXX:GMGI3=+00009		GMGI3=+00009	✓	✓
		17x17		VXX:GMGI3=+00017		GMGI3=+00017	✓	✓
	GEOMETRY - FREE GRID - GRID COLOR	OFF		VXX:GMGI4=+00000	QVX:GMGI4	GMGI4=+00000	✓	✓
		WHITE		VXX:GMGI4=+00001		GMGI4=+00001	✓	✓
		BLACK		VXX:GMGI4=+00002		GMGI4=+00002	✓	✓
		RED		VXX:GMGI4=+00003		GMGI4=+00003	✓	✓
		GREEN		VXX:GMGI4=+00004		GMGI4=+00004	✓	✓
		BLUE		VXX:GMGI4=+00005		GMGI4=+00005	✓	✓
		CYAN		VXX:GMGI4=+00006		GMGI4=+00006	✓	✓
		MAGENTA		VXX:GMGI4=+00007		GMGI4=+00007	✓	✓
		YELLOW		VXX:GMGI4=+00008		GMGI4=+00008	✓	✓
	GEOMETRY - FREE GRID - CONTROL POINTS	POINT		VXX:GMGI5=+00000	QVX:GMGI5	GMGI5=+00000	✓	✓
		HORIZONTAL LINE		VXX:GMGI5=+00001		GMGI5=+00001	✓	✓
		VERTICAL LINE		VXX:GMGI5=+00002		GMGI5=+00002	✓	✓
	GEOMETRY - FREE GRID - GRID WIDTH	1		VXX:GMGI7=+00001	QVX:GMGI7	GMGI7=+00001	✓	✓
		10		VXX:GMGI7=+00010		GMGI7=+00010	✓	✓
	GEOMETRY - FREE GRID - CONTROL POINTS COLOR	WHITE		VXX:GMGI8=+00001	QVX:GMGI8	GMGI8=+00001	✓	✓
		BLACK		VXX:GMGI8=+00002		GMGI8=+00002	✓	✓
		RED		VXX:GMGI8=+00003		GMGI8=+00003	✓	✓
		GREEN		VXX:GMGI8=+00004		GMGI8=+00004	✓	✓
		BLUE		VXX:GMGI8=+00005		GMGI8=+00005	✓	✓
		CYAN		VXX:GMGI8=+00006		GMGI8=+00006	✓	✓
		MAGENTA		VXX:GMGI8=+00007		GMGI8=+00007	✓	✓
		YELLOW		VXX:GMGI8=+00008		GMGI8=+00008	✓	✓
	CONVERGENCE	OFF		VXX:CNVI1=+00000	QVX:CNVI1	CNVI1=+00000	✓	✓
		ON		VXX:CNVI1=+00001		CNVI1=+00001	✓	✓
	CONVERGENCE - UPPER LEFT VERTICAL			VXX:CNVS2=*:*****	QVX:CNVS2	CNVS2=*:*****	✓	✓
				VXX:CNVS2=R:*****		CNVS2=R:*****	✓	✓
				VXX:CNVS2=G:*****		CNVS2=G:*****	✓	✓
				VXX:CNVS2=B:*****		CNVS2=B:*****	✓	✓
				VXX:CNVS2=*:+00.00		CNVS2=*:+00.00	✓	✓
				VXX:CNVS2=*:+03.75		CNVS2=*:+03.75	✓	✓
	CONVERGENCE - UPPER LEFT HORIZONTAL			VXX:CNVS3=*:*****	QVX:CNVS3	CNVS3=*:*****	✓	✓
				VXX:CNVS3=R:*****		CNVS3=R:*****	✓	✓
				VXX:CNVS3=G:*****		CNVS3=G:*****	✓	✓
				VXX:CNVS3=B:*****		CNVS3=B:*****	✓	✓
				VXX:CNVS3=*:+00.00		CNVS3=*:+00.00	✓	✓
				VXX:CNVS3=*:+03.75		CNVS3=*:+03.75	✓	✓
	CONVERGENCE - UPPER RIGHT VERTICAL			VXX:CNVS4=*:*****	QVX:CNVS4	CNVS4=*:*****	✓	✓
				VXX:CNVS4=R:*****		CNVS4=R:*****	✓	✓
				VXX:CNVS4=G:*****		CNVS4=G:*****	✓	✓
				VXX:CNVS4=B:*****		CNVS4=B:*****	✓	✓
				VXX:CNVS4=*:+00.00		CNVS4=*:+00.00	✓	✓
				VXX:CNVS4=*:+03.75		CNVS4=*:+03.75	✓	✓
	CONVERGENCE - UPPER RIGHT HORIZONTAL			VXX:CNVS5=*:*****	QVX:CNVS5	CNVS5=*:*****	✓	✓
				VXX:CNVS5=R:*****		CNVS5=R:*****	✓	✓
				VXX:CNVS5=G:*****		CNVS5=G:*****	✓	✓
				VXX:CNVS5=B:*****		CNVS5=B:*****	✓	✓
				VXX:CNVS5=*:-03.75		CNVS5=*:-03.75	✓	✓
				VXX:CNVS5=*:+00.00		CNVS5=*:+00.00	✓	✓
	CONVERGENCE - LOWER LEFT VERTICAL			VXX:CNVS6=*:*****	QVX:CNVS6	CNVS6=*:*****	✓	✓
				VXX:CNVS6=R:*****		CNVS6=R:*****	✓	✓
				VXX:CNVS6=G:*****		CNVS6=G:*****	✓	✓
				VXX:CNVS6=B:*****		CNVS6=B:*****	✓	✓
				VXX:CNVS6=*:+00.00		CNVS6=*:+00.00	✓	✓
				VXX:CNVS6=*:+03.75		CNVS6=*:+03.75	✓	✓
	CONVERGENCE - LOWER LEFT HORIZONTAL			VXX:CNVS7=*:*****	QVX:CNVS7	CNVS7=*:*****	✓	✓
				VXX:CNVS7=R:*****		CNVS7=R:*****	✓	✓
				VXX:CNVS7=G:*****		CNVS7=G:*****	✓	✓
				VXX:CNVS7=B:*****		CNVS7=B:*****	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
	CONVERGENCE - LOWER RIGHT VERTICAL			VXX:CNVS7=*:-03.75 VXX:CNVS7=*:+00.00		CNVS7=*:-03.75 CNVS7=*:+00.00	✓ ✓	✓ ✓
				VXX:CNVS8=*:***** VXX:CNVS8=R:***** VXX:CNVS8=G:***** VXX:CNVS8=B:***** VXX:CNVS8=*:-03.75 VXX:CNVS8=*:+00.00	QVX:CNVS8	CNVS8=*:***** CNVS8=R:***** CNVS8=G:***** CNVS8=B:***** CNVS8=*:-03.75 CNVS8=*:+00.00	✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓
	CONVERGENCE - LOWER RIGHT HORIZONTAL			VXX:CNVS9=*:***** VXX:CNVS9=R:***** VXX:CNVS9=G:***** VXX:CNVS9=B:***** VXX:CNVS9=*:-03.75 VXX:CNVS9=*:+00.00	QVX:CNVS9	CNVS9=*:***** CNVS9=R:***** CNVS9=G:***** CNVS9=B:***** CNVS9=*:-03.75 CNVS9=*:+00.00	✓ ✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓ ✓
	SHIFT-HORIZONTAL	0 +4095		VTH:0000 VTH:4095	QTH	0000 4095	✓ ✓	✓ ✓
	SHIFT-VERTICAL	0 +4094		VTV:0000 VTV:4094	QTV	0000 4094	✓ ✓	✓ ✓
	ASPECT	AUTO/VID AUTO/DEFAULT		VSE:0	QSE	0	✓	✓
		NORMAL(4:3)		VSE:1		1	✓	✓
		WIDE(16:9)		VSE:2		2	✓	✓
		NATIVE(through)		VSE:5		5	✓	✓
		FULL(HV FIT)		VSE:6		6	✓	✓
		H-FIT		VSE:9		9	✓	✓
	ZOOM-HORIZONTAL	50 999		OZH:050 OZH:999	QZH	050 999	✓ ✓	✓ ✓
	ZOOM-VERTICAL	50 999		OZV:050 OZV:999	QZV	050 999	✓ ✓	✓ ✓
	ZOOM-BOTH	50 999		OZO:050 OZO:999	QZO	050 999	✓ ✓	✓ ✓
	ZOOM-INTERLOCKED	OFF ON		OZS:0 OZS:1	QZS	0 1	✓ ✓	✓ ✓
	ZOOM-MODE	INTERNAL FULL		OZT:0 OZT:1	QZT	0 1	✓ ✓	✓ ✓
ADVANCED	DIGITAL CINEMA REALITY	AUTO OFF 30p/25p FIXED		OPD:0 OPD:1 OPD:2	QPD	0 1 2	✓ ✓ ✓	✓ ✓ ✓
	GRADATION SMOOTHER	OFF 1 2 3		VXX:GRSII1=+00000 VXX:GRSII1=+00001 VXX:GRSII1=+00002 VXX:GRSII1=+00003	QVX:GRSII1	GRSII1=+00000 GRSII1=+00001 GRSII1=+00002 GRSII1=+00003	✓ ✓ ✓ ✓	
	BLANKING-UPPER	min. max.		DBU:0000 DBU:2398	QLU	0000 2398	0 2398	0 1198
	BLANKING-LOWER	min. max.		DBB:0000 DBB:2398	QLB	0000 2398	0 2398	0 1198
	BLANKING-RIGHT	min. max.		DBR:0000 DBR:3838	QLR	0000 3838	0 3838	0 1918
	BLANKING-LEFT	min. max.		DBL:0000 DBL:3838	QLL	0000 3838	0 3838	0 1918
	CUSTOM MASKING *	OFF PC-1 PC-2 PC-3		VXX:MSKI1=+00000 VXX:MSKI1=+00001 VXX:MSKI1=+00002 VXX:MSKI1=+00003	QVX:MSKI1	MSKI1=+00000 MSKI1=+00001 MSKI1=+00002 MSKI1=+00003	✓ ✓ ✓ ✓	✓ ✓ ✓ ✓
	EDGE BLENDING	OFF ON USER		VXX:EDBI0=+00000 VXX:EDBI0=+00001 VXX:EDBI0=+00002	QVX:EDBI0	EDBI0=+00000 EDBI0=+00001 EDBI0=+00002	✓ ✓ ✓	✓ ✓ ✓
	EDGE BLENDING-UPPER ON/OFF	OFF ON		VGU:0 VGU:1	QGU	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-LOWER ON/OFF	OFF ON		VGB:0 VGB:1	QGB	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-LEFT ON/OFF	OFF ON		VGL:0 VGL:1	QGL	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-RIGHT ON/OFF	OFF ON		VGR:0 VGR:1	QGR	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-START-UPPER	min. max.		VEU:0000 VEU:2272	QEU	0000 2272	0 2272	0 1023
	EDGE BLENDING-START-LOWER	min. max.		VEB:0000 VEB:2272	QEB	0000 2272	0 2272	0 1199
	EDGE BLENDING-START-LEFT	min. max.		VEL:0000 VEL:3712	QEL	0000 3712	0 3712	0 1023
	EDGE BLENDING-START-RIGHT	min. max.		VER:0000 VER:3712	QER	0000 3712	0 3712	0 1919
	EDGE BLENDING-WIDTH-UPPER	min. max.		VXX:EUIWIO=+00000 VXX:EUIWIO=+02272	QVX:EUIWIO	EUIWIO=+00000 EUIWIO=+02272	0 2272	0 1023
	EDGE BLENDING-WIDTH-LOWER	min. max.		VXX:EBWIO=+00000 VXX:EBWIO=+02272	QVX:EBWIO	EBWIO=+00000 EBWIO=+02272	0 2272	0 1199
	EDGE BLENDING-WIDTH-LEFT	min. max.		VXX:ELWIO=+00000 VXX:ELWIO=+03712	QVX:ELWIO	ELWIO=+00000 ELWIO=+03712	0 3712	0 1023
	EDGE BLENDING-WIDTH-RIGHT	min. max.		VXX:ERWIO=+00000 VXX:ERWIO=+03712	QVX:ERWIO	ERWIO=+00000 ERWIO=+03712	0 3712	0 1919
	EDGE BLENDING-MARKER-ON/OFF	OFF ON		VGM:0 VGM:1	QGM	0 1	✓ ✓	✓ ✓
	EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL	0 (W,R,G,B) 255 (W,R,G,B)		VJI:000,000,000,000 VJI:255,255,255,255	QJI	000,000,000,000 255,255,255,255	✓ ✓	✓ ✓
	EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-INTERLOCKED	OFF ON		VXX:EBII1=+00000 VXX:EBII1=+00001	QVX:EBII1	EBII1=+00000 EBII1=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-BLACK BORDER LEVEL	0 (W,R,G,B) 255 (W,R,G,B)		VJO:000,000,000,000 VJO:255,255,255,255	QJO	000,000,000,000 255,255,255,255	✓ ✓	✓ ✓
	EDGE BLENDING-BLACK BORDER LEVEL-INTERLOCKED	OFF ON		VXX:EBII2=+00000 VXX:EBII2=+00001	QVX:EBII2	EBII2=+00000 EBII2=+00001	✓ ✓	✓ ✓
	EDGE BLENDING-BLACK BORDER WIDTH-UPPER	min. max.		VJU:0000 VJU:2272	QJU	0000 2272	0 2272	0 1023
	EDGE BLENDING-BLACK BORDER WIDTH-LOWER	min. max.		VJB:0000 VJB:2272	QJB	0000 2272	0 2272	0 1199
	EDGE BLENDING-BLACK BORDER WIDTH-LEFT	min. max.		VJL:0000 VJL:3712	QJL	0000 3712	0 3712	0 1023
	EDGE BLENDING-BLACK BORDER WIDTH-RIGHT	min. max.		VJR:0000 VJR:3712	QJR	0000 3712	0 3712	0 1919
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE -	OFF ON		VXX:EBFI1=+00000 VXX:EBFI1=+00001	QVX:EBFI1	EBFI1=+00000 EBFI1=+00001	✓ ✓	✓ ✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE -	OFF ON		VXX:EBFI2=+00000 VXX:EBFI2=+00001	QVX:EBFI2	EBFI2=+00000 EBFI2=+00001	✓ ✓	✓ ✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - LEFT	OFF ON		VXX:EBFI3=+00000 VXX:EBFI3=+00001	QVX:EBFI3	EBFI3=+00000 EBFI3=+00001	✓ ✓	✓ ✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE -	OFF ON		VXX:EBFI4=+00000 VXX:EBFI4=+00001	QVX:EBFI4	EBFI4=+00000 EBFI4=+00001	✓ ✓	✓ ✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - UPPER - ADJUSTMENT POINTS	2 3 5 9 17		VXX:EFPI1=+00002 VXX:EFPI1=+00003 VXX:EFPI1=+00005 VXX:EFPI1=+00009 VXX:EFPI1=+00017	QVX:EFPI1	EFPI1=+00002 EFPI1=+00003 EFPI1=+00005 EFPI1=+00009 EFPI1=+00017	✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓
	- UPPER - INITIALIZE	EXECUTE		VXX:EFII1=+00001			✓	✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - LEFT - ADJUSTMENT POINTS	2 3 5 9 17		VXX:EFPI2=+00002 VXX:EFPI2=+00003 VXX:EFPI2=+00005 VXX:EFPI2=+00009 VXX:EFPI2=+00017	QVX:EFPI2	EFPI2=+00002 EFPI2=+00003 EFPI2=+00005 EFPI2=+00009 EFPI2=+00017	✓ ✓ ✓ ✓ ✓	✓ ✓ ✓ ✓ ✓
	- LEFT - INITIALIZE	EXECUTE		VXX:EFII2=+00001			✓	✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - LEFT - ADJUSTMENT POINTS	2 3 5 9		VXX:EFPI3=+00002 VXX:EFPI3=+00003 VXX:EFPI3=+00005 VXX:EFPI3=+00009	QVX:EFPI3	EFPI3=+00002 EFPI3=+00003 EFPI3=+00005 EFPI3=+00009	✓ ✓ ✓ ✓	✓ ✓ ✓ ✓

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
		17		VXX:EFPI3=+00017		EFPI3=+00017	✓	✓
	- LEFT - INITIALIZE	EXECUTE		VXX:EFII3=+00001			✓	✓
	EDGE BLENDING - BLACK LEVEL ADJUST -	2		VXX:EFPI4=+00002	QVX:EFPI4	EFPI4=+00002	✓	✓
	BLACK BORDER AREA - FREE SHAPE	3		VXX:EFPI4=+00003		EFPI4=+00003	✓	✓
	- RIGHT - ADJUSTMENT POINTS	5		VXX:EFPI4=+00005		EFPI4=+00005	✓	✓
		9		VXX:EFPI4=+00009		EFPI4=+00009	✓	✓
		17		VXX:EFPI4=+00017		EFPI4=+00017	✓	✓
	- RIGHT - INITIALIZE	EXECUTE		VXX:EFII4=+00001			✓	✓
	EDGE BLENDING-OVERLAPPED BLACK	0 (W,R,G,B)		VXX:EBBS0=000,000,000,000	QVX:EBBS0	EBBS0=000,000,000,000	✓	✓
	LEVEL-UPPER	255 (W,R,G,B)		VXX:EBBS0=255,255,255,255		EBBS0=255,255,255,255	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK	0 (W,R,G,B)		VXX:EBBS1=000,000,000,000	QVX:EBBS1	EBBS1=000,000,000,000	✓	✓
	LEVEL-LOWER	255 (W,R,G,B)		VXX:EBBS1=255,255,255,255		EBBS1=255,255,255,255	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK	0 (W,R,G,B)		VXX:EBBS2=000,000,000,000	QVX:EBBS2	EBBS2=000,000,000,000	✓	✓
	LEVEL-LEFT	255 (W,R,G,B)		VXX:EBBS2=255,255,255,255		EBBS2=255,255,255,255	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK	0 (W,R,G,B)		VXX:EBBS3=000,000,000,000	QVX:EBBS3	EBBS3=000,000,000,000	✓	✓
	LEVEL-RIGHT	255 (W,R,G,B)		VXX:EBBS3=255,255,255,255		EBBS3=255,255,255,255	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK	OFF		VXX:EBII3=+00000	QVX:EBII3	EBII3=+00000	✓	✓
	LEVEL-UPPER INTERLOCKED	ON		VXX:EBII3=+00001		EBII3=+00001	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK	OFF		VXX:EBII4=+00000	QVX:EBII4	EBII4=+00000	✓	✓
	LEVEL-LOWER INTERLOCKED	ON		VXX:EBII4=+00001		EBII4=+00001	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK	OFF		VXX:EBII5=+00000	QVX:EBII5	EBII5=+00000	✓	✓
	LEVEL-LEFT INTERLOCKED	ON		VXX:EBII5=+00001		EBII5=+00001	✓	✓
	EDGE BLENDING-OVERLAPPED BLACK	OFF		VXX:EBII6=+00000	QVX:EBII6	EBII6=+00000	✓	✓
	LEVEL-RIGHT INTERLOCKED	ON		VXX:EBII6=+00001		EBII6=+00001	✓	✓
	EDGE BLENDING-MODE	SOFTEDGE/BLACK LEVEL		VXX:EBMI1=+00000	QVX:EBMI1	EBMI1=+00000	✓	✓
		BLACK LEVEL ONLY		VXX:EBMI1=+00001		EBMI1=+00001	✓	✓
	EDGE BLENDING-AUTO TESTPATTERN	OFF		VXX:EATII=+00000	QVX:EATII	EATII=+00000	✓	✓
		ON		VXX:EATII=+00001		EATII=+00001	✓	✓
	FRAME RESPONSE	NORMAL		VXX:FDYI0=+00000	QVX:FDYI0	FDYI0=+00000	✓	✓
		FIXED		VXX:FDYI0=+00005		FDYI0=+00005	✓	✓
	FRAME DELAY	0.00		VXX:FDYS1=+0.00	QVX:FDYS1	FDYS1=+0.00	✓	✓
		100.00		VXX:FDYS1=+100.00		FDYS1=+100.00	✓	✓
DISPLAY LANGUAGE	FILM DETECTION	OFF		VXX:FDTI1=+00000	QVX:FDTI1	FDTI1=+00000	✓	✓
		ON		VXX:FDTI1=+00001		FDTI1=+00001	✓	✓
	QUAD PIXEL DRIVE	OFF		VXX:QPDII=+00000	QVX:QPDII	QPDII=+00000	✓	
		ON		VXX:QPDII=+00001		QPDII=+00001	✓	
	RASTER POSITION-HORIZONTAL	-2048		VRH:2952	QRH	2952	✓	✓
		+2047		VRH:7047		7047	✓	✓
	RASTER POSITION-VERTICAL	-2048		VRV:2952	QRV	2952	✓	✓
		+2047		VRV:7047		7047	✓	✓
	LANGUAGE	English		OLG:ENG	QLG	ENG	✓	✓
		German		OLG:DEU		DEU	✓	✓
3D SETTINGS		French		OLG:FRA		FRA	✓	✓
		Spanish		OLG:ESP		ESP	✓	✓
		Italian		OLG:ITL		ITL	✓	✓
		Japanese		OLG:JPN		JPN	✓	✓
		Chinese		OLG:CHI		CHI	✓	✓
		Russian		OLG:RUS		RUS	✓	✓
		Korea		OLG:KOR		KOR	✓	✓
		Portuguse		OLG:POR		POR	✓	✓
	3D SYSTEM SETTING	SINGLE		VXX:DSYI1=+00000	QVX:DSYI1	DSYI1=+00000		✓
		DUAL(LEFT)		VXX:DSYI1=+00001		DSYI1=+00001		✓
		DUAL(RIGHT)		VXX:DSYI1=+00002		DSYI1=+00002		✓
	3D SYNC SETTING	OFF		VXX:DSNI1=+00000	QVX:DSNI1	DSNI1=+00000		✓
		1		VXX:DSNI1=+00001		DSNI1=+00001		✓
		2		VXX:DSNI1=+00002		DSNI1=+00002		✓
		3		VXX:DSNI1=+00003		DSNI1=+00003		✓
		4		VXX:DSNI1=+00004		DSNI1=+00004		✓
		5		VXX:DSNI1=+00005		DSNI1=+00005		✓
		6		VXX:DSNI1=+00006		DSNI1=+00006		✓
		7		VXX:DSNI1=+00007		DSNI1=+00007		✓
		8		VXX:DSNI1=+00008		DSNI1=+00008		✓
		9		VXX:DSNI1=+00009		DSNI1=+00009		✓
		10		VXX:DSNI1=+00010		DSNI1=+00010		✓
		11		VXX:DSNI1=+00011		DSNI1=+00011		✓
	3D SYNC SETTING-STEREO SYNC OUTPUT	0	10 step	VXX:DSNI2=+00000	QVX:DSNI2	DSNI2=+00000		✓
	DELAY	25000		VXX:DSNI2=+25000		DSNI2=+25000		✓
	3D SIMUL INPUT SETTING-	OFF		VXX:DSMI4=+00000	QVX:DSMI4	DSMI4=+00000		✓
	L:HDMI1/R:HDMI2	AUTO		VXX:DSMI4=+00002		DSMI4=+00002		✓
	3D INPUT FORMAT	AUTO		VXX:DIFI1=+00000	QVX:DIFI1	DIFI1=+00000		✓
		NATIVE(2D)		VXX:DIFI1=+00001		DIFI1=+00001		✓
		SIDE BY SIDE		VXX:DIFI1=+00003		DIFI1=+00003		✓
		TOP AND BOTTOM		VXX:DIFI1=+00004		DIFI1=+00004		✓
		FRAME SEQUENTIAL		VXX:DIFI1=+00006		DIFI1=+00006		✓
	3D LEFT/RIGHT SWAP	NORMAL		VXX:DSWI1=+00000	QVX:DSWI1	DSWI1=+00000		✓
		SWAPPED		VXX:DSWI1=+00001		DSWI1=+00001		✓
	3D COLOR MATCHING	SHARED 2D/3D		VXX:DCMI1=+00000	QVX:DCMI1	DCMI1=+00000		✓
		SEPARATE 2D/3D		VXX:DCMI1=+00001		DCMI1=+00001		✓
	3D DARK TIME SETTING	0.5		VXX:DDTS1=+0.5	QVX:DDTS1	DDTS1=+0.5		✓
		1.0		VXX:DDTS1=+1.0		DDTS1=+1.0		✓
		1.5		VXX:DDTS1=+1.5		DDTS1=+1.5		✓
		2.0		VXX:DDTS1=+2.0		DDTS1=+2.0		✓
		2.5		VXX:DDTS1=+2.5		DDTS1=+2.5		✓
		2.7		VXX:DDTS1=+2.7		DDTS1=+2.7		✓
	3D TEST MODE	NORMAL		VXX:DTSI1=+00000	QVX:DTSI1	DTSI1=+00000		✓
		SIDE BY SIDE		VXX:DTSI1=+00001		DTSI1=+00001		✓
		LEFT/LEFT		VXX:DTSI1=+00002		DTSI1=+00002		✓
		RIGHT/RIGHT		VXX:DTSI1=+00003		DTSI1=+00003		✓
		LEFT/BLACK		VXX:DTSI1=+00004		DTSI1=+00004		✓
		BLACK/RIGHT		VXX:DTSI1=+00005		DTSI1=+00005		✓
	3D SAFETY PRECAUTIONS MESSAGE	OFF		VXX:DMGI1=+00000	QVX:DMGI1	DMGI1=+00000		✓
		ON		VXX:DMGI1=+00001		DMGI1=+00001		✓
	COLOR MATCHING	OFF		VXX:CMAI0=+00000	QVX:CMAI0	CMAI0=+00000	✓	✓
		3COLORS		VXX:CMAI0=+00001		CMAI0=+00001	✓	✓
		7COLORS		VXX:CMAI0=+00002		CMAI0=+00002	✓	✓
		MEASURED		VXX:CMAI0=+00004		CMAI0=+00004	✓	✓
	COLOR MATCHING-RESET MODE	NATIVE		VXX:CRMI1=+00000	QVX:CRMI1	CRMI1=+00000	✓	✓
		PICTURE		VXX:CRMI1=+00001		CRMI1=+00001	✓	✓
		REC709		VXX:CRMI1=+00002		CRMI1=+00002	✓	✓
	COLOR MATCHING-3COLORS-RED	0 (R,G,B)		VMR:0000,0000,0000	QMR	0000,0000,0000	✓	✓
		2048,2048,2048(R,G,B)		VMR:2048,2048,2048		2048,2048,2048	✓	✓
	COLOR MATCHING-3COLORS-GREEN	0 (R,G,B)		VMG:0000,0000,0000	QMG	0000,0000,0000	✓	✓
		2048,2048,2048(R,G,B)		VMG:2048,2048,2048		2048,2048,2048	✓	✓
	COLOR MATCHING-3COLORS-BLUE	0 (R,G,B)		VMB:0000,0000,0000	QMB	0000,0000,0000	✓	✓
		2048,2048,2048(R,G,B)		VMB:2048,2048,2048		2048,2048,2048	✓	✓
	COLOR MATCHING-3COLORS-AUTO	OFF		VXX:CATI0=+00000	QVX:CATI0	CATI0=+00000	✓	✓
	TESTPATTERN	ON		VXX:CATI0=+00001		CATI0=+00001	✓	✓
	COLOR MATCHING-3COLORS-RESET	EXECUTE		VXX:CREI1=+00001			✓	✓
	COLOR MATCHING-7COLORS-RED	0 (R,G,B)		VXX:C7CS0=0000,0000,0000	QVX:C7CS0	C7CS0=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS0=2048,2048,2048		C7CS0=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLORS-GREEN	0 (R,G,B)		VXX:C7CS1=0000,0000,0000	QVX:C7CS1	C7CS1=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS1=2048,2048,2048		C7CS1=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLORS-BLUE	0 (R,G,B)		VXX:C7CS2=0000,0000,0000	QVX:C7CS2	C7CS2=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS2=2048,2048,2048		C7CS2=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLORS-CYAN	0 (R,G,B)		VXX:C7CS3=0000,0000,0000	QVX:C7CS3	C7CS3=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS3=2048,2048,2048		C7CS3=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLORS-MAGENTA	0 (R,G,B)		VXX:C7CS4=0000,0000,0000	QVX:C7CS4	C7CS4=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS4=2048,2048,2048		C7CS4=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLORS-YELLOW	0 (R,G,B)		VXX:C7CS5=0000,0000,0000	QVX:C7CS5	C7CS5=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS5=2048,2048,2048		C7CS5=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLORS-WHITE	0 (R,G,B)		VXX:C7CS6=0000,0000,0000	QVX:C7CS6	C7CS6=0000,0000,0000	✓	✓
		2048(R,G,B)		VXX:C7CS6=2048,2048,2048		C7CS6=2048,2048,2048	✓	✓
	COLOR MATCHING-7COLORS-AUTO	OFF		VXX:CATI1=+00000	QVX:CATI1	CATI1=+00000	✓	✓

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
	TESTPATTERN	ON		VXX:CATI1=+00001		CATI1=+00001	✓	✓
	COLOR MATCHING-7COLORS-RESET	EXECUTE		VXX:CREI2=+00001			✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLACK	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS0=00000,0001,0001 VXX:CMMS0=65535,0999,0999	QVX:CMMS0	CMMS0=00000,0001,0001 CMMS0=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS1=00000,0001,0001 VXX:CMMS1=65535,0999,0999	QVX:CMMS1	CMMS1=00000,0001,0001 CMMS1=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS2=00000,0001,0001 VXX:CMMS2=65535,0999,0999	QVX:CMMS2	CMMS2=00000,0001,0001 CMMS2=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS3=00000,0001,0001 VXX:CMMS3=65535,0999,0999	QVX:CMMS3	CMMS3=00000,0001,0001 CMMS3=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMMS4=00000,0001,0001 VXX:CMMS4=65535,0999,0999	QVX:CMMS4	CMMS4=00000,0001,0001 CMMS4=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS0=00000,0001,0001 VXX:CMTS0=65535,0999,0999	QVX:CMTS0	CMTS0=00000,0001,0001 CMTS0=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS1=00000,0001,0001 VXX:CMTS1=65535,0999,0999	QVX:CMTS1	CMTS1=00000,0001,0001 CMTS1=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS2=00000,0001,0001 VXX:CMTS2=65535,0999,0999	QVX:CMTS2	CMTS2=00000,0001,0001 CMTS2=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA CYAN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS3=00000,0001,0001 VXX:CMTS3=65535,0999,0999	QVX:CMTS3	CMTS3=00000,0001,0001 CMTS3=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA MAGENTA	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS4=00000,0001,0001 VXX:CMTS4=65535,0999,0999	QVX:CMTS4	CMTS4=00000,0001,0001 CMTS4=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA YELLOW	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS5=00000,0001,0001 VXX:CMTS5=65535,0999,0999	QVX:CMTS5	CMTS5=00000,0001,0001 CMTS5=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX:CMTS6=00000,0001,0001 VXX:CMTS6=65535,0999,0999	QVX:CMTS6	CMTS6=00000,0001,0001 CMTS6=65535,0999,0999	✓	✓
	COLOR MATCHING-MEASURED MODE-AUTO TESTPATTERN	OFF ON		VXX:CATI3=+00000 VXX:CATI3=+00001	QVX:CATI3	CATI3=+00000 CATI3=+00001	✓	✓
	COLOR MATCHING-MEASURED MODE-RESET	EXECUTE		VXX:CREI3=+00001			✓	✓
	BACKUP INPUT SETTING-BACKUP INPUT	PRIMARY SECONDARY TOGGLE		VXX:BACI1=+00001 VXX:BACI1=+00002 VXX:BACI1=+00010	QVX:BACI1	BACI1=+00001 BACI1=+00002 BACI1=+00010	✓	✓
	BACKUP INPUT SETTING-BACKUP INPUT MODE	OFF HDMI1 / HDMI2 HDMI1 / SDI(SLOT1)		VXX:BACI6=+00000 VXX:BACI6=+00002 VXX:BACI6=+10111	QVX:BACI6	BACI6=+00000 BACI6=+00002 BACI6=+10111	✓	✓
	BACKUP INPUT SETTING-AUTOMATIC SWITCHING	DISABLE ENABLE		VXX:BACI3=+00001 VXX:BACI3=+00002	QVX:BACI3	BACI3=+00001 BACI3=+00002	✓	✓
	BACKUP INPUT SETTING-BACKUP INPUT STATUS	INACTIVE ACTIVE			QVX:BACI4	BACI4=+00000 BACI4=+00001	✓	✓
	HDMI IN-HDMI1 SIGNAL LEVEL	0-1023 64-940 AUTO		VXX:HSLI1=+00000 VXX:HSLI1=+00001 VXX:HSLI1=+00002	QVX:HSLI1	HSLI1=+00000 HSLI1=+00001 HSLI1=+00002	✓	✓
	HDMI IN-HDMI2 SIGNAL LEVEL	0-1023 64-940 AUTO		VXX:HSLI2=+00000 VXX:HSLI2=+00001 VXX:HSLI2=+00002	QVX:HSLI2	HSLI2=+00000 HSLI2=+00001 HSLI2=+00002	✓	✓
	HDMI IN-HDMI1 AUTO GAMMA SELECT	DISABLE ENABLE		VXX:HAGI1=+00000 VXX:HAGI1=+00001	QVX:HAGI1	HAGI1=+00000 HAGI1=+00001	✓	✓
	HDMI IN-HDMI2 AUTO GAMMA SELECT	DISABLE ENABLE		VXX:HAGI2=+00000 VXX:HAGI2=+00001	QVX:HAGI2	HAGI2=+00000 HAGI2=+00001	✓	✓
	HDMI IN-HDMI1 AUTO COLOR SPACE SELECT	DISABLE ENABLE		VXX:HACI1=+00000 VXX:HACI1=+00001	QVX:HACI1	HACI1=+00000 HACI1=+00001	✓	✓
	HDMI IN-HDMI2 AUTO COLOR SPACE SELECT	DISABLE ENABLE		VXX:HACI2=+00000 VXX:HACI2=+00001	QVX:HACI2	HACI2=+00000 HACI2=+00001	✓	✓
	HDMI IN-HDMI1 EQUALIZER	0 1 2 3 4 5 6 7		VXX:HEQI1=+00000 VXX:HEQI1=+00001 VXX:HEQI1=+00002 VXX:HEQI1=+00003 VXX:HEQI1=+00004 VXX:HEQI1=+00005 VXX:HEQI1=+00006 VXX:HEQI1=+00007	QVX:HEQI1	HEQI1=+00000 HEQI1=+00001 HEQI1=+00002 HEQI1=+00003 HEQI1=+00004 HEQI1=+00005 HEQI1=+00006 HEQI1=+00007	✓	✓
	HDMI IN-HDMI2 EQUALIZER	0 1 2 3 4 5 6 7		VXX:HEQI2=+00000 VXX:HEQI2=+00001 VXX:HEQI2=+00002 VXX:HEQI2=+00003 VXX:HEQI2=+00004 VXX:HEQI2=+00005 VXX:HEQI2=+00006 VXX:HEQI2=+00007	QVX:HEQI2	HEQI2=+00000 HEQI2=+00001 HEQI2=+00002 HEQI2=+00003 HEQI2=+00004 HEQI2=+00005 HEQI2=+00006 HEQI2=+00007	✓	✓
	HDMI IN-HDMI1 EDID SELECT	4K/60p 4K/30p 2K 4K/60p/HDR		VXX:HESI1=+00000 VXX:HESI1=+00001 VXX:HESI1=+00002 VXX:HESI1=+00010	QVX:HESI1	HESI1=+00000 HESI1=+00001 HESI1=+00002 HESI1=+00010	✓	✓
	HDMI IN-HDMI2 EDID SELECT	4K/60p 4K/30p 2K 4K/60p/HDR		VXX:HESI2=+00000 VXX:HESI2=+00001 VXX:HESI2=+00002 VXX:HESI2=+00010	QVX:HESI2	HESI2=+00000 HESI2=+00001 HESI2=+00002 HESI2=+00010	✓	✓
	HDMI IN-HDM1 EDID MODE	DEFAULT SCREEN FIT USER		VXX:EDMI3=+00000 VXX:EDMI3=+00001 VXX:EDMI3=+00010	QVX:EDMI3	EDMI3=+00000 EDMI3=+00001 EDMI3=+00010	✓	✓
	HDMI IN-HDM2 EDID MODE	DEFAULT SCREEN FIT USER		VXX:EDMI6=+00000 VXX:EDMI6=+00001 VXX:EDMI6=+00010	QVX:EDMI6	EDMI6=+00000 EDMI6=+00001 EDMI6=+00010	✓	✓
	HDMI IN-HDMI* EDID RESOLUTION	HDMI1 HDMI2		VXX:EDRS3=*****:*****: * VXX:EDRS6=*****:*****: *	QVX:EDRS3 QVX:EDRS6	EDRS3=*****:*****: * EDRS6=*****:*****: *	✓	✓
			1024x768p	VXX:*****=1024:0768: p		*****=1024:0768: p	✓	✓
			1280x720p	VXX:*****=1280:0720: p		*****=1280:0720: p	✓	✓
			1280x800p	VXX:*****=1280:0800: p		*****=1280:0800: p	✓	✓
			1280x1024p	VXX:*****=1280:1024: p		*****=1280:1024: p	✓	✓
			1366x768p	VXX:*****=1366:0768: p		*****=1366:0768: p	✓	✓
			1400x1050p	VXX:*****=1400:1050: p		*****=1400:1050: p	✓	✓
			1440x900p	VXX:*****=1440:0900: p		*****=1440:0900: p	✓	✓
			1600x900p	VXX:*****=1600:0900: p		*****=1600:0900: p	✓	✓
			1600x1200p	VXX:*****=1600:1200: p		*****=1600:1200: p	✓	✓
			1680x1050p	VXX:*****=1680:1050: p		*****=1680:1050: p	✓	✓
			1920x1080p	VXX:*****=1920:1080: p		*****=1920:1080: p	✓	✓
			1920x1080i	VXX:*****=1920:1080: i		*****=1920:1080: i	✓	✓
			1920x1200p	VXX:*****=1920:1200: p		*****=1920:1200: p	✓	✓
			2048x1080p	VXX:*****=2048:1080: p		*****=2048:1080: p	✓	✓
			2560x1080p	VXX:*****=2560:1080: p		*****=2560:1080: p	✓	✓
			2560x1440p	VXX:*****=2560:1440: p		*****=2560:1440: p	✓	✓
			2560x1600p	VXX:*****=2560:1600: p		*****=2560:1600: p	✓	✓
			3440x1440p	VXX:*****=3440:1440: p		*****=3440:1440: p	✓	✓
			3840x2400p	VXX:*****=3840:2400: p		*****=3840:2400: p	✓	✓
	HDMI IN-HDMI* EDID VERTICAL SCAN FREQUENCY	HDMI1 HDMI2		VXX:EDVI3=***** VXX:EDVI6=*****	QVX:EDVI3 QVX:EDVI6	EDVI3=***** EDVI6=*****	✓	✓
			240Hz	VXX:*****=+24000		*****=+24000	✓	
			120Hz	VXX:*****=+12000		*****=+12000	✓	✓
			100Hz	VXX:*****=+10000		*****=+10000	✓	✓
			60Hz	VXX:*****=+06000		*****=+06000	✓	✓
			50Hz	VXX:*****=+05000		*****=+05000	✓	✓
			48Hz	VXX:*****=+04800		*****=+04800	✓	✓
			30Hz	VXX:*****=+03000		*****=+03000	✓	✓
			25Hz	VXX:*****=+02500		*****=+02500	✓	✓
			24Hz	VXX:*****=+02400		*****=+02400	✓	✓
	HDMI IN-HDMI* EDID RESOLUTION / VERTICAL SCAN FREQUENCY	HDMI1 HDMI2		VXX:EDHS1=*****:*****: * VXX:EDHS2=*****:*****: *	QVX:EDHS1 QVX:EDHS2	EDHS1=*****:*****: * EDHS2=*****:*****: *	✓	✓
			1024x768	VXX:*****=1024:0768: * *****:*****: *		*****=1024:0768: * *****:*****: *	✓	✓
			1280x720	VXX:*****=1280:0720: * *****:*****: *		*****=1280:0720: * *****:*****: *	✓	✓
			1280x800	VXX:*****=1280:0800: * *****:*****: *		*****=1280:0800: * *****:*****: *	✓	✓
			1280x1024	VXX:*****=1280:1024: * *****:*****: *		*****=1280:1024: * *****:*****: *	✓	✓
			1366x768	VXX:*****=1366:0768: * *****:*****: *		*****=1366:0768: * *****:*****: *	✓	✓

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
		* PARAMETER1	1400x1050	VXX:*****=1400:1050:*:*****		*****=1400:1050:*:*****	✓	✓
			1440x900	VXX:*****=1440:0900:*:*****		*****=1440:0900:*:*****	✓	✓
			1600x900	VXX:*****=1600:0900:*:*****		*****=1600:0900:*:*****	✓	✓
			1600x1200	VXX:*****=1600:1200:*:*****		*****=1600:1200:*:*****	✓	✓
			1680x1050	VXX:*****=1680:1050:*:*****		*****=1680:1050:*:*****	✓	✓
			1920x1080	VXX:*****=1920:1080:*:*****		*****=1920:1080:*:*****	✓	✓
			1920x1200	VXX:*****=1920:1200:*:*****		*****=1920:1200:*:*****	✓	✓
			2048x1080	VXX:*****=2048:1080:*:*****		*****=2048:1080:*:*****	✓	✓
			2560x1080	VXX:*****=2560:1080:*:*****		*****=2560:1080:*:*****	✓	✓
			2560x1440	VXX:*****=2560:1440:*:*****		*****=2560:1440:*:*****	✓	✓
			2560x1600	VXX:*****=2560:1600:*:*****		*****=2560:1600:*:*****	✓	✓
			3440x1440	VXX:*****=3440:1440:*:*****		*****=3440:1440:*:*****	✓	✓
			3840x2400	VXX:*****=3840:2400:*:*****		*****=3840:2400:*:*****	✓	✓
		* PARAMETER2	Progressive	VXX:*****=*****:p:*****		*****=*****:p:*****	✓	✓
			Interlace	VXX:*****=*****:i:*****		*****=*****:i:*****	✓	✓
		* PARAMETER3	240Hz	VXX:*****=*****:*:24000		*****=*****:*:24000	✓	✓
			120Hz	VXX:*****=*****:*:12000		*****=*****:*:12000	✓	✓
			100Hz	VXX:*****=*****:*:10000		*****=*****:*:10000	✓	✓
			60Hz	VXX:*****=*****:*:06000		*****=*****:*:06000	✓	✓
			50Hz	VXX:*****=*****:*:05000		*****=*****:*:05000	✓	✓
			48Hz	VXX:*****=*****:*:04800		*****=*****:*:04800	✓	✓
			30Hz	VXX:*****=*****:*:03000		*****=*****:*:03000	✓	✓
			25Hz	VXX:*****=*****:*:02500		*****=*****:*:02500	✓	✓
			24Hz	VXX:*****=*****:*:02400		*****=*****:*:02400	✓	✓
	HDMI IN-HDMI* EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	HDMI1			QVX: ESHS1	ESHS1=*****:*:*****	✓	✓
		HDMI2			QVX: ESHS2	ESHS2=*****:*:*****	✓	✓
		* PARAMETER1	1024x768			*****=1024:0768:*:*****	✓	✓
			1280x720			*****=1280:0720:*:*****	✓	✓
			1280x800			*****=1280:0800:*:*****	✓	✓
			1280x1024			*****=1280:1024:*:*****	✓	✓
			1366x768			*****=1366:0768:*:*****	✓	✓
			1400x1050			*****=1400:1050:*:*****	✓	✓
			1440x900			*****=1440:0900:*:*****	✓	✓
			1600x900			*****=1600:0900:*:*****	✓	✓
			1600x1200			*****=1600:1200:*:*****	✓	✓
			1680x1050			*****=1680:1050:*:*****	✓	✓
			1920x1080			*****=1920:1080:*:*****	✓	✓
			1920x1200			*****=1920:1200:*:*****	✓	✓
			2048x1080			*****=2048:1080:*:*****	✓	✓
			2560x1080			*****=2560:1080:*:*****	✓	✓
			2560x1440			*****=2560:1440:*:*****	✓	✓
			2560x1600			*****=2560:1600:*:*****	✓	✓
			3440x1440			*****=3440:1440:*:*****	✓	✓
			3840x2400			*****=3840:2400:*:*****	✓	✓
		* PARAMETER2	Progressive			*****=*****:p:*****	✓	✓
			Interlace			*****=*****:i:*****	✓	✓
		* PARAMETER3	240Hz			*****=*****:*:24000	✓	✓
			120Hz			*****=*****:*:12000	✓	✓
			100Hz			*****=*****:*:10000	✓	✓
			60Hz			*****=*****:*:06000	✓	✓
			50Hz			*****=*****:*:05000	✓	✓
			48Hz			*****=*****:*:04800	✓	✓
			30Hz			*****=*****:*:03000	✓	✓
			25Hz			*****=*****:*:02500	✓	✓
			24Hz			*****=*****:*:02400	✓	✓
	DisplayPort IN-SIGNAL LEVEL	AUTO		VXX:DPLI1=+00000	QVX:DPLI1	DPLI1=+00000	✓	✓
		0-1023		VXX:DPLI1=+00001		DPLI1=+00001	✓	✓
		64-940		VXX:DPLI1=+00002		DPLI1=+00002	✓	✓
	DisplayPort IN -AUTO GAMMA SELECT	DISABLE		VXX:DAGI1=+00000	QVX:DAGI1	DAGI1=+00000	✓	✓
		ENABLE		VXX:DAGI1=+00001		DAGI1=+00001	✓	✓
	DisplayPort IN - AUTO COLOR SPACE SELECT	DISABLE		VXX:DACI1=+00000	QVX:DACI1	DACI1=+00000	✓	✓
		ENABLE		VXX:DACI1=+00001		DACI1=+00001	✓	✓
	DisplayPort IN-EDID SELECT	4K/60p		VXX:DESI1=+00000	QVX:DESI1	DESI1=+00000	✓	✓
		4K/30p		VXX:DESI1=+00001		DESI1=+00001	✓	✓
		2K		VXX:DESI1=+00002		DESI1=+00002	✓	✓
		4K/60p/HDR		VXX:DESI1=+00010		DESI1=+00010	✓	✓
	DisplayPort IN-EDID MODE	DEFAULT		VXX:EDMI8=+00000	QVX:EDMI8	EDMI8=+00000	✓	✓
		SCREEN FIT		VXX:EDMI8=+00001		EDMI8=+00001	✓	✓
		USER		VXX:EDMI8=+00010		EDMI8=+00010	✓	✓
	DisplayPort IN-EDID RESOLUTION	1024x768p		VXX:EDRS8=1024:0768:p	QVX:EDRS8	EDRS8=1024:0768:p	✓	✓
		1280x720p		VXX:EDRS8=1280:0720:p		EDRS8=1280:0720:p	✓	✓
		1280x800p		VXX:EDRS8=1280:0800:p		EDRS8=1280:0800:p	✓	✓
		1400x1050p		VXX:EDRS8=1400:1050:p		EDRS8=1400:1050:p	✓	✓
		1600x900p		VXX:EDRS8=1600:0900:p		EDRS8=1600:0900:p	✓	✓
		1600x1200p		VXX:EDRS8=1600:1200:p		EDRS8=1600:1200:p	✓	✓
		1920x1080p		VXX:EDRS8=1920:1080:p		EDRS8=1920:1080:p	✓	✓
		1920x1200p		VXX:EDRS8=1920:1200:p		EDRS8=1920:1200:p	✓	✓
		2048x1080p		VXX:EDRS8=2048:1080:p		EDRS8=2048:1080:p	✓	✓
		2560x1080p		VXX:EDRS8=2560:1080:p		EDRS8=2560:1080:p	✓	✓
		2560x1440p		VXX:EDRS8=2560:1440:p		EDRS8=2560:1440:p	✓	✓
		2560x1600p		VXX:EDRS8=2560:1600:p		EDRS8=2560:1600:p	✓	✓
		3440x1440p		VXX:EDRS8=3440:1440:p		EDRS8=3440:1440:p	✓	✓
		3840x2400p		VXX:EDRS8=3840:2400:p		EDRS8=3840:2400:p	✓	✓
	DisplayPort IN-EDID VERTICAL SCAN FREQUENCY	240Hz		VXX:EDVI8=+24000	QVX:EDVI8	EDVI8=+24000	✓	✓
		120Hz		VXX:EDVI8=+12000		EDVI8=+12000	✓	✓
		100Hz		VXX:EDVI8=+10000		EDVI8=+10000	✓	✓
		60Hz		VXX:EDVI8=+06000		EDVI8=+06000	✓	✓
		50Hz		VXX:EDVI8=+05000		EDVI8=+05000	✓	✓
		48Hz		VXX:EDVI8=+04800		EDVI8=+04800	✓	✓
		30Hz		VXX:EDVI8=+03000		EDVI8=+03000	✓	✓
		25Hz		VXX:EDVI8=+02500		EDVI8=+02500	✓	✓
		24Hz		VXX:EDVI8=+02400		EDVI8=+02400	✓	✓
	DisplayPort IN -EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:EDPS1=*****:*:*****	QVX:EDPS1	EDPS1=*****:*:*****	✓	✓
		* PARAMETER1	1024x768	VXX:EDPS1=1024:0768:*:*****		EDPS1=1024:0768:*:*****	✓	✓
			1280x720	VXX:EDPS1=1280:0720:*:****		EDPS1=1280:0720:*:*****	✓	✓
			1280x800	VXX:EDPS1=1280:0800:*:*****		EDPS1=1280:0800:*:*****	✓	✓
			1400x1050	VXX:EDPS1=1400:1050:*:*****		EDPS1=1400:1050:*:*****	✓	✓
			1600x900	VXX:EDPS1=1600:0900:*:*****		EDPS1=1600:0900:*:*****	✓	✓
			1600x1200	VXX:EDPS1=1600:1200:*:*****		EDPS1=1600:1200:*:*****	✓	✓
			1920x1080	VXX:EDPS1=1920:1080:*:*****		EDPS1=1920:1080:*:*****	✓	✓
			1920x1200	VXX:EDPS1=1920:1200:*:*****		EDPS1=1920:1200:*:*****	✓	✓
			2048x1080	VXX:EDPS1=2048:1080:*:*****		EDPS1=2048:1080:*:*****	✓	✓
			2560x1080	VXX:EDPS1=2560:1080:*:*****		EDPS1=2560:1080:*:*****	✓	✓
			2560x1440	VXX:EDPS1=2560:1440:*:*****		EDPS1=2560:1440:*:*****	✓	✓
			2560x1600	VXX:EDPS1=2560:1600:*:*****		EDPS1=2560:1600:*:*****	✓	✓
			3440x1440	VXX:EDPS1=3440:1440:*:*****		EDPS1=3440:1440:*:*****	✓	✓
			3840x2400	VXX:EDPS1=3840:2400:*:*****		EDPS1=3840:2400:*:*****	✓	✓
			Progressive	VXX:EDPS1=*****:p:*****		EDPS1=*****:p:*****	✓	✓
			Interlace	VXX:EDPS1=*****:i:*****		EDPS1=*****:i:*****	✓	✓
		* PARAMETER2	120Hz	VXX:EDPS1=*****:*:12000		EDPS1=*****:*:12000	✓	✓
			100Hz	VXX:EDPS1=*****:*:10000		EDPS1=*****:*:10000	✓	✓
			60Hz	VXX:EDPS1=*****:*:06000		EDPS1=*****:*:06000	✓	✓
			50Hz	VXX:EDPS1=*****:*:05000		EDPS1=*****:*:05000	✓	✓
			48Hz	VXX:EDPS1=*****:*:04800		EDPS1=*****:*:04800	✓	✓
			30Hz	VXX:EDPS1=*****:*:03000		EDPS1=*****:*:03000	✓	✓
			25Hz	VXX:EDPS1=*****:*:02500		EDPS1=*****:*:02500	✓	✓
			24Hz	VXX:EDPS1=*****:*:02400		EDPS1=*****:*:02400	✓	✓
	DisplayPort IN -EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER			QVX:ESPS1	ESHS1=*****:*:*****	✓	✓
			1024x768			ESHS1=1024:0768:*:*****	✓	✓
			1280x720			ESHS1=1280:0720:*:*****	✓	✓
			1280x800			ESHS1=1280:0800:*:*****	✓	✓
			1400x1050			ESHS1=1400:1050:*:*****	✓	✓
			1600x900			ESHS1=1600:0900:*:*****	✓	✓

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES	
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC	
DISPLAY OPTION		* PARAMETER1	1600x1200			ESHS1=1600:1200:*:****	✓	✓	
			1920x1080			ESHS1=1920:1080:*:****	✓	✓	
			1920x1200			ESHS1=1920:1200:*:****	✓	✓	
			2048x1080			ESHS1=2048:1080:*:****	✓	✓	
			2560x1080			ESHS1=2560:1080:*:****	✓	✓	
			2560x1440			ESHS1=2560:1440:*:****	✓	✓	
			2560x1600			ESHS1=2560:1600:*:****	✓	✓	
			3440x1440			ESHS1=3440:1440:*:****	✓	✓	
			3840x2400			ESHS1=3840:2400:*:****	✓	✓	
		* PARAMETER2	Progressive		ESHS1=*****:p:****	✓	✓		
			Interlace		ESHS1=*****:i:****	✓	✓		
				120Hz		ESHS1=*****:*:12000	✓	✓	
				100Hz		ESHS1=*****:*:10000	✓	✓	
				60Hz		ESHS1=*****:*:06000	✓	✓	
		50Hz			ESHS1=*****:*:05000	✓	✓		
		48Hz			ESHS1=*****:*:04800	✓	✓		
		30Hz			ESHS1=*****:*:03000	✓	✓		
		25Hz			ESHS1=*****:*:02500	✓	✓		
		24Hz		ESHS1=*****:*:02400	✓	✓			
		SLOT : SDI RESOLUTION	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓
			* PARAMETER1, 2	SDI1	VXX:SLSS1=VXX:SRSI1=+*****		SLSS1=SRSI1=+*****	✓	✓
			* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓
				1920x1080i	VXX:*****=VXX:*****=+00005		*****=*****=+00005	✓	✓
				1920x1080p	VXX:*****=VXX:*****=+00006		*****=*****=+00006	✓	✓
	2048x1080p			VXX:*****=VXX:*****=+00009		*****=*****=+00009	✓	✓	
	3840x2160p			VXX:*****=VXX:*****=+00011		*****=*****=+00011	✓	✓	
	4096x2160p			VXX:*****=VXX:*****=+00013		*****=*****=+00013	✓	✓	
	SLOT - SDI IN - AUTO GAMMA SELECT	DISABLE		VXX:SLSS1=VXX:SAGI1=+00000	QVX:SLSS1=SAGI1	SLSS1=SAGI1=+00000	✓	✓	
		ENABLE		VXX:SLSS1=VXX:SAGI1=+00001		SLSS1=SAGI1=+00001	✓	✓	
	SLOT - SDI IN - AUTO COLOR SPACE SELECT	DISABLE		VXX:SLSS1=VXX:SACI1=+00000	QVX:SLSS1=SACI1	SLSS1=SACI1=+00000	✓	✓	
		ENABLE		VXX:SLSS1=VXX:SACI1=+00001		SLSS1=SACI1=+00001	✓	✓	
	SLOT : SDI : SDI 4K DIVISION	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	
		* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)	VXX:SLSS1=VXX:SKSI1=+*****		SLSS1=SKSI1=+*****	✓	✓	
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	
			SQUARE	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	
			INTERLEAVE	VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓	
	SLOT : SDI : SDI SYSTEM SELECTOR	* PARAMETER		VXX:*****=VXX:*****=*:*:****:****	QVX:*****=QVX:*****=*:*:****:****	*****=*****=*:*:****:****	✓	✓	
		* PARAMETER1, 2	SDI1	VXX:SLSS1=VXX:SYSS1=1:1:*****	QVX:SLSS1=QVX:SYSS1=1:1	SLSS1=SYSS1=1:1:*****	✓	✓	
		* PARAMETER3	AUTO	VXX:*****=VXX:SYSS1=*:*:****:00000		*****=SYSS1=*:*:****:00000	✓	✓	
			RGB	VXX:*****=VXX:SYSS1=*:*:****:00001		*****=SYSS1=*:*:****:00001	✓	✓	
			YPbPr4:4:4	VXX:*****=VXX:SYSS1=*:*:****:00002		*****=SYSS1=*:*:****:00002	✓	✓	
			YPbPr4:2:2	VXX:*****=VXX:SYSS1=*:*:****:00003		*****=SYSS1=*:*:****:00003	✓	✓	
	SLOT : SDI : BIT DEPTH	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	
		* PARAMETER1, 2	SDI1	VXX:SLSS1=VXX:SBTI1=+*****		SLSS1=SBTI1=+*****	✓	✓	
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	
			12-bit	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	
	10-bit		VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓		
	SLOT : SDI : SIGNAL LEVEL	* PARAMETER		VXX:*****=VXX:*****=+*****	QVX:*****=QVX:*****	*****=*****=+*****	✓	✓	
		* PARAMETER1, 2	SDI1	VXX:SLSS1=VXX:SSLI1=+*****		SLSS1=SSLI1=+*****	✓	✓	
		* PARAMETER3	64-940	VXX:*****=VXX:*****=+00000		*****=*****=+00000	✓	✓	
			4-1019	VXX:*****=VXX:*****=+00001		*****=*****=+00001	✓	✓	
	AUTO		VXX:*****=VXX:*****=+00002		*****=*****=+00002	✓	✓		
	SLOT : DIGITAL LINK : SIGNAL LEVEL	0-1023		VXX:SLSS1=VXX:DKLI1=+00000	QVX:SLSS1=QVX:DKLI1	SLSS1=DKLI1=+00000	✓	✓	
		64-940		VXX:SLSS1=VXX:DKLI1=+00001		SLSS1=DKLI1=+00001	✓	✓	
		AUTO		VXX:SLSS1=VXX:DKLI1=+00002		SLSS1=DKLI1=+00002	✓	✓	
	SLOT : DIGITAL LINK : AUTO GAMMA SELECT	DISABLE		VXX:SLSS1=VXX:LAGI1=+00000	QVX:SLSS1=QVX:LAGI1	SLSS1=LAGI1=+00000	✓	✓	
		ENABLE		VXX:SLSS1=VXX:LAGI1=+00001		SLSS1=LAGI1=+00001	✓	✓	
	SLOT : DIGITAL LINK : AUTO COLOR SPACE SELECT	DISABLE		VXX:SLSS1=VXX:LACI1=+00000	QVX:SLSS1=QVX:LACI1	SLSS1=LACI1=+00000	✓	✓	
		ENABLE		VXX:SLSS1=VXX:LACI1=+00001		SLSS1=LACI1=+00001	✓	✓	
	SLOT : DIGITAL LINK : EDID SELECT	4K/60p/SDR		VXX:SLSS1=VXX:LESI1=+00000	QVX:SLSS1=QVX:LESI1	SLSS1=LESI1=+00000	✓	✓	
		4K/30p		VXX:SLSS1=VXX:LESI1=+00001		SLSS1=LESI1=+00001	✓	✓	
		2K		VXX:SLSS1=VXX:LESI1=+00002		SLSS1=LESI1=+00002	✓	✓	
		4K/30p/HDR		VXX:SLSS1=VXX:LESI1=+00011		SLSS1=LESI1=+00011	✓	✓	
	SLOT : DIGITAL LINK : EDID MODE	DEFAULT		VXX:SLSS1=VXX:EDMI4=+00000	QVX:SLSS1=QVX:EDMI4	SLSS1=EDMI4=+00000	✓	✓	
		SCREEN FIT		VXX:SLSS1=VXX:EDMI4=+00001		SLSS1=EDMI4=+00001	✓	✓	
		USER		VXX:SLSS1=VXX:EDMI4=+00010		SLSS1=EDMI4=+00010	✓	✓	
	SLOT : DIGITAL LINK : EDID RESOLUTION	* PARAMETER	1024x768	VXX:SLSS1=VXX:EDRS4=1024:0768:*	QVX:SLSS1=QVX:EDRS4	SLSS1=EDRS4=1024:0768:*	✓	✓	
			1280x720	VXX:SLSS1=VXX:EDRS4=1280:0720:*		SLSS1=EDRS4=1280:0720:*	✓	✓	
			1280x800	VXX:SLSS1=VXX:EDRS4=1280:0800:*		SLSS1=EDRS4=1280:0800:*	✓	✓	
			1280x1024	VXX:SLSS1=VXX:EDRS4=1280:1024:*		SLSS1=EDRS4=1280:1024:*	✓	✓	
			1366x768	VXX:SLSS1=VXX:EDRS4=1366:0768:*		SLSS1=EDRS4=1366:0768:*	✓	✓	
			1400x1050	VXX:SLSS1=VXX:EDRS4=1400:1050:*		SLSS1=EDRS4=1400:1050:*	✓	✓	
			1440x900	VXX:SLSS1=VXX:EDRS4=1440:0900:*		SLSS1=EDRS4=1440:0900:*	✓	✓	
			1600x900	VXX:SLSS1=VXX:EDRS4=1600:0900:*		SLSS1=EDRS4=1600:0900:*	✓	✓	
			1600x1200	VXX:SLSS1=VXX:EDRS4=1600:1200:*		SLSS1=EDRS4=1600:1200:*	✓	✓	
			1680x1050	VXX:SLSS1=VXX:EDRS4=1680:1050:*		SLSS1=EDRS4=1680:1050:*	✓	✓	
			1920x1080	VXX:SLSS1=VXX:EDRS4=1920:1080:*		SLSS1=EDRS4=1920:1080:*	✓	✓	
			1920x1200	VXX:SLSS1=VXX:EDRS4=1920:1200:*		SLSS1=EDRS4=1920:1200:*	✓	✓	
			2048x1080	VXX:SLSS1=VXX:EDRS4=2048:1080:*		SLSS1=EDRS4=2048:1080:*	✓	✓	
			2560x1080	VXX:SLSS1=VXX:EDRS4=2560:1080:*		SLSS1=EDRS4=2560:1080:*	✓	✓	
			2560x1440	VXX:SLSS1=VXX:EDRS4=2560:1440:*		SLSS1=EDRS4=2560:1440:*	✓	✓	
			2560x1600	VXX:SLSS1=VXX:EDRS4=2560:1600:*		SLSS1=EDRS4=2560:1600:*	✓	✓	
			3840x2400	VXX:SLSS1=VXX:EDRS4=3840:2400:*		SLSS1=EDRS4=3840:2400:*	✓	✓	
		* PARAMETER1	Progressive Interlace	VXX:SLSS1=VXX:EDRS4=*****:p		SLSS1=EDRS4=*****:p	✓	✓	
				VXX:SLSS1=VXX:EDRS4=*****:i		SLSS1=EDRS4=*****:i	✓	✓	
	SLOT : DIGITAL LINK : EDID VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:SLSS1=VXX:EDVI4=+*****	QVX:SLSS1=QVX:EDVI4	SLSS1=EDVI4=+*****	✓	✓	
		* PARAMETER1	120Hz	VXX:SLSS1=VXX:EDVI4=+12000		SLSS1=EDVI4=+12000	✓	✓	
			100Hz	VXX:SLSS1=VXX:EDVI4=+10000		SLSS1=EDVI4=+10000	✓	✓	
			60Hz	VXX:SLSS1=VXX:EDVI4=+06000		SLSS1=EDVI4=+06000	✓	✓	
			50Hz	VXX:SLSS1=VXX:EDVI4=+05000		SLSS1=EDVI4=+05000	✓	✓	
			48Hz	VXX:SLSS1=VXX:EDVI4=+04800		SLSS1=EDVI4=+04800	✓	✓	
			30Hz	VXX:SLSS1=VXX:EDVI4=+03000		SLSS1=EDVI4=+03000	✓	✓	
			25Hz	VXX:SLSS1=VXX:EDVI4=+02500		SLSS1=EDVI4=+02500	✓	✓	
			24Hz	VXX:SLSS1=VXX:EDVI4=+02400		SLSS1=EDVI4=+02400	✓	✓	
	SLOT : DIGITAL LINK : EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER	1024x768	VXX:SLSS1=VXX:EDLS1=1024:0768:*:****	QVX:SLSS1=QVX:EDLS1	SLSS1=EDLS1=1024:0768:*:****	✓	✓	
			1280x720	VXX:SLSS1=VXX:EDLS1=1280:0720:*:****		SLSS1=EDLS1=1280:0720:*:****	✓	✓	
			1280x800	VXX:SLSS1=VXX:EDLS1=1280:0800:*:****		SLSS1=EDLS1=1280:0800:*:****	✓	✓	
			1280x1024	VXX:SLSS1=VXX:EDLS1=1280:1024:*:****		SLSS1=EDLS1=1280:1024:*:****	✓	✓	
1366x768			VXX:SLSS1=VXX:EDLS1=1366:0768:*:****		SLSS1=EDLS1=1366:0768:*:****	✓	✓		
1400x1050			VXX:SLSS1=VXX:EDLS1=1400:1050:*:****		SLSS1=EDLS1=1400:1050:*:****	✓	✓		
1440x900			VXX:SLSS1=VXX:EDLS1=1440:0900:*:****		SLSS1=EDLS1=1440:0900:*:****	✓	✓		
1600x900			VXX:SLSS1=VXX:EDLS1=1600:0900:*:****		SLSS1=EDLS1=1600:0900:*:****	✓	✓		
1600x1200			VXX:SLSS1=VXX:EDLS1=1600:1200:*:****		SLSS1=EDLS1=1600:1200:*:****	✓	✓		
1680x1050			VXX:SLSS1=VXX:EDLS1=1680:1050:*:****		SLSS1=EDLS1=1680:1050:*:****	✓	✓		
1920x1080			VXX:SLSS1=VXX:EDLS1=1920:1080:*:****		SLSS1=EDLS1=1920:1080:*:****	✓	✓		
1920x1200			VXX:SLSS1=VXX:EDLS1=1920:1200:*:****		SLSS1=EDLS1=1920:1200:*:****	✓	✓		
2048x1080			VXX:SLSS1=VXX:EDLS1=2048:1080:*:****		SLSS1=EDLS1=2048:1080:*:****	✓	✓		
2560x1080			VXX:SLSS1=VXX:EDLS1=2560:1080:*:****		SLSS1=EDLS1=2560:1080:*:****	✓	✓		
2560x1440			VXX:SLSS1=VXX:EDLS1=2560:1440:*:****		SLSS1=EDLS1=2560:1440:*:****	✓	✓		
2560x1600			VXX:SLSS1=VXX:EDLS1=2560:1600:*:****		SLSS1=EDLS1=2560:1600:*:****	✓	✓		
3840x2400			VXX:SLSS1=VXX:EDLS1=3840:2400:*:****		SLSS1=EDLS1=3840:2400:*:****	✓	✓		
* PARAMETER1		Progressive Interlace	VXX:SLSS1=VXX:EDLS1=*****:p		SLSS1=EDLS1=*****:p	✓	✓		
			VXX:SLSS1=VXX:EDLS1=*****:i		SLSS1=EDLS1=*****:i	✓	✓		
* PARAMETER2		120Hz	VXX:SLSS1=VXX:EDLS1=*****:*:12000		SLSS1=EDLS1=*****:*:12000	✓	✓		
		100Hz	VXX:SLSS1=VXX:EDLS1=*****:*:10000		SLSS1=EDLS1=*****:*:10000	✓	✓		
		60Hz	VXX:SLSS1=VXX:EDLS1=*****:*:06000		SLSS1=EDLS1=*****:*:06000	✓	✓		
		50Hz	VXX:SLSS1=VXX:EDLS1=*****:*:05000		SLSS1=EDLS1=*****:*:05000	✓	✓		
		48Hz	VXX:SLSS1=VXX:EDLS1=*****:*:04800		SLSS1=EDLS1=*****:*:04800	✓	✓		
		30Hz	VXX:SLSS1=VXX:EDLS1=*****:*:03000		SLSS1=EDLS1=*****:*:03000	✓	✓		
		25Hz	VXX:SLSS1=VXX:EDLS1=*****:*:02500		SLSS1=EDLS1=*****:*:02500	✓	✓		
24Hz	VXX:								

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
	SLOT : DIGITAL LINK : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER	1024x768		QVX: SLSS1=QVX: ESLS1	SLSS1=ESLS1=1024:0768:*:*****	✓	✓
			1280x720			SLSS1=ESLS1=1280:0720:*:*****	✓	✓
			1280x800			SLSS1=ESLS1=1280:0800:*:*****	✓	✓
			1280x1024			SLSS1=ESLS1=1280:1024:*:*****	✓	✓
			1366x768			SLSS1=ESLS1=1366:0768:*:*****	✓	✓
			1400x1050			SLSS1=ESLS1=1400:1050:*:*****	✓	✓
			1440x900			SLSS1=ESLS1=1440:0900:*:*****	✓	✓
			1600x900			SLSS1=ESLS1=1600:0900:*:*****	✓	✓
			1600x1200			SLSS1=ESLS1=1600:1200:*:*****	✓	✓
			1680x1050			SLSS1=ESLS1=1680:1050:*:*****	✓	✓
			1920x1080			SLSS1=ESLS1=1920:1080:*:*****	✓	✓
			1920x1200			SLSS1=ESLS1=1920:1200:*:*****	✓	✓
			2048x1080			SLSS1=ESLS1=2048:1080:*:*****	✓	✓
			2560x1440			SLSS1=ESLS1=2560:1440:*:*****	✓	✓
			2560x1080			SLSS1=ESLS1=2560:1080:*:*****	✓	✓
			2560x1600			SLSS1=ESLS1=2560:1600:*:*****	✓	✓
			3840x2400			SLSS1=ESLS1=3840:2400:*:*****	✓	✓
		* PARAMETER1	Progressive			SLSS1=ESLS1=*****:p:*****	✓	✓
			Interlace			SLSS1=ESLS1=*****:i:*****	✓	✓
		* PARAMETER2	120Hz			SLSS1=ESLS1=*****:*:12000	✓	✓
			100Hz			SLSS1=ESLS1=*****:*:10000	✓	✓
			60Hz			SLSS1=ESLS1=*****:*:06000	✓	✓
			50Hz			SLSS1=ESLS1=*****:*:05000	✓	✓
			48Hz			SLSS1=ESLS1=*****:*:04800	✓	✓
			30Hz			SLSS1=ESLS1=*****:*:03000	✓	✓
			25Hz			SLSS1=ESLS1=*****:*:02500	✓	✓
			24Hz			SLSS1=ESLS1=*****:*:02400	✓	✓
	SLOT : DIGITAL LINK : DIGITAL LINK OUT	DISABLE		VXX: SLSS1=VXX: DLOI1=+00000	QVX: SLSS1=QVX: DLOI1	SLSS1=DLOI1=+00000	✓	✓
		ENABLE		VXX: SLSS1=VXX: DLOI1=+00001		SLSS1=DLOI1=+00001	✓	✓
	SLOT : 12G SDI OPT : RESOLUTION	* PARAMETER		VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	12G SDI OPT1	VXX: SLSS1=VXX: OREI1=*****		SLSS1=OREI1=+*****	✓	✓
			12G SDI OPT2	VXX: SLSS1=VXX: OREI2=*****		SLSS1=OREI2=+*****	✓	✓
		* PARAMETER3	AUTO	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓
			1280x720p	VXX: *****=VXX: *****=+00003		*****=*****=+00003	✓	✓
			1920x1080i	VXX: *****=VXX: *****=+00005		*****=*****=+00005	✓	✓
			1920x1080p	VXX: *****=VXX: *****=+00006		*****=*****=+00006	✓	✓
			1920x1080sF	VXX: *****=VXX: *****=+00007		*****=*****=+00007	✓	✓
			2048x1080p	VXX: *****=VXX: *****=+00009		*****=*****=+00009	✓	✓
			3840x2160p	VXX: *****=VXX: *****=+00011		*****=*****=+00011	✓	✓
			4096x2160p	VXX: *****=VXX: *****=+00013		*****=*****=+00013	✓	✓
	SLOT : 12G SDI OPT : SYSTEM SELECTOR	* PARAMETER		VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	12G SDI OPT1	VXX: SLSS1=VXX: OSYI1=*****		SLSS1=OSYI1=+*****	✓	✓
			12G SDI OPT2	VXX: SLSS1=VXX: OSYI2=*****		SLSS1=OSYI2=+*****	✓	✓
		* PARAMETER3	AUTO	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓
			RGB	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓	✓
			YPbPr 4:4:4	VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓	✓
			YPbPr 4:2:2	VXX: *****=VXX: *****=+00003		*****=*****=+00003	✓	✓
	SLOT : 12G SDI OPT : BIT DEPTH	* PARAMETER		VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	12G SDI OPT1	VXX: SLSS1=VXX: OBTI1=*****		SLSS1=OBTI1=+*****	✓	✓
			12G SDI OPT2	VXX: SLSS1=VXX: OBTI2=*****		SLSS1=OBTI2=+*****	✓	✓
		* PARAMETER3	AUTO	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓
			12-bit	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓	✓
			10-bit	VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓	✓
	SLOT : 12G SDI OPT : SIGNAL LEVEL	* PARAMETER		VXX: *****=VXX: *****=*****	QVX: *****=QVX: *****	*****=*****=+*****	✓	✓
		* PARAMETER1, 2	12G SDI OPT1	VXX: SLSS1=VXX: OSLI1=*****		SLSS1=OSLI1=+*****	✓	✓
			12G SDI OPT2	VXX: SLSS1=VXX: OSLI2=*****		SLSS1=OSLI2=+*****	✓	✓
		* PARAMETER3	64-940	VXX: *****=VXX: *****=+00000		*****=*****=+00000	✓	✓
			4-1019	VXX: *****=VXX: *****=+00001		*****=*****=+00001	✓	✓
			AUTO	VXX: *****=VXX: *****=+00002		*****=*****=+00002	✓	✓
	SLOT : 12G SDI OPT : AUTO GAMMA SELECT	DISABLE		VXX: SLSS1=VXX: OAGI1=+00000	QVX: SLSS1=OAGI1	SLSS1=OAGI1=+00000	✓	✓
		ENABLE		VXX: SLSS1=VXX: OAGI1=+00001		SLSS1=OAGI1=+00001	✓	✓
	SLOT : 12G SDI OPT : AUTO COLOR SPACE SELECT	DISABLE		VXX: SLSS1=VXX: OACI1=+00000	QVX: SLSS1=OACI1	SLSS1=OACI1=+00000	✓	✓
		ENABLE		VXX: SLSS1=VXX: OACI1=+00001		SLSS1=OACI1=+00001	✓	✓
	SLOT : 12G SDI OPT : SDI OPT OUT	* PARAMETER		VXX: OOMS1=*:*:*****	QVX: OOMS1=*:*:	OOMS1=*:*:*****	✓	✓
		* PARAMETER1	SLOT1	VXX: OOMS1=1:*:*****		OOMS1=1:*:*****	✓	✓
			SLOT2	VXX: OOMS1=2:*:*****		OOMS1=2:*:*****	✓	✓
			SFP2	VXX: OOMS1=*:2:*****		OOMS1=*:2:*****	✓	✓
		* PARAMETER3	DISABLE	VXX: OOMS1=*:*:00000		OOMS1=*:*:00000	✓	✓
		ENABLE		VXX: OOMS1=*:*:00001		OOMS1=*:*:00001	✓	✓
	SLOT : PressIT : SIGNAL LEVEL	64-940		VXX: SLSS1=VXX: WSLI1=+00000	QVX: SLSS1=QVX: WSLI1	SLSS1=WSLI1=+00000	✓	✓
		0-1023		VXX: SLSS1=VXX: WSLI1=+00001		SLSS1=WSLI1=+00001	✓	✓
		AUTO		VXX: SLSS1=VXX: WSLI1=+00002		SLSS1=WSLI1=+00002	✓	✓
	SLOT : 3rd Party Board : SIGNAL LEVEL	64-940		VXX: SLSS1=VXX: USLI1=+00000	QVX: SLSS1=QVX: USLI1	SLSS1=USLI1=+00000	✓	✓
		0-1023		VXX: SLSS1=VXX: USLI1=+00001		SLSS1=USLI1=+00001	✓	✓
		AUTO		VXX: SLSS1=VXX: USLI1=+00002		SLSS1=USLI1=+00002	✓	✓
	SLOT : 3rd Party Board : AUTO GAMMA SELECT	DISABLE		VXX: SLSS1=VXX: UAGI1=+00000	QVX: SLSS1=QVX: UAGI1	SLSS1=UAGI1=+00000	✓	✓
		ENABLE		VXX: SLSS1=VXX: UAGI1=+00001		SLSS1=UAGI1=+00001	✓	✓
	SLOT : 3rd Party Board : AUTO COLOR SPACE SELECT	DISABLE		VXX: SLSS1=VXX: UACI1=+00000	QVX: SLSS1=QVX: UACI1	SLSS1=UACI1=+00000	✓	✓
		ENABLE		VXX: SLSS1=VXX: UACI1=+00001		SLSS1=UACI1=+00001	✓	✓
	SLOT : 3rd Party Board : EQUALIZER	0		VXX: SLSS1=VXX: UEQI1=+00000	QVX: SLSS1=QVX: UEQI1	SLSS1=VXX: UEQI1=+00000	✓	✓
		1		VXX: SLSS1=VXX: UEQI1=+00001		SLSS1=VXX: UEQI1=+00001	✓	✓
		2		VXX: SLSS1=VXX: UEQI1=+00002		SLSS1=VXX: UEQI1=+00002	✓	✓
		3		VXX: SLSS1=VXX: UEQI1=+00003		SLSS1=VXX: UEQI1=+00003	✓	✓
		4		VXX: SLSS1=VXX: UEQI1=+00004		SLSS1=VXX: UEQI1=+00004	✓	✓
		5		VXX: SLSS1=VXX: UEQI1=+00005		SLSS1=VXX: UEQI1=+00005	✓	✓
		6		VXX: SLSS1=VXX: UEQI1=+00006		SLSS1=VXX: UEQI1=+00006	✓	✓
		7		VXX: SLSS1=VXX: UEQI1=+00007		SLSS1=VXX: UEQI1=+00007	✓	✓
	SLOT : 3rd Party Board : EDID SELECT	4K/60p/SDR		VXX: SLSS1=VXX: UESI1=+00000	QVX: SLSS1=QVX: UESI1	SLSS1=UESI1=+00000	✓	✓
		4K/30p		VXX: SLSS1=VXX: UESI1=+00001		SLSS1=UESI1=+00001	✓	✓
		2K		VXX: SLSS1=VXX: UESI1=+00002		SLSS1=UESI1=+00002	✓	✓
		4K/60p/HDR		VXX: SLSS1=VXX: UESI1=+00010		SLSS1=UESI1=+00010	✓	✓
	SLOT : 3rd Party Board : EDID MODE	DEFAULT		VXX: SLSS1=VXX: EDMIB=+00000	QVX: SLSS1=QVX: EDMIB	SLSS1=EDMIB=+00000	✓	✓
		SCREEN FIT		VXX: SLSS1=VXX: EDMIB=+00001		SLSS1=EDMIB=+00001	✓	✓
		USER		VXX: SLSS1=VXX: EDMIB=+00010		SLSS1=EDMIB=+00010	✓	✓
	SLOT : 3rd Party Board : EDID RESOLUTION	* PARAMETER	1024x768	VXX: SLSS1=VXX: EDRSB=1024:0768:*	QVX: SLSS1=QVX: EDRSB	SLSS1=EDRSB=1024:0768:*	✓	✓
			1280x720	VXX: SLSS1=VXX: EDRSB=1280:0720:*		SLSS1=EDRSB=1280:0720:*	✓	✓
			1280x800	VXX: SLSS1=VXX: EDRSB=1280:0800:*		SLSS1=EDRSB=1280:0800:*	✓	✓
			1280x1024	VXX: SLSS1=VXX: EDRSB=1280:1024:*		SLSS1=EDRSB=1280:1024:*	✓	✓
			1366x768	VXX: SLSS1=VXX: EDRSB=1366:0768:*		SLSS1=EDRSB=1366:0768:*	✓	✓
			1400x1050	VXX: SLSS1=VXX: EDRSB=1400:1050:*		SLSS1=EDRSB=1400:1050:*	✓	✓
			1440x900	VXX: SLSS1=VXX: EDRSB=1440:0900:*		SLSS1=EDRSB=1440:0900:*	✓	✓
			1600x900	VXX: SLSS1=VXX: EDRSB=1600:0900:*		SLSS1=EDRSB=1600:0900:*	✓	✓
			1600x1200	VXX: SLSS1=VXX: EDRSB=1600:1200:*		SLSS1=EDRSB=1600:1200:*	✓	✓
			1680x1050	VXX: SLSS1=VXX: EDRSB=1680:1050:*		SLSS1=EDRSB=1680:1050:*	✓	✓
			1920x1080	VXX: SLSS1=VXX: EDRSB=1920:1080:*		SLSS1=EDRSB=1920:1080:*	✓	✓
			1920x1200	VXX: SLSS1=VXX: EDRSB=1920:1200:*		SLSS1=EDRSB=1920:1200:*	✓	✓
			2048x1080	VXX: SLSS1=VXX: EDRSB=2048:1080:*		SLSS1=EDRSB=2048:1080:*	✓	✓
			2560x1080	VXX: SLSS1=VXX: EDRSB=2560:1080:*		SLSS1=EDRSB=2560:1080:*	✓	✓
			2560x1440	VXX: SLSS1=VXX: EDRSB=2560:1440:*		SLSS1=EDRSB=2560:1440:*	✓	✓
			2560x1600	VXX: SLSS1=VXX: EDRSB=2560:1600:*		SLSS1=EDRSB=2560:1600:*	✓	✓
			3440x1440	VXX: SLSS1=VXX: EDRSB=3440:1440:*		SLSS1=EDRSB=3440:1440:*	✓	✓
			3840x2400	VXX: SLSS1=VXX: EDRSB=3840:2400:*		SLSS1=EDRSB=3840:2400:*	✓	✓
		* PARAMETER1	Progressive	VXX: SLSS1=VXX: EDRSB=*****:p		SLSS1=EDRSB=*****:p	✓	✓
			Interlace	VXX: SLSS1=VXX: EDRSB=*****:i		SLSS1=EDRSB=*****:i	✓	✓
	SLOT : 3rd Party Board : EDID VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: SLSS1=VXX: EDVIB=+*****	QVX: SLSS1=QVX: EDVIB	SLSS1=EDVIB=+*****	✓	✓
		* PARAMETER1	240Hz	VXX: SLSS1=VXX: EDVIB=+24000		SLSS1=EDVIB=+24000	✓	✓
			120Hz	VXX: SLSS1=VXX: EDVIB=+12000		SLSS1=EDVIB=+12000	✓	✓
			100Hz	VXX: SLSS1=VXX: EDVIB=+10000		SLSS1=EDVIB=+10000	✓	✓
			60Hz	VXX: SLSS1=VXX: EDVIB=+06000		SLSS1=EDVIB=+06000	✓	✓
			50Hz	VXX: SLSS1=VXX: EDVIB=+05000		SLSS1=EDVIB=+05000	✓	✓
			48Hz	VXX: SLSS1=VXX: EDVIB=+04800		SLSS1=EDVIB=+04800	✓	✓
			30Hz	VXX: SLSS1=VXX: EDVIB=+03000		SLSS1=EDVIB=+03000	✓	✓

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
	SLOT : 3rd Party Board : EDID RESOLUTION / VERTICAL SCAN FREQUENCY		25Hz	VXX:SLSS1=VXX:EDVIB=+02500		SLSS1=EDVIB=+02500	✓	✓
			24Hz	VXX:SLSS1=VXX:EDVIB=+02400		SLSS1=EDVIB=+02400	✓	✓
		* PARAMETER	1024x768	VXX:SLSS1=VXX:EDUS1=1024:0768*:*****	QVX:SLSS1=QVX:EDUS1	SLSS1=EDUS1=1024:0768*:*****	✓	✓
			1280x720	VXX:SLSS1=VXX:EDUS1=1280:0720*:*****		SLSS1=EDUS1=1280:0720*:*****	✓	✓
			1280x800	VXX:SLSS1=VXX:EDUS1=1280:0800*:*****		SLSS1=EDUS1=1280:0800*:*****	✓	✓
			1280x1024	VXX:SLSS1=VXX:EDUS1=1280:1024*:*****		SLSS1=EDUS1=1280:1024*:*****	✓	✓
			1366x768	VXX:SLSS1=VXX:EDUS1=1366:0768*:*****		SLSS1=EDUS1=1366:0768*:*****	✓	✓
			1400x1050	VXX:SLSS1=VXX:EDUS1=1400:1050*:*****		SLSS1=EDUS1=1400:1050*:*****	✓	✓
			1440x900	VXX:SLSS1=VXX:EDUS1=1440:0900*:*****		SLSS1=EDUS1=1440:0900*:*****	✓	✓
			1600x900	VXX:SLSS1=VXX:EDUS1=1600:0900*:*****		SLSS1=EDUS1=1600:0900*:*****	✓	✓
			1600x1200	VXX:SLSS1=VXX:EDUS1=1600:1200*:*****		SLSS1=EDUS1=1600:1200*:*****	✓	✓
			1680x1050	VXX:SLSS1=VXX:EDUS1=1680:1050*:*****		SLSS1=EDUS1=1680:1050*:*****	✓	✓
			1920x1080	VXX:SLSS1=VXX:EDUS1=1920:1080*:*****		SLSS1=EDUS1=1920:1080*:*****	✓	✓
			1920x1200	VXX:SLSS1=VXX:EDUS1=1920:1200*:*****		SLSS1=EDUS1=1920:1200*:*****	✓	✓
			2048x1080	VXX:SLSS1=VXX:EDUS1=2048:1080*:*****		SLSS1=EDUS1=2048:1080*:*****	✓	✓
			2560x1080	VXX:SLSS1=VXX:EDUS1=2560:1080*:*****		SLSS1=EDUS1=2560:1080*:*****	✓	✓
			2560x1440	VXX:SLSS1=VXX:EDUS1=2560:1440*:*****		SLSS1=EDUS1=2560:1440*:*****	✓	✓
			2560x1600	VXX:SLSS1=VXX:EDUS1=2560:1600*:*****		SLSS1=EDUS1=2560:1600*:*****	✓	✓
			3440x1440	VXX:SLSS1=VXX:EDUS1=3440:1440*:*****		SLSS1=EDUS1=3440:1440*:*****	✓	✓
			3840x2400	VXX:SLSS1=VXX:EDUS1=3840:2400*:*****		SLSS1=EDUS1=3840:2400*:*****	✓	✓
		* PARAMETER1	Progressive Interlace	VXX:SLSS1=VXX:EDUS1=*****:p VXX:SLSS1=VXX:EDUS1=*****:i		SLSS1=EDUS1=*****:p SLSS1=EDUS1=*****:i	✓ ✓	✓ ✓
		* PARAMETER2	240Hz	VXX:SLSS1=VXX:EDUS1=******:24000		SLSS1=EDUS1=******:24000	✓	
			120Hz	VXX:SLSS1=VXX:EDUS1=******:12000		SLSS1=EDUS1=******:12000	✓	✓
			100Hz	VXX:SLSS1=VXX:EDUS1=******:10000		SLSS1=EDUS1=******:10000	✓	✓
			60Hz	VXX:SLSS1=VXX:EDUS1=******:06000		SLSS1=EDUS1=******:06000	✓	✓
			50Hz	VXX:SLSS1=VXX:EDUS1=******:05000		SLSS1=EDUS1=******:05000	✓	✓
			48Hz	VXX:SLSS1=VXX:EDUS1=******:04800		SLSS1=EDUS1=******:04800	✓	✓
			30Hz	VXX:SLSS1=VXX:EDUS1=******:03000		SLSS1=EDUS1=******:03000	✓	✓
			25Hz	VXX:SLSS1=VXX:EDUS1=******:02500		SLSS1=EDUS1=******:02500	✓	✓
			24Hz	VXX:SLSS1=VXX:EDUS1=******:02400		SLSS1=EDUS1=******:02400	✓	✓
	SLOT : 3rd Party Board : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER	1024x768		QVX:SLSS1=QVX:ESUS1	SLSS1=ESUS1=1024:0768*:*****	✓	✓
			1280x720			SLSS1=ESUS1=1280:0720*:*****	✓	✓
			1280x800			SLSS1=ESUS1=1280:0800*:*****	✓	✓
			1280x1024			SLSS1=ESUS1=1280:1024*:*****	✓	✓
			1366x768			SLSS1=ESUS1=1366:0768*:*****	✓	✓
			1400x1050			SLSS1=ESUS1=1400:1050*:*****	✓	✓
			1440x900			SLSS1=ESUS1=1440:0900*:*****	✓	✓
			1600x900			SLSS1=ESUS1=1600:0900*:*****	✓	✓
			1600x1200			SLSS1=ESUS1=1600:1200*:*****	✓	✓
			1680x1050			SLSS1=ESUS1=1680:1050*:*****	✓	✓
			1920x1080			SLSS1=ESUS1=1920:1080*:*****	✓	✓
			1920x1200			SLSS1=ESUS1=1920:1200*:*****	✓	✓
			2048x1080			SLSS1=ESUS1=2048:1080*:*****	✓	✓
			2560x1080			SLSS1=ESUS1=2560:1080*:*****	✓	✓
			2560x1440			SLSS1=ESUS1=2560:1440*:*****	✓	✓
			2560x1600			SLSS1=ESUS1=2560:1600*:*****	✓	✓
			3440x1440			SLSS1=ESUS1=3440:1440*:*****	✓	✓
			3840x2400			SLSS1=ESUS1=3840:2400*:*****	✓	✓
		* PARAMETER1	Progressive Interlace			SLSS1=ESUS1=*****:p:***** SLSS1=ESUS1=*****:i:*****	✓ ✓	✓ ✓
		* PARAMETER2	240Hz			SLSS1=ESUS1=******:24000	✓	
			120Hz			SLSS1=ESUS1=******:12000	✓	✓
			120Hz			SLSS1=ESUS1=******:12000	✓	✓
			60Hz			SLSS1=ESUS1=******:06000	✓	✓
			50Hz			SLSS1=ESUS1=******:05000	✓	✓
			48Hz			SLSS1=ESUS1=******:04800	✓	✓
			30Hz			SLSS1=ESUS1=******:03000	✓	✓
			25Hz			SLSS1=ESUS1=******:02500	✓	✓
			24Hz			SLSS1=ESUS1=******:02400	✓	✓
	MULTI PROJECTOR SYNC - MODE	OFF		VXX:MPSI1=+00000	QVX:MPSI1	MPSI1=+00000	✓	✓
		MAIN		VXX:MPSI1=+00001		MPSI1=+00001	✓	✓
		SUB		VXX:MPSI1=+00002		MPSI1=+00002	✓	✓
	MULTI PROJECTOR SYNC - LINK STATUS	NO LINK LINKED			QVX:MPSI2	MPSI2=+00000 MPSI2=+00001	✓ ✓	✓ ✓
	FRAME SYNC SETTING(MULTI PROJECTOR SYNC) - CONTRAST SYNC.	OFF		VXX:CSYI1=+00000	QVX:CSYI1	CSYI1=+00000	✓	✓
		ON		VXX:CSYI1=+00001		CSYI1=+00001	✓	✓
	MULTI PROJECTOR SYNC - SHUTTER SYNC.	OFF		VXX:SSYI1=+00000	QVX:SSYI1	SSYI1=+00000	✓	✓
		ON		VXX:SSYI1=+00001		SSYI1=+00001	✓	✓
	INPUT GUIDE	OFF		OID:0	QDI	0	✓	✓
		ON (SIMPLE)		OID:1		1	✓	✓
	OSD POSITION	UPPER LEFT		ODP:1	QDP	1	✓	✓
		CETRE LEFT		ODP:2		2	✓	✓
		LOWER LEFT		ODP:3		3	✓	✓
		TOP CENTER		ODP:4		4	✓	✓
		CENTER		ODP:5		5	✓	✓
		LOEER CENTER		ODP:6		6	✓	✓
		UPPER RIGHT		ODP:7		7	✓	✓
		CENTER RIGHT		ODP:8		8	✓	✓
		LOWER RIGHT		ODP:9		9	✓	✓
	OSD ROTATION	OFF		VXX:OSRI1=+00000	QVX:OSRI1	OSRI1=+00000	✓	✓
		CLOCKWISE		VXX:OSRI1=+00001		OSRI1=+00001	✓	✓
		COUNTER CLOCKWISE		VXX:OSRI1=+00002		OSRI1=+00002	✓	✓
	OSD MEMORY	OFF		VXX:OMYI0=+00000	QVX:OMYI0	OMYI0=+00000	✓	✓
		ON		VXX:OMYI0=+00001		OMYI0=+00001	✓	✓
	ON SCREEN	OFF		OOS:0	QOS	0	✓	✓
		ON		OOS:1		1	✓	✓
	WARNING MESSAGE	OFF		VXX:WMDI0=+00000	QVX:WMDI0	WMDI0=+00000	✓	✓
		ON		VXX:WMDI0=+00001		WMDI0=+00001	✓	✓
	OSD DESIGN	1(YELLOW)		MOD:0	QOD	0	✓	✓
		2(BLUE)		MOD:1		1	✓	✓
		3(WHITE)		MOD:2		2	✓	✓
		4(GREEN)		MOD:3		3	✓	✓
		5(Peach)		MOD:4		4	✓	✓
		6(BROWN)		MOD:5		5	✓	✓
	MENU MODE	NORMAL		VXX:MMDI1=+00000	QVX:MMDI1	MMDI1=+00000	✓	✓
		SIMPLE		VXX:MMDI1=+00001		MMDI1=+00001	✓	✓
	SCREEN SETTING	16:10		VSF:0	QSF	0	✓	✓
		16:9		VSF:1		1	✓	✓
		4:3		VSF:2		2	✓	✓
	SCREEN POSITION-VERTICAL	min. max.		VXX:VSPI0=-00120 VXX:VSPI0=+00120	QVX:VSPI0	VSPI0=-00120 VSPI0=+00120	-120 120	-60 60
	SCREEN POSITION-HORIZONTAL	min. max.		VXX:HSPI0=-00320 VXX:HSPI0=+00320	QVX:HSPI0	HSPI0=-00320 HSPI0=+00320	-320 320	-160 160
	SCREEN MARKER	OFF ON		VXX:SSMI1=+00000 VXX:SSMI1=+00001	QVX:SSMI1	SSMI1=+00000 SSMI1=+00001	✓ ✓	✓ ✓
	SCREEN MARKER - UPPER	min. max.		VXX:SCMI1=+00000 VXX:SCMI1=+02399	QVX:SCMI1	SCMI1=+00000 SCMI1=+02399	0 2399	0 1199
	SCREEN MARKER - LOWER	min. max.		VXX:SCMI2=+00000 VXX:SCMI2=+02399	QVX:SCMI2	SCMI2=+00000 SCMI2=+02399	0 2399	0 1199
	SCREEN MARKER - LEFT	min. max.		VXX:SCMI3=+00000 VXX:SCMI3=+03839	QVX:SCMI3	SCMI3=+00000 SCMI3=+03839	0 3839	0 1919
	SCREEN MARKER - RIGHT	min. max.		VXX:SCMI4=+00000 VXX:SCMI4=+03839	QVX:SCMI4	SCMI4=+00000 SCMI4=+03839	0 3839	0 1919
	STARTUP LOGO	OFF		MLO:0	QLO	0	✓	✓
		USER LOGO		MLO:1		1	✓	✓
		DEFAULT LOGO		MLO:2		2	✓	✓
	UNIFORMITY-FLEXIBLE CORRECTION *	OFF		VXX:UFMI1=+00000	QVX:UFMI1	UFMI1=+00000	✓	✓
		ON(PRE)		VXX:UFMI1=+00011		UFMI1=+00011	✓	✓
		ON(POST)		VXX:UFMI1=+00021		*	✓	✓
	UNIFORMITY-INITILIZE	EXECUTE		VXX:UFMI2=+00001			✓	✓
	UNIFORMITY-MODE	CHROMA ONLY		VXX:UFMI3=+00001	QVX:UFMI3	UFMI3=+00001	✓	✓
		LUMINACE/CHROMA		VXX:UFMI3=+00011		UFMI3=+00011	✓	✓

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
	UNIFORMITY-WHITE/RED/GREEN/RED	* PARAMETER		E\$W:*,****,****	E\$R:*	** ,****,****	✓	✓
		* PARAMETER 1	WHITE	E\$W:W,****,****	E\$R:W	** ,****,****	✓	✓
			RED	E\$W:R,****,****	E\$R:R	** ,****,****	✓	✓
			GREEN	E\$W:G,****,****	E\$R:G	** ,****,****	✓	✓
			BLUE	E\$W:B,****,****	E\$R:B	** ,****,****	✓	✓
		* PARAMETER 2	VERTICAL(-127)	E\$W:*, -127,****		** , -127,****	✓	✓
			VERTICAL(+127)	E\$W:*, +127,****		** , +127,****	✓	✓
	SHUTTER SETTING-FADE IN	* PARAMETER 3	HORIZONTAL(-127)	E\$W:*, *****, -127		** ,*****, -127	✓	✓
			HORORIZONTAL(+127)	E\$W:*, *****, +127		** ,*****, +127	✓	✓
			L1(ON)			1*, *****, ****	✓	✓
			L2(OFF)			*0, *****, ****	✓	✓
		0.0s(OFF)		VXX:SEFS1=0.0	QVX:SEFS1	SEFS1=0.0	✓	✓
		0.5s		VXX:SEFS1=0.5		SEFS1=0.5	✓	✓
		1.0s		VXX:SEFS1=1.0		SEFS1=1.0	✓	✓
		1.5s		VXX:SEFS1=1.5		SEFS1=1.5	✓	✓
		2.0s		VXX:SEFS1=2.0		SEFS1=2.0	✓	✓
		2.5s		VXX:SEFS1=2.5		SEFS1=2.5	✓	✓
		3.0s		VXX:SEFS1=3.0		SEFS1=3.0	✓	✓
		3.5s		VXX:SEFS1=3.5		SEFS1=3.5	✓	✓
		4.0s		VXX:SEFS1=4.0		SEFS1=4.0	✓	✓
		5.0s		VXX:SEFS1=5.0		SEFS1=5.0	✓	✓
		7.0s		VXX:SEFS1=7.0		SEFS1=7.0	✓	✓
		10.0s		VXX:SEFS1=10.0		SEFS1=10.0	✓	✓
	SHUTTER SETTING-FADE OUT	0.0s(OFF)		VXX:SEFS2=0.0	QVX:SEFS2	SEFS2=0.0	✓	✓
		0.5s		VXX:SEFS2=0.5		SEFS2=0.5	✓	✓
		1.0s		VXX:SEFS2=1.0		SEFS2=1.0	✓	✓
		1.5s		VXX:SEFS2=1.5		SEFS2=1.5	✓	✓
		2.0s		VXX:SEFS2=2.0		SEFS2=2.0	✓	✓
		2.5s		VXX:SEFS2=2.5		SEFS2=2.5	✓	✓
		3.0s		VXX:SEFS2=3.0		SEFS2=3.0	✓	✓
		3.5s		VXX:SEFS2=3.5		SEFS2=3.5	✓	✓
		4.0s		VXX:SEFS2=4.0		SEFS2=4.0	✓	✓
		5.0s		VXX:SEFS2=5.0		SEFS2=5.0	✓	✓
	SHUTTER SETTING -MECHANICAL SHUTTER	DISABLE		VXX:SEFI5=+00000	QVX:SEFI5	SEFS5=+00000	✓	✓
		ENABLE		VXX:SEFI5=+00001		SEFS5=+00001	✓	✓
	SHUTTER SETTING-STARTUP	OPEN		VXX:SEFI3=+00000	QVX:SEFI3	SEFI3=+00000	✓	✓
		CLOSE		VXX:SEFI3=+00001		SEFI3=+00001	✓	✓
	SHUTTER SETTING-SHUT OFF	OPEN		VXX:SEFI4=+00000	QVX:SEFI4	SEFI4=+00000	✓	✓
		CLOSE		VXX:SEFI4=+00001		SEFI4=+00001	✓	✓
		KEEP CURRENT STATE		VXX:SEFI4=+00002		SEFI4=+00002	✓	✓
	BACK COLOR	BLUE		OBC:0	QBC	0	✓	✓
		BLACK		OBC:1		1	✓	✓
		USER LOGO		OBC:2		2	✓	✓
		DEFAULT LOGO		OBC:3		3	✓	✓
	WAVEFORM MONITOR	OFF		OWM:0	QWM	0	✓	✓
		LUMINANCE		OWM:5		5	✓	✓
		RED		OWM:6		6	✓	✓
		GREEN		OWM:7		7	✓	✓
		BLUE		OWM:8		8	✓	✓
	WAVEFORM MONITOR-LINE ADJ.	0		VXX:WMLI0=+00000	QVX:WMLI0	WMLI0=+00000	✓	✓
		+2159		VXX:WMLI0=+02159		WMLI0=+02159	✓	✓
	AC VOLTAGE				QVX:VMOI2	VMOI2=+00000	✓	✓
	CUT OFF-RED	OFF		VXX:CUTI1=+00000	QVX:CUTI1	CUTI1=+00000	✓	✓
		ON		VXX:CUTI1=+00001		CUTI1=+00001	✓	✓
	CUT OFF-GREEN	OFF		VXX:CUTI2=+00000	QVX:CUTI2	CUTI2=+00000	✓	✓
		ON		VXX:CUTI2=+00001		CUTI2=+00001	✓	8%
	CUT OFF-BLUE	OFF		VXX:CUTI3=+00000	QVX:CUTI3	CUTI3=+00000	✓	✓
		ON		VXX:CUTI3=+00001		CUTI3=+00001	✓	✓
	PROJECTOR ID	0(ALL)		RIS:00			✓	✓
		64		RIS:64			✓	✓
	ID ALL	OFF		RVS:0	QVY	0	✓	✓
		ON		RVS:1		1	✓	✓
	PROJECTION METHOD INSTALLATION	FRONT/DESK		OIL:0	QSP	0	✓	✓
		REAR/DESK		OIL:1		1	✓	✓
		FRONT/CEILING		OIL:2		2	✓	✓
		REAR/CEILING		OIL:3		3	✓	✓
		FRONT/AUTO		OIL:4		4	✓	✓
		REAR/AUTO		OIL:5		5	✓	✓
	AUTO COOLING CONDITION-STATUS	FLOOR			QVX:ADRI1	ADRI1=+00000	✓	✓
		CEILING				ADRI1=+00001	✓	✓
		VERTICAL UP				ADRI1=+00002	✓	✓
		VERTICAL DOWN				ADRI1=+00003	✓	✓
		PORTRAIT				ADRI1=+00004	✓	✓
	OPERATING MODE	NORMAL		VXX:OPEI1=+00000	QVX:OPEI1	OPEI1=+00000	✓	✓
		ECO		VXX:OPEI1=+00001		OPEI1=+00001	✓	✓
		QUIET1(QUIET)		VXX:OPEI1=+00021		OPEI1=+00021	✓	✓
		USER1(USER)		VXX:OPEI1=+00101		OPEI1=+00101	✓	✓
		USER2		VXX:OPEI1=+00102		OPEI1=+00102	✓	✓
		USER3		VXX:OPEI1=+00103		OPEI1=+00103	✓	✓
	LIGHT OUTPUT	min.		VXX:LOPI2=+00050	QVX:LOPI2	LOPI2=+00050	8%	8%
		max.		VXX:LOPI2=+01000		LOPI2=+01000	100%	100%
	MAX LIGHT OUTPUT	min.		VXX:LOPI3=+00050	QVX:LOPI3	LOPI3=+00050	8%	8%
		max.		VXX:LOPI3=+01000		LOPI3=+01000	100%	100%
	BRIGHTNESS CONTROL-SETUP- CALIBRATION MESSAGE	OFF		VXX:BMGI1=+00000	QVX:BMGI1	BMGI1=+00000	✓	✓
		ON		VXX:BMGI1=+00001		BMGI1=+00001	✓	✓
	BRIGHTNESS CONTROL-SETUP-CONSTANT MODE	OFF		VXX:BCMI0=+00000	QVX:BCMI0	BCMI0=+00000	✓	✓
		AUTO		VXX:BCMI0=+00001		BCMI0=+00001	✓	✓
		PC		VXX:BCMI0=+00002		BCMI0=+00002	✓	✓
	BRIGHTNESS CONTROL-SETUP-LINK	OFF		VXX:BCLI0=+00000	QVX:BCLI0	BCLI0=+00000	✓	✓
		GROUP A		VXX:BCLI0=+00001		BCLI0=+00001	✓	✓
		GROUP B		VXX:BCLI0=+00002		BCLI0=+00002	✓	✓
		GROUP C		VXX:BCLI0=+00003		BCLI0=+00003	✓	✓
		GROUP D		VXX:BCLI0=+00004		BCLI0=+00004	✓	✓
	BRIGHTNESS CONTROL-SETUP APPLY	APPLY		VXX:BCSI0=+00001			✓	✓
	BRIGHTNESS CONTROL- PREVIOUS TARGET BRIGHTNESS	***** : target			QVX:BCSS1	BCSS1=*****:yyyymmddhhmmss	✓	✓
		brightness(00000~0					✓	✓
		1000f0.0~100.0%)					✓	✓
		yy : year					✓	✓
		mm : month					✓	✓
		dd : day					✓	✓
		hh : hour					✓	✓
	SLOT SETTING-SLOT STANDBY	DISABLE		VXX:SSBI1=+00000	QVX:SSBI1	SSBI1=+00000	✓	✓
		ENABLE		VXX:SSBI1=+00001		SSBI1=+00001	✓	✓
	SLOT SETTING-POWER ON			VXX:SSBI2=+00001			✓	✓
	SLOT SETTING-FORCED TERMINATION			VXX:SSBI3=+00001			✓	✓
	SCHEDULE	OFF		VXX:SCHIO=+00000	QVX:SCHIO	SCHIO=+00000	✓	✓
		ON		VXX:SCHIO=+00001		SCHIO=+00001	✓	✓
	SCHEDULE-PROGRAM ASSIGN	OFF		VXX:SPGI*=+00000	QVX:SPGI*	SPGI*=+00000	✓	✓
		PROGRAM1		VXX:SPGI*=+00001		SPGI*=+00001	✓	✓
		PROGRAM2		VXX:SPGI*=+00002		SPGI*=+00002	✓	✓
		PROGRAM3		VXX:SPGI*=+00003		SPGI*=+00003	✓	✓
		PROGRAM4		VXX:SPGI*=+00004		SPGI*=+00004	✓	✓
		PROGRAM5		VXX:SPGI*=+00005		SPGI*=+00005	✓	✓
		PROGRAM6		VXX:SPGI*=+00006		SPGI*=+00006	✓	✓
		PROGRAM7		VXX:SPGI*=+00007		SPGI*=+00007	✓	✓
			SUN	VXX:SPGIO=+0000*	QVX:SPGIO	SPGIO=+0000*	✓	✓
			MON	VXX:SPGI1=+0000*	QVX:SPGI1	SPGI1=+0000*	✓	✓
			TUE	VXX:SPGI2=+0000*	QVX:SPGI2	SPGI2=+0000*	✓	✓

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
PROJECTOR SETUP	SCHEDULE-COMMAND SETTING	* PARAMETER	WED	VXX:SPGI3=+0000*	QVX:SPGI3	SPGI3=+0000*	✓	✓
			THU	VXX:SPGI4=+0000*	QVX:SPGI4	SPGI4=+0000*	✓	✓
			FRI	VXX:SPGI5=+0000*	QVX:SPGI5	SPGI5=+0000*	✓	✓
			SAT	VXX:SPGI6=+0000*	QVX:SPGI6	SPGI6=+0000*	✓	✓
		COMMAND Del		VXX:SCCS*=**00****	QVX:SCCS*=**	SCCS*=**00****	✓	✓
		STANDBY		VXX:SCCS*=**10****		SCCS*=**10****	✓	✓
		POWER ON		VXX:SCCS*=**11****		SCCS*=**11****	✓	✓
		SHUTTER OPEN		VXX:SCCS*=**20****		SCCS*=**20****	✓	✓
		SHUTTER CLOSE		VXX:SCCS*=**21****		SCCS*=**21****	✓	✓
		HDMI1 INPUT		VXX:SCCS*=**53****		SCCS*=**53****	✓	✓
		HDMI2 INPUT		VXX:SCCS*=**54****		SCCS*=**54****	✓	✓
		DisplayPort		VXX:SCCS*=**5D****		SCCS*=**5D****	✓	✓
		SLOT1-1 INPUT		VXX:SCCS*=**68****		SCCS*=**68****	✓	✓
		SLOT1 DIGITAL LINK		VXX:SCCS*=**G0****		SCCS*=**G0****	✓	✓
		SLOT1-DIGITAL LINK-INPUT 1		VXX:SCCS*=**G1****		SCCS*=**G1****	✓	✓
		SLOT1-DIGITAL LINK-INPUT 2		VXX:SCCS*=**G2****		SCCS*=**G2****	✓	✓
		SLOT1-DIGITAL LINK-INPUT 3		VXX:SCCS*=**G3****		SCCS*=**G3****	✓	✓
		SLOT1-DIGITAL LINK-INPUT 4		VXX:SCCS*=**G4****		SCCS*=**G4****	✓	✓
		SLOT1-DIGITAL LINK-INPUT 5		VXX:SCCS*=**G5****		SCCS*=**G5****	✓	✓
		SLOT1-DIGITAL LINK-INPUT 6		VXX:SCCS*=**G6****		SCCS*=**G6****	✓	✓
		SLOT1-DIGITAL LINK-INPUT 7		VXX:SCCS*=**G7****		SCCS*=**G7****	✓	✓
		SLOT1-DIGITAL LINK-INPUT 8		VXX:SCCS*=**G8****		SCCS*=**G8****	✓	✓
		SLOT1-DIGITAL LINK-INPUT 9		VXX:SCCS*=**G9****		SCCS*=**G9****	✓	✓
		SLOT1-DIGITAL LINK-INPUT 10		VXX:SCCS*=**GA****		SCCS*=**GA****	✓	✓
		NORMAL		VXX:SCCS*=**70****		SCCS*=**70****	✓	✓
		ECO		VXX:SCCS*=**71****		SCCS*=**71****	✓	✓
		USER1(USER)		VXX:SCCS*=**75****		SCCS*=**75****	✓	✓
		USER2		VXX:SCCS*=**76****		SCCS*=**76****	✓	✓
		USER3		VXX:SCCS*=**77****		SCCS*=**77****	✓	✓
		SILENT1(QUIET1/QUIET)		VXX:SCCS*=**7A****		SCCS*=**7A****	✓	✓
		* PARAMETER1	PROGRAM1	VXX:SCCS1=*****	QVX:SCCS1=**	SCCS1=*****	✓	✓
			PROGRAM2	VXX:SCCS2=*****	QVX:SCCS2=**	SCCS2=*****	✓	✓
			PROGRAM3	VXX:SCCS3=*****	QVX:SCCS3=**	SCCS3=*****	✓	✓
			PROGRAM4	VXX:SCCS4=*****	QVX:SCCS4=**	SCCS4=*****	✓	✓
			PROGRAM5	VXX:SCCS5=*****	QVX:SCCS5=**	SCCS5=*****	✓	✓
			PROGRAM6	VXX:SCCS6=*****	QVX:SCCS6=**	SCCS6=*****	✓	✓
			PROGRAM7	VXX:SCCS7=*****	QVX:SCCS7=**	SCCS7=*****	✓	✓
		* PARAMETER2	COMMAND 1	VXX:SCCS*=01*****	QVX:SCCS*=01	SCCS*=01*****	✓	✓
			COMMAND 16	VXX:SCCS*=16*****	QVX:SCCS*=16	SCCS*=16*****	✓	✓
		* PARAMETER3	00:00	VXX:SCCS*=***0000		SCCS*=***0000	✓	✓
			23:59	VXX:SCCS*=***2359		SCCS*=***2359	✓	✓
	STARTUP INPUT SELECT	HDMI1		VXX:SISS1=HD1	QVX:SISS1	SISS1=HD1	✓	✓
		HDMI2		VXX:SISS1=HD2		SISS1=HD2	✓	✓
		DisplayPort		VXX:SISS1=DP1		SISS1=DP1	✓	✓
		SLOT1 : SDM : 12G SDI		VXX:SISS1=DM1,SD1		SISS1=DM1,SD1	✓	✓
		SLOT1 : SDM : Digital Link		VXX:SISS1=DM1,DL1		SISS1=DM1,DL1	✓	✓
		SLOT1 : SDM : PressIT		VXX:SISS1=DM1,WP1		SISS1=DM1,WP1	✓	✓
		SLOT1 : SDM : 3rd Party Board		VXX:SISS1=DM1,TP1		SISS1=DM1,TP1	✓	✓
		SLOT1 : SDM : 12G SDI OPT1		VXX:SISS1=DM1,OP1		SISS1=DM1,OP1	✓	✓
		SLOT1 : SDM : 12G SDI OPT2		VXX:SISS1=DM1,OP2		SISS1=DM1,OP2	✓	✓
		LAST USED		VXX:SISS1=LSU		SISS1=LSU	✓	✓
	STARTUP INPUT SELECT (SLOT : DIGITAL LINK)	LAST USED		VXX:SLSS1=VXX:SISI2=+00000	QVX:SLSS1=QVX:SISI2	SLSS1=SISI2=+00000	✓	✓
		INPUT1		VXX:SLSS1=VXX:SISI2=+00001		SLSS1=SISI2=+00001	✓	✓
		INPUT2		VXX:SLSS1=VXX:SISI2=+00002		SLSS1=SISI2=+00002	✓	✓
		INPUT3		VXX:SLSS1=VXX:SISI2=+00003		SLSS1=SISI2=+00003	✓	✓
		INPUT4		VXX:SLSS1=VXX:SISI2=+00004		SLSS1=SISI2=+00004	✓	✓
		INPUT5		VXX:SLSS1=VXX:SISI2=+00005		SLSS1=SISI2=+00005	✓	✓
		INPUT6		VXX:SLSS1=VXX:SISI2=+00006		SLSS1=SISI2=+00006	✓	✓
		INPUT7		VXX:SLSS1=VXX:SISI2=+00007		SLSS1=SISI2=+00007	✓	✓
		INPUT8		VXX:SLSS1=VXX:SISI2=+00008		SLSS1=SISI2=+00008	✓	✓
		INPUT9		VXX:SLSS1=VXX:SISI2=+00009		SLSS1=SISI2=+00009	✓	✓
	NO SIGNAL SHUT-OFF	INPIT10		VXX:SLSS1=VXX:SISI2=+00010		SLSS1=SISI2=+00010	✓	✓
		DISABLE		OAF:00	QAF	00	✓	✓
		10min		OAF:10		10	✓	✓
		20min		OAF:20		20	✓	✓
		30min		OAF:30		30	✓	✓
		40min		OAF:40		40	✓	✓
		50min		OAF:50		50	✓	✓
		60min		OAF:60		60	✓	✓
		70min		OAF:70		70	✓	✓
		80min		OAF:80		80	✓	✓
		90min		OAF:90		90	✓	✓
	NO SIGNAL LIGHTS-OUT	DISABLE		VXX:SLOI1=+00000	QVX:SLOI1	SLOI1=+00000	✓	✓
		10SEC.		VXX:SLOI1=+00010		SLOI1=+00010	✓	✓
		20SEC.		VXX:SLOI1=+00020		SLOI1=+00020	✓	✓
		30SEC.		VXX:SLOI1=+00030		SLOI1=+00030	✓	✓
		1MIN.		VXX:SLOI1=+00060		SLOI1=+00060	✓	✓
		2MIN.		VXX:SLOI1=+00120		SLOI1=+00120	✓	✓
		3MIN.		VXX:SLOI1=+00180		SLOI1=+00180	✓	✓
	NO SIGNAL SETTING - SECONDARY INPUT	5MIN.		VXX:SLOI1=+00300		SLOI1=+00300	✓	✓
		OFF		VXX:SINS1=OFF	QVX:SINS1	SINS1=OFF	✓	✓
		HDMI1		VXX:SINS1=HD1		SINS1=HD1	✓	✓
		HDMI2		VXX:SINS1=HD2		SINS1=HD2	✓	✓
		DisplayPort		VXX:SINS1=DP1		SINS1=DP1	✓	✓
		SLOT1 : SDM : 12G SDI		VXX:SINS1=DM1,SD1		SINS1=DM1,SD1	✓	✓
		SLOT1 : SDM : Digital Link		VXX:SINS1=DM1,DL1		SINS1=DM1,DL1	✓	✓
		SLOT1 : SDM : PressIT		VXX:SINS1=DM1,WP1		SINS1=DM1,WP1	✓	✓
		SLOT1 : SDM : 3rd Party Board		VXX:SINS1=DM1,TP1		SINS1=DM1,TP1	✓	✓
		SLOT1 : SDM : 12G SDI OPT1		VXX:SINS1=DM1,OP1		SINS1=DM1,OP1	✓	✓
		SLOT1 : SDM : 12G SDI OPT2		VXX:SINS1=DM1,OP2		SINS1=DM1,OP2	✓	✓
	REMOTE2 - MODE	DEFAULT		VXX:RMPI0=+00000	QVX:RMPI0	RMPI0=+00000	✓	✓
		USER		VXX:RMPI0=+00001		RMPI0=+00001	✓	✓
	REMOTE2 - PIN2	NONE		VXX:RMPS1=P2<NONE	QVX:RMPS1=P2	RMPS1=P2<NONE	✓	✓
		POWER		VXX:RMPS1=P2<POWER		RMPS1=P2<POWER	✓	✓
	REMOTE2 - PIN3 - 7	* PARAMETER		VXX:RMPS1=P*<*****	QVX:RMPS1=P*		✓	✓
		* PARAMETER1	PIN3	VXX:RMPS1=P3<*****		RMPS1=P3<*****	✓	✓
			PIN4	VXX:RMPS1=P4<*****		RMPS1=P4<*****	✓	✓
			PIN5	VXX:RMPS1=P5<*****		RMPS1=P5<*****	✓	✓
			PIN6	VXX:RMPS1=P6<*****		RMPS1=P6<*****	✓	✓
			PIN7	VXX:RMPS1=P7<*****		RMPS1=P7<*****	✓	✓
		* PARAMETER2	NONE	VXX:RMPS1=P*<NONE		RMPS1=P*<NONE	✓	✓
			HDMI	VXX:RMPS1=P*<HDMI		RMPS1=P*<HDMI	✓	✓
			HDMI1	VXX:RMPS1=P*<HDMI1		RMPS1=P*<HDMI1	✓	✓
			HDMI2	VXX:RMPS1=P*<HDMI2		RMPS1=P*<HDMI2	✓	✓
			DisplayPort	VXX:RMPS1=P*<DP1		RMPS1=P*<DP1	✓	✓
			SLOT1 : SDM : 12G SDI	VXX:RMPS1=P*<DM1,SD1		RMPS1=P*<DM1,SD1	✓	✓
			SLOT1 : SDM : Digital Link	VXX:RMPS1=P*<DM1,DL1		RMPS1=P*<DM1,DL1	✓	✓
			SLOT1 : SDM : PressIT	VXX:RMPS1=P*<DM1,WP1		RMPS1=P*<DM1,WP1	✓	✓
			SLOT1 : SDM : 3rd Party Board	VXX:RMPS1=P*<DM1,TP1		RMPS1=P*<DM1,TP1	✓	✓
			SLOT1 : SDM : 12G SDI OPT1	VXX:RMPS1=P*<DM1,OP1		RMPS1=P*<DM1,OP1	✓	✓
			SLOT1 : SDM : 12G SDI OPT2	VXX:RMPS1=P*<DM1,OP2		RMPS1=P*<DM1,OP2	✓	✓
	REMOTE2 - PIN8	NONE	NONE	VXX:RMPS1=P8<NONE	QVX:RMPS1=P8	RMPS1=P8<NONE	✓	✓
		SHUTTER	SHUTTER	VXX:RMPS1=P8<SHUTTER		RMPS1=P8<SHUTTER	✓	✓
	FUNCTION BUTTON	DISABLE		OFC:0	QFC	0	✓	✓
		SYSTEM SELECTOR		OFC:1		1	✓	✓
		SYSTEM DAYLIGHT VIEW		OFC:2		2	✓	✓
		SUB MEMORY		OFC:3		3	✓	✓
		FREEZE		OFC:4		4	✓	✓
		WAVEFORM MONITOR		OFC:6		6	✓	✓
		LENS MEMORY LOAD		OFC:7		7	✓	✓
		LEFT/RIGHT SWAP		OFC:8		8	✓	✓
		PROJECTION METHOD		OFC:10		10	✓	✓
		GEOMETRY		OFC:13		13	✓	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
	DATE AND TIME-DATE SETTING	Year: yyyy		TSD:201506151	QGD	201506161	✓	✓
		Month: mm		TSD:yyyyymmddw		yyyyymmddw	✓	✓
		Date: dd					✓	✓
		Day:w(1~7:Mon~Sun)					✓	✓
	DATE AND TIME-TIME SETTING	Hour: hh		TST:154503	QGT	154503	✓	✓
		Minute: mm		TST:hmmss		hmmss	✓	✓
		Second: ss					✓	✓
	DATE AND TIME-NTP SYNCHRONIZATION	OFF		VXX:NTPI0=+00000	QVX:NTPI0	NTPI0=+00000	✓	✓
		ON		VXX:NTPI0=+00001		NTPI0=+00001	✓	✓
	LENS TYPE	ET-D75LE6		VXX:LNEI1=+00001	QVX:LNEI1	LNEI1=+00001	✓	✓
		ET-D75LE10		VXX:LNEI1=+00002		LNEI1=+00002	✓	✓
		ET-D75LE20		VXX:LNEI1=+00003		LNEI1=+00003	✓	✓
		ET-D75LE30		VXX:LNEI1=+00004		LNEI1=+00004	✓	✓
		ET-D75LE40		VXX:LNEI1=+00005		LNEI1=+00005	✓	✓
		ET-D75LE8		VXX:LNEI1=+00006		LNEI1=+00006	✓	✓
		ET-D75LE95		VXX:LNEI1=+00007		LNEI1=+00007	✓	✓
		ET-D75LE50		VXX:LNEI1=+00009		LNEI1=+00009	✓	✓
	LENS ID	All		VXX:LNEI4=+00000	QVX:LNEI4	LNEI4=+00000	✓	✓
		1		VXX:LNEI4=+00001		LNEI4=+00001	✓	✓
		255		VXX:LNEI4=+00255		LNEI4=+00255	✓	✓
	LENS NAME			VXX:LNES5=LENSNAME	QVX:LNES5	LNES5=LENSNAME	✓	✓
	LENS CALIBRATION	EXECUTE (ALL)		VXX:LNSI0=+00001			✓	✓
		EXECUTE (SHIFT)		VXX:LNSI0=+00011			✓	✓
		EXECUTE (FOCUS)		VXX:LNSI0=+00012			✓	✓
		EXECUTE (ZOOM)		VXX:LNSI0=+00013			✓	✓
		EXECUTE (SHIFT/FOCUS)		VXX:LNSI0=+00021			✓	✓
		EXECUTE (SHIFT/ZOOM)		VXX:LNSI0=+00022			✓	✓
	EXECUTE (FOCUS/ZOOM)			VXX:LNSI0=+00023			✓	✓
	LENS MEMORY1 NAME CHANGE	LENSMEMORY1		VXX:NCGS5=LENSMEMORY1	QVX:NCGS5	NCGS5=LENSMEMORY1	✓	✓
	LENS MEMORY2 NAME CHANGE	LENSMEMORY2		VXX:NCGS6=LENSMEMORY2	QVX:NCGS6	NCGS6=LENSMEMORY2	✓	✓
	LENS MEMORY3 NAME CHANGE	LENSMEMORY3		VXX:NCGS7=LENSMEMORY3	QVX:NCGS7	NCGS7=LENSMEMORY3	✓	✓
	LENS MEMORY4 NAME CHANGE	LENSMEMORY4		VXX:NCGS9=LENSMEMORY4	QVX:NCGS9	NCGS9=LENSMEMORY4	✓	✓
	LENS MEMORY5 NAME CHANGE	LENSMEMORY5		VXX:NCGSA=LENSMEMORY5	QVX:NCGSA	NCGSA=LENSMEMORY5	✓	✓
	LENS MEMORY6 NAME CHANGE	LENSMEMORY6		VXX:NCGSB=LENSMEMORY6	QVX:NCGSB	NCGSB=LENSMEMORY6	✓	✓
	LENS MEMORY7 NAME CHANGE	LENSMEMORY7		VXX:NCGSC=LENSMEMORY7	QVX:NCGSC	NCGSC=LENSMEMORY7	✓	✓
	LENS MEMORY8 NAME CHANGE	LENSMEMORY8		VXX:NCGSD=LENSMEMORY8	QVX:NCGSD	NCGSD=LENSMEMORY8	✓	✓
	LENS MEMORY9 NAME CHANGE	LENSMEMORY9		VXX:NCGSE=LENSMEMORY9	QVX:NCGSE	NCGSE=LENSMEMORY9	✓	✓
	LENS MEMORY10 NAME CHANGE	LENSMEMORY10		VXX:NCGSF=LENSMEMORY10	QVX:NCGSF	NCGSF=LENSMEMORY10	✓	✓
	LENS MEMORY-LOAD	LENS MEMORY1		VXX:LNMI1=+00000			✓	✓
		LENS MEMORY2		VXX:LNMI1=+00001			✓	✓
		LENS MEMORY3		VXX:LNMI1=+00002			✓	✓
		LENS MEMORY4		VXX:LNMI1=+00003			✓	✓
		LENS MEMORY5		VXX:LNMI1=+00004			✓	✓
		LENS MEMORY6		VXX:LNMI1=+00005			✓	✓
		LENS MEMORY7		VXX:LNMI1=+00006			✓	✓
		LENS MEMORY8		VXX:LNMI1=+00007			✓	✓
		LENS MEMORY9		VXX:LNMI1=+00008			✓	✓
		LENS MEMORY10		VXX:LNMI1=+00009			✓	✓
	LENS MEMORY-SAVE	LENS MEMORY1		VXX:LNMI2=+00000			✓	✓
		LENS MEMORY2		VXX:LNMI2=+00001			✓	✓
		LENS MEMORY3		VXX:LNMI2=+00002			✓	✓
		LENS MEMORY4		VXX:LNMI2=+00003			✓	✓
		LENS MEMORY5		VXX:LNMI2=+00004			✓	✓
		LENS MEMORY6		VXX:LNMI2=+00005			✓	✓
		LENS MEMORY7		VXX:LNMI2=+00006			✓	✓
		LENS MEMORY8		VXX:LNMI2=+00007			✓	✓
		LENS MEMORY9		VXX:LNMI2=+00008			✓	✓
		LENS MEMORY10		VXX:LNMI2=+00009			✓	✓
	LENS MEMORY-DELETE	LENS MEMORY1		VXX:LNMI3=+00000			✓	✓
		LENS MEMORY2		VXX:LNMI3=+00001			✓	✓
		LENS MEMORY3		VXX:LNMI3=+00002			✓	✓
		LENS MEMORY4		VXX:LNMI3=+00003			✓	✓
		LENS MEMORY5		VXX:LNMI3=+00004			✓	✓
		LENS MEMORY6		VXX:LNMI3=+00005			✓	✓
		LENS MEMORY7		VXX:LNMI3=+00006			✓	✓
		LENS MEMORY8		VXX:LNMI3=+00007			✓	✓
		LENS MEMORY9		VXX:LNMI3=+00008			✓	✓
		LENS MEMORY10		VXX:LNMI3=+00009			✓	✓
	LENS MEMORY1-DEFAULT NAME	LENSMEMORY1		VXX:NCLI5=+00000			✓	✓
	LENS MEMORY2-DEFAULT NAME	LENSMEMORY2		VXX:NCLI6=+00000			✓	✓
	LENS MEMORY3-DEFAULT NAME	LENSMEMORY3		VXX:NCLI7=+00000			✓	✓
	LENS MEMORY4-DEFAULT NAME	LENSMEMORY4		VXX:NCLI9=+00000			✓	✓
	LENS MEMORY5-DEFAULT NAME	LENSMEMORY5		VXX:NCLIA=+00000			✓	✓
	LENS MEMORY6-DEFAULT NAME	LENSMEMORY6		VXX:NCLIB=+00000			✓	✓
	LENS MEMORY7-DEFAULT NAME	LENSMEMORY7		VXX:NCLIC=+00000			✓	✓
	LENS MEMORY8-DEFAULT NAME	LENSMEMORY8		VXX:NCLID=+00000			✓	✓
	LENS MEMORY9-DEFAULT NAME	LENSMEMORY9		VXX:NCLIE=+00000			✓	✓
	LENS MEMORY10-DEFAULT NAME	LENSMEMORY10		VXX:NCLIF=+00000			✓	✓
	INITIALIZE-ALL USER DATA	USER INITILIZE		VXX:RSTS1=0password			✓	✓
		USER RESTORE		VXX:RSTS1=1password			✓	✓
	INITIAL START UP	STANDBY		OPY:0	QPY	0	✓	✓
		ON		OPY:1		1	✓	✓
		LAST MEMORY		OPY:2		2	✓	✓
	MODEL NAME	MODEL NAME			QID	MODELNAME	✓	✓
	SERIAL NUMBER	SW0101234			QSN	SW0101234	✓	✓
	PROJECTOR RUNTIME	7864320H			QVX:RTMS1	RTMS1=7864320	✓	✓
	LAMP1(LIGHT1) RUNTIME	9999H			Q\$1:1	9999	✓	✓
	LIGHT1 RUNTIME	7864320H			QVX:LRTS3=00	LRTS3=00:7864320	✓	✓
	LIGHT STATUS	ALL OFF			QLS	0	✓	✓
		1:ON, 2:OFF				1	✓	✓
	CONTINUOUS LIGHTING TIME	7864320H00M			QVX:CLTS1	CLTS1=7864320:00	✓	✓
	CONSOLIDATED RUNTIME	7864320H			QVX:CRTS1	CRTS1=7864320	✓	✓
	LAMP(LIGHT) CONTROL STATUS	LAMP OFF			Q\$S	0	✓	✓
		In turning ON				1	✓	✓
		LAMP ON				2	✓	✓
		LAMP Cooling				3	✓	✓
	POWER STATUS	POWER OFF			QVX:POWI1	POWI1=+00001	✓	✓
		In turning ON				POWI1=+00002	✓	✓
		POWER ON				POWI1=+00003	✓	✓
		Cooling				POWI1=+00004	✓	✓
	MAC ADDRESS	AB0102030405			QMA	AB0102030405	✓	✓
	MAIN FIRMWARE VERSION	V1.00.01			QVX:SVRS0	SVRS0=1.00.01	✓	✓
	NETWORK FIRMWARE VERSION	V1.00			QVX:SVRS1	SVRS1=1.00	✓	✓
	SUB FIRMWARE VERSION	V1.00.01			QVX:SVRS2	SVRS2=1.00.01	✓	✓
	FIRMWARE VERSION	V1.00			QVX:SVRSE	SVRSE=1.00	✓	✓
	INPUT SIGNAL NAME	CHANNEL1 (MAIN CH)			QVX:NSGS1	NSGS1=*****	✓	✓
	TEMPERATURE (INTAKE)	0030/0080			QTM:0	0030/0080	✓	✓
	TEMPERATURE (EXHAUST AIR)	0030/0080			QTM:1	0030/0080	✓	✓
	SDI ERROR STATUS	---			QVX:SESI1	SESI1=+00000	✓	✓
		NOT ID				SESI1=+00001	✓	✓
		ID				SESI1=+00002	✓	✓
		CRCC				SESI1=+00003	✓	✓
	LAN data Cloning Write protect	OFF		LCL:WRP0	QCL:WRP	QCL:WRP0	✓	✓
		ON		LCL:WRP1		QCL:WRP1	✓	✓
	MECH. SHUTTER COUNT				QVX:MSCI0	MSCI0=+*****	✓	✓
	INFO MONITOR SETTING - DEFAULT	OFF		VXX:INFI1=+00000	QVX:INFI1	INFI1=+00000	✓	✓
		USER VIEW		VXX:INFI1=+00001		INFI1=+00001	✓	✓
	INFO MONITOR SETTING - USER VIEW	INPUT		VXX:INFS2=01:*****	QVX:INFS2=01	INFS2=01:*****	✓	✓
		SIGNAL		VXX:INFS2=02:*****	QVX:INFS2=02	INFS2=02:*****	✓	✓
		AC VOLTAGE		VXX:INFS2=03:*****	QVX:INFS2=03	INFS2=03:*****	✓	✓
		INTAKE AIR TEMP.		VXX:INFS2=04:*****	QVX:INFS2=04	INFS2=04:*****	✓	✓
		EXHAUST AIR TEMP.		VXX:INFS2=05:*****	QVX:INFS2=05	INFS2=05:*****	✓	✓
		SHUTTER		VXX:INFS2=06:*****	QVX:INFS2=06	INFS2=06:*****	✓	✓

				CONTROL	QUERY		RQ25K SERIES	RZ24K SERIES
CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	COMMANDS/CALL BACK	COMMANDS	CALL BACK	RQ25K SRQ25KC RQ18K SRQ18KC	RZ24K SRZ24KC RZ17K SRZ17KC
		OSD		VXX:INFS2=07:*****	QVX:INFS2=07	INFS2=07:*****	✓	✓
		IP ADDRESS		VXX:INFS2=08:*****	QVX:INFS2=08	INFS2=08:*****	✓	✓
		FREEZE		VXX:INFS2=09:*****	QVX:INFS2=09	INFS2=09:*****	✓	✓
		OFF		VXX:INFS2=**:00000			✓	✓
		ON		VXX:INFS2=**:00001			✓	✓
	INFO MONITOR SETTING - DIRECTION	AUTO		VXX:INFI3=+00000	QVX:INFI3	INFI3=+00000	✓	✓
		NORMAL		VXX:INFI3=+00001		INFI3=+00001	✓	✓
		FLIPPED		VXX:INFI3=+00002		INFI3=+00002	✓	✓
	INFO MONITOR SETTING - BRIGHTNESS	30%		VXX:INFI4=+00030	QVX:INFI4	INFI4=+00030	✓	✓
		100%		VXX:INFI4=+00100		INFI4=+00100	✓	✓
TEST PATTERN	TEST PATTERN	Off		OTS:00	QTS	00	✓	✓
		White		OTS:01		01	✓	✓
		Black		OTS:02		02	✓	✓
		Window		OTS:05		05	✓	✓
		Reversed Window		OTS:06		06	✓	✓
		Cross Hatch		OTS:07		07	✓	✓
		Color Bar V		OTS:08		08	✓	✓
		Focus (Level 0%)		OTS:32		32	✓	✓
		Focus (Level 50%)		OTS:33		33	✓	✓
		Focus (Level 100%)		OTS:34		34	✓	✓
		Color Bar Side		OTS:51		51	✓	✓
		16:9/4:3		OTS:59		59	✓	✓
		Focus Red		OTS:70		70	✓	✓
		Focus Green		OTS:71		71	✓	✓
		Focus Blue		OTS:72		72	✓	✓
		Focus Cyan		OTS:73		73	✓	✓
		Focus Magenta		OTS:74		74	✓	✓
		Focus Yellow		OTS:75		75	✓	✓
		Focus		OTS:78		78	✓	✓
		3D-1		OTS:80		80		✓
		3D-2		OTS:81		81		✓
		3D-3		OTS:82		82		✓
		3D-4		OTS:83		83		✓
		CIRCLE		OTS:87		87	✓	✓
		USER TEST PATTERN 1		OTS:A1		A1	✓	✓
		USER TEST PATTERN 2		OTS:A2		A2	✓	✓
		USER TEST PATTERN 3		OTS:A3		A3	✓	✓
	USER TEST PATTERN - RENAME USER TEST PATTERN	USER TEST PATTERN 1 - NAME		VXX:TPNS1=01:USERTESTPATTERN1	QVX:TPNS1=01	TPNS1=01:USERTESTPATTERN1	✓	✓
		USER TEST PATTERN 2 - NAME		VXX:TPNS1=02:USERTESTPATTERN2	QVX:TPNS1=02	TPNS1=02:USERTESTPATTERN2	✓	✓
		USER TEST PATTERN 3 - NAME		VXX:TPNS1=03:USERTESTPATTERN3	QVX:TPNS1=03	TPNS1=03:USERTESTPATTERN3	✓	✓
	USER TEST PATTERN - DELETE USER TEST PATTERN	USER TEST PATTERN 1 - DELETE		VXX:TPNS2=01			✓	✓
		USER TEST PATTERN 2 - DELETE		VXX:TPNS2=02			✓	✓
		USER TEST PATTERN 3 - DELETE		VXX:TPNS2=03			✓	✓
SIGNAL LIST	SIGNAL LIST-REGISTRATION			OEM			✓	✓
	SIGNAL LIST-DELETE	A1		ODM:A1			✓	✓
		A2		ODM:A2			✓	✓
		A7		ODM:A7			✓	✓
		A8		ODM:A8			✓	✓
		L1		ODM:L1			✓	✓
		L2		ODM:L2			✓	✓
		L7		ODM:L7			✓	✓
		L8		ODM:L8			✓	✓
	SUB MEMORY LIST-CHANGEOVER	01		OCS:01			✓	✓
		96		OCS:96			✓	✓
	SUB MEMORY LIST-CHANGEOVER (EXTENDED)	01		OCS:01-01			✓	✓
		96		OCS:95-96			✓	✓
	SUB MEMORY LIST-REGISTRATION			OES			✓	✓
	SUB MEMORY LIST-DELETE	01		ODS:01-01			✓	✓
		96		ODS:95-96			✓	✓
	SUB MEMORY USAGE STATE	01			QSB	01	✓	✓
		96				96	✓	✓
SECURITY	SECURITY SETTING	OFF			QVX:SPWI1	SPWI1=+00000	✓	✓
		ON				SPWI1=+00001	✓	✓
	CONTROL DEVICE SETUP-CONTROL PANEL	DISABLE		VXX:CDSI1=+00000	QVX:CDSI1	CDSI1=+00000	✓	✓
		ENABLE		VXX:CDSI1=+00001		CDSI1=+00001	✓	✓
		USER		VXX:CDSI1=+00002		CDSI1=+00002	✓	✓
	CONTROL DEVICE SETUP-REMOTE CONTROL	DISABLE		VXX:CDSI2=+00000	QVX:CDSI2	CDSI2=+00000	✓	✓
		ENABLE		VXX:CDSI2=+00001		CDSI2=+00001	✓	✓
		USER		VXX:CDSI2=+00002		CDSI2=+00002	✓	✓
NETWORK	ETHERNET TYPE	LAN		VXX:ETHI1=+00001	QVX:ETHI1	ETHI1=+00001	✓	✓
		DIGITAL LINK		VXX:ETHI1=+00002		ETHI1=+00002	✓	✓
		LAN & DIGITAL LINK		VXX:ETHI1=+00003		ETHI1=+00003	✓	✓
	WIRED LAN-IP VERSION	IPv4		VXX:IPVI1=+00001	QVX:IPVI1	IPVI1=+00001	✓	✓
		IPv6		VXX:IPVI1=+00002		IPVI1=+00002	✓	✓
		IPv4 & IPv6		VXX:IPVI1=+00003		IPVI1=+00003	✓	✓
	WIRELESS LAN	OFF(DISABLE)		ONS:0	QVX:WLSI1	WLSI1=+00000	✓	✓
		ON(ENABLE)		ONS:14		WLSI1=+00014	✓	✓
	SLOT : DIGITAL LINK MODE	AUTO		VXX:SLSS1=VXX:DKMI1=+00001	QVX:SLSS1=QVX:DKMI1	SLSS1=DKMI1=+00001	✓	✓
		DIGITAL LINK		VXX:SLSS1=VXX:DKMI1=+00002		SLSS1=DKMI1=+00002	✓	✓
		ETHERNET		VXX:SLSS1=VXX:DKMI1=+00003		SLSS1=DKMI1=+00003	✓	✓
		LONG REACH MODE		VXX:SLSS1=VXX:DKMI1=+00004		SLSS1=DKMI1=+00004	✓	✓
	DIGITAL LINK-EXTRON XTP	OFF		VXX:EXTI1=+00000	QVX:EXTI1	EXTI1=+00000	✓	✓
		ON		VXX:EXTI1=+00001		EXTI1=+00001	✓	✓
	SLOT : DIGITAL LINK STATUS-LINK	NO LINK			QVX:SLSS1=QVX:DKSI1	SLSS1=DKSI1=+00000	✓	✓
		DIGITAL LINK				SLSS1=DKSI1=+00001	✓	✓
		LPM				SLSS1=DKSI1=+00002	✓	✓
		ETHERNET				SLSS1=DKSI1=+00003	✓	✓
	SLOT : DIGITAL LINK STATUS-HDCP STATUS	NO SIGNAL			QVX:SLSS1=QVX:DKSI2	SLSS1=DKSI2=+00000	✓	✓
		OFF				SLSS1=DKSI2=+00001	✓	✓
		ON				SLSS1=DKSI2=+00002	✓	✓
	SLOT : DIGITAL LINK STATUS-SIGNAL QUALITY (MIN)	-255			QVX:SLSS1=QVX:DKSI3	SLSS1=DKSI3=-00255	✓	✓
		0				SLSS1=DKSI3=+00000	✓	✓
	SLOT : DIGITAL LINK STATUS-SIGNAL QUALITY (MAX)	-255			QVX:SLSS1=QVX:DKSI4	SLSS1=DKSI4=-00255	✓	✓
		0				SLSS1=DKSI4=+00000	✓	✓
	SLOT : DIGITAL LINK INPUT CH LIST	HD1:HDMI1,HD2:HDMI2-...			QVX:SLSS1=QVX:DL1S1	SLSS1=DL1S1=HD1:HDMI1,***:***	✓	✓
	PROJECTOR NAME SETTING	PROJECTOR1		VXX:NCGS8=PROJECTOR1	QVX:NCGS8	NCGS8=PROJECTOR1	✓	✓
	NFC SETTING	OFF		VXX:NFCI1=+00000	QVX:NFCI1	NFCI1=+00000	✓	✓
		READ ONLY		VXX:NFCI1=+00001		NFCI1=+00001	✓	✓
		READ/WRITE		VXX:NFCI1=+00003		NFCI1=+00003	✓	✓
	Art-Net SETUP	OFF		VXX:DANI1=+00000	QVX:DANI1	DANI1=+00000	✓	✓
		ON(2,*,*)		VXX:DANI1=+00002		DANI1=+00002	✓	✓
		ON(10,*,*)		VXX:DANI1=+00003		DANI1=+00003	✓	✓
		ON(MANUAL)		VXX:DANI1=+00004		DANI1=+00004	✓	✓
	Art-Net SETUP-START ADDRESS	1		VXX:DANI3=+00001	QVX:DANI3	DANI3=+00001	✓	✓
		501		VXX:DANI3=+00501		DANI3=+00501	✓	✓
	Art-Net SETUP-NET	0		VXX:DANI4=+00000	QVX:DANI4	DANI4=+00000	✓	✓
		127		VXX:DANI4=+00127		DANI4=+00127	✓	✓
	Art-Net SETUP-SUB NET	0		VXX:DANI5=+00000	QVX:DANI5	DANI5=+00000	✓	✓
		15		VXX:DANI5=+00015		DANI5=+00015	✓	✓
	Art-Net SETUP-UNIVERS	0		VXX:DANI6=+00000	QVX:DANI6	DANI6=+00000	✓	✓
		15		VXX:DANI6=+00015		DANI6=+00015	✓	✓
	Art-Net SETUP-CHANNEL SETTING	DEFAULT		VXX:DANI8=+00000	QVX:DANI8	DANI8=+00000	✓	✓
		1		VXX:DANI8=+00001		DANI8=+00001	✓	✓
		2		VXX:DANI8=+00002		DANI8=+00002	✓	✓
		USER		VXX:DANI8=+00100		DANI8=+00100	✓	✓
	PRESHOW MODE	OFF			QVX:PSMI1	PSMI1=+00000	✓	✓
		ON				PSMI1=+00001	✓	✓

Note: The commands or parameters with "*" shows available commands or parameters for the projector which has been activated by the Upgrade Kit.