

Pin Nb	PINs	FUNCTIONs	LABELs	NOTE
A2	PE0	GPIO_EXTI0	SYSMCU_IRQ	
A3	PF3	GPIO_EXTI3	DIB3_IRQ	
A4	PF2	GPIO_EXTI2	DIB2_IRQ	
A5	PG3	GPIO_Output	WDG_OUT	
A7	PM12*	USB_OTG_FS_DM		
A9	PM6	USB_OTG_HS_DP		
A10	PM3	GPIO_Output	DIB3_CSA	
A12	PD3	LTDC_B1		24-bit RGB data
A13	PE14	SPI4_MOSI	DIB2/DIB5_MOSI	
A14	PD2	SDMMC1_CMD		SDcard control
B1	PB8*	SDMMC1_D4		Not used
B2	PE2	SPI4_SCK	DIB2/DIB5_SCK	
B3	PB5	LTDC_R2		24-bit RGB data
B4	PF4	GPIO_EXTI4	DIB4_IRQ	
B5	PF0	I2C2_SDA	SDA	
B6	PD7	ETH_RMII_REF_CLK		Ethernet MII
B7	PM11*	USB_OTG_FS_DP		
B8	PM9*	USB_OTG_HS_ID		
B9	PM5	USB_OTG_HS_DM		
B10	PM2	GPIO_Input	DIN2	
B11	PG0	LTDC_R7		24-bit RGB data
B12	PE13	SPI4_MISO	DIB2/DIB5_MISO	
B13	PD1	UART4_TX	RS485_TX/DOUT3	
B14	PC10	SDMMC1_D2		SDcard data
B15	PC11	SDMMC1_D3		SDcard data
C2	PB9*	SDMMC1_D5		Not used
C4	PB3(JTDO/TRACESWO)	LTDC_R4		24-bit RGB data
C5	PF1	I2C2_SCL	SCL	
C6	PG2	LTDC_HSYNC		24-bit RGB control
C7	PM13	SPI5_MOSI	DIB4_MOSI	
C8	PM14	SPI5_MISO	DIB4_MISO	
C9	PM8*	USB_OTG_HS_VBUS		
C12	PE11	LTDC_VSYNC		24-bit RGB control
C13	PD0	UART4_RX	RS485_RX/DIN3	
C14	PA12	SPI2_SCK	DIB1/DIB3_SCK	
C15	PA11	LTDC_B3		24-bit RGB data
D1	PC15-OSC32_OUT(OSC32_OUT)	GPIO_Output	ETH_RESET	Ethernet PHY dedicated RESET (optional)
D2	PC14-OSC32_IN(OSC32_IN)	RCC_OSC32_IN		RTC input
D4	PB7	ETH_RMII_TXD1		Ethernet MII
D5	PB4(NJTRST)	SPI2_NSS	DIB1_CSA	
D7	PD5	GPIO_EXTI5	DIB5_IRQ	
D10	PM0	GPIO_Input	SD_DETECT	SDcard detect
D11	PE15	GPIO_Output	LED_PWR	
D12	PC12	SDMMC1_CK		SDcard control
D13	PA14(JTCK/SWCLK)	DEBUG_JTCK-SWCLK	SWCLK	JTAG clock
D14	PA9	LTDC_B5		24-bit RGB data
D15	PC8	SDMMC1_D0		SDcard data
E1	PE6	GPIO_Output	DIB5_CSA	
E2	PE4	SPI4_NSS	DIB2_CSA	
E5	PB6	CEC	DVID_CEC	HDMI CEC
E7	PD6	ETH_CLK		Ethernet MII
E10	PG1	LTDC_R6		24-bit RGB data
E11	PE12	GPIO_EXTI12	DVID_HPD	HDMI hotplug detection
E12	PA13(JTMS/SWDIO)	DEBUG_JTMS-SWDIO	SWDIO	JTAG data
E13	PA10	LTDC_B4		24-bit RGB data
E14	PC9	SDMMC1_D1		SDcard data
E15	PC6*	SDMMC1_D6		Not used
F1	PG14	GPIO_Output	SYSMCU_CS	
F2	PG12	LTDC_G1		24-bit RGB data
F3	PG11	ETH_RMII_TX_EN		Ethernet MII
F12	PA8	LTDC_B6		24-bit RGB data
F13	PC7*	SDMMC1_D7		Not used
F14	PN1	XSPIM_P2_NCS1		FLASH memory control
G5	PG13	ETH_RMII_TXD0		Ethernet MII
G11	PA15(JTDI)	LTDC_R5		24-bit RGB data
G13	PN3	XSPIM_P2_IO1		FLASH memory data

G14	PN0	XSPIM_P2_DQS0		FLASH memory control
G15	PN11	XSPIM_P2_IO7		FLASH memory data
H4	PF7	UART7_TX	UART_TX/DOUT1	
H5	PF6	GPIO_Output	DIB4_CSA	
H13	PN10	XSPIM_P2_IO6		FLASH memory data
H14	PN9	XSPIM_P2_IO5		FLASH memory data
H15	PN2	XSPIM_P2_IO0		FLASH memory data
J2	PF9	LTDC_R0		24-bit RGB data
J3	PF10	LTDC_R1		24-bit RGB data
J14	PN6	XSPIM_P2_CLK		
K1	PH0-OSC_IN(PH0)	RCC_OSC_IN		RCC XTAL input
K2	PH1-OSC_OUT(PH1)	RCC_OSC_OUT		RCC XTAL output
K13	PN8	XSPIM_P2_IO4		FLASH memory data
K14	PN4	XSPIM_P2_IO2		FLASH memory data
K15	PN5	XSPIM_P2_IO3		FLASH memory data
L1	PC1	ETH_MDC		Ethernet MII
L2	PC2	SPI2_MISO	DIB1/DIB3_MISO	
L3	PC3	SPI2_MOSI	DIB1/DIB3_MOSI	
L4	PA2	ETH_MDIO		Ethernet MII
L5	PC4	ETH_RMII_RXD0		Ethernet MII
L12	PB12	LTDC_G5		24-bit RGB data
L14	PD14	GPIO_Output	USB_FS_SEL	USB mux selection
M1	PA0	LTDC_G3		24-bit RGB data
M2	PA1	LTDC_G2		24-bit RGB data
M3	PA4	LTDC_R3		24-bit RGB data
M4	PA7	ETH_RMII_CRS_DV		Ethernet MII
M5	PF11	LTDC_B0		24-bit RGB data
M6	PE7	UART7_RX	UART_RX/DIN1	
M11	PO3	XSPIM_P1_DQS1		PSRAM control
M12	PP10	XSPIM_P1_IO10		PSRAM data
M13	PB14	UART4_DE	RS485_TX_EN/DOUT2	
M14	PB15	LTDC_G7		24-bit RGB data
N1	PA3	LTDC_DE		24-bit RGB control
N2	PA5	LTDC_CLK		24-bit RGB control
N3	PC5	ETH_RMII_RXD1		Ethernet MII
N4	PB2	LTDC_B2		24-bit RGB data
N5	PF15	SPI5_SCK	DIB4_SCK	
N6	PP12	XSPIM_P1_IO12		PSRAM data
N7	PP14	XSPIM_P1_IO14		PSRAM data
N9	PP2	XSPIM_P1_IO2		PSRAM data
N10	PP5	XSPIM_P1_IO5		PSRAM data
N11	PO2	XSPIM_P1_DQS0		PSRAM control
N12	PP1	XSPIM_P1_IO1		PSRAM data
N14	PB11	LTDC_G6		24-bit RGB data
N15	PB13	LTDC_G4		24-bit RGB data
P1	PA6	LTDC_B7		24-bit RGB data
P2	PB0	GPIO_Output	VMUX_EN	Video mux enable
P3	PF13	GPIO_Output	VMUX_SEL	Video mux selection
P4	PF14	LTDC_G0		24-bit RGB data
P6	PP11	XSPIM_P1_IO11		PSRAM data
P8	PP15	XSPIM_P1_IO15		PSRAM data
P9	PP3	XSPIM_P1_IO3		PSRAM data
P11	PP0	XSPIM_P1_IO0		PSRAM data
P12	PP7	XSPIM_P1_IO7		PSRAM data
P13	PP8	XSPIM_P1_IO8		PSRAM data
P15	PB10*	ETH_MII_RX_ER		Ethernet MII
R2	PB1	GPIO_EXTI1	DIB1_IRQ	
R4	PE8	GPIO_EXTI8	TFT_IRQ	
R5	PE10	GPIO_Output	LED_nACT	Active LED
R7	PP13	XSPIM_P1_IO13		PSRAM data
R8	PP4	XSPIM_P1_IO4		PSRAM data
R10	PO4	XSPIM_P1_CLK		PSRAM control
R11	PP6	XSPIM_P1_IO6		PSRAM data
R13	PO0	XSPIM_P1_NCS1		PSRAM control