

--	--

--	--


USB Port	USB type	STM32H7 CM5	Raspberry PI CM5
Rear top	USB A	FS only	USB #0, HS/SS
Rear bottom	USB A	FS/HS	USB Hub PI Flex
Front	USB C	USB Hub P2, HS/SS, Dual role	
DIB #1	DIB 2.0	USB Hub P7, HS/SS	
DIB #2	DIB 2.0	USB Hub P6, HS/SS	
DIB #3	DIB 2.0	USB Hub P5, HS/SS	
DIB #4	DIB 2.0	USB Hub P4, HS/SS	
DIB #5	DIB 2.0	USB Hub P3, HS/SS	


I2C address	Device
0x51	EEPROM M24C32
0x2F	Fan controller EMC2301
0x2D	USB3 Hub
0x7A	PTN5150A USB CC controller








SIZE: A1	
KiCad E.D.A. 10.0.6	

Id: 1/10










Device	What It protects	What it does in normal operation	What it does in a fault
D12	Q4 base-emitter junction	Clamps reverse Vbe to about 0.7 V	Prevents Q4 from entering damaging reverse base-emitter breakdown
Z01	Attenuated AC LINE sense node	Limits the sampled mains node to about 5.1 V relative to AC_NEUTRAL	Stops the sense node from overdriving the downstream stage during spikes or abnormal circumstances
Z02	Low-voltage Internal node after Z01	Usually inactive; only conducts on transients	Clamps fast surges/ESD/ESD to downstream circuitry does not see excessive voltage
Z03	PE-related clamping node / floating PE path	Usually inactive when PE is healthy	Limits the PE-opp floating node during its handling (polarity reversals and surges

Envox d.o.o.
Sheet: /AC power, DC power, AC sync/
File: ac_dc_power.kicad_sch

Size: A4	Date: 2026-10-09
KiCad E.D.A. 10.0.6	

Rev: r1B3
Id: 4/10


Isolated digital I/O & RS485 transceiver (half-duplex)




Rear panel I/O connector

- +VCC_ISO 1
- RS485_A_ISO 2
- RS485_B_ISO 3
- GND_ISO 4
- UART_TX/DOUT1 5
- DOUT2 6
- DOUT3 7
- UART_RX/DIN1 8
- DIN2 9
- DIN3 10

Isolated regulated power supply (+5V)




Encoder with switch



Encoder shaft length: 15 mm / Flatted
 Knob head Ø31mm A1031648 (OKW) + Knob pointer A1101007 (OKW)
 Optional: Knob head Ø31mm A3131068 (OKW) + Knob cap A3231007 (OKW)
 Knob head Ø24mm A1024648 (OKW) + Knob pointer A1101007 (OKW)

12V DC Fan speed controllers



- Connector for 3- or 4-pin DC 12V Fan
- 1 Fan- (Black)
 - 2 Fan+ (Yellow or Red)
 - 3 Fan sense (Green or Yellow)
 - 4 Fan control (Blue)

<https://github.com/eez-open/eez-bb3plus>

More info at <http://www.envox.eu/>

Licensed under the TAPR Open Hardware License (www.tapr.org/OHL)

Envox d.o.o.

Sheet: /Isolated digital IO, Fan controller, Encoder/

File: digital_io_fan_encoder.kicad_sch

Title: BB3+ mainboard


Size: A4 Date: 2026-10-09

KiCad E.D.A. 10.0.6


Rev: r1B3

Id: 5/10


USB-C 3.0 front port (source max 1.5A)




USB-C 3.0 Protection and Mux



USB2.0 Type-A (Rear panel)



VBus Discharge Circuit



<https://github.com/eez-open/eez-bb3plus>

More info at <http://www.envox.eu/>

Licensed under the TAPR Open Hardware License (www.tapr.org/OHL)

Envox d.o.o.

Sheet: /Rear USB, USB-C/

File: usb_conn.kicad_sch

Title: BB3+ mainboard


Size: A4 Date: 2026-10-09

KiCad E.D.A. 10.0.6


Rev: r1B3

Id: 7/10


External monitor digital output




TFT Touchscreen display DVID output (22-pin FFC)




TFT Touchscreen display DSI output (22-pin FFC)



10MHz refclk & fanout



Ethernet RJ45+mag



<https://github.com/eez-open/eez-bb3plus>

More info at <http://www.envox.eu/>

Licensed under the TAPR Open Hardware License (www.tapr.org/OHL)

Envox d.o.o.

Sheet: /Ethernet, Video outputs, Ref clk/

File: video_outputs.kicad_sch

Title: BB3+ mainboard

Size: A4 Date: 2026-10-09

KiCad E.D.A. 10.0.6



Rev: r1B3

Id: 8/10


DIB 2.0 Power modules coupling

20-pin DIB v2.0 Power connector

PWR+ IN 1	☐	☐	2 PWR+ IN
PWR+ IN 3	☐	☐	4 PWR+ IN
PWR+ IN 5	☐	☐	6 PWR+ OUT
PWR+ OUT 7	☐	☐	8 PWR+ OUT
PWR+ OUT 9	☐	☐	10 PWR+ OUT
PWR- OUT 11	☐	☐	12 PWR- OUT
PWR- OUT 13	☐	☐	14 PWR- OUT
PWR- IN 15	☐	☐	16 PWR- IN
PWR- IN 17	☐	☐	18 PWR- IN
SENSE- 19	☐	☐	20 SENSE+



Rear front power outputs



Rear panel power connector

CH2_OUT+	1	☐
CH2_OUT-	2	☐
CH2_SENSE+	3	☐
CH2_SENSE-	4	☐
PE	5	☐
CH1_OUT+	6	☐
CH1_OUT-	7	☐
CH1_SENSE+	8	☐
CH1_SENSE-	9	☐
PE	10	☐

<https://github.com/eez-open/eez-bb3plus>

More info at <http://www.envox.eu/>

Licensed under the TAPR Open Hardware License (www.tapr.org/OHL)

Envox d.o.o.

Sheet: /Power modules coupling/

File: power_coupling.kicad_sch

Title: BB3+ mainboard

Size: A4	Date: 2026-10-09
----------	------------------

Size: A4	
KiCad E.D.A. 10.0.6	

Rev: r1B3

Id: 10/10