

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Blu-ray
Manufacturer: TASCAM
Firmware Version: N/A
Model(s): BD-MP4K

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.17.0000-b002	2.19.0.48

Version History

Module Version	Date	Notes
1_0_0_0	6/26/2023	Initial Version

Module Notes

- Device documentation mentions that Wake-on-LAN is required to power on the device when using Ethernet control, thus Ethernet control does not support Power “On” in this module. Reference Extron Wake-on-LAN function, however this is not guaranteed to work.
- A 0.03 second command pacing is recommended between all commands.

Supported Classes and Examples

SerialClass
InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='BD-MP4K')
SerialOverEthernetClass
InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='BD-MP4K')
EthernetClass
InterfaceName = ModuleName.EthernetClass('192.168.254.254', 9030, Model='BD-MP4K')

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	Value	Value
DiskTray	'Open'	'Close'	
# DiskTray example InterfaceName.Set('DiskTray', 'Open')			
Menu	'Setup Menu' 'Enter' 'Up' 'Right'	'Top/Disc Menu' 'Return' 'Down' 'Option Menu'	'Popup Menu' 'Home' 'Left'
# Menu example InterfaceName.Set('Menu', 'Setup Menu')			
Mute	'On'	'Off'	
# Mute example InterfaceName.Set('Mute', 'On')			
Power ¹	'On'	'Off'	
# Power example InterfaceName.Set('Power', 'On')			
PowerOff ²	'Off'		
# PowerOff example InterfaceName.Set('PowerOff', 'Off')			
Transport	'Stop' 'Fast Forward' 'Track Skip Previous'	'Play' 'Rewind'	'Play Pause' 'Track Skip Next'
# Transport example InterfaceName.Set('Transport', 'Stop')			

¹ Only supported for Serial control.

² Only supported for Ethernet control.

Cable and Adapter Requirements

Captive Screw to Male DB9 RS-232 Serial Cable

Notes for the Device

The 'Power On' command should be sent in the transfer speed of 57600 bits/sec.

Serial communication

Port Type: RS-232

Baud Rate: 57600


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD		2	TxD
RxD		3	RxD
GND		1	GND



Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type: Ethernet (TCP)

Default Port: 9030

Logon Credentials Supported: No

Multi-Connection Capabilities: No

Port Changeability: No

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

Appendix A. Set Commands

Disk Tray Close	!70PCCL\x0D
Disk Tray Open	!70PCOP\x0D
Menu Down	!70SD4\x0D
Menu Enter	!7ENT\x0D
Menu Home	!7HOM\x0D
Menu Left	!70SD1\x0D
Menu Option Menu	!7OMN\x0D
Menu Popup Menu	!7PMN\x0D
Menu Return	!7RET\x0D
Menu Right	!70SD2\x0D
Menu Setup Menu	!7SMN\x0D
Menu Top/Disc Menu	!7TMN\x0D
Menu Up	!70SD3\x0D
Mute Off	!7MUT01\x0D
Mute On	!7MUT00\x0D
Power Off	!7PWR00\x0D
Power On	!7PWR01\x0D
Transport Fast Forward	!7SCNFf\x0D
Transport Play	!7PLY\x0D
Transport Play Pause	!7PAS\x0D
Transport Rewind	!7SCNRf\x0D
Transport Stop	!7STP\x0D
Transport Track Skip Next	!7SKPNX\x0D
Transport Track Skip Previous	!7SKPPV\x0D