Applying Compressive Sensing to Sparse Microwave Imaging: A Practical Perspective

Chen Wei-Cheng, R11942012

Abstract

Microwave imaging is a valuable tool in a variety of applications, including medical diagnostics, security, and non-destructive testing. However, traditional imaging methods often require dense sampling, which increases both hardware and computational costs. This paper explores the application of *compressive sensing (CS)* to microwave imaging, focusing on how it addresses these challenges. Compressive sensing allows for accurate signal reconstruction with significantly fewer measurements, taking advantage of signal sparsity. The paper details the mathematical foundation of CS, including the use of *Matching Pursuit (MP)* and *Basis Pursuit (BP)* algorithms, and discusses the regularization technique known as the *2k filter*. By comparing the inverse problem with and without compressive sensing algorithm *SPGL1*, we demonstrate how CS improves reconstruction accuracy with reduced data acquisition, making the process more efficient. This paper also highlights the practical implementation of these methods, ensuring that complex algorithms are presented in a way that is accessible to a wide audience. Additionally, the final section provides a thorough discussion of promising future directions.

1 Introduction

Microwave imaging utilizes the penetrative properties of microwaves to visualize the internal structure of objects. Unlike visible light, microwaves can pass through materials, making them ideal for applications such as *breast cancer detection*, *through-wall imaging*, and *material inspection*. Additionally, the non-ionizing property of microwaves opens up possibilities for safer medical imaging alternatives to radioactive technologies such as X-ray and computed tomography. However, traditional microwave imaging methods often require dense spatial sampling or mechanical scanning, which can be time-consuming and computationally expensive. To address these challenges, *compressive sensing (CS)* offers a solution that allows signal reconstruction from much fewer measurements than is traditionally required by the *Nyquist sampling theorem*.

This paper explores the integration of compressive sensing into microwave imaging, specifically focusing on the inverse problem of reconstructing the permittivity distribution $\epsilon(\mathbf{r})$ from sparse data. The use of *Matching Pursuit (MP)* and *Basis Pursuit (BP)* methods for sparse signal recovery is detailed, along with the application of the *2k filter* as a regularization technique. Through this approach, we demonstrate how compressive sensing can significantly improve the efficiency of microwave imaging by reducing the data acquisition requirements by about 30 percent of the Nyquist limit while maintaining high accuracy in reconstruction.

2 Background

2.1 Microwave Imaging Problems

Microwave imaging aims to reconstruct the *permittivity distribution* $\epsilon(\mathbf{r})$ of an object from the scattered electromagnetic fields. This is framed as an *inverse scattering problem*, where measurements of the scattered fields are used to infer the internal properties of the target.




Figure 1: [5] (a) Schematic of the transmitting antenna when the target object is absent. (b) Equivalent circuit for the transmitting antenna. (c) Schematic of the receiving antenna excited by an external source J_{eq}. (d) Equivalent circuit for the receiving antenna.

In this specific scenario, we need an expression for the received voltage due to the scattering

of interest. As shown in Figure 1, a receiving probe antenna detects its response by integrating the scattered vector fields within the scanning area, which are induced by the target scatterer. This response is represented as a Thevenin equivalent voltage across the open terminals of the antenna. According to the antenna reciprocity theorem, in a linear, isotropic material environment, the power applied to the scatterer by the transmitter is equal to the power received from the scatterer by the receiver. This relationship can be mathematically expressed to describe the connection between the measurable quantity and the target object function:

$$\int_V \mathbf{E}_{\text{inc}}(\mathbf{r}' - \mathbf{r}, f) \cdot J_{\text{eq}}(\mathbf{r}', \mathbf{r}, f)\, d\tau = -I_{\text{in}} V_{\text{oc}}(\mathbf{r}, f)$$

By applying the volume equivalence principle, the dielectric target can be replaced with an equivalent current source J_{eq}. For weak scatterers, we can simplify the equation using the first-order Born approximation, where $E_{\text{tot}} \approx E_{\text{inc}}$. This approximation simplifies the complex interactions within the system, representing the dielectric target as an equivalent source that emits the measured electromagnetic response. The mathematical formulation for the measured voltage V_{oc} at the receiving antenna is then given by:

$$V_{\text{oc}}(\mathbf{r}, f) \approx -\frac{i\omega}{I_{\text{in}}} \int_V |\mathbf{E}_{\text{inc}}(\mathbf{r}' - \mathbf{r}, f)|^2 (\epsilon(\mathbf{r}') - \epsilon_0)\, d\tau$$

where $\mathbf{E}_{\text{inc}}$ is the incident electric field and $\epsilon(\mathbf{r}')$ is the permittivity distribution.

2.2 Fundamentals of Compressive Sensing

2.2.1 Norms and Their Physical Interpretations

1. L_0 **Norm**: Counts the number of nonzero coefficients. It directly measures sparsity but is non-convex and computationally hard to optimize.

2. L_1 **Norm**: Encourages sparsity by summing the absolute values of coefficients. It is convex, making it suitable for practical optimization:

$$||c||_1 = \sum |c_m|.$$

3. L_2 **Norm**: Measures the Euclidean distance, used for error minimization in reconstruction:

$$||x||_2 = \sqrt{\sum x[n]^2}.$$

2.2.2 Introduction to Compressive Sensing

Compressive sensing exploits the fact that many signals (including the permittivity distribution in microwave imaging) are *sparse* in an appropriate basis. Instead of acquiring all the data points required by traditional methods, compressive sensing allows for accurate reconstruction from fewer measurements by solving an optimization problem:

$$\min \|\mathbf{x}\|_1 \quad \text{subject to} \quad \|\Phi\mathbf{x} - \mathbf{y}\|_2^2 \leq \epsilon,$$

where:

- $\mathbf{x}$ is the sparse representation of the signal.
- Φ is the measurement matrix, which relates the signal to the measurements.
- $\mathbf{y}$ is the observed measurement vector.

For compressive sensing to work, the signal must be sparse in some basis, and the measurement matrix Φ must be *incoherent* with this basis.

2.2.3 Optimization Problems in Compressive Sensing

Compressive sensing (CS) tackles the challenge of reconstructing signals with far fewer measurements than required by traditional sampling methods, such as the Nyquist criterion. The method is rooted in the assumption that signals are sparse in a certain basis, meaning they can be represented by a small number of nonzero coefficients.

The objective in CS is to find the sparsest representation of a signal $x(t)$, subject to constraints derived from the available measurements. Three common formulations are:

- **Sparsity Problem**: Minimize the number of nonzero coefficients (L_0 norm) in the signal's expansion:

  $$\min ||c||_0, \quad \text{such that} \quad x(t) = \sum c_m b_m(t),$$

  where $b_m(t)$ are basis functions (e.g., wavelets or atoms from an overcomplete dictionary).

- **Error-Constrained Problem**: Minimize the sparsity of the representation while keeping the reconstruction error below a threshold ϵ:

  $$\min ||c||_0, \quad \text{such that} \quad \int \left(x(t) - \sum c_m b_m(t)\right)^2 dt < \epsilon.$$

- **Fixed Sparsity Problem**: For a fixed number of coefficients ($||c||_0 = M$), minimize the reconstruction error:

$$\min \int \left(x(t) - \sum_{m=1}^{M} c_m b_m(t) \right)^2 dt.$$

2.2.4 Matching Pursuit (MP)

Matching Pursuit is a greedy algorithm that iteratively approximates a signal by selecting atoms from an overcomplete dictionary. Each iteration minimizes the residual (the difference between the signal and its current approximation) by projecting it onto the dictionary atom that best matches its structure.

Algorithm Steps:

1. Initialize Residual: Start with the signal itself as the residual, $r_0(t) = x(t)$.
2. Select Atom: Find the dictionary atom $b_m(t)$ that maximizes the correlation with the residual:
$$b_m(t) = \arg\max \int r_n(t) b_m^*(t) dt.$$
3. Update Residual: Subtract the contribution of the selected atom from the residual:
$$r_{n+1}(t) = r_n(t) - c_m b_m(t),$$
where c_m is the coefficient of the selected atom.
4. Iterate: Repeat until the residual norm falls below a threshold.

MP is adaptive to signal structures and computationally efficient compared to global optimization methods. But its results depend on the choice of the dictionary and may not find the globally optimal solution.

2.2.5 Basis Pursuit (BP)

Basis Pursuit solves the L_0 norm minimization indirectly by relaxing it into a convex L_1 norm minimization problem:

$$\min ||c||_1, \quad \text{such that} \quad x(t) = \sum c_m b_m(t).$$

This approach guarantees a globally optimal solution and is robust to noise, making it suitable for noisy imaging systems. BP achieves higher accuracy than MP but is computationally more intensive while MP offers faster solutions for applications requiring real-time processing.

3 Methodology

3.1 Solving the Microwave Imaging Inverse Problem




Figure 2: [5] Microwave Imaging Measurement Setup.

Electromagnetic scattering occurs when scatterers are illuminated by a radiation source. The resulting perturbation field due to the presence of scatterers is referred to as the scattered field. Specifically, the scattered field is the difference between the fields with and without the scatterers. In this work, we focus exclusively on nonmagnetic dielectric materials. Broadly speaking, scatterers can be classified into two categories: penetrable and impenetrable scatterers.

For penetrable scatterers, the wave field is non-zero within the scatterers and satisfies the wave equation, which depends on the constitutive parameters of the scatterer. On the other hand, for impenetrable scatterers, the wave field is zero inside the scatterer, and the total field must satisfy certain boundary conditions. Our work concentrates on penetrable scatterers, specifically nonmagnetic dielectric materials.

As discussed in the previous section, by solving Maxwell's equations and applying Lorentz's reciprocity, the volume equivalence principle, and the first-order Born approximation, we derived the following formula:

$$V_{\text{oc}}(\mathbf{r}, f) \approx -\frac{i\omega}{I_{\text{in}}} \int_V |\mathbf{E}_{\text{inc}}(\mathbf{r}' - \mathbf{r}, f)|^2 (\epsilon(\mathbf{r}') - \epsilon_0)\, d\tau,$$

Next, by applying the 2D Fourier transform with respect to x and y, the integral equation

can be reformulated as:

$$T(k_x, k_y, f) \approx -\frac{i\omega}{I_{\text{in}}(f)} \int G(k_x, k_y, z, f) F(k_x, k_y, z)\, dz$$

After discretizing and reshaping the formula, we can rewrite the equations in a more compact form:

$$T_m \approx G_m F_m$$

If we can compute the inverse of G_m, we can determine the function of F_m, which represents the collection of the Fourier transforms of the permittivity distribution of the scatterer at different frequencies. However, a significant issue arises: the inverse scattering problem is ill-posed.




Figure 3: Ground truth of the scatterer on the left, angular spectrum in the middle, and the recovered dielectric scatterer on the right.

While proper modeling of the measurable quantities and the target response generally ensures the existence of a solution, the solution to the imaging problem may not be unique or stable due to the sensitivity of output data to the input source and the overdetermined kernel used in three-dimensional imaging problems. Consequently, the goal of solving such an imaging problem is not to recover the exact solution, but rather to find a meaningful approximation for the specific application.

To address this, we must solve a linear least-squares problem. By applying the Moore-Penrose pseudo-inverse to the equation, we obtain:

$$G_m^\dagger G_m F_m = G_m^\dagger T_m$$

Then, by solving for each spatial frequency set within the angular spectrum matrix and applying the 2D inverse Fourier transform to the entire matrix, we can finally obtain the permittivity distribution of the target object:

$$\epsilon(x, y, z_n) = \mathrm{FT}^{-1}\{F_m(k_x, k_y, z_n)\} + \epsilon_0$$

The results are shown in Figure 3. As seen, this method approximately reconstructs both the shape and permittivity of the dielectric scatterer from the electromagnetic field received at the aperture.

3.2 Regularization Techniques

It is important to note that the solution described earlier is typically overdetermined, as we are attempting to recover the permittivity distribution from the data acquired at an aperture. In other words, the rank of the Fourier transform of $|E_{\mathrm{inc}}(\mathbf{r}' - \mathbf{r}, f)|^2$ is much higher than necessary for a valid solution. One straightforward method to address this is by using truncated singular value decomposition (SVD). The basic idea behind SVD is that it decomposes a matrix of rank N into N rank-1 matrices. By truncating the less significant components, we can lower the rank. However, this approach becomes impractical for large-scale or real-world imaging scenarios.

A more effective regularization technique, proposed by Yang, is the 2k-numerical filter, which takes into account the electromagnetic properties of the system. High-frequency noise in the angular spectrum domain of the electromagnetic field satisfies the following relationship:

$$k^2 = k_x^2 + k_y^2 + k_z^2.$$

In practical measurement systems, the imaginary part of k_z is typically considered as an evanescent component or noise that should be filtered out. It is important to note that the filter has a cutoff frequency of $2k$, or more precisely, $2k - 1$, rather than k, since we are filtering the angular spectrum of the *square* of the electric field where $k_z \leq k$. This filtering process is carried out through convolution.




Figure 4: Unfiltered angular spectrum on the left, angular spectrum filtered by the 2k filter in the middle, and the reconstructed dielectric scatterer on the right, which closely matches the ground truth shown in Figure 3.

By attenuating the components with large k_z (the vertical wave number), the 2k filter is specifically tailored to the physical properties of the electromagnetic field. This results in a more accurate reconstruction of the permittivity distribution, as illustrated in Figure 4.

In summary, the 2k filter significantly improves the quality of the reconstructed permittivity distribution by removing unphysical components from the solution, thereby providing a more reliable and physically consistent result.

3.3 Compressive Sensing Algorithm: SPGL1

3.3.1 Overview of SPGL1

SPGL1 (Spectral Projected Gradient for L_1 minimization) is a specialized optimization algorithm designed for large-scale sparse reconstruction problems, particularly in the context of compressive sensing. The algorithm was developed to efficiently solve optimization problems where the objective involves minimizing the L_1 norm, promoting sparsity in the solution. The key advantage of SPGL1 is its ability to handle large, sparse data sets and provide accurate solutions with fewer measurements than traditional methods.

The SPGL1 algorithm is based on a projected gradient descent method that efficiently minimizes the L_1 norm of the solution while respecting the constraints of the measurement model. It has been widely adopted in fields such as signal processing, image reconstruction, and machine learning, where sparse signals are common. In microwave imaging, where the goal is often to reconstruct an image from a limited set of measurements, SPGL1 provides a powerful tool for reducing the required number of measurements without compromising image quality.

3.3.2 Mathematical Formulations

In compressive sensing, the goal is to reconstruct a sparse signal x from a limited number of measurements y. The measurement model is typically expressed as a linear equation:

$$y = Ax + \epsilon$$

where A is the sensing matrix that encodes the measurement process, x is the sparse signal (or image), and ϵ is the noise present in the measurements.

The core idea behind compressive sensing is to recover the signal x by solving an optimization problem that encourages sparsity, typically by minimizing the L_1-norm of the signal. This is done while ensuring that the reconstructed signal x fits the observed measurements as closely as possible. The following are common optimization problems formulated in compressive sensing:

- **Basis Pursuit Denoising (BPDN)**:

$$\min \|x\|_1 \quad \text{subject to} \quad \|Ax - y\|_2 \leq \sigma$$

where $\|x\|_1$ is the L_1-norm of x, which encourages sparsity, and $\|Ax - y\|_2 \leq \sigma$ ensures that the reconstructed signal is close to the observed measurements, within a tolerance σ.

- **Basis Pursuit (BP)**:

$$\min \|x\|_1 \quad \text{subject to} \quad Ax = y$$

This formulation aims to find a sparse signal x that exactly satisfies the measurement equation $Ax = y$.

- **Lasso (Least Absolute Shrinkage and Selection Operator)**:

$$\min \|Ax - y\|_2^2 \quad \text{subject to} \quad \|x\|_1 \leq \tau$$

Lasso is commonly used in regression problems, where it seeks to minimize the least squares error while enforcing a sparsity constraint on x by limiting the L_1-norm.

These optimization problems are typically solved using algorithms that efficiently handle large, sparse data sets. SPGL1 is one such algorithm that has been designed to solve these problems effectively, even in the presence of noise and incomplete measurements.

3.3.3 SPGL1 Algorithm Steps

The SPGL1 algorithm operates by iteratively solving the optimization problem using a projected gradient descent method. The basic steps of the SPGL1 algorithm are as follows:

1. Compute the gradient of the cost function:

$$g^{(k)} = A^*(Ax^{(k)} - y)$$

where A^* is the adjoint (transpose) of the sensing matrix A, and $x^{(k)}$ is the current estimate of the sparse signal.

2. Perform a line search to find the optimal step size $t^{(k)}$ that minimizes the cost function along the negative gradient direction:

$$t^{(k)} = \arg\min_t f(x^{(k)} - tg^{(k)})$$

3. Update the estimate of x:

$$x^{(k+1)} = P_{\mathcal{C}}(x^{(k)} - t^{(k)}g^{(k)})$$

where $P_{\mathcal{C}}$ is the projection operator that enforces sparsity by setting non-zero entries of $x^{(k+1)}$ according to a sparsity criterion (typically using a threshold).

4. Repeat the process until convergence, i.e., until the change in the solution x or the gradient g is smaller than a predefined threshold.

The SPGL1 algorithm is efficient and has been proven to work well in practice, especially for large-scale imaging problems like microwave imaging, where the goal is to reconstruct high-quality images from a limited set of measurements.

3.3.4 Summary

In simple terms, the compressive sensing algorithm SPGL1 can be thought of as an interpolation technique that reconstructs the full dataset from a sparse, random subset of data. By leveraging compressive sensing, we can significantly reduce the scanning time and the number of antenna probes required, while still maintaining high-quality reconstruction resolution for microwave imaging. The results of this approach are presented in the following section.

4 Results and Analysis






Figure 5: [5] Device under test and probe in simulation model setup.

For simplicity, we use the full-wave electromagnetic simulation software FEKO to replace actual measurements. FEKO is a powerful computational electromagnetics tool developed by


Altair Engineering, known for its comprehensive capabilities in high-frequency electromagnetic simulations. It is particularly adept at solving integral equations related to electromagnetic fields using the Method of Moments (MoM). In our imaging simulation setup, as shown in Figure 5, the targets are dielectric blocks, specifically a cruciform block, placed within the radiative near-field of the probe antenna. The simulations are conducted at X-band frequencies (centered at 10 GHz) with a half-wave dipole serving as the probe antenna. We use an oversampled grid with adjustable sampling distances to assess the fidelity of the reconstruction. The goal is to reconstruct the cruciform block from the scattered electromagnetic waves detected by the scanning probe, which constitutes an inverse problem.




(a) PSNR=20.62, SSIM=0.184




(b) PSNR=21.09, SSIM=0.842




(c) PSNR=21.03, SSIM=0.164



(d) PSNR=21.00, SSIM=0.668



(e) PSNR=22.43, SSIM=0.188




(f) PSNR=20.94, SSIM=0.649

Figure 6: Comparison of image reconstructions with and without compressive sensing from 75%, 50%, and 25% of the Nyquist limit probe sampling.

The purpose of the simulation is to demonstrate the effectiveness of compressive sensing in microwave imaging. To do so, we simulate measurements with different sampling rates and then apply compressive sensing reconstruction algorithms to recover the image. The sampling rates used in the simulations are 75%, 50%, and 25% of the Nyquist limit, with each

rate corresponding to a different level of measurement sparsity. These rates reflect common scenarios where only partial data is available, either due to time or resource constraints.

Figures 6a through 6f present the reconstruction results obtained from simulations at three different sampling rates. The images are reconstructed using both traditional methods and compressive sensing techniques. In every case, the images reconstructed using compressive sensing demonstrate significant improvements in image quality, as measured by the Peak Signal-to-Noise Ratio (PSNR) and the Structural Similarity Index (SSIM).



(a) Angular spectrum of 6b (b) Angular spectrum of 6d (c) Angular spectrum of 6f

Figure 7: Angular spectrum of images reconstructed by compressive sensing.

It is evident that compressive sensing plays a pivotal role in enhancing image recovery. To quantify image quality, two metrics are employed: Peak Signal-to-Noise Ratio (PSNR) and Structural Similarity Index (SSIM). PSNR quantifies the numerical differences between the original and reconstructed images, with higher values indicating greater similarity. SSIM, on the other hand, complements PSNR by assessing human perception of image structure through comparisons of luminance, contrast, and structural features. Together, these metrics provide a comprehensive evaluation of image quality during both simulation and experimental phases.

In summary, this paper demonstrates the use of the SPGL1 algorithm, a compressive sensing method based on convex optimization. A comparative analysis between compressive sensing and traditional methods highlights the improved accuracy, reduced measurement requirements, and effective noise handling achievable with compressive sensing. Notably, the results are promising, as the image can be recovered using only 29 percent of the data required by the Nyquist limit.

5 Conclusion

Compressive sensing has proven to be a transformative approach in microwave imaging, significantly enhancing the efficiency of data acquisition while preserving high reconstruction accuracy. By utilizing advanced algorithms such as Matching Pursuit, Basis Pursuit, and tailored regularization filters, compressive sensing enables dramatic reductions in measurement

requirements. This efficiency not only improves image quality but also broadens the potential applications of microwave imaging in fields such as medical diagnostics, non-destructive testing, and security screening.

6 Future Work

6.1 Tailored Sensing

The application of compressive sensing has significantly enhanced the efficiency of microwave imaging, yet there remains substantial potential for innovation in the design of the measurement process itself. A particularly promising avenue is the concept of tailored sensing, wherein the sensing matrix Φ is deliberately designed to optimize signal recovery for specific imaging scenarios. This approach could involve the dynamic adjustment of the measurement strategy based on intermediate reconstructions, allowing for a focus on regions of interest, such as suspected anomalies in medical imaging. Another aspect of tailored sensing is the optimization of physical sensor configurations, such as antenna arrays, to inherently promote incoherence in the measurement matrix. Additionally, the customization of measurement frequencies to exploit the spectral properties of specific materials or targets presents an opportunity to enhance the accuracy and resolution of reconstructions. By integrating tailored sensing strategies with advanced compressive sensing algorithms, future systems could achieve superior imaging performance while maintaining efficiency.

6.2 Machine Learning Integration

Another area of significant potential is the integration of machine learning techniques to enhance both the accuracy and computational efficiency of compressive sensing-based microwave imaging. Deep learning models, for instance, can be trained to learn the mapping between sparse measurements and the underlying permittivity distribution, offering a data-driven approach to signal recovery. Furthermore, recent advancements in physics-informed neural networks (PINNs) provide an opportunity to incorporate physical laws into the learning process, ensuring that the reconstructions remain consistent with the governing electromagnetic equations. This fusion of machine learning with compressive sensing could be particularly impactful in scenarios involving complex or noisy measurement environments, where traditional methods often struggle.

6.3 Real-Time Imaging

Real-time imaging represents a critical requirement for applications such as security screening, medical diagnostics, and non-destructive testing. Achieving this goal requires advance-

ments in both hardware and algorithm design. Future research could focus on developing parallelized implementations of compressive sensing algorithms that leverage the computational power of GPUs or specialized hardware such as field-programmable gate arrays (FPGAs). These optimizations could reduce latency in data acquisition and processing, enabling practical deployment of real-time imaging systems.

6.4 Noise Robustness and Uncertainty Quantification

While compressive sensing algorithms are inherently robust to noise, further improvements can be made by explicitly modeling measurement noise and incorporating uncertainty quantification. Bayesian compressive sensing is a promising approach in this regard, as it provides a probabilistic framework for signal reconstruction that accounts for noise and offers confidence intervals for reconstructed images. This capability is particularly important in critical applications such as medical imaging, where accurate interpretation of reconstructed data can have life-altering implications.

6.5 Multimodal Imaging

Combining microwave imaging with other imaging modalities, such as ultrasound or infrared imaging, presents an opportunity to obtain complementary information about the target. Multimodal imaging can improve reconstruction fidelity by integrating data from different physical mechanisms. Future research could focus on developing frameworks for multimodal data fusion, leveraging compressive sensing principles to design joint sparsity models that exploit shared features across modalities while preserving modality-specific details. Such approaches would significantly enhance the diagnostic and analytical capabilities of imaging systems.

6.6 Extending to Nonlinear Inverse Problems

The methods discussed in this paper primarily address linear inverse problems, which are a simplification of many real-world scenarios. In practice, microwave interactions with materials often involve nonlinear effects, particularly in cases involving strong scatterers or high permittivity contrasts. Extending compressive sensing techniques to address these nonlinearities represents a challenging but impactful direction for future research. Techniques such as iterative linearization or the incorporation of nonlinear physics into the sensing model could provide pathways to tackle these more complex problems.

6.7 Generalization Across Applications

Although the focus of this paper has been on microwave imaging, the principles of compressive sensing are broadly applicable across various imaging domains. Potential extensions include applications in radar imaging, seismic tomography, and quantum sensing. Each of these fields presents unique challenges and opportunities, and tailoring compressive sensing techniques to their specific requirements could unlock new possibilities in imaging science. For instance, in radar imaging, the incorporation of sparsity in the Doppler domain could enable efficient tracking of dynamic targets. Similarly, in seismic tomography, compressive sensing could reduce the data acquisition burden while maintaining high-resolution reconstructions of subsurface structures.

6.8 Summary of Future Directions

In summary, this paper outlines several promising directions for future work, including tailored sensing, machine learning integration, real-time imaging, and multimodal imaging. Extending the methods to nonlinear problems and generalizing them to other imaging domains further underscores the versatility and potential of compressive sensing. By addressing these challenges, future research can not only advance the field of microwave imaging but also contribute broadly to the development of next-generation imaging technologies.

References

1. N. K. Nikolova, "Microwave Imaging for Breast Cancer," *IEEE Microwave Magazine*, vol. 12, no. 7, pp. 78–94, Dec. 2011.

2. M. Bassi *et al.*, "An Integrated Microwave Imaging Radar With Planar Antennas for Breast Cancer Detection," *IEEE Transactions on Microwave Theory and Techniques*, vol. 61, no. 5, pp. 2108–2118, May 2013.

3. J. Lien, N. Gillian, M. E. Karagozler, P. Amihood, and C. Schwesig, "Soli: Ubiquitous Gesture Sensing With Millimeter Wave Radar," *ACM Transactions on Graphics*, vol. 35, no. 4, pp. 1–19, Jul. 2016.

4. T. S. Ralston, G. L. Charvat, and J. E. Peabody, "Real-Time Through-wall Imaging Using an Ultrawideband Multiple-Input Multiple-Output (MIMO) Phased Array Radar System," *2010 IEEE International Symposium on Phased Array Systems and Technology*, Waltham, MA, United States, Oct. 2010, pp. 551–558.

5. H.-J. Yang, "Sparsely-Sampled Microwave and Millimeter-Wave Holographic Imaging Using Compressed Sensing," 10.6342/NTU202301937.

6. R. F. Harrington, *Time-Harmonic Electromagnetic Fields*. New York: IEEE Press/Wiley-Interscience, 2001.

7. G. Golub and W. Kahan, "Calculating the Singular Values and Pseudo-Inverse of a Matrix," *Journal of the Society for Industrial and Applied Mathematics: Series B, Numerical Analysis*, vol. 2, no. 2, pp. 205–224, 1965.

8. E. van den Berg and M. P. Friedlander, "Probing the Pareto Frontier for Basis Pursuit Solutions," *SIAM Journal on Scientific Computing*, vol. 31, no. 2, pp. 890–912, Jan. 2009.

9. E. Candes *et al.*, "Robust Uncertainty Principles: Exact Signal Reconstruction From Highly Incomplete Frequency Information," *IEEE Transactions on Information Theory*, vol. 52, no. 2, pp. 489–509, 2006.

10. R. Baraniuk, "Compressive Sensing," *IEEE Signal Processing Magazine*, vol. 24, no. 4, pp. 118–121, 2007.

11. S. Mallat and Z. Zhang, "Matching Pursuits With Time-Frequency Dictionaries," *IEEE Transactions on Signal Processing*, vol. 41, no. 12, pp. 3397–3415, 1993.