




J1 FRONT VIEW: latch below contacts; 1..4 left to right.
1 BLACK/GND; 2 RED/3V3; 3 GREEN/SCL; 4 YELLOW/SDA.

J2: 0.1 inch / 2.54 mm MALE
J3: JST-SH 1 mm TOP ENTRY (Qwiic)



R1 = 0 ohm, 1206. Fit this link for SCL continuity.
SDA passes under its insulated body on the front copper.

2 x 3.00 mm NON-PLATED holes.
All copper routing on F.Cu; no vias.
3.3 V confirmed by user; no regulator or level conversion.

Cable convention: plug nose away, cable toward viewer.
Latch-side view YELLOW GREEN RED BLACK.
Contact-side view BLACK RED GREEN YELLOW.
Before powering the first assembled board, continuity-check
actual cable colors against J2 labels, including both cable ends.

Passive adapter. R1 is the single-sided crossover link.

Sheet: / File: nezha-qwiic.kicad_sch		
Title: Nezha 3.3 V / 4P4C to Qwiic		
Size: A4	Date: 2026-10-05	Rev: A
KiCad E.D.A. 9.0.8		Id: 1/1