UNIVERSIDAD AUTÓNOMA METROPOLITANA UNIDAD AZCAPOTZALCO

Division: Basic Sciences and Engineering

IMU Hardware Characterization, Firmware Modularization, and Full 6-Axis Data Acquisition on ESP32

Author: Zaldivar Peñaflor Eric Zuriel – 2183082002

Assignment: Microelectronics

Professor: JOSE LUIS ZAMORANO FLORES

Date: 02/07/2026

Índice

Abstract 3
1. Introduction 3
2.Hardware configuration 3
2.1 Microcontroller — ESP32 DOIT DevKit V1 3
2.2 Inertial Sensor Module 3
2.3 OLED Display (attempted) 3
3. Electrical Connections 3
3.1 IMU 3
3.2 I2C Bus Notes 4
4. Phase 1 — Initial Hardware Characterization 4
4.1 I2C Bus Validation 4
4.2 Device Identification 4
4.3 Power Management 4
4.4 Configuration Registers 4
4.5 Raw Accelerometer Data 4
5. Phase 2 — Firmware Modularization and Full 6-Axis Acquisition 4
5.1 Code Architecture 4
5.2 Gyroscope Data Acquisition 4
5.3 Scale Conversion 5
5.4 Offset Calibration 5
5.5 Calibrated Output — Stationary 5
6. OLED Display Integration Attempt 5
7. Diagnostic Tooling 5
8. Key Findings 6
9. Implications for TinyML Development 6
10. Future Work 6
Conclusion 6

Abstract

This report documents the first two development phases of a TinyML-oriented embedded systems project based on an ESP32 DOIT DevKit V1 and a commercially labeled MPU-6050 IMU module.

Phase 1 established low-level I2C communication, confirmed device identity through direct register interrogation, and validated raw accelerometer data acquisition without vendor libraries. Unexpectedly, the sensor returned WHO_AM_I = 0x72 instead of the MPU-6050 standard value of 0x68, indicating a pin-compatible replacement device.

Phase 2 extended the firmware to include full 6-axis acquisition (accelerometer and gyroscope), offset calibration, scale conversion to physical units (m/s2 and deg/s), and a modular code architecture separating hardware logic from the main application loop. An OLED display integration attempt was conducted and documented as a hardware failure due to a defective unit.

1. Introduction

TinyML applications depend on reliable, calibrated sensor pipelines. Before collecting training datasets or developing inference models, the sensing subsystem must be fully validated at every layer: physical connections, communication protocol, register behavior, scale factors, and noise characteristics.

This report covers:

- I2C bus validation and device identification
- Accelerometer and gyroscope register characterization
- Offset calibration and scale conversion
- Firmware modularization
- OLED display integration attempt and diagnosis
- I2C diagnostic tooling

2.Hardware configuration

2.1 Microcontroller — ESP32 DOIT DevKit V1

Specification	Value
Architecture	Dual-core Xtensa LX6
Clock frequency	240 MHz
Wireless	Wi-Fi + Bluetooth
USB-UART bridge	CP2102

2.2 Inertial Sensor Module

Commercial label: MPU-6050 | Actual device: Unknown — WHO_AM_I = 0x72 | Protocol: I2C | Address: 0x68

Available pins: VCC, GND, SDA, SCL, XDA, XCL, ADO, INT

2.3 OLED Display (attempted)

Label: DST-015 | Expected controller: SSD1306 | Interface: I2C

Status: Defective — unit did not respond on I2C bus and caused bus collapse when connected. Excluded from current hardware configuration.

3. Electrical Connections

3.1 IMU

ESP32 Pin	IMU Pin
3V3	VCC
GND	GND
GPIO21	SDA
GPIO22	SCL

3.2 I2C Bus Notes

Pull-up resistors (10 kOhm) were added between 3V3 and SDA/SCL during OLED integration attempts. Removed after confirming the OLED was defective. The protoboard showed partial rail failures during testing; IMU placement was validated by I2C scan before each session.

4. Phase 1 — Initial Hardware Characterization

4.1 I2C Bus Validation

I2C address scan confirmed device presence at 0x68.

4.2 Device Identification

Register	Expected (MPU-6050)	Observed
WHO_AM_I (0x75)	0x68	0x72

The device is not a genuine MPU-6050. It is likely a pin-compatible InvenSense/TDK-family replacement. The register map behaves identically to the MPU-6050 specification.

4.3 Power Management

Register	Initial value	Action
0x6B	0x40 (sleep)	Write 0x00 to wake

Bidirectional register access confirmed.

4.4 Configuration Registers

Register	Value	Interpretation
ACCEL_CONFIG (0x1C)	0x00	+-2g range (default)
GYRO_CONFIG (0x1B)	0x00	+-250 deg/s range (default)

4.5 Raw Accelerometer Data

Registers 0x3B–0x40 read directly. Representative raw values (stationary):

Axis	Raw value
AX	-1876
AY	524
AZ	17556

5. Phase 2 — Firmware Modularization and Full 6-Axis Acquisition

5.1 Code Architecture

File	Role
src/main.cpp	Initialization and main loop
src/imu.cpp	IMU hardware logic
include/imu.h	Public interface declarations
tools/i2c_scan.cpp	Standalone I2C diagnostic tool

5.2 Gyroscope Data Acquisition

Gyroscope output registers 0x43–0x48 read and confirmed functional.

5.3 Scale Conversion

Sensor	Range	Scale factor
Accelerometer	+-2g	16384 LSB/g
Gyroscope	+-250 deg/s	131 LSB/deg/s

Accelerometer: (raw - offset) / 16384 x 9.81 = m/s2

Gyroscope: (raw - offset) / 131 = deg/s

5.4 Offset Calibration

200-sample stationary routine. AZ offset subtracts 1g (16384 LSB) to account for gravity.

Parameter	Value
Offset AX	-1411
Offset AY	467
Offset AZ	1261
Offset GX	185
Offset GY	355
Offset GZ	-103

5.5 Calibrated Output — Stationary

Accelerometer (m/s2):

Axis	Typical	Noise range
AX	~0.000	+-0.060
AY	~0.000	+-0.050
AZ	~9.810	+-0.080

Gyroscope (deg/s):

Axis	Typical	Noise range
GX	~0.000	+-0.350
GY	~0.000	+-0.350
GZ	~0.000	+-0.320

6. OLED Display Integration Attempt

A DST-015 OLED display module was connected to the I2C bus (GPIO21/GPIO22) to display real-time sensor data.

Findings:

- Unit did not appear in I2C address scans (0x3C and 0x3D absent).
- When connected, caused complete I2C bus collapse (Error -1 on all transactions).
- Failure persisted with 10 kOhm pull-up resistors on SDA and SCL.
- Failure persisted with VIN (5V) supply instead of 3V3.
- Connecting only VCC and GND (no SDA/SCL) still caused bus collapse — internal short circuit confirmed.

Conclusion: The OLED unit is defective. Integration deferred pending replacement hardware.

7. Diagnostic Tooling

A standalone I2C bus scanner was implemented as a separate PlatformIO environment ([env:i2c-scan]) with dedicated source directory (tools/i2c_scan.cpp). Allows bus diagnostics without modifying the main firmware.

8. Key Findings

- IMU is not a genuine MPU-6050 (WHO_AM_I = 0x72) but is fully register-compatible.
- ACCEL_CONFIG and GYRO_CONFIG default to 0x00: +-2g and +-250 deg/s confirmed.
- All 6 axes operational and calibrated.
- Calibrated accelerometer at rest: AX ~ AY ~ 0 m/s2, AZ ~ 9.81 m/s2.
- Calibrated gyroscope at rest: GX ~ GY ~ GZ ~ 0 deg/s.
- Protoboard has partially failed rails; IMU placement must be validated each session.
- OLED display unit is defective and excluded from current configuration.

9. Implications for TinyML Development

The sensing subsystem is fully operational for dataset collection. Calibrated 6-axis data at ~5 Hz provides the foundation for:

- Digital filtering (complementary filter, Kalman)
- Orientation estimation (roll, pitch)
- Windowed feature extraction
- Dataset labeling and collection
- TinyML model training and quantization
- On-device inference

10. Future Work

- Digital filtering implementation (complementary filter as next step)
- Roll/pitch estimation from fused accelerometer + gyroscope data
- OLED display integration with replacement hardware
- Dataset collection framework
- Noise characterization and spectral analysis

Conclusion

Phase 1 established hardware identity and low-level communication without vendor libraries. Phase 2 extended the system to full 6-axis calibrated acquisition with a modular firmware architecture. The sensing pipeline is validated, calibrated, and ready for the signal processing and dataset collection phases of the TinyML project.